ME 5309 – Mid-Semester Examination

Answer Booklet

Instructions: Attempt any three questions. Each question carries 10 marks. Show working where appropriate.

Question 1 [10 marks]

Q1(a) [4 marks]

Pixel pitch = 0.005 mm, sensor width = 1280x0.005 = 6.4 mm. how to calculate the belt field of view.

Q1(b) [3 marks]

$$Sensitivity = 10mV/N$$

The ADC has 12 bits, so there are 4096 levels.

Q1(c) [3 marks]

$$F = e^(AT) = e^(-0.2) = 0.818731$$

Question 2 [10 marks]

Q2(a) [2 marks]

The state model is $\dot{x}_1 = x_2$, $\dot{x}_2 = (\tau - 0.05x_2 - 2.4525 \sin x_1)/0.02$. Equilibrium requires $\tau_0 = 2.4525 \sin \theta_e$, so τ_0 must be between -2.4525 and +2.4525 N m.

Q2(b) [2 marks]

$$A = [[0, 1], [-mg\ell sin(60^\circ)/J, -b/J]] = [[0, 1], [-106.2, -2.5]],$$
$$B = [[0], [50]]$$

Q2(c) [4 marks]

At rest, $\dot{\theta} = \ddot{\theta} = 0$, so the torque balance is $K_p(\theta_d - \theta_{ss}) = mg\ell \sin\theta_{ss}$. With $K_p = 50$, $\theta_d = \pi/2$ and $mg\ell = 2.4525$, solve $50(\pi/2 - \theta_{ss}) = 2.4525 \sin\theta_{ss}$. This gives θ_{ss} approximately 1.52181 rad = 87.193°, so the error is 90°-87.193° = 2.807°; it is not zero.

Rearranging the steady-state equation gives $50(\pi/2 - \theta_{ss}) = 2.4525 \sin\theta_{ss}$. I used radians in the equation. Solving numerically gives $\theta_{ss} \approx 1.522$ rad $\approx 87.19^\circ$, so the gap from 90° is about 2.81°.

Q2(d) [2 marks]

With gravity compensation, the gravity term cancels the plant's mgℓ sin θ term. At rest, Kp(θd-θss)=0, so θss=θd and the steady-state error is zero. The linearised gravity stiffness term is also cancelled, so the closed-loop poles generally change; the stiffness contribution mgℓ cos θd is removed.

The compensation term cancels the nominal gravity torque in the plant model. At steady state the proportional term must then be zero, which requires $\theta_d - \theta_{ss} = 0$. This does not mean the transient response is unchanged: removing the gravity derivative changes the linearized stiffness.

Question 4 [10 marks]

Q4(a) [2 marks]

The closed-loop poles are -2±2j. I use Nff=c/b=6 for unity DC gain.

Q4(b) [2 marks]

The nominal controller has unity DC gain, so θss=1 and the tracking error is zero even after the actuator gain changes.

Q4(c) [4 marks]

The desired polynomial is $(s+4)(s^2+4s+8)$. The closed-loop polynomial should be cubic because an integrator is added.

Q4(d) [2 marks]

Integral action removes steady-state error, although this only holds for the nominal values of b and c. Saturation can cause windup, which should be handled by anti-windup.