ME 5309 – Mid-Semester Examination

Answer Booklet

Instructions: Attempt any three questions. Each question carries 10 marks. Show working where appropriate.

Question 1 [10 marks]

Q1(a) [4 marks]

Pixel pitch = 0.005 mm, sensor width = 1280x0.005 = 6.4 mm. how to calculate the belt field of view.

Q1(b) [3 marks]

ADC step = 5/4096 = 1.2207 mV. I divide by 0.1 mV/N, giving ΔF = 12.207 N.

Q1(c) [3 marks]

$$F = e^(- 2 \times 0.1) = 0.818731$$

I used G = (1-F)/(-2) = -0.0906346. So:

$$x_{k+1} = 0.818731 x_k - 0.0906346 u_k$$

Question 2 [10 marks]

Q2(a) [2 marks]

At equilibrium the velocity should be zero. The torque and gravity torque must balance.

Q2(b) [2 marks]

With x = [θ, $\dot{\theta}$]^T, A = [[0,1], [-(mgℓ/J)cos θ_e, -b/J]], B = [[0],[1/J]]. At θ_e = 60°, A = [[0,1], [-61.3125, -2.5]] and B = [[0],[50]].

At the equilibrium, the constant torque balances gravity. For a small perturbation, use $\sin(\theta_e + \delta\theta) \approx \sin\theta_e + \cos\theta_e\,\delta\theta$. The constant terms cancel against τ_0; the remaining linear term gives the local state matrix.

Q2(c) [4 marks]

At rest, 50(π/2-θss) = 2.4525. This gives θss = 1.5218 rad = 87.19°, so error approximately 2.81°.

Q2(d) [2 marks]

The gravity term changes the equilibrium, so the steady-state error is still nonzero. The poles should change.

Question 3 [10 marks]

Q3(a) [2 marks]

Q3(b) [2 marks]

For H(s)=ωc/(s+ωc), ωc=2π(20)=125.664 rad/s and T=0.001 s. Tustin gives H(z)=α(1+z^{-1})/[(1+α)+(α-1)z^{-1}], α=ωcT/2=0.0628319. Thus:

$$y[k] = 0.881765y[k-1] + 0.0591175(x_k + x[k-1])$$

DC gain = (2x0.0591175)/(1-0.881765) approximately 1.000.

$\omega_c = 2\pi(20) = 125.664$ rad/s. With $T = 0.001$ s, $\alpha = \omega_c T/2 = 125.664(0.001)/2 = 0.062832$. The recurrence coefficients are approximately 0.881765 on the previous output and 0.0591175 on each input sample. Check: $2(0.0591175)/(1 - 0.881765) \approx 1$, so the DC gain is close to one.

Q3(c) [4 marks]

A-LC=[[-ℓ_1,1], [-ℓ_2,-2]]. The desired polynomial is (s+10)^2 = s^2+20s+100.

Q3(d) [2 marks]

An observer uses the plant model and known control input to estimate unmeasured states such as velocity, and its poles can be designed. A simple low-pass filter cannot exploit the state-space model in this way. A filter may be safer when the model is poorly known or unreliable, because it relies less on model accuracy.

The observer uses the plant model and the measured output to reconstruct the unmeasured state. Its convergence depends on the model and the observer poles. A low-pass filter is simpler, but generally introduces phase lag and does not explicitly use the plant dynamics.

Question 4 [10 marks]

Q4(a) [2 marks]

The closed-loop poles are -2±2j. I use Nff=c/b=6 for unity DC gain.

Q4(b) [2 marks]

The actual feedforward contribution is 0.75x8=6.

Q4(c) [4 marks]

With $\dot{\xi}$=r-θ and u=-k$_1$θ-k$_2\dot{\theta}$+K_Iξ, the homogeneous closed-loop characteristic polynomial is s^3+(a+bk$_2$)s^2+(c+
Desired polynomial: (s+4)[(s+2)^2+4]=(s+4)(s^2+4s+8)=s^3+8s^2+24s+32. For a=2,b=1,c=6, matching coefficients gives k$_2$=6, k$_1$=18 and K_I=32.

First multiply $(s+4)(s^2+4s+8) = s^3+8s^2+24s+32$. Comparing this with the augmented characteristic polynomial gives $k_2 = 6$, $k_1 = 18$, and $K_I = 32$. I checked the coefficients in descending powers of s.

Q4(d) [2 marks]

Integral action removes steady-state error, although this only holds for the nominal values of b and c. Saturation can cause windup, which should be handled by anti-windup.