ME 5309 – Mid-Semester Examination: ANSWER SHEET

Roll No.: ME25M017 **Name:** Harsh Agarwal

Questions attempted: Q1, Q2, Q4

Question 1

Given: sensor 1280 px wide, pixel pitch p = 5 μm (square), lens f = 16 mm, standoff Z = 400 mm; force sensor 10 mV/N, 12-bit ADC over 0–5 V; plant $\dot{x} = -2x + u$ with zero-order hold, T = 0.1 s.

(a) (i) $f_x = f/p = 16\times10^{-3} / 5\times10^{-6} =$ **3200 px**.

(ii) Sensor width = 1280 × 5 μm = 6.4 mm. Using similar triangles, FOV = $W_s \cdot f / Z = 6.4 \times 16/400 =$ **0.256 mm**.

Distance per pixel = FOV/1280 = 0.256/1280 = **2×10^{-4} mm** = 0.2 μm.

(b) LSB = 5 V/2^{12} = 5/4096 = 1.2207 mV = 1.2207×10^{-3} V.

ΔF = LSB/S with S = 10 mV/N = 10 V/N (taking the mV as V in the denominator): ΔF = $1.2207\times10^{-3}/10 =$ **1.22×10^{-4} N**.

(c) With u held constant over [kT, (k+1)T] (zero-order hold) the variation-of-constants formula gives $x((k+1)T) = e^{AT} x(kT) + \int_0^T e^{A(T-s)} B\, u(kT)\, ds$. Since u(kT) is constant it leaves the integral, so $F = e^{AT}$ and $G = \int_0^T e^{A\sigma} B\, d\sigma = A^{-1}(e^{AT} - I)B$ for invertible A.

Substitutting A = −2, B = 1, T = 0.1 s: $F = e^{-0.2} = 0.81873$. G = (0.81873 − 1)/(−2) = 0.090635.

Sanity check: the DC gain of the continuous plant is $-A^{-1}B = 0.5$, and the discrete DC gain G/(1 − F) = 0.090635/0.18127 = 0.5 ✓.

$$\mathbf{x_{k+1} = 0.8187\, x_k + 0.0906\, u_k}$$

Sanity check: a 160 mm field of view across 1280 pixels is plausible for a 400 mm standoff and a 16 mm lens.

Question 2

Given: J = 0.02 kg·m², b = 0.05 N·m·s/rad, m = 1 kg, ℓ = 0.25 m, g = 9.81 m/s². So mgℓ = 1 × 9.81 × 0.25 = 2.4525 N·m (used throughout).

(a) The model is second order, so I choose the position and velocity as states: $x = [x_1, x_2]^T = [\theta, \dot{\theta}]^T$, with input τ.

Rewriting $J\ddot{\theta} + b\dot{\theta} + mg\ell \sin\theta = \tau$ gives the nonlinear state-space model: $\dot{x}_1 = x_2$, $\dot{x}_2 = (1/J)(\tau - b\, x_2 - mg\ell \sin x_1)$, i.e. $\dot{x} = f(x, \tau)$.

Equilibria for constant τ_0 need $\dot{x} = 0$: the first equation gives $x_2 = 0$, and the second then gives $mg\ell \sin\theta_e = \tau_0$, i.e. $\sin\theta_e = \tau_0/(mg\ell)$.

This has a solution only if $|\tau_0/(mg\ell)| \le 1$, so **$|\tau_0| \le mg\ell = 2.4525$ N·m**. For $|\tau_0| < mg\ell$ there are two equilibria per revolution (θ_e and $\pi - \theta_e$); at $|\tau_0| = mg\ell$ they merge, and beyond it the joint cannot be held statically.

(b) The equilibrium at $\theta_e = 60°$ needs the torque $\tau_e = mg\ell \sin 60° = 2.4525 \times 0.8660 = 2.124$ N·m. Define deviations $\delta x = x - x_e$ with $x_e = [60°, 0]^T$ and $\delta\tau = \tau - \tau_e$; then $\delta\dot{x} \approx A\,\delta x + B\,\delta\tau$ with the Jacobians evaluated at the equilibrium.

$\partial f_1/\partial x = [0, 1]$. $\partial f_2/\partial x_1 = -(mg\ell/J)\cos x_1 = -(2.4525/0.02)(0.5) = -122.625 \times 0.5 = -61.31$ (s^{-2}). $\partial f_2/\partial x_2 = -b/J = -0.05/0.02 = -2.5\ s^{-1}$.

A = [0, 1; −61.31, −2.5], and sence $\partial f_2/\partial\tau = 1/J = 50$, **B = [0; 50]**.

Check: the characteristic equation $\lambda^2 + 2.5\lambda + 61.31 = 0$ gives $\lambda = -1.25 \pm 7.73j$, a lightly damped stabel oscillation, as expected for a pendulum hanging near-vertical (60° below the downward

vertical).

(c) At rest $\dot{\theta} = \ddot{\theta} = 0$: $K_p(\theta_d - \theta_{ss}) = mg\ell \sin\theta_{ss} = 2.4525 \sin\theta_{ss}$. At $\theta_d = 90°$ the right side $\neq 0$ while the left side = 0, so the joint cannot rest at θ_d.

With $\sin\theta_{ss} \approx 1$: $\theta_d - \theta_{ss} = 2.4525/50 = 0.00491$ rad = **0.281°**.

(d) Steady state: $\dot{\theta} = \ddot{\theta} = 0$ and the control law gives $\tau = K_p(\theta_d - \theta_{ss}) + mg\ell \sin\theta_{ss}$. Plugging into the plant, $mg\ell \sin\theta_{ss} = K_p(\theta_d - \theta_{ss}) + mg\ell \sin\theta_{ss}$, so $K_p(\theta_d - \theta_{ss}) = 0$ and **$\theta_{ss} = \theta_d$: stedy-state error is zero**.

Poles: linearise the closed loop about θ_d. Before compensation, $J\ddot{\theta} + (b + K_d)\dot{\theta} + (K_p + mg\ell \cos\theta_d)\,\delta\theta = 0$, characterstic polynomial $J\lambda^2 + (b + K_d)\lambda + K_p + mg\ell \cos\theta_d$. After compensation the added term $mg\ell \sin\theta$ cancels the plant's gravity term exactly, leaving $J\lambda^2 + (b + K_d)\lambda + K_p$.

The two differ only by $mg\ell \cos\theta_d$, and for $\theta_d = 90°$ this is $2.4525 \times 0 = 0$. So **the closed-loop poles are unchanged** at this operating angle. I should stress this is because $\cos 90° = 0$; if θ_d were, say, 60°, the compensation would raise the stiffness by 61.3×0.02... i.e. it would move the poles.

Question 4

Given: plant $\ddot{\theta} + a\dot{\theta} + c\theta = b\,u$ with $a = 2$, $c = 6$, $b = 1$; controller $u = N_{ff}\,r - k_1\theta - k_2\dot{\theta}$.

(a) Substitute the control law into the plant: $\ddot{\theta} + a\dot{\theta} + c\theta = b\,N_{ff}\,r - b\,k_1\,\theta - b\,k_2\,\dot{\theta}$. Moving the feedback terms to the left: $\ddot{\theta} + (a + b\,k_2)\,\dot{\theta} + (c + b\,k_1)\,\theta = b\,N_{ff}\,r$.

Numerically, $a + b\,k_2 = 2 + 2 = 4$ and $c + b\,k_1 = 6 + 2 = 8$, so the characteristic equation is $s^2 + 4s + 8 = 0$. Roots: $s = [-4 \pm \sqrt{(16 - 32)}]/2 = -2 \pm 2j$. They have negative real parts, so the loop is stable; $\omega_n = \sqrt{8} = 2.83$ rad/s and $\zeta = 4/(2 \times 2.83) = 0.707$.

Transfer function from r to θ: $T(s) = b\,N_{ff} / (s^2 + 4s + 8)$. DC gain (s = 0): $T(0) = N_{ff}/8$. For unity DC gain, **$N_{ff} = 8$**. (Note that this is larger than 1 because the gravity-related stiffness c and the feedback k_1 both resist the displacement.)

(b) With the actual $b = 0.75$ and unchanged $N_{ff} = 8$, $k_1 = k_2 = 2$, the closed loop becomes $\ddot{\theta} + (a + bk_2)\dot{\theta} + (c + bk_1)\theta = bN_{ff}\,r$, i.e. $\ddot{\theta} + 3.5\dot{\theta} + 7.5\theta = 6\,r$.

For a unit step the stedy state is found by setting derivatives to zero: $7.5\,\theta_{ss} = 6 \times 1$, so $\theta_{ss} = 6/7.5 = \mathbf{0.8}$.

Tracking error $= (r - \theta_{ss})/r \times 100\% = (1 - 0.8) \times 100 = \mathbf{20\%}$. A common mistake would be to say the output falls by the same 25% as the actuator gain; that is wrong here, becuase b also appears in the feedback stiffness $c + bk_1$, which decreases from 8 to 7.5 and partially compensates. The poles also change: $s^2 + 3.5s + 7.5 \rightarrow s = -1.75 \pm 2.11j$, still stable.

(c) Take the state $z = [\theta, \dot{\theta}, \xi]^T$. The plant gives $\ddot{\theta} = -a\dot{\theta} - c\theta + b\,u$ with $u = -k_1\theta - k_2\dot{\theta} + K_I\xi$, and $\dot{\xi} = r - \theta$. With $r = 0$ (r only shifts the equilibrium) the closed-loop matrix is $A_{cl} = [0, 1, 0;\ -(c + bk_1), -(a + bk_2), bK_I;\ -1, 0, 0]$.

Characteristic polynomial $\det(sI - A_{cl})$, expanding along the first row: $s\cdot[(s + a + bk_2)s - 0] + 1\cdot[(c + bk_1)s + bK_I] = s^3 + (a + bk_2)s^2 + (c + bk_1)s + bK_I$. **(Result)**

Desiered poles -4 and $-2 \pm 2j$: $(s + 2 - 2j)(s + 2 + 2j) = (s + 2)^2 + 4 = s^2 + 4s + 8$. Multiply by $(s + 4)$: $s^3 + 4s^2 + 8s + 4s^2 + 16s + 32 = s^3 + 8s^2 + 24s + 32$.

Compare coefficients with $a = 2$, $b = 1$, $c = 6$: s^2: $2 + k_2 = 8 \Rightarrow \mathbf{k_2 = 6}$. s^1: $6 + k_1 = 24 \Rightarrow \mathbf{k_1 = 18}$. s^0: $b\,K_I = 32 \Rightarrow \mathbf{K_I = 32}$.

Chek: all coefficients of the desired polynomial are positive and $(8)(24) = 192 > 32$, so Routh–Hurwitz confirms the three poles are in the left half plane ✓.

(d) In stedy state $\dot{\xi} = 0$, so $r - \theta_{ss} = 0 \Rightarrow \theta_{ss} = r$ for any b and c as long as the system is stable.

Failure mode: integral action amplifies noise and makes the system oscillate. Remidy: put a low-pass filter on the measurement.

Note: the integrator adds one state, so the loop becomes third order.