ME 5309 – Mid-Semester Examination: ANSWER SHEET

Roll No.: ME25M036 **Name:** Bhavna Rathore

Questions attempted: Q1, Q2, Q3, Q4

Question 1

Given: sensor 1280 px wide, pixel pitch p = 5 μm (square), lens f = 16 mm, standoff Z = 400 mm; force sensor 10 mV/N, 12-bit ADC over 0–5 V; plant $\dot{x} = -2x + u$ with zero-order hold, T = 0.1 s.

(a) (i) $f_x = f/p = 16\text{ mm} / 5\ \mu\text{m} =$ **3200 px**.

(ii) Sensor width = 1280 × 5 μm = 6.4 mm; FOV = $W_s \cdot Z/f = 6.4 \times 400/16 =$ **160 mm**.

(b) Assumptions: ideal 12-bit ADC (4096 codes), the full 0–5 V range is used, no offset or gain error, and sensor noise is below one LSB so quantisation sets the limit.

Voltage step: 1 LSB = $V_{FS}/2^N = 5\text{ V}/4096 = 1.2207\times10^{-3}$ V = 1.2207 mV.

The sensor maps force to voltage by V = S·F with S = 10 mV/N, so $\Delta F_{min} = \Delta V/S = 1.2207\text{ mV} / (10\text{ mV/N}) = 0.12207$ N. $\mathbf{\Delta F_{min} \approx 0.122\ N}$. (Using 4095 steps instead of 4096 codes gives 0.1221 N, the same at 3 s.f.)

(c) With u held constant over [kT, (k+1)T] (zero-order hold) the variation-of-constants formula gives $x((k+1)T) = e^{AT}x(kT) + \int_0^T e^{A(T-s)}B\,u(kT)\,ds$. Since u(kT) is constant it leaves the integral, so $F = e^{AT}$ and $G = \int_0^T e^{A\sigma}B\,d\sigma = A^{-1}(e^{AT} - I)B$ for invertible A.

Substituting A = −2, B = 1, T = 0.1 s: $F = e^{-0.2} = 0.81873$. $G = (0.81873 - 1)/(-2) = 0.090635$.

Sanity check: the DC gain of the continuous plant is $-A^{-1}B = 0.5$, and the discrete DC gain $G/(1 - F) = 0.090635/0.18127 = 0.5$ ✓.

$$\mathbf{x_{k+1} = 0.8187\,x_k + 0.0906\,u_k}$$

Question 2

Given: J = 0.02 kg·m², b = 0.05 N·m·s/rad, m = 1 kg, ℓ = 0.25 m, g = 9.81 m/s². So mgℓ = 1 × 9.81 × 0.25 = 2.4525 N·m (used throughout).

(a) The model is second order, so I choose the position and velocity as states: $x = [x_1, x_2]^T = [\theta, \dot{\theta}]^T$, with input τ.

Rewriting $J\ddot{\theta} + b\dot{\theta} + mg\ell\sin\theta = \tau$ gives the nonlinear state-space model: $\dot{x}_1 = x_2$, $\dot{x}_2 = (1/J)(\tau - b\,x_2 - mg\ell\sin x_1)$, i.e. $\dot{x} = f(x, \tau)$.

Equilibria for constant τ_0 need $\dot{x} = 0$: the first equation gives $x_2 = 0$, and the second then gives $mg\ell\sin\theta_e = \tau_0$, i.e. $\sin\theta_e = \tau_0/(mg\ell)$.

This has a solution only if $|\tau_0/(mg\ell)| \le 1$, so $\mathbf{|\tau_0| \le mg\ell = 2.4525\ N\cdot m}$. For $|\tau_0| < mg\ell$ there are two equilibria per revolution (θ_e and $\pi - \theta_e$); at $|\tau_0| = mg\ell$ they merge, and beyond it the joint cannot be held statically.

(b) Jacobian at $\theta_e = 60°$: $A = [0, 1; -(mg\ell/J)\cos\theta_e, -b/J]$.

$mg\ell/J = 2.4525/0.02 = 122.625$; $\cos(60) = -0.9524$, so $A_{21} = -122.625 \times (-0.9524) = +116.8$. $A_{22} = -b/J = -2.5$.

A = [0, 1; 116.8, −2.5], **B = [0; 50]**.

(c) Set all time derivatives to zero in the closed loop. With $\tau = K_p(\theta_d - \theta) - K_d\dot{\theta}$ and $\dot{\theta} = \ddot{\theta} = 0$ the damper term vanishes (so K_d has no effect on the final position) and the dynamics reduce to $mg\ell\sin\theta_{ss} = K_p(\theta_d - \theta_{ss})$.

Why $\theta_{ss} \neq \theta_d$: if the joint were at rest exactly at $\theta_d = 90°$ the PD torque would be $K_p\cdot0 - K_d\cdot0 = 0$, yet gravity pulls with $mg\ell\sin 90° = 2.4525$ N·m. The net torque would be non-zero, so the joint

could not be at rest. A purely proportional-derivative law can only hold a load if there is a steady error.

Let $e = \theta_d - \theta_{ss}$ (in rad). Then $\sin \theta_{ss} = \sin(\pi/2 - e) = \cos e$, and the equation becomes $50\, e = 2.4525 \cos e$. Fixed-point iteration: $e_0 = 2.4525/50 = 0.04905$ (taking $\cos e \approx 1$); $e_1 = 0.04905 \times \cos(0.04905) = 0.04899$; $e_2 = 0.04905 \times \cos(0.04899) = 0.04899$, converged.

$e = 0.04899$ rad $\times (180/\pi) = 2.807°$, so $\theta_{ss} = 87.19°$. **Steady-state error ≈ 2.81° (the arm sags below the target).** This is small becuase K_p is much larger than $mg\ell$ ($K_p/mg\ell \approx 20$).

(d) Graviy compensation reduces the steady-state error to about 0.5°, not exactly zero, since the compensaton is evaluated at the measured angle and the sensor and model are not perfect.

Pols: unchanged. The linearisation of the gravity term about θ_d is $mg\ell \cos \theta_d$, which is zero at 90°, so the stiffness stays K_p.

Question 3

Given: $A = [0, 1; 0, -2]$, $B = [0; 1]$, $C = [1, 0]$, $f_s = 1$ kHz so the sample time is $T = 1/f_s = 1$ ms.

(a) Reason 1 – noice amplification: the backward difference $\hat{\omega}_k = (\theta_k - \theta_{k-1})/T$ has frequncy response $(1 - e^{-j\omega T})/T$, whose magnitude grows with frequency ($\approx \omega$ for small ωT), i.e. it is a high-pass operation. Any noise on the encoder signal therefore appears in the velocity multiplied by roughly $1/T = 1000\ s^{-1}$, and can swamp the true velocity.

Reason 2 – quantisation: the encoder only reports integer counts, so $\Delta\theta$ is an integer multiple of the count size q. Dividing by T = 1 ms gives velocity steps of q/T; for a 4096-count encoder $q = 2\pi/4096 = 1.53 \times 10^{-3}$ rad, so one step is 1.53 rad/s. At low speed the estimate flips between 0 and one step (a noisy staircase), exactly where the damping term of the PD law is needed.

(A further, smaller issue is the half-sample delay of a backward difference, but the two reasons above are the main ones.)

(b) The analogue prototype is the first-order low-pass $H(s) = \omega_c/(s + \omega_c)$ with $\omega_c = 2\pi f_c = 2\pi \times 20 = 125.66$ rad/s. The bilinear (Tustin) transform replaces s by $(2/T)(z - 1)/(z + 1)$ with $T = 1/f_s = 0.001$ s.

Define $a = \omega_c T/2 = 125.66 \times 0.001/2 = 0.062832$. Then $H(z) = \omega_c / [(2/T)(z-1)/(z+1) + \omega_c] = a(z + 1) / [(1 + a)\, z - (1 - a)] = a(1 + z^{-1}) / [(1 + a) - (1 - a)\, z^{-1}]$.

Dividing through by $(1 + a)$: $a/(1 + a) = 0.062832/1.062832 = 0.059117$ and $(1 - a)/(1 + a) = 0.937168/1.062832 = 0.881767$. Hence with u = differenced signal and y = filtered velocity: $\mathbf{y_k = 0.05912\,(u_k + u_{k-1}) + 0.88177\, y_{k-1}}$. (Frequency pre-warping is neglected since $f_c \ll f_s/2$.)

Verification of the DC gain: set u and y constant (z = 1): $y = 2(0.05912)u + 0.88177\, y \Rightarrow y(1 - 0.88177) = 0.11824\, u \Rightarrow y/u = 0.11824/0.11823 = 1.000$. In general $H(1) = 2a/[(1 + a) - (1 - a)] = 2a/2a = 1$ exactly, so the steady-state output equals the commanded input ✓.

(c) $A - LC = [-\ell_1, 1; -\ell_2, -2]$. $\det(sI - A + LC) = (s + \ell_1)(s + 2) - \ell_2 = s^2 + (2 + \ell_1)s + (2\ell_1 - \ell_2)$.

Desired $(s + 10)^2 = s^2 + 20s + 100$. So $2 + \ell_1 = 20 \Rightarrow \ell_1 = 18$ and $2\ell_1 - \ell_2 = 100 \Rightarrow \ell_2 = 36 - 100 = -64$.

$\mathbf{L = [18, -64]^T}$.

(d) The observer is more accurate than the filter.

The filter is safer when you need something simple and cheap to implement.

Question 4

Given: plant $\theta\ddot{} + a\theta\dot{} + c\theta = b\, u$ with $a = 2$, $c = 6$, $b = 1$; controler $u = N_{ff}\, r - k_1\theta - k_2\theta\dot{}$.

(a) Substitute the control law into the plant: $\ddot{\theta} + a\dot{\theta} + c\theta = b\,N_{ff}\,r - b\,k_1\,\theta - b\,k_2\,\dot{\theta}$. Moving the feedback terms to the left: $\ddot{\theta} + (a + b\,k_2)\,\dot{\theta} + (c + b\,k_1)\,\theta = b\,N_{ff}\,r$.

Numerically, $a + b\,k_2 = 2 + 2 = 4$ and $c + b\,k_1 = 6 + 2 = 8$, so the characterstic equation is $s^2 + 4s + 8 = 0$. Roots: $s = [-4 \pm \sqrt{(16 - 32)}]/2 = -2 \pm 2j$. They have negative real parts, so the loop is stable; $\omega_n = \sqrt{8} = 2.83$ rad/s and $\zeta = 4/(2 \times 2.83) = 0.707$.

Transfer function from r to θ: $T(s) = b\,N_{ff} / (s^2 + 4s + 8)$. DC gain ($s = 0$): $T(0) = N_{ff}/8$. For unity DC gain, $\mathbf{N_{ff} = 8}$. (Note that this is larger than 1 because the gravity-related stiffness c and the feedback k_1 both resist the displacement.)

(b) With the actual $b = 0.75$ and unchanged $N_{ff} = 8$, $k_1 = k_2 = 2$, the closed loop becomes $\ddot{\theta} + (a + bk_2)\dot{\theta} + (c + bk_1)\theta = bN_{ff}\,r$, i.e. $\ddot{\theta} + 3.5\dot{\theta} + 7.5\theta = 6\,r$.

For a unit step the stedy state is found by setting derivatives to zero: $7.5\,\theta_{ss} = 6 \times 1$, so $\theta_{ss} = 6/7.5 = \mathbf{0.8}$.

Tracking error $= (r - \theta_{ss})/r \times 100\% = (1 - 0.8) \times 100 = \mathbf{20\%}$. A common mistake would be to say the output falls by the same 25% as the actuator gain; that is wrong here, because b also appears in the feedback stiffness $c + bk_1$, which decreases from 8 to 7.5 and partially compensates. The poles also change: $s^2 + 3.5s + 7.5 \rightarrow s = -1.75 \pm 2.11j$, still stable.

(c) Take the state $z = [\theta, \dot{\theta}, \xi]^T$. The plant gives $\ddot{\theta} = -a\dot{\theta} - c\theta + b\,u$ with $u = -k_1\theta - k_2\dot{\theta} + K_I\xi$, and $\dot{\xi} = r - \theta$. With $r = 0$ (r only shifts the equilibrium) the closed-loop matrix is $A_{cl} = [0, 1, 0; -(c + bk_1), -(a + bk_2), bK_I; -1, 0, 0]$.

Characteristic polynomial $\det(sI - A_{cl})$, expanding along the first row: $s\cdot[(s + a + bk_2)s - 0] + 1\cdot[(c + bk_1)s + bK_I] = s^3 + (a + bk_2)s^2 + (c + bk_1)s + bK_I$. **(ReusIt)**

Desired poles -4 and $-2 \pm 2j$: $(s + 2 - 2j)(s + 2 + 2j) = (s + 2)^2 + 4 = s^2 + 4s + 8$. Multiply by $(s + 4)$: $s^3 + 4s^2 + 8s + 4s^2 + 16s + 32 = s^3 + 8s^2 + 24s + 32$.

Compare coefficients with $a = 2$, $b = 1$, $c = 6$: s^2: $2 + k_2 = 8 \Rightarrow \mathbf{k_2 = 6}$. s^1: $6 + k_1 = 24 \Rightarrow \mathbf{k_1 = 18}$. s^0: $b\,K_I = 32 \Rightarrow \mathbf{K_I = 32}$.

Check: all coefficients of the desired polynomial are positive and $(8)(24) = 192 > 32$, so Routh–Hurwitz confirms the three poles are in the left half plane ✓.

(d) Suppose the closed loop is stable and r is constant. Then the state converges to a constant, so $\dot{\theta} = \ddot{\theta} = 0$ and, crucially, $\dot{\xi} = 0$ as well (ξ itself is constant at its final value ξ_{ss}). From the integrator equation $\dot{\xi} = r - \theta$, we get $r - \theta_{ss} = 0$, i.e. $\mathbf{\theta_{ss} = r}$.

Neither b nor c appears in this argument. They only influence the value of ξ_{ss} needed to hold the equilibrium (from the plant equation $c\theta_{ss} = bu_{ss} = b(-k_1\theta_{ss} + K_I\xi_{ss})$), and the pole locations, so the zero error survives any error in the model parameters provided the loop stays stable (unlike the feed-forward N_{ff} scheme of part (b)).

Practical failure mode: integrator windup. If the acuator saturates (torque limit), the loop is effectively open, the error stays non-zero and ξ keeps integrating to a huge value. When the reference becomes reachable the stored integral forces a large overshoot and a long recovery. Standard remidy: anti-windup, such as clamping the integrater when the actuator is saturated, conditional integration, or back-calculation that feeds the difference between commanded and saturated torque back to the integrator.

Remark: with integral action the exact value of N_{ff} matters less because the integrator enforces tracking.