Launch Control 3

PERFORMANCE MAP · WORKING SOURCE
16 endless encoders · 8 buttons · no faders
Compact LC3 — not Launch Control XL 3

EQ/FILTER + MIXER FEEDBACK REQUIRED. Syndicate OSC input: **9090** · feedback: **127.0.0.1:9096** · **Toggle All**. Missing feedback blocks EQ/filter pickup and Mute/Cue toggles; FX instead uses dry-home with no macro feedback.

FUNCTION · LAYER
Hot Cues → Mixer → FX → repeat
Startup: Hot Cues / Deck 1

TRACK ◀ / ▶ · DECK 1–4
Select hot-cue target · no wrap
Screen shows deck and button layer

BROWSER · TOP RIGHT
Clockwise: Down · anticlockwise: Up
Same encoder in both modes

EQ / FILTER ENCODERS
Mode + Function (DAW)
Always fixed mixer CH1–4

Read each row left → right, positions 1–8. The two diagrams are alternative modes of the same surface. "—" means unassigned.

MODE 1 · DAW MIXER → EQ

Console mode: eq · startup requests this mode

	1	2	3	4	5	6	7	8
TOP	LOW CH1	MID CH1	HIGH CH1	LOW CH2	MID CH2	HIGH CH2	— unassigned	BROWSE Up / Down
BOTTOM	LOW CH3	MID CH3	HIGH CH3	LOW CH4	MID CH4	HIGH CH4	— unassigned	— unassigned

MODE 2 · DAW CONTROL → FILTERS

Console mode: filter · inputs documented in Syndicate §14.9

	1	2	3	4	5	6	7	8
TOP	FILTER 1 CH1	FILTER 2 CH1	FILTER 1 CH2	FILTER 2 CH2	— unassigned	— unassigned	— unassigned	BROWSE Up / Down
BOTTOM	FILTER 1 CH3	FILTER 2 CH3	FILTER 1 CH4	FILTER 2 CH4	— unassigned	— unassigned	— unassigned	— unassigned

Cues & mixer

Function: Hot Cues → Mixer → FX
EQ/filter encoders unchanged across first two layers

HOT CUES LAYER — bottom buttons 1–8 tap selected-deck cue slots. Function cycles Hot Cues → Mixer → FX → Hot Cues; EQ/filter encoders work in Hot Cues and Mixer, FX overrides them.

HOT CUE 1	HOT CUE 2	HOT CUE 3	HOT CUE 4	HOT CUE 5	HOT CUE 6	HOT CUE 7	HOT CUE 8

MIXER LAYER — Mute/headphone Cue buttons for fixed CH1–4, unchanged by Track selection.

1 MUTE CH1	2 MUTE CH2	3 MUTE CH3	4 MUTE CH4	5 CUE CH1	6 CUE CH2	7 CUE CH3	8 CUE CH4

Hot-cue colours: fixed Candy Pop RGB palette, NOT populated-cue indicators. Empty slots can set cues. Use the screen for layer identity: Function is purple in Hot Cues and FX, cyan in Mixer. FX action colours: page 3.

Mixer LEDs: red = mute; cyan = headphone cue. Bright/dim follows Syndicate on/off feedback; grey = unknown. EQ/filter knobs are unchanged between Hot Cues and Mixer; FX overrides them.

Modes & encoder pickup

Hold **Mode**, press **Function (DAW)** to switch DAW Mixer ↔ DAW Control, then exit mode selection. Other device modes are not mapped. A confirmed mode change re-arms controls. Syndicate feedback synchronizes EQ/filter encoders in Hot Cues/Mixer; **no position feedback → no EQ/filter output**. FX overrides them in either reported mode and uses dry-home (page 3).

Function alone cycles Hot Cues → Mixer → FX. Switching Hot Cues ↔ Mixer preserves unchanged encoder captures; entering/leaving FX re-arms them. Track ◀/▶ selects the Hot Cue target Deck 1–4 independently of FLX4, stopping at either end. EQ/filter, FX and Mixer buttons stay on main CH1–4, never arrangement trims or cue-selected decks.

Browser & buttons

Top encoder 8: clockwise Down, anticlockwise Up; recentres over DAW MIDI output. After a mode switch, the first non-echo report may establish a baseline. Echo suppression can drop identical physical reports within 500 ms; it is not an acknowledgment.

Cue buttons tap once, no held preview or LC3 cue-region loops. Fixed HotCue hold/SetCueLoop are not mapped. Candy Pop colours do not track later palette/cue changes; empty slots can set cues, CueMomentary/Slip remain untouched, arrangement routes act as markers (not clip/sampler cues). Mixer Mute/Cue buttons invert confirmed 0/1; grey/unknown blocks toggles.

No Browser Enter, Back or Load: use Syndicate or FLX4. `/Syndicate/Mixer/CHn/Filter1` and `Filter2` are documented in Syndicate §14.9; missing feedback blocks pickup. Hardware/end-to-end operation is unverified.

FX macros

Fixed mixer CH1–4 · both confirmed DAW modes
Static action colours, not FX state

CONFIGURE SYNDICATE FIRST. On each of CH1–4 enable the VST3 insert chain; assign Macro 1 to plugin wet/dry (0 dry → 1 wet), Macro 2 to a mappable plugin enable (0 off, 1 on). Invert a bypass assignment if necessary. The bridge does not toggle the chain or configure the plugin.

Press **Function** through Hot Cues → Mixer → **FX**. The screen labels FX CH1–4 and button ON/OFF roles. FX works in either confirmed DAW Mixer (EQ) or DAW Control (filter) hardware mode; while active, it overrides the EQ/filter encoders. Track ◀/▶ still selects a Hot Cue deck, but does **not** retarget fixed FX channels.

FX LAYER · ENCODERS

Top row · fixed mixer channels · 7-bit Macro 1 wet

	1	2	3	4	5	6	7	8
TOP	**WET** CH1	**WET** CH2	**WET** CH3	**WET** CH4	—	—	—	**BROWSE** Up / Down
BOTTOM	—	—	—	—	—	—	—	—

Dry-home safety: There is no documented macro feedback or position pickup. Each time you enter or return to FX, or change the confirmed hardware mode, the first FX-encoder report establishes a baseline only. Then physically turn that encoder to **exact 0/dry** to send 0 and arm; if it starts dry, nudge away and back. Subsequent motion sends normalized Macro 1 wet. Another known bridge writer, including the FLX4, re-arms dry-home; mouse/external changes cannot be detected.

FX LAYER · BUTTONS

Explicit Macro 2 writes · not toggles

ON CH1	ON CH2	ON CH3	ON CH4	OFF CH1	OFF CH2	OFF CH3	OFF CH4

Buttons 1–4 send Macro 2 = **1**; 5–8 send Macro 2 = **0** for CH1–4. Green/red are **static action labels**, never effect state or confirmation. No macro feedback subscription, fake LED status, or startup/shutdown macro writes. Enable-button writes do not alter Macro 1 wet amount or the entire insert chain.

Other layers: Function to Hot Cues restores EQ/filter encoders in the confirmed hardware mode. Switching Hot Cues ↔ Mixer does not re-arm unchanged encoder bindings; entering/leaving FX does. Browser top encoder 8 works in all layers.

Setup & feedback

One bridge · shared Syndicate connection
Use alongside FLX4 or on its own

1 · Configure Syndicate

Setting	Value
OSC input / listen	**Enabled · 9090**
OSC feedback destination	**127.0.0.1 · 9096**
Feedback subscriptions	**Toggle All → all checked**
Browser Mode	**CONTROL MODE**
Direct Syndicate MIDI inputs	**Disable LC3** and any other bridged controller

Feedback is change-only since 0.1.902; no rate setting. Blocked takeovers may request a resend after 250 ms, globally at most once/sec; no timeout confirms success. Details.

For selective LC3 subscriptions: CH1–4 `EQ/Low`, `EQ/Mid`, `EQ/High`, `Filter1`, `Filter2`, `Mute`, `Cue`. FX macros have no documented feedback; FLX4 needs additional subscriptions.

If controls do nothing

Check console mode, DAW input/output, feedback subscriptions/destination and Browser CONTROL MODE. The bridge does not configure Syndicate.

Default profile/wire root: `/Syndicate/` (0.1.903+). Custom `osc_root` must match feedback; update old profiles explicitly. Root rules.

Keep the console open. Ctrl+C attempts standalone mode and held releases, both best-effort, never confirmed. Hotplug is automatic; restart after Syndicate restarts or uncertain state. Force-kills/UDP loss cannot guarantee cleanup.

2 · Use the DAW USB ports

Close other apps holding LC3's DAW ports. On Windows the documented DAW connection is **USB MIDI port 2**, not Main.

Input	`MIDIIN2 (LC3 1 MIDI)`
Output	`MIDIOUT2 (LC3 1 MIDI)`

These are the development machine's names. Run `ap-midi-osc-bridge.exe --list` to list yours without sending MIDI. If different, edit `inputs` / `outputs` in `profiles/launch-control-3.json`. Input/output indices are independent; selectors must match uniquely.

Do not select: Main `LC3 1 MIDI` or an LCXL3 port.

3 · Start the shared bridge

Keep `profiles/` beside the current executable. The bridge automatically matches connected controllers to their profiles; absent devices are skipped. Connect only LC3 for LC3-only use. No device-list config or Components remapping is needed.

On Windows, double-click **ap-midi-osc-bridge.exe**; on macOS/Linux, run `./ap-midi-osc-bridge`. No command launcher is needed. **Run only one bridge instance.**

Startup requests DAW Mixer (EQ), with the **Hot Cues** button layer and **Deck 1**. The controller must report a mapped DAW mode before controls become active. No firmware or stored Custom Modes are overwritten.

References: setup · complete LC3 operation · editable profile · schema · Syndicate guide §§14.2, 14.9–14.10; recent changes 0.1.901–0.1.903. **Scope:** bundled layout; hardware and Syndicate end-to-end operation unverified. Edited profiles may differ.