



NVIDIA SN2100 Switches

ONTAP Systems Switches

NetApp
July 18, 2022

Table of Contents

- NVIDIA SN2100 Switches 1
 - NVIDIA SN2100 switch 1
 - Setup and configure NVIDIA SN2100 switches 2
 - Migrate from a Cisco cluster switch to a NVIDIA SN2100 cluster switch 18
 - Migrate from a Cisco storage switch to a NVIDIA SN2100 storage switch 31
 - Migrate to a two-node switched cluster with NVIDIA SN2100 cluster switches 41
 - Replace NVIDIA SN2100 switches 54

NVIDIA SN2100 Switches

NVIDIA SN2100 switch

From ONTAP 9.10.1P3, you can use NVIDIA SN2100 switches to combine storage and cluster functionality into a shared switch scenario.

If you want to build ONTAP clusters with more than two nodes, you need two supported cluster network switches. You can use additional management switches, which are optional.

You install the NVIDIA SN2100 switch (X190006/X190106) in the NVIDIA dual/single switch cabinet with the standard brackets that are included with the switch.

SN2100 switches and rail kit details

The following table lists the part number and description for the MSN2100 switches and rail kits:

Part number	Description
X190006-PE	Cluster Switch, NVIDIA SN2100, 16PT 100G, PTSX
X190006-PI	Cluster Switch, NVIDIA SN2100, 16PT 100G, PSIN
X190106-FE-PE	Switch, NVIDIA SN2100, 16PT 100G, PTSX, Front End
X190106-FE-PI	Switch, NVIDIA SN2100, 16PT 100G, PSIN, Front End
X-MTEF-KIT-D	Rail Kit, NVIDIA Dual switch side by side
X-MTEF-KIT-E	Rail Kit, NVIDIA Single switch short depth



See NVIDIA documentation for details on [installing your SN2100 switch and rail kit](#).

Available documentation

The following table lists the documentation available for the NVIDIA SN2100 switches.

Title	Description
Setup and configure your NVIDIA SN2100 switches	Describes how to setup and configure your NVIDIA SN2100 switches, including installing Cumulus Linux and applicable RCFs.
Migrate from a Cisco cluster switch to a NVIDIA SN2100 cluster switch	Describes how to migrate from environments that use Cisco cluster switches to environments that use NVIDIA SN2100 cluster switches.
Migrate from a Cisco storage switch to a NVIDIA storage switch	Describes how to migrate from environments that use Cisco storage switches to environments that use NVIDIA SN2100 storage switches.

Title	Description
Migrate to a two-node switched cluster with NVIDIA SN2100 cluster switches	Describes how to migrate to a two-node switched environment using NVIDIA SN2100 cluster switches.
Replace a NVIDIA SN2100 cluster switch	Describes the procedure to replace a defective NVIDIA SN2100 switch in a cluster and download Cumulus Linux and reference configuration file.
Replace a NVIDIA SN2100 storage switch	Describes the procedure to replace a defective NVIDIA SN2100 storage switch and download Cumulus Linux and reference configuration file.

Setup and configure NVIDIA SN2100 switches

Setup and configure the NVIDIA SN2100 switches

The NVIDIA SN2100 switch is a 10/25/40/100 Gb Ethernet switch running Cumulus Linux. The SN2100 switch serves Cluster and Storage applications in ONTAP 9.10.1P3 over different switch-pairs.

Cumulus Linux (CL) OS can be installed either when the switch is running Cumulus Linux or ONIE. For this release, the minimal version of Cumulus Linux supported is 4.4.2.



The procedures here use Network Command Line Utility (NCLU) which is a command line interface that ensures Cumulus Linux is fully accessible to all. The net command is the wrapper utility you use to execute actions from a terminal.



When using breakout cables for 10G and 25G, make sure that auto-negotiation is off and hard set the port speed on the switch. See [Cabling and configuration considerations](#) for further details.

Cabling and configuration considerations

Before configuring your NVIDIA SN2100 switch, review the following information:

- Only optical connections are supported on SN2100 switches with X1151A NIC, X1146A NIC, or onboard 100GbE ports. For example:
 - AFF A800 on ports e0a and e0b
 - AFF A320 on ports e0g and e0h
- When a QSA adapter is used to connect to the onboard Intel cluster ports on a platform, not all links come up.

Example platforms are: FAS2750, AFF A300, and FAS8200 (all 10G) and AFF A250 (25G).

To resolve this issue, do the following:

- For Intel 10G, manually set the swp1s0-3 link speed to 10000 and set auto-negotiation to offset

- b. For Chelsio 25G, manually set the swp2s0-3 link speed to 25000 and set auto-negotiation to off



Using 10G/25G QSA, use the non-breakout 40/100G ports. Do not insert the QSA adapter on ports that are configured for breakout.

3. Depending on the transceiver in the switchport, you might need to set the speed on the switchport to fixed speed. If using 10G and 25G breakout ports, make sure that auto-negotiation is off and hard set the port speed on the switch. For example:

```
cumulus@cumulus:mgmt:~$ net add int swpls3 link autoneg on && net com
--- /etc/network/interfaces      2019-11-17 00:17:13.470687027 +0000
+++ /run/nclu/ifupdown2/interfaces.tmp  2019-11-24 00:09:19.435226258
+0000
@@ -37,21 +37,21 @@
     alias 10G Intra-Cluster Node
     link-autoneg off
     link-speed 10000
     mstpctl-bpduguard yes
     mstpctl-portadmededge yes
     mtu 9216

auto swpls3
iface swpls3
    alias 10G Intra-Cluster Node
-   link-autoneg off
+   link-autoneg on
    link-speed 10000
    mstpctl-bpduguard yes
    mstpctl-portadmededge yes
    mtu 9216

auto swp2s0
iface swp2s0
    alias 25G Intra-Cluster Node
    link-autoneg off
    link-speed 25000
```

Install Cumulus Linux in Cumulus mode

Cumulus Linux (CL) OS can be installed either when the switch is running Cumulus Linux or ONIE.

Before you begin

The following assumptions are made:

- You have intermediate-level Linux knowledge.

- You are familiar with basic text editing, UNIX file permissions, and process monitoring. A variety of text editors are pre-installed, including `vi` and `nano`.
- You must have access to a Linux or UNIX shell. If you are running Windows, use a Linux environment as your command line tool for interacting with Cumulus Linux.



Each time Cumulus Linux is installed, the entire file system structure is erased and rebuilt.



The default password for the `cumulus` user account is **cumulus**. The first time you log into Cumulus Linux, you must change this default password. Be sure to update any automation scripts before installing a new image. Cumulus Linux provides command line options to change the default password automatically during the installation process.

The baud rate requirement must be set to 115200 on the serial console switch for NVIDIA SN2100 switch console access, as follows:

- 115200 baud
- 8 data bits
- 1 stop bit
- parity: none
- flow control: none

Steps

1. Log in to the switch. First time log in to the switch requires username/password of **cumulus/cumulus** with `sudo` privileges:

```
cumulus login: cumulus
Password: cumulus
You are required to change your password immediately (administrator
enforced)
Changing password for cumulus.
Current password: cumulus
New password: netappl!
Retype new password: netappl!
```

2. Check the Cumulus Linux version:

```
cumulus@cumulus:mgmt:~$ net show system
Hostname..... cumulus
Build..... Cumulus Linux 4.4.2
Uptime..... 0:08:20.860000
Model..... Mlnx X86
CPU..... x86_64 Intel Atom C2558 2.40GHz
Memory..... 8GB
Disk..... 14.7GB
ASIC..... Mellanox Spectrum MT52132
Ports..... 16 x 100G-QSFP28
Part Number..... MSN2100-CB2FC
Serial Number.... MT2105T05177
Platform Name.... x86_64-mlnx_x86-r0
Product Name..... MSN2100
ONIE Version..... 2019.11-5.2.0020-115200
Base MAC Address. 04:3F:72:43:92:80
Manufacturer..... Mellanox
```

3. Configure the hostname, IP address, subnet mask, and default gateway. The new hostname only becomes effective after restarting the console/SSH session.



A Cumulus Linux switch provides at least one dedicated Ethernet management port called `eth0`. This interface is specifically for out-of-band management use. By default, the management interface uses DHCPv4 for addressing.



Do not use an underscore (`_`), apostrophe (`'`), or non-ASCII characters in the hostname.

```
cumulus@cumulus:mgmt:~$ net add hostname sw1
cumulus@cumulus:mgmt:~$ net add interface eth0 ip address
10.233.204.71/23
cumulus@cumulus:mgmt:~$ net add interface eth0 ip gateway 10.233.204.1
cumulus@cumulus:mgmt:~$ net pending
cumulus@cumulus:mgmt:~$ net commit
```

This command modifies both the `/etc/hostname` and `/etc/hosts` files.

4. Confirm that the hostname, IP address, subnet mask, and default gateway have been updated:

```

cumulus@sw1:mgmt:~$ hostname sw1
cumulus@sw1:mgmt:~$ ifconfig eth0
eth0: flags=4163<UP,BROADCAST,RUNNING,MULTICAST> mtu 1500
inet 10.233.204.71 netmask 255.255.254.0 broadcast 10.233.205.255
inet6 fe80::bace:f6ff:fe19:1df6 prefixlen 64 scopeid 0x20<link>
ether b8:ce:f6:19:1d:f6 txqueuelen 1000 (Ethernet)
RX packets 75364 bytes 23013528 (21.9 MiB)
RX errors 0 dropped 7 overruns 0 frame 0
TX packets 4053 bytes 827280 (807.8 KiB)
TX errors 0 dropped 0 overruns 0 carrier 0 collisions 0 device memory
0xdfc00000-dfc1ffff

cumulus@sw1:mgmt:~$ ip route show vrf mgmt
default via 10.233.204.1 dev eth0
unreachable default metric 4278198272
10.233.204.0/23 dev eth0 proto kernel scope link src 10.233.204.71
127.0.0.0/8 dev mgmt proto kernel scope link src 127.0.0.1

```

5. Configure the time zone using NTP interactive mode.

- a. On a terminal, run the following command:

```

cumulus@sw1:~$ sudo dpkg-reconfigure tzdata

```

- b. Follow the on-screen menu options to select the geographic area and region.
c. To set the time zone for all services and daemons, reboot the switch.
d. Verify that the date and time on the switch are correct and update if necessary.

6. Install Cumulus Linux 4.4.2:

```

cumulus@sw1:mgmt:~$ sudo onie-install -a -i
http://10.60.132.97/x/eng/testbedN,svl/nic/files/cumulus-linux-4.4.2-
mlx-amd64.bin

```

The installer starts the download. Type **y** when prompted.

7. Reboot the NVIDIA SN2100 switch:

```

cumulus@sw1:mgmt:~$ sudo reboot

```

8. The installation starts automatically, and the following GRUB screens appear. Do **not** make any selections:

- Cumulus-Linux GNU/Linux
- ONIE: Install OS

- CUMULUS-INSTALL
- Cumulus-Linux GNU/Linux

9. Repeat steps 1 to 4 to log in.

10. Verify that the Cumulus Linux version is 4.4.2:

```
cumulus@sw1:mgmt:~$ net show version
NCLU_VERSION=1.0-cl4.4.2u0
DISTRIB_ID="Cumulus Linux"
DISTRIB_RELEASE=4.4.2
DISTRIB_DESCRIPTION="Cumulus Linux 4.4.2"
```

11. Create a new user and add this user to the `sudo` group. This user only becomes effective after the console/SSH session is restarted:

```
cumulus@sw1:mgmt:~$ sudo adduser --ingroup netedit admin
[sudo] password for cumulus:
Adding user `admin' ...
Adding new user `admin' (1001) with group `netedit' ...
Creating home directory `/home/admin' ...
Copying files from `/etc/skel' ...
New password:
Retype new password:
passwd: password updated successfully
Changing the user information for admin
Enter the new value, or press ENTER for the default
Full Name []:
Room Number []:
Work Phone []:
Home Phone []:
Other []:
Is the information correct? [Y/n] y
```

```
cumulus@sw1:mgmt:~$ sudo adduser admin sudo
[sudo] password for cumulus:
Adding user `admin' to group `sudo' ...
Adding user admin to group sudo
Done.
cumulus@sw1:mgmt:~$ exit
logout
Connection to 10.233.204.71 closed.
```

```
[admin@cycrh6svl01 ~]$ ssh admin@10.233.204.71
admin@10.233.204.71's password:
Linux sw1 4.19.0-cl-1-amd64 #1 SMP Cumulus 4.19.206-1+cl4.4.1u1 (2021-
09-09) x86_64
Welcome to NVIDIA Cumulus (R) Linux (R)
```

For support and online technical documentation, visit
<http://www.cumulusnetworks.com/support>

The registered trademark Linux (R) is used pursuant to a sublicense from LMI, the exclusive licensee of Linus Torvalds, owner of the mark on a world-wide basis.
admin@sw1:mgmt:~\$

Install Cumulus Linux in ONIE mode

Cumulus Linux (CL) OS can be installed either when the switch is running Cumulus Linux or ONIE.

Before you begin

You can install the Cumulus Linux using Open Network Install Environment (ONIE) that allows for automatic discovery of a network installer image. This facilitates the system model of securing switches with an operating system choice, such as Cumulus Linux. The easiest way to install Cumulus Linux with ONIE is with local HTTP discovery.



If your host is IPv6-enabled, make sure it is running a web server. If your host is IPv4-enabled, make sure it is running DHCP in addition to a web server.

This procedure demonstrates how to upgrade Cumulus Linux after the admin has booted in ONIE.

Steps

1. Download the Cumulus Linux installation file to the root directory of the web server. Rename this file `onie-installer`.
2. Connect your host to the management Ethernet port of the switch using an Ethernet cable.
3. Power on the switch. The switch downloads the ONIE image installer and boots. After the installation completes, the Cumulus Linux login prompt appears in the terminal window.



Each time Cumulus Linux is installed, the entire file system structure is erased and rebuilt.

4. Reboot the SN2100 switch:

```
cumulus@cumulus:mgmt:~$ sudo reboot
```

5. Hit the **Esc** key at the GNU GRUB screen to interrupt the normal boot process, select **ONIE** and press Enter.
6. On the next screen displayed, select **ONIE: Install OS**.
7. The ONIE installer discovery process runs searching for the automatic installation. Press Enter to temporarily stop the process.
8. When the discovery process has stopped:

```
ONIE:/ # onie-stop  
discover: installer mode detected.  
Stopping: discover...start-stop-daemon: warning: killing process 427:  
No such process done.
```

9. If the DHCP service is running on your network, verify that the IP address, subnet mask, and the default gateway are correctly assigned:

```

ONIE:/ # ifconfig eth0
eth0    Link encap:Ethernet  HWaddr B8:CE:F6:19:1D:F6
        inet addr:10.233.204.71  Bcast:10.233.205.255  Mask:255.255.254.0
        inet6 addr: fe80::bace:f6ff:fe19:1df6/64 Scope:Link
        UP BROADCAST RUNNING MULTICAST  MTU:1500  Metric:1
        RX packets:21344 errors:0 dropped:2135 overruns:0 frame:0
        TX packets:3500 errors:0 dropped:0 overruns:0 carrier:0
        collisions:0 txqueuelen:1000
        RX bytes:6119398 (5.8 MiB)  TX bytes:472975 (461.8 KiB)
        Memory:dfc00000-dfc1ffff

ONIE:/ # route
Kernel IP routing table
Destination        Gateway            Genmask           Flags Metric Ref    Use
Iface

default            10.233.204.1      0.0.0.0           UG      0      0      0
eth0
10.233.204.0       *                  255.255.254.0     U        0      0      0
eth0

```

10. If the IP addressing scheme is manually defined, do the following:

```

ONIE:/ # ifconfig eth0 10.233.204.71 netmask 255.255.254.0
ONIE:/ # route add default gw 10.233.204.1

```

11. Repeat step 9 to verify that the static information is correctly entered.
12. Install Cumulus Linux:

```
ONIE:/ # route
```

```
Kernel IP routing table
```

```
ONIE:/ # onie-nos-install
```

```
http://10.60.132.97/x/eng/testbedN,svl/nic/files/cumulus-linux-4.4.2-mlx-amd64.bin
```

```
Stopping: discover... done.
```

```
Info: Attempting
```

```
http://10.60.132.97/x/eng/testbedN,svl/nic/files/cumulus-linux-4.4.2-mlx-amd64.bin ...
```

```
Connecting to 10.60.132.97 (10.60.132.97:80)
```

```
installer          100% |*|    552M  0:00:00 ETA
```

```
...
```

```
...
```

13. Once the installation has completed, log in to the switch:

```
cumulus login: cumulus
```

```
Password: cumulus
```

```
You are required to change your password immediately (administrator enforced)
```

```
Changing password for cumulus.
```

```
Current password: cumulus
```

```
New password: netappl!
```

```
Retype new password: netappl!
```

14. Verify the Cumulus Linux version:

```
cumulus@cumulus:mgmt:~$ net show version
```

```
NCLU_VERSION=1.0-cl4.4.2u4
```

```
DISTRIB_ID="Cumulus Linux"
```

```
DISTRIB_RELEASE=4.4.2
```

```
DISTRIB_DESCRIPTION="Cumulus Linux 4.4.2"
```

Install the RCF script

Before installing the RCF script, ensure that the following are available on the switch:

- Cumulus Linux 4.4.2 is installed.
- IP address, subnet mask, and default gateway defined via DHCP or manually configured.



See [Cabling and configuration considerations](#) for caveats and further details.

Current RCF script versions

There are two RCF scripts available for Clustering and Storage applications. The procedure for each is the same.

- Clustering: **MSN2100-RCF-v1.8-Cluster**
- Storage: **MSN2100-RCF-v1.8-Storage**



The following example procedure shows how to download and apply the RCF script for Clusters.

Steps

1. Display the available interfaces on the SN2100 switch:

```
cumulus@cumulus:mgmt:~$ net show interface all
```

State	Name	Spd	MTU	Mode	LLDP	Summary
-----	-----	---	-----	-----	-----	
...						
...						
ADMDN	swp1	N/A	9216	NotConfigured		
ADMDN	swp2	N/A	9216	NotConfigured		
ADMDN	swp3	N/A	9216	NotConfigured		
ADMDN	swp4	N/A	9216	NotConfigured		
ADMDN	swp5	N/A	9216	NotConfigured		
ADMDN	swp6	N/A	9216	NotConfigured		
ADMDN	swp7	N/A	9216	NotConfigure		
ADMDN	swp8	N/A	9216	NotConfigured		
ADMDN	swp9	N/A	9216	NotConfigured		
ADMDN	swp10	N/A	9216	NotConfigured		
ADMDN	swp11	N/A	9216	NotConfigured		
ADMDN	swp12	N/A	9216	NotConfigured		
ADMDN	swp13	N/A	9216	NotConfigured		
ADMDN	swp14	N/A	9216	NotConfigured		
ADMDN	swp15	N/A	9216	NotConfigured		
ADMDN	swp16	N/A	9216	NotConfigured		

2. Copy the RCF script to the switch:

```
cumulus@cumulus:mgmt:~$ pwd
/home/cumulus
cumulus@cumulus:mgmt: /tmp$ scp
ssologin@10.60.132.97:/x/eng/testbedN,svl/nic/files/MSN2100-RCF-v1.8-
Cluster
ssologin@10.60.132.97's password:
MSN2100-RCF-v1.8-Cluster          100% 8607    111.2KB/s
00:00
```

3. Apply the RCF script **MSN2100-RCF-v1.8-Cluster**:

```
cumulus@cumulus:mgmt:/tmp$ sudo python3 MSN2100-RCF-v1.8-Cluster
[sudo] password for cumulus:
...
```

The RCF script completes the following steps:

- a. Updates the banner MOTD
- b. Disables the apt-get for OS updates
- c. Defines breakout and non-breakout interfaces
- d. Configures interfaces and SNMP
- e. Disables CDP
- f. Changes the LLDP configuration
- g. Adds a RoCE configuration
- h. Modifies the RoCE configuration for HA and Cluster RDMA
- i. Reboots the switch

4. Verify the configuration after the reboot:

```
cumulus@cumulus:mgmt:~$ net show interface all
```

State	Name	Spd	MTU	Mode	LLDP	Summary
...						
...						
DN	swp1s0	N/A	9216	Trunk/L2		Master:
	bridge(UP)					
DN	swp1s1	N/A	9216	Trunk/L2		Master:
	bridge(UP)					
DN	swp1s2	N/A	9216	Trunk/L2		Master:
	bridge(UP)					
DN	swp1s3	N/A	9216	Trunk/L2		Master:
	bridge(UP)					

DN	swp2s0	N/A	9216	Trunk/L2	Master:
bridge(UP)					
DN	swp2s1	N/A	9216	Trunk/L2	Master:
bridge(UP)					
DN	swp2s2	N/A	9216	Trunk/L2	Master:
bridge(UP)					
DN	swp2s3	N/A	9216	Trunk/L2	Master:
bridge(UP)					
UP	swp3	100G	9216	Trunk/L2	Master:
bridge(UP)					
UP	swp4	100G	9216	Trunk/L2	Master:
bridge(UP)					
DN	swp5	N/A	9216	Trunk/L2	Master:
bridge(UP)					
DN	swp6	N/A	9216	Trunk/L2	Master:
bridge(UP)					
DN	swp7	N/A	9216	Trunk/L2	Master:
bridge(UP)					
DN	swp8	N/A	9216	Trunk/L2	Master:
bridge(UP)					
DN	swp9	N/A	9216	Trunk/L2	Master:
bridge(UP)					
DN	swp10	N/A	9216	Trunk/L2	Master:
bridge(UP)					
DN	swp11	N/A	9216	Trunk/L2	Master:
bridge(UP)					
DN	swp12	N/A	9216	Trunk/L2	Master:
bridge(UP)					
DN	swp13	N/A	9216	Trunk/L2	Master:
bridge(UP)					
DN	swp14	N/A	9216	Trunk/L2	Master:
bridge(UP)					
UP	swp15	N/A	9216	BondMember	Master:
bond_15_16(UP)					
UP	swp16	N/A	9216	BondMember	Master:
bond_15_16(UP)					
...					
...					

```
cumulus@cumulus:mgmt:~$ net show roce config
```

```
RoCE mode..... lossless
```

```
Congestion Control:
```

```
Enabled SPs.... 0 2 5
```

```
Mode..... ECN
```

```
Min Threshold.. 150 KB
```

```
Max Threshold.. 1500 KB
```


PFC:

Status..... enabled

Enabled SPs.... 2 5

Interfaces..... swp10-16,swp1s0-3,swp2s0-3,swp3-9

DSCP	802.1p	switch-priority
0 1 2 3 4 5 6 7	0	0
8 9 10 11 12 13 14 15	1	1
16 17 18 19 20 21 22 23	2	2
24 25 26 27 28 29 30 31	3	3
32 33 34 35 36 37 38 39	4	4
40 41 42 43 44 45 46 47	5	5
48 49 50 51 52 53 54 55	6	6
56 57 58 59 60 61 62 63	7	7

switch-priority	TC	ETS
0 1 3 4 6 7	0	DWRR 28%
2	2	DWRR 28%
5	5	DWRR 43%

5. Verify information for the transceiver in the interface. `net show interface pluggables`

```
cumulus@cumulus:mgmt:~$ net show interface pluggables
```

Interface	Identifier	Vendor	Name	Vendor PN	Vendor SN
Vendor	Rev				
swp3	0x11 (QSFP28)	Amphenol		112-00574	APF20379253516
B0					
swp4	0x11 (QSFP28)	AVAGO		332-00440	AF1815GU05Z
A0					
swp15	0x11 (QSFP28)	Amphenol		112-00573	APF21109348001
B0					
swp16	0x11 (QSFP28)	Amphenol		112-00573	APF21109347895
B0					

6. Verify that the nodes each have a connection to each switch: `net show lldp`

```
cumulus@cumulus:mgmt:~$ net show lldp
```

LocalPort	Speed	Mode	RemoteHost	RemotePort
swp3	100G	Trunk/L2	sw1	e3a
swp4	100G	Trunk/L2	sw2	e3b
swp15	100G	BondMember	sw13	swp15
swp16	100G	BondMember	sw14	swp16

7. Verify the health of cluster ports on the cluster.

- a. Verify that e0d ports are up and healthy across all nodes in the cluster: `network port show -role cluster`

```
cluster1::~*> network port show -role cluster
```

Node: node1

Ignore

Health	Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
	e3a	Cluster	Cluster		up	9000	auto/10000	healthy
	e3b	Cluster	Cluster		up	9000	auto/10000	healthy

Node: node2

Ignore

Health	Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
	e3a	Cluster	Cluster		up	9000	auto/10000	healthy
	e3b	Cluster	Cluster		up	9000	auto/10000	healthy

- b. Verify the switch health from the cluster (this might not show switch sw2, since LIFs are not homed on

e0d).

```
cluster1::*> network device-discovery show -protocol lldp
```

Node/ Protocol	Local Port	Discovered Device (LLDP: ChassisID)	Interface	Platform

node1/lldp				
	e3a	sw1 (b8:ce:f6:19:1a:7e)	swp3	-
	e3b	sw2 (b8:ce:f6:19:1b:96)	swp3	-
node2/lldp				
	e3a	sw1 (b8:ce:f6:19:1a:7e)	swp4	-
	e3b	sw2 (b8:ce:f6:19:1b:96)	swp4	-

```
cluster1::*> system switch ethernet show -is-monitoring-enabled  
-operational true
```

Switch	Type	Address	Model

sw1	cluster-network	10.233.205.90	
MSN2100-CB2RC			
Serial Number: MNXXXXXXGD			
Is Monitored: true			
Reason: None			
Software Version: Cumulus Linux version 4.4.2 running on Mellanox Technologies Ltd. MSN2100			
Version Source: LLDP			
sw2	cluster-network	10.233.205.91	
MSN2100-CB2RC			
Serial Number: MNCXXXXXXGS			
Is Monitored: true			
Reason: None			
Software Version: Cumulus Linux version 4.4.2 running on Mellanox Technologies Ltd. MSN2100			
Version Source: LLDP			

Cable NS224 shelves as switch-attached storage

If you have a system in which the NS224 drive shelves need to be cabled as switch-attached storage (not direct-attached storage), use the information provided here.

- Cable NS224 drive shelves through storage switches:

[Information for cabling switch-attached NS224 drive shelves](#)

- Install your storage switches:

[AFF and FAS Switch Documentation](#)

- Confirm supported hardware, such as storage switches and cables, for your platform model:

[NetApp Hardware Universe](#)

Migrate from a Cisco cluster switch to a NVIDIA SN2100 cluster switch

You can migrate nondisruptively Cisco cluster switches for an ONTAP cluster to NVIDIA SN2100 cluster switches. You must be aware of certain configuration information, port connections and cabling requirements when you are replacing some older Cisco cluster switches with NVIDIA SN2100 cluster switches.

The following Cisco cluster switches are supported:

- Nexus 9336C-FX2
- Nexus 92300YC
- Nexus 5596UP
- Nexus 3232C
- Nexus 3132Q-V

Before you begin

You can migrate nondisruptively older Cisco cluster switches for an ONTAP cluster to NVIDIA SN2100 cluster switches.

- The existing cluster must be properly set up and functioning.
- All cluster ports must be in the up state to ensure nondisruptive operations.
- The NVIDIA SN2100 cluster switches must be configured and operating under the proper version of Cumulus Linux installed with the reference configuration file (RCF) applied.
- The existing cluster network configuration must have the following:
 - A redundant and fully functional NetApp cluster using both older Cisco switches.
 - Management connectivity and console access to both the older Cisco switches and the new switches.
 - All cluster LIFs in the up state with the cluster LIFs are on their home ports.
 - ISL ports enabled and cabled between the older Cisco switches and between the new switches.
- See the [Hardware Universe](#) for full details of supported ports and their configurations.
- You have configured some of the ports on NVIDIA SN2100 switches to run at 40 GbE or 100 GbE.
- You have planned, migrated, and documented 40 GbE and 100 GbE connectivity from nodes to NVIDIA SN2100 cluster switches.



In this procedure, Cisco Nexus 3232C cluster switches are used for example commands and outputs.

About this task

The examples in this procedure use the following switch and node nomenclature:

- The existing Cisco Nexus 3232C cluster switches are *c1* and *c2*.
- The new NVIDIA SN2100 cluster switches are *sw1* and *sw2*.
- The nodes are *node1* and *node2*.
- The cluster LIFs are *node1_clus1* and *node1_clus2* on node 1, and *node2_clus1* and *node2_clus2* on node 2 respectively.
- The `cluster1::*>` prompt indicates the name of the cluster.
- The cluster ports used in this procedure are *e3a* and *e3b*.
- Breakout ports take the format: `swp[port]s[breakout port 0-3]`. For example, four breakout ports on `swp1` are *swp1s0*, *swp1s1*, *swp1s2*, and *swp1s3*.
- Switch *c2* is replaced by switch *sw2* first and then switch *c1* is replaced by switch *sw1*.
 - Cabling between the nodes and *c2* are then disconnected from *c2* and reconnected to *sw2*.
 - Cabling between the nodes and *c1* are then disconnected from *c1* and reconnected to *sw1*.

Steps

1. If AutoSupport is enabled on this cluster, suppress automatic case creation by invoking an AutoSupport message: `system node autosupport invoke -node * -type all -message MAINT=xh`

where *x* is the duration of the maintenance window in hours.

2. Change the privilege level to advanced, entering *y* when prompted to continue: `set -privilege advanced`

The advanced prompt (**>*) appears.

3. Disable auto-revert on the cluster LIFs: `network interface modify -vserver Cluster -lif * -auto-revert false`

```
cluster1::*> network interface modify -vserver Cluster -lif * -auto-revert false
```

```
Warning: Disabling the auto-revert feature of the cluster logical interface may effect the availability of your cluster network. Are you sure you want to continue? {y|n}: y
```

```
4 entries were modified.
```

4. Determine the administrative or operational status for each cluster interface:

Each port should display up for Link and healthy for Health Status.

- a. Display the network port attributes: `network port show -ipspace Cluster`

```
cluster1::*> network port show -ipspace Cluster
```

```
Node: node1
```

```
Ignore
```

						Speed(Mbps)	Health
Health							
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
Status							
-----	-----	-----	-----	----	-----	-----	
-----	-----						
e3a	Cluster	Cluster		up	9000	auto/100000	healthy
false							
e3b	Cluster	Cluster		up	9000	auto/100000	healthy
false							

```
Node: node2
```

```
Ignore
```

						Speed(Mbps)	Health
Health							
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
Status							
-----	-----	-----	-----	----	-----	-----	
-----	-----						
e3a	Cluster	Cluster		up	9000	auto/100000	healthy
false							
e3b	Cluster	Cluster		up	9000	auto/100000	healthy
false							

- b. Display information about the logical interfaces and their designated home nodes: `network interface show -vserver Cluster`

Each LIF should display up/up for Status Admin/Oper and true for Is Home.

```
cluster1::*> network interface show -vserver Cluster
```

	Logical	Status	Network	Current
Current Is				
Vserver	Interface	Admin/Oper	Address/Mask	Node
Port	Home			

Cluster				
e3a	node1_clus1	up/up	169.254.209.69/16	node1
e3b	node1_clus2	up/up	169.254.49.125/16	node1
e3a	node2_clus1	up/up	169.254.47.194/16	node2
e3b	node2_clus2	up/up	169.254.19.183/16	node2

5. The cluster ports on each node are connected to existing cluster switches in the following way (from the nodes' perspective) using the command: `network device-discovery show -protocol lldp`

```
cluster1::*> network device-discovery show -protocol lldp
```

Node/	Local	Discovered		
Protocol	Port	Device (LLDP: ChassisID)	Interface	Platform

node1	/lldp			
	e3a	c1 (6a:ad:4f:98:3b:3f)	Eth1/1	-
	e3b	c2 (6a:ad:4f:98:4c:a4)	Eth1/1	-
node2	/lldp			
	e3a	c1 (6a:ad:4f:98:3b:3f)	Eth1/2	-
	e3b	c2 (6a:ad:4f:98:4c:a4)	Eth1/2	-

6. The cluster ports and switches are connected in the following way (from the switches' perspective) using the command: `show cdp neighbors`

```
c1# show cdp neighbors
```

Capability Codes: R - Router, T - Trans-Bridge, B - Source-Route-Bridge
S - Switch, H - Host, I - IGMP, r - Repeater,
V - VoIP-Phone, D - Remotely-Managed-Device,
s - Supports-STP-Dispute

Device-ID Port ID	Local Intrfce	Hldtme	Capability	Platform
node1 e3a	Eth1/1	124	H	AFF-A400
node2 e3a	Eth1/2	124	H	AFF-A400
c2 Eth1/31	Eth1/31	179	S I s	N3K-C3232C
c2 Eth1/32	Eth1/32	175	S I s	N3K-C3232C

```
c2# show cdp neighbors
```

Capability Codes: R - Router, T - Trans-Bridge, B - Source-Route-Bridge
S - Switch, H - Host, I - IGMP, r - Repeater,
V - VoIP-Phone, D - Remotely-Managed-Device,
s - Supports-STP-Dispute

Device-ID Port ID	Local Intrfce	Hldtme	Capability	Platform
node1 e3b	Eth1/1	124	H	AFF-A400
node2 e3b	Eth1/2	124	H	AFF-A400
c1 Eth1/31	Eth1/31	175	S I s	N3K-C3232C
c1 Eth1/32	Eth1/32	175	S I s	N3K-C3232C

7. Ensure that the cluster network has full connectivity using the command: `cluster ping-cluster -node node-name`


```

cluster1::*> cluster ping-cluster -node node2

Host is node2
Getting addresses from network interface table...
Cluster node1_clus1 169.254.209.69 node1      e3a
Cluster node1_clus2 169.254.49.125 node1      e3b
Cluster node2_clus1 169.254.47.194 node2      e3a
Cluster node2_clus2 169.254.19.183 node2      e3b
Local = 169.254.47.194 169.254.19.183
Remote = 169.254.209.69 169.254.49.125
Cluster Vserver Id = 4294967293
Ping status:
....
Basic connectivity succeeds on 4 path(s)
Basic connectivity fails on 0 path(s)
.....
Detected 9000 byte MTU on 4 path(s):
    Local 169.254.19.183 to Remote 169.254.209.69
    Local 169.254.19.183 to Remote 169.254.49.125
    Local 169.254.47.194 to Remote 169.254.209.69
    Local 169.254.47.194 to Remote 169.254.49.125
Larger than PMTU communication succeeds on 4 path(s)
RPC status:
2 paths up, 0 paths down (tcp check)
2 paths up, 0 paths down (udp check)

```

8. On switch c2, shut down the ports connected to the cluster ports of the nodes.

```

(c2)# configure
Enter configuration commands, one per line. End with CNTL/Z.

(c2) (Config)# interface
(c2) (config-if-range)# shutdown interface-list
(c2) (config-if-range)# exit
(c2) (Config)# exit
(c2)#

```

9. Move the node cluster ports from the old switch c2 to the new switch sw2, using appropriate cabling supported by NVIDIA SN2100.
10. Display the network port attributes: `network port show -ipspace Cluster`

```
cluster1::*> network port show -ipspace Cluster
```

Node: node1

Ignore

						Speed (Mbps)	Health
Health							
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
Status							
-----	-----	-----	-----	-----	-----	-----	-----
e3a	Cluster	Cluster		up	9000	auto/100000	healthy
false							
e3b	Cluster	Cluster		up	9000	auto/100000	healthy
false							

Node: node2

Ignore

						Speed (Mbps)	Health
Health							
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
Status							
-----	-----	-----	-----	-----	-----	-----	-----
e3a	Cluster	Cluster		up	9000	auto/100000	healthy
false							
e3b	Cluster	Cluster		up	9000	auto/100000	healthy
false							

11. The cluster ports on each node are now connected to cluster switches in the following way, from the nodes' perspective:

```
cluster1::*> network device-discovery show -protocol lldp
```

Node/ Protocol	Local Port	Discovered Device (LLDP: ChassisID)	Interface	Platform
node1	/lldp			
	e3a	c1 (6a:ad:4f:98:3b:3f)	Eth1/1	-
	e3b	sw2 (b8:ce:f6:19:1a:7e)	swp3	-
node2	/lldp			
	e3a	c1 (6a:ad:4f:98:3b:3f)	Eth1/2	-
	e3b	sw2 (b8:ce:f6:19:1b:96)	swp4	-

12. On switch sw2, verify that all node cluster ports are up: `net show interface`

```
cumulus@sw2:~$ net show interface
```

State	Name	Spd	MTU	Mode	LLDP	Summary
...						
UP	swp3	100G	9216	Trunk/L2	e3b	Master:
bridge(UP)						
UP	swp4	100G	9216	Trunk/L2	e3b	Master:
bridge(UP)						
UP	swp15	100G	9216	BondMember	sw1 (swp15)	Master:
cluster_isl(UP)						
UP	swp16	100G	9216	BondMember	sw1 (swp16)	Master:
cluster_isl(UP)						

13. On switch c1, shut down the ports connected to the cluster ports of the nodes.

```
(c1)# configure
Enter configuration commands, one per line. End with CNTL/Z.

(c1) (Config)# interface
(c1) (config-if-range)# shutdown interface-list
(c1) (config-if-range)# exit
(c1) (Config)# exit
(c1)#
```

14. Move the node cluster ports from the old switch c1 to the new switch sw1, using appropriate cabling

supported by NVIDIA SN2100.

15. Verify the final configuration of the cluster: `network port show -ipspace Cluster`

Each port should display up for Link and healthy for Health Status.

```
cluster1::*> network port show -ipspace Cluster
```

```
Node: node1
```

```
Ignore
```

					Speed (Mbps)	Health
Health						
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper
Status						Status
-----	-----	-----	-----	-----	-----	-----
e3a	Cluster	Cluster		up	9000	auto/100000
false						healthy
e3b	Cluster	Cluster		up	9000	auto/100000
false						healthy

```
Node: node2
```

```
Ignore
```

					Speed (Mbps)	Health
Health						
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper
Status						Status
-----	-----	-----	-----	-----	-----	-----
e3a	Cluster	Cluster		up	9000	auto/100000
false						healthy
e3b	Cluster	Cluster		up	9000	auto/100000
false						healthy

16. The cluster ports on each node are now connected to cluster switches in the following way, from the nodes' perspective:

```
cluster1::*> network device-discovery show -protocol lldp
```

Node/ Protocol	Local Port	Discovered Device (LLDP: ChassisID)	Interface	Platform

node1	/lldp			
	e3a	sw1 (b8:ce:f6:19:1a:7e)	swp3	-
	e3b	sw2 (b8:ce:f6:19:1b:96)	swp3	-
node2	/lldp			
	e3a	sw1 (b8:ce:f6:19:1a:7e)	swp4	-
	e3b	sw2 (b8:ce:f6:19:1b:96)	swp4	-

17. On switches sw1 and sw2, verify that all node cluster ports are up: `net show interface`

```
cumulus@sw1:~$ net show interface
```

State	Name	Spd	MTU	Mode	LLDP	Summary
-----	-----	----	-----	-----	-----	

...						
...						
UP	swp3	100G	9216	Trunk/L2	e3a	Master:
bridge (UP)						
UP	swp4	100G	9216	Trunk/L2	e3a	Master:
bridge (UP)						
UP	swp15	100G	9216	BondMember	sw2 (swp15)	Master:
cluster_isl (UP)						
UP	swp16	100G	9216	BondMember	sw2 (swp16)	Master:
cluster_isl (UP)						

```
cumulus@sw2:~$ net show interface
```

State	Name	Spd	MTU	Mode	LLDP	Summary
-----	-----	----	-----	-----	-----	

...						
...						
UP	swp3	100G	9216	Trunk/L2	e3b	Master:
bridge (UP)						
UP	swp4	100G	9216	Trunk/L2	e3b	Master:
bridge (UP)						
UP	swp15	100G	9216	BondMember	sw1 (swp15)	Master:
cluster_isl (UP)						
UP	swp16	100G	9216	BondMember	sw1 (swp16)	Master:
cluster_isl (UP)						

18. Verify that both nodes each have one connection to each switch: `net show lldp`

The following example shows the appropriate results for both switches:

```
cumulus@sw1:~$ net show lldp
```

LocalPort	Speed	Mode	RemoteHost	RemotePort
swp3	100G	Trunk/L2	node1	e3a
swp4	100G	Trunk/L2	node2	e3a
swp15	100G	BondMember	sw2	swp15
swp16	100G	BondMember	sw2	swp16

```
cumulus@sw2:~$ net show lldp
```

LocalPort	Speed	Mode	RemoteHost	RemotePort
swp3	100G	Trunk/L2	node1	e3b
swp4	100G	Trunk/L2	node2	e3b
swp15	100G	BondMember	sw1	swp15
swp16	100G	BondMember	sw1	swp16

19. Enable auto-revert on the cluster LIFs: `cluster1::*> network interface modify -vserver Cluster -lif * -auto-revert true`

20. Verify that all cluster network LIFs are back on their home ports: `network interface show`

```
cluster1::*> network interface show -vserver Cluster
```

Current Is	Logical	Status	Network	Current	
Vserver	Interface	Admin/Oper	Address/Mask	Node	Port
Home					
Cluster					
true	node1_clus1	up/up	169.254.209.69/16	node1	e3a
true	node1_clus2	up/up	169.254.49.125/16	node1	e3b
true	node2_clus1	up/up	169.254.47.194/16	node2	e3a
true	node2_clus2	up/up	169.254.19.183/16	node2	e3b

21. Enable the Ethernet switch health monitor log collection feature for collecting switch-related log files, using the two commands: `system switch ethernet log setup-password` and `system switch ethernet log enable-collection`

Enter: `system switch ethernet log setup-password`

```
cluster1::*> system switch ethernet log setup-password
Enter the switch name: <return>
The switch name entered is not recognized.
Choose from the following list:
sw1
sw2

cluster1::*> system switch ethernet log setup-password

Enter the switch name: sw1
RSA key fingerprint is e5:8b:c6:dc:e2:18:18:09:36:63:d9:63:dd:03:d9:cc
Do you want to continue? {y|n}::[n] y

Enter the password: <enter switch password>
Enter the password again: <enter switch password>

cluster1::*> system switch ethernet log setup-password

Enter the switch name: sw2
RSA key fingerprint is 57:49:86:a1:b9:80:6a:61:9a:86:8e:3c:e3:b7:1f:b1
Do you want to continue? {y|n}:: [n] y

Enter the password: <enter switch password>
Enter the password again: <enter switch password>
```

Followed by: `system switch ethernet log enable-collection`

```
cluster1::*> system switch ethernet log enable-collection

Do you want to enable cluster log collection for all nodes in the
cluster?
{y|n}: [n] y

Enabling cluster switch log collection.

cluster1::*>
```



If any of these commands return an error, contact NetApp support.

22. Initiate the switch log collection feature: `system switch ethernet log collect -device *`

Wait for 10 minutes and then check that the log collection was successful using the command: `system switch ethernet log show`


```
cluster1::*> system switch ethernet log show
Log Collection Enabled: true
```

Index	Switch	Log Timestamp	Status
1	sw1 (b8:ce:f6:19:1b:42)	4/29/2022 03:05:25	complete
2	sw2 (b8:ce:f6:19:1b:96)	4/29/2022 03:07:42	complete

23. Change the privilege level back to admin: `set -privilege admin`

24. If you suppressed automatic case creation, reenable it by invoking an AutoSupport message: `system node autosupport invoke -node * -type all -message MAINT=END`

Migrate from a Cisco storage switch to a NVIDIA SN2100 storage switch

You must be aware of certain configuration information, port connections and cabling requirements when you are replacing some older Cisco switches with NVIDIA SN2100 storage switches.

- The following storage switches are supported:
 - Cisco Nexus 9336C-FX2
 - Cisco Nexus 3232C
- See the [Hardware Universe](#) for full details of supported ports and their configurations.

Before you begin

You can migrate nondisruptively older Cisco storage switches for an ONTAP cluster to NVIDIA SN2100 storage switches.

- The existing cluster must be properly set up and functioning.
- All storage ports must be in the up state to ensure nondisruptive operations.
- The NVIDIA SN2100 storage switches must be configured and operating under the proper version of Cumulus Linux installed with the reference configuration file (RCF) applied.
- The existing storage network configuration must have the following:
 - A redundant and fully functional NetApp cluster using both older Cisco switches.
 - Management connectivity and console access to both the older Cisco switches and the new switches.
 - All cluster LIFs in the up state with the cluster LIFs are on their home ports.
 - ISL ports enabled and cabled between the older Cisco switches and between the new switches.
- See the [Hardware Universe](#) for full details of supported ports and their configurations.
- You have configured some of the ports on NVIDIA SN2100 switches to run at 100 GbE.
- You have planned, migrated, and documented 100 GbE connectivity from nodes to NVIDIA SN2100 storage switches.



In this procedure, Cisco Nexus 9336C-FX2 storage switches are used for example commands and outputs.

About this task

The examples in this procedure use the following switch and node nomenclature:

- The existing Cisco Nexus 9336C-FX2 storage switches are *S1* and *S2*.
- The new NVIDIA SN2100 storage switches are *sw1* and *sw2*.
- The nodes are *node1* and *node2*.
- The cluster LIFs are *node1_clus1* and *node1_clus2* on node 1, and *node2_clus1* and *node2_clus2* on node 2 respectively.
- The `cluster1::*>` prompt indicates the name of the cluster.
- The network ports used in this procedure are *e5a* and *e5b*.
- Breakout ports take the format: *swp1s0-3*. For example four breakout ports on *swp1* are *swp1s0*, *swp1s1*, *swp1s2*, and *swp1s3*.
- Switch *S2* is replaced by switch *sw2* first and then switch *S1* is replaced by switch *sw1*.
 - Cabling between the nodes and *S2* are then disconnected from *S2* and reconnected to *sw2*.
 - Cabling between the nodes and *S1* are then disconnected from *S1* and reconnected to *sw1*.

Steps

1. If AutoSupport is enabled, suppress automatic case creation by invoking an AutoSupport message:
`system node autosupport invoke -node * -type all -message MAINT=xh`

where *x* is the duration of the maintenance window in hours.

2. Change the privilege level to advanced, entering *y* when prompted to continue: `set -privilege advanced`

The advanced prompt (**>*) appears.

3. Determine the administrative or operational status for each storage interface:

Each port should display enabled for *Status*.

Display the network port attributes: `storage port show`

```
cluster1::*> storage port show
```

Node	Port	Type	Mode	Speed (Gb/s)	State	Status	VLAN ID

node1	e0c	ENET	storage	100	enabled	online	30
	e0d	ENET	storage	0	enabled	offline	30
	e5a	ENET	storage	0	enabled	offline	30
	e5b	ENET	storage	100	enabled	online	30
node2	e0c	ENET	storage	100	enabled	online	30
	e0d	ENET	storage	0	enabled	offline	30
	e5a	ENET	storage	0	enabled	offline	30
	e5b	ENET	storage	100	enabled	online	30

```
cluster1::*>
```

4. The storage ports on each node are connected to existing storage switches in the following way (from the nodes' perspective) using the command: `network device-discovery show -protocol lldp`

```
cluster1::*> network device-discovery show -protocol lldp
```

Node/ Protocol	Local Port	Discovered Device (LLDP: ChassisID)	Interface	Platform

node1	/lldp			
	e0c	S1 (7c:ad:4f:98:6d:f0)	Eth1/1	-
	e5b	S2 (7c:ad:4f:98:8e:3c)	Eth1/1	-
node2	/lldp			
	e0c	S1 (7c:ad:4f:98:6d:f0)	Eth1/2	-
	e5b	S2 (7c:ad:4f:98:8e:3c)	Eth1/2	-

5. On switch S1 and S2, the storage ports and switches are connected in the following way (from the switches' perspective) using the command: `show lldp neighbors`

S1# **show lldp neighbors**

Capability Codes: (R) Router, (B) Bridge, (T) Telephone, (C) DOCSIS
Cable Device,

(W) WLAN Access Point, (P) Repeater, (S) Station (O)

Other

Device-ID Port ID	Local Intf	Holdtime	Capability
node1 e0c	Eth1/1	121	S
node2 e0c	Eth1/2	121	S
SHFGD1947000186 e0a	Eth1/10	120	S
SHFGD1947000186 e0a	Eth1/11	120	S
SHFGB2017000269 e0a	Eth1/12	120	S
SHFGB2017000269 e0a	Eth1/13	120	S

S2# **show lldp neighbors**

Capability Codes: (R) Router, (B) Bridge, (T) Telephone, (C) DOCSIS
Cable Device,

(W) WLAN Access Point, (P) Repeater, (S) Station (O)

Other

Device-ID Port ID	Local Intf	Holdtime	Capability	
node1 e0b	Eth1/1	121	S	e5b
node2 e0b	Eth1/2	121	S	e5b
SHFGD1947000186 e0b	Eth1/10	120	S	
SHFGD1947000186 e0b	Eth1/11	120	S	
SHFGB2017000269 e0b	Eth1/12	120	S	
SHFGB2017000269 e0b	Eth1/13	120	S	e0b

6. On switch sw2, shut down the ports connected to the storage ports and nodes of the disk shelves.

```
cumulus@sw2:~$ net add interface swp1-16 link down
cumulus@sw2:~$ net pending
cumulus@sw2:~$ net commit
```

7. Move the node storage ports of the controller and disk shelves from the old switch S2 to the new switch sw2, using appropriate cabling supported by NVIDIA SN2100.
8. On switch sw2, bring up the ports connected to the storage ports of the nodes and the disk shelves.

```
cumulus@sw2:~$ net del interface swp1-16 link down
cumulus@sw2:~$ net pending
cumulus@sw2:~$ net commit
```

9. The storage ports on each node are now connected to the switches in the following way, from the nodes' perspective:

```
cluster1::~*> network device-discovery show -protocol lldp
```

Node/ Protocol	Local Port	Discovered Device (LLDP: ChassisID)	Interface	Platform
node1	/lldp			
	e0c	S1 (7c:ad:4f:98:6d:f0)	Eth1/1	-
	e5b	sw2 (b8:ce:f6:19:1a:7e)	swp1	-
node2	/lldp			
	e0c	S1 (7c:ad:4f:98:6d:f0)	Eth1/2	-
	e5b	sw2 (b8:ce:f6:19:1a:7e)	swp2	-

10. Verify the network port attributes: storage port show

```
cluster1::*> storage port show
```

Node	Port	Type	Mode	Speed (Gb/s)	State	Status	VLAN ID

node1							
	e0c	ENET	storage	100	enabled	online	30
	e0d	ENET	storage	0	enabled	offline	30
	e5a	ENET	storage	0	enabled	offline	30
	e5b	ENET	storage	100	enabled	online	30
node2							
	e0c	ENET	storage	100	enabled	online	30
	e0d	ENET	storage	0	enabled	offline	30
	e5a	ENET	storage	0	enabled	offline	30
	e5b	ENET	storage	100	enabled	online	30

```
cluster1::*>
```

11. On switch sw2, verify that all node storage ports are up:

```
cumulus@sw2:~$ net show interface
```

State	Name	Spd	MTU	Mode	LLDP	Summary

...						
...						
UP	swp1	100G	9216	Trunk/L2	node1 (e5b)	Master:
bridge(UP)						
UP	swp2	100G	9216	Trunk/L2	node2 (e5b)	Master:
bridge(UP)						
UP	swp3	100G	9216	Trunk/L2	SHFFG1826000112 (e0b)	Master:
bridge(UP)						
UP	swp4	100G	9216	Trunk/L2	SHFFG1826000112 (e0b)	Master:
bridge(UP)						
UP	swp5	100G	9216	Trunk/L2	SHFFG1826000102 (e0b)	Master:
bridge(UP)						
UP	swp6	100G	9216	Trunk/L2	SHFFG1826000102 (e0b)	Master:
bridge(UP)						
...						
...						

12. On switch sw1, shut down the ports connected to the storage ports of the nodes and the disk shelves.

```
cumulus@sw1:~$ net add interface swp1-16 link down
cumulus@sw1:~$ net pending
cumulus@sw1:~$ net commit
```

13. Move the node storage ports of the controller and the disk shelves from the old switch S1 to the new switch sw1, using appropriate cabling supported by NVIDIA SN2100.
14. On switch sw1, bring up the ports connected to the storage ports of the nodes and the disk shelves.

```
cumulus@sw1:~$ net del interface swp1-16 link down
cumulus@sw1:~$ net pending
cumulus@sw1:~$ net commit
```

15. The storage ports on each node are now connected to the switches in the following way, from the nodes' perspective:

```
cluster1::~*> network device-discovery show -protocol lldp
```

Node/ Protocol	Local Port	Discovered Device (LLDP: ChassisID)	Interface	Platform
node1	/lldp			
	e0c	sw1 (b8:ce:f6:19:1b:96)	swp1	-
	e5b	sw2 (b8:ce:f6:19:1a:7e)	swp1	-
node2	/lldp			
	e0c	sw1 (b8:ce:f6:19:1b:96)	swp2	-
	e5b	sw2 (b8:ce:f6:19:1a:7e)	swp2	-

16. Verify the final configuration: `storage port show`

Each port should display enabled for State and enabled for Status.

```
cluster1::~*> storage port show
```

Node	Port	Type	Mode	Speed (Gb/s)	State	Status	VLAN ID

node1							
	e0c	ENET	storage	100	enabled	online	30
	e0d	ENET	storage	0	enabled	offline	30
	e5a	ENET	storage	0	enabled	offline	30
	e5b	ENET	storage	100	enabled	online	30
node2							
	e0c	ENET	storage	100	enabled	online	30
	e0d	ENET	storage	0	enabled	offline	30
	e5a	ENET	storage	0	enabled	offline	30
	e5b	ENET	storage	100	enabled	online	30

```
cluster1::~*>
```

17. On switch sw2, verify that all node storage ports are up:

```
cumulus@sw2::~$ net show interface
```

State	Name	Spd	MTU	Mode	LLDP	Summary

...						
...						
UP	swp1	100G	9216	Trunk/L2	node1 (e5b)	Master:
bridge(UP)						
UP	swp2	100G	9216	Trunk/L2	node2 (e5b)	Master:
bridge(UP)						
UP	swp3	100G	9216	Trunk/L2	SHFFG1826000112 (e0b)	Master:
bridge(UP)						
UP	swp4	100G	9216	Trunk/L2	SHFFG1826000112 (e0b)	Master:
bridge(UP)						
UP	swp5	100G	9216	Trunk/L2	SHFFG1826000102 (e0b)	Master:
bridge(UP)						
UP	swp6	100G	9216	Trunk/L2	SHFFG1826000102 (e0b)	Master:
bridge(UP)						
...						
...						

18. Verify that both nodes each have one connection to each switch: `net show lldp`

The following example shows the appropriate results for both switches:


```
cumulus@sw1:~$ net show lldp
```

LocalPort	Speed	Mode	RemoteHost	RemotePort
...				
swp1	100G	Trunk/L2	node1	e0c
swp2	100G	Trunk/L2	node2	e0c
swp3	100G	Trunk/L2	SHFFG1826000112	e0a
swp4	100G	Trunk/L2	SHFFG1826000112	e0a
swp5	100G	Trunk/L2	SHFFG1826000102	e0a
swp6	100G	Trunk/L2	SHFFG1826000102	e0a

```
cumulus@sw2:~$ net show lldp
```

LocalPort	Speed	Mode	RemoteHost	RemotePort
...				
swp1	100G	Trunk/L2	node1	e5b
swp2	100G	Trunk/L2	node2	e5b
swp3	100G	Trunk/L2	SHFFG1826000112	e0b
swp4	100G	Trunk/L2	SHFFG1826000112	e0b
swp5	100G	Trunk/L2	SHFFG1826000102	e0b
swp6	100G	Trunk/L2	SHFFG1826000102	e0b

19. Enable the Ethernet switch health monitor log collection feature for collecting switch-related log files, using the two commands: `system switch ethernet log setup-password` and `system switch ethernet log enable-collection`

Enter: `system switch ethernet log setup-password`

```
cluster1::*> system switch ethernet log setup-password
```

```
Enter the switch name: <return>
```

```
The switch name entered is not recognized.
```

```
Choose from the following list:
```

```
sw1
```

```
sw2
```

```
cluster1::*> system switch ethernet log setup-password
```

```
Enter the switch name: sw1
```

```
RSA key fingerprint is e5:8b:c6:dc:e2:18:18:09:36:63:d9:63:dd:03:d9:cc
```

```
Do you want to continue? {y|n}::[n] y
```

```
Enter the password: <enter switch password>
```

```
Enter the password again: <enter switch password>
```

```
cluster1::*> system switch ethernet log setup-password
```

```
Enter the switch name: sw2
```

```
RSA key fingerprint is 57:49:86:a1:b9:80:6a:61:9a:86:8e:3c:e3:b7:1f:b1
```

```
Do you want to continue? {y|n}:: [n] y
```

```
Enter the password: <enter switch password>
```

```
Enter the password again: <enter switch password>
```

Followed by: `system switch ethernet log enable-collection`

```
cluster1::*> system switch ethernet log enable-collection
```

```
Do you want to enable cluster log collection for all nodes in the  
cluster?
```

```
{y|n}: [n] y
```

```
Enabling cluster switch log collection.
```

```
cluster1::*>
```



If any of these commands return an error, contact NetApp support.

20. Initiate the switch log collection feature: `system switch ethernet log collect -device *`

Wait for 10 minutes and then check that the log collection was successful using the command: `system switch ethernet log show`

```
cluster1::*> system switch ethernet log show
```

```
Log Collection Enabled: true
```

Index	Switch	Log Timestamp	Status
1	sw1 (b8:ce:f6:19:1b:42)	4/29/2022 03:05:25	complete
2	sw2 (b8:ce:f6:19:1b:96)	4/29/2022 03:07:42	complete

21. Change the privilege level back to admin: `set -privilege admin`

22. If you suppressed automatic case creation, reenable it by invoking an AutoSupport message: `system node autosupport invoke -node * -type all -message MAINT=END`

Migrate to a two-node switched cluster with NVIDIA SN2100 cluster switches

You must be aware of certain configuration information, port connections, and cabling requirements when you migrate a two-node switchless cluster, non-disruptively, to a cluster with NVIDIA SN2100 cluster switches. The procedure you use depends on whether you have two dedicated cluster-network ports on each controller or a single cluster port on each controller. The process documented works for all nodes using optical or Twinax ports but is not supported on this switch if nodes are using onboard 10GBASE-T RJ45 ports for the cluster-network ports.

Two-node switchless configuration

- The two-node switchless configuration must be properly set up and functioning.
- The nodes must be running ONTAP 9.10.1P3 and later.
- All cluster ports must be in the up state.
- All cluster logical interfaces (LIFs) must be in the up state and on their home ports.

NVIDIA SN2100 cluster switch configuration

- Both switches must have management network connectivity.
- There must be console access to the cluster switches.
- NVIDIA SN2100 node-to-node switch and switch-to-switch connections must use Twinax or fiber cables.



See [Cabling and configuration considerations](#) for caveats and further details.

The [Hardware Universe - Switches](#) contains more information about cabling.

- Inter-Switch Link (ISL) cables must be connected to ports swp15 and swp16 on both NVIDIA SN2100 switches.
- Initial customization of both the SN2100 switches must be completed. So that the:
 - SN2100 switches are running the latest version of Cumulus Linux
 - Reference Configuration Files (RCFs) have been applied to the switches

- Any site customization, such as SMTP, SNMP, and SSH must be configured on the new switches.

About this task

The examples in this procedure use the following cluster switch and node nomenclature:

- The names of the SN2100 switches are *sw1* and *sw2*.
- The names of the cluster SVMs are *node1* and *node2*.
- The names of the LIFs are *node1_clus1* and *node1_clus2* on node 1, and *node2_clus1* and *node2_clus2* on node 2 respectively.
- The `cluster1::*>` prompt indicates the name of the cluster.
- The cluster ports used in this procedure are *e3a* and *e3b*.
- Breakout ports take the format: `swp[port]s[breakout port 0-3]`. For example, four breakout ports on `swp1` are *swp1s0*, *swp1s1*, *swp1s2*, and *swp1s3*.

The [Hardware Universe](#) contains the latest information about the actual cluster ports for your platforms.

Steps

1. If AutoSupport is enabled on this cluster, suppress automatic case creation by invoking an AutoSupport message: `system node autosupport invoke -node * -type all -message MAINT=xh`

where *x* is the duration of the maintenance window in hours.

2. Change the privilege level to advanced, entering *y* when prompted to continue: `set -privilege advanced`

The advanced prompt (`*>`) appears.

3. Disable all node-facing ports (not ISL ports) on both the new cluster switches *sw1* and *sw2*.

You must not disable the ISL ports.

The following commands disable the node-facing ports on switches *sw1* and *sw2*:

```
cumulus@sw1:~$ net add interface swp1s0-3, swp2s0-3, swp3-14 link down
cumulus@sw1:~$ net pending
cumulus@sw1:~$ net commit

cumulus@sw2:~$ net add interface swp1s0-3, swp2s0-3, swp3-14 link down
cumulus@sw2:~$ net pending
cumulus@sw2:~$ net commit
```

4. Verify that the ISL and the physical ports on the ISL between the two SN2100 switches *sw1* and *sw2* are up on ports `swp15` and `swp16`: `net show interface`

The following example shows that the ISL ports are up on switch *sw1*:

```
cumulus@sw1:~$ net show interface
```

State	Name	Spd	MTU	Mode	LLDP	Summary
UP	swp15	100G	9216	BondMember	sw2 (swp15)	Master: cluster_isl (UP)
UP	swp16	100G	9216	BondMember	sw2 (swp16)	Master: cluster_isl (UP)

The following example shows that the ISL ports are up on switch sw2:

```
cumulus@sw2:~$ net show interface
```

State	Name	Spd	MTU	Mode	LLDP	Summary
UP	swp15	100G	9216	BondMember	sw1 (swp15)	Master: cluster_isl (UP)
UP	swp16	100G	9216	BondMember	sw1 (swp16)	Master: cluster_isl (UP)

5. Verify that all cluster ports are up: `network port show`

Each port should display up for Link and healthy for Health Status.

```
cluster1::*> network port show
```

```
Node: node1
```

```
Ignore
```

						Speed(Mbps)	Health
Health							
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
Status							
-----	-----	-----	-----	----	----	-----	-----

e3a	Cluster	Cluster		up	9000	auto/100000	healthy
false							
e3b	Cluster	Cluster		up	9000	auto/100000	healthy
false							

```
Node: node2
```

```
Ignore
```

						Speed(Mbps)	Health
Health							
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
Status							
-----	-----	-----	-----	----	----	-----	-----

e3a	Cluster	Cluster		up	9000	auto/100000	healthy
false							
e3b	Cluster	Cluster		up	9000	auto/100000	healthy
false							

6. Verify that all cluster LIFs are up and operational: `network interface show`

Each cluster LIF should display true for `Is Home` and have a `Status Admin/Oper` of `up/up`

```
cluster1::*> network interface show -vserver Cluster
```

	Logical	Status	Network	Current	
Current Is					
Vserver	Interface	Admin/Oper	Address/Mask	Node	Port
Home					
-----	-----	-----	-----	-----	-----
-----	-----				
Cluster					
	node1_clus1	up/up	169.254.209.69/16	node1	e3a
true					
	node1_clus2	up/up	169.254.49.125/16	node1	e3b
true					
	node2_clus1	up/up	169.254.47.194/16	node2	e3a
true					
	node2_clus2	up/up	169.254.19.183/16	node2	e3b
true					

7. Disable auto-revert on the cluster LIFs: `network interface modify -vserver Cluster -lif * -auto-revert false`

```
cluster1::*> network interface modify -vserver Cluster -lif * -auto-revert false
```

	Logical	
Vserver	Interface	Auto-revert
-----	-----	-----
Cluster		
	node1_clus1	false
	node1_clus2	false
	node2_clus1	false
	node2_clus2	false

8. Disconnect the cable from cluster port e3a on node1, and then connect e3a to port 3 on cluster switch sw1, using the appropriate cabling supported by the SN2100 switches.

The [Hardware Universe - Switches](#) contains more information about cabling.

9. Disconnect the cable from cluster port e3a on node2, and then connect e3a to port 4 on cluster switch sw1, using the appropriate cabling supported by the SN2100 switches.
10. On switch sw1, enable all node-facing ports.

The following command enables all node-facing ports on switch sw1:

```
cumulus@sw1:~$ net del interface swp1s0-3, swp2s0-3, swp3-14 link down
cumulus@sw1:~$ net pending
cumulus@sw1:~$ net commit
```

11. On switch sw1, verify that all ports are up: `net show interface all`

```
cumulus@sw1:~$ net show interface all
```

State	Name	Spd	MTU	Mode	LLDP	Summary
...						
DN	swp1s0	10G	9216	Trunk/L2		Master: br_default(UP)
DN	swp1s1	10G	9216	Trunk/L2		Master: br_default(UP)
DN	swp1s2	10G	9216	Trunk/L2		Master: br_default(UP)
DN	swp1s3	10G	9216	Trunk/L2		Master: br_default(UP)
DN	swp2s0	25G	9216	Trunk/L2		Master: br_default(UP)
DN	swp2s1	25G	9216	Trunk/L2		Master: br_default(UP)
DN	swp2s2	25G	9216	Trunk/L2		Master: br_default(UP)
DN	swp2s3	25G	9216	Trunk/L2		Master: br_default(UP)
UP	swp3	100G	9216	Trunk/L2	node1 (e3a)	Master: br_default(UP)
UP	swp4	100G	9216	Trunk/L2	node2 (e3a)	Master: br_default(UP)
...						
UP	swp15	100G	9216	BondMember	swp15	Master: cluster_isl(UP)
UP	swp16	100G	9216	BondMember	swp16	Master: cluster_isl(UP)
...						

12. Verify that all cluster ports are up: `network port show -ip space Cluster`

The following example shows that all of the cluster ports are up on node1 and node2:


```
cluster1::*> network port show -ipspace Cluster
```

Node: node1

Ignore

						Speed(Mbps)	Health
Health							
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
Status							
-----	-----	-----	-----	----	----	-----	-----
e3a	Cluster	Cluster		up	9000	auto/100000	healthy
false							
e3b	Cluster	Cluster		up	9000	auto/100000	healthy
false							

Node: node2

Ignore

						Speed(Mbps)	Health
Health							
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
Status							
-----	-----	-----	-----	----	----	-----	-----
e3a	Cluster	Cluster		up	9000	auto/100000	healthy
false							
e3b	Cluster	Cluster		up	9000	auto/100000	healthy
false							

13. Display information about the status of the nodes in the cluster: `cluster show`

The following example displays information about the health and eligibility of the nodes in the cluster:

```
cluster1::*> cluster show
```

Node	Health	Eligibility	Epsilon
-----	-----	-----	-----
node1	true	true	false
node2	true	true	false

14. Disconnect the cable from cluster port e3b on node1, and then connect e3b to port 3 on cluster switch sw2, using the appropriate cabling supported by the SN2100 switches.
15. Disconnect the cable from cluster port e3b on node2, and then connect e3b to port 4 on cluster switch sw2,

using the appropriate cabling supported by the SN2100 switches.

16. On switch sw2, enable all node-facing ports.

The following commands enable the node-facing ports on switch sw2:

```
cumulus@sw2:~$ net del interface swp1s0-3, swp2s0-3, swp3-14 link down
cumulus@sw2:~$ net pending
cumulus@sw2:~$ net commit
```

17. On switch sw2, verify that all ports are up: `net show interface all`

```
cumulus@sw2:~$ net show interface all
```

State	Name	Spd	MTU	Mode	LLDP	Summary
-----	-----	----	-----	-----	-----	-----
...						
DN	swp1s0	10G	9216	Trunk/L2		Master: br_default(UP)
DN	swp1s1	10G	9216	Trunk/L2		Master: br_default(UP)
DN	swp1s2	10G	9216	Trunk/L2		Master: br_default(UP)
DN	swp1s3	10G	9216	Trunk/L2		Master: br_default(UP)
DN	swp2s0	25G	9216	Trunk/L2		Master: br_default(UP)
DN	swp2s1	25G	9216	Trunk/L2		Master: br_default(UP)
DN	swp2s2	25G	9216	Trunk/L2		Master: br_default(UP)
DN	swp2s3	25G	9216	Trunk/L2		Master: br_default(UP)
UP	swp3	100G	9216	Trunk/L2	node1 (e3b)	Master: br_default(UP)
UP	swp4	100G	9216	Trunk/L2	node2 (e3b)	Master: br_default(UP)
...						
UP	swp15	100G	9216	BondMember	swp15	Master: cluster_isl(UP)
UP	swp16	100G	9216	BondMember	swp16	Master: cluster_isl(UP)
...						

18. On both switches sw1 and sw2, verify that both nodes each have one connection to each switch: `net show lldp`

The following example shows the appropriate results for both switches sw1 and sw2:

```
cumulus@sw1:~$ net show lldp
```

LocalPort	Speed	Mode	RemoteHost	RemotePort
swp3	100G	Trunk/L2	node1	e3a
swp4	100G	Trunk/L2	node2	e3a
swp15	100G	BondMember	sw2	swp15
swp16	100G	BondMember	sw2	swp16

```
cumulus@sw2:~$ net show lldp
```

LocalPort	Speed	Mode	RemoteHost	RemotePort
swp3	100G	Trunk/L2	node1	e3b
swp4	100G	Trunk/L2	node2	e3b
swp15	100G	BondMember	sw1	swp15
swp16	100G	BondMember	sw1	swp16

19. Display information about the discovered network devices in your cluster: `net device-discovery show -protocol lldp`

```
cluster1::~*> network device-discovery show -protocol lldp
```

Node/	Local	Discovered		
Protocol	Port	Device (LLDP: ChassisID)	Interface	Platform
node1	/lldp			
	e3a	sw1 (b8:ce:f6:19:1a:7e)	swp3	-
	e3b	sw2 (b8:ce:f6:19:1b:96)	swp3	-
node2	/lldp			
	e3a	sw1 (b8:ce:f6:19:1a:7e)	swp4	-
	e3b	sw2 (b8:ce:f6:19:1b:96)	swp4	-

20. Verify that all cluster ports are up: `network port show -ip space Cluster`

The following example shows that all of the cluster ports are up on node1 and node2:

```
cluster1::*> network port show -ipspace Cluster
```

Node: node1

Ignore

						Speed(Mbps)	Health
Health							
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
Status							
-----	-----	-----	-----	----	----	-----	-----

e3a	Cluster	Cluster		up	9000	auto/10000	healthy
false							
e3b	Cluster	Cluster		up	9000	auto/10000	healthy
false							

Node: node2

Ignore

						Speed(Mbps)	Health
Health							
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
Status							
-----	-----	-----	-----	----	----	-----	-----

e3a	Cluster	Cluster		up	9000	auto/10000	healthy
false							
e3b	Cluster	Cluster		up	9000	auto/10000	healthy
false							

21. Enable auto-revert on all cluster LIFs: `net interface modify -vserver Cluster -lif * -auto-revert true`

```
cluster1::*> net interface modify -vserver Cluster -lif * -auto-revert true
```

	Logical	
Vserver	Interface	Auto-revert
-----	-----	-----
Cluster		
	node1_clus1	true
	node1_clus2	true
	node2_clus1	true
	node2_clus2	true

22. Verify that all interfaces display true for Is Home: `net interface show -vserver Cluster`



This might take a minute to complete.

The following example shows that all LIFs are up on node1 and node2 and that Is Home results are true:

```
cluster1::*> net interface show -vserver Cluster
```

Is	Logical	Status	Network	Current	Current
Vserver	Interface	Admin/Oper	Address/Mask	Node	Port
Home					
-----	-----	-----	-----	-----	-----

Cluster					
true	node1_clus1	up/up	169.254.209.69/16	node1	e3a
true	node1_clus2	up/up	169.254.49.125/16	node1	e3b
true	node2_clus1	up/up	169.254.47.194/16	node2	e3a
true	node2_clus2	up/up	169.254.19.183/16	node2	e3b
true					

23. Verify that the settings are disabled: `network options switchless-cluster show`

The false output in the following example shows that the configuration settings are disabled:

```
cluster1::*> network options switchless-cluster show
Enable Switchless Cluster: false
```

24. Verify the status of the node members in the cluster: `cluster show`

The following example shows information about the health and eligibility of the nodes in the cluster:

```
cluster1::*> cluster show
```

Node	Health	Eligibility	Epsilon
-----	-----	-----	-----
node1	true	true	false
node2	true	true	false

25. Ensure that the cluster network has full connectivity: `cluster ping-cluster -node node-name`

```

cluster1::*> cluster ping-cluster -node node1
Host is node1
Getting addresses from network interface table...
Cluster node1_clus1 169.254.209.69 node1 e3a
Cluster node1_clus2 169.254.49.125 node1 e3b
Cluster node2_clus1 169.254.47.194 node2 e3a
Cluster node2_clus2 169.254.19.183 node2 e3b
Local = 169.254.47.194 169.254.19.183
Remote = 169.254.209.69 169.254.49.125
Cluster Vserver Id = 4294967293
Ping status:

Basic connectivity succeeds on 4 path(s)
Basic connectivity fails on 0 path(s)

Detected 9000 byte MTU on 4 path(s):
Local 169.254.47.194 to Remote 169.254.209.69
Local 169.254.47.194 to Remote 169.254.49.125
Local 169.254.19.183 to Remote 169.254.209.69
Local 169.254.19.183 to Remote 169.254.49.125
Larger than PMTU communication succeeds on 4 path(s)
RPC status:
2 paths up, 0 paths down (tcp check)
2 paths up, 0 paths down (udp check)

```

26. Enable the Ethernet switch health monitor log collection feature for collecting switch-related log files, using the commands: `system switch ethernet log setup-password` and `system switch ethernet log enable-collection`

Enter: `system switch ethernet log setup-password`

```
cluster1::*> system switch ethernet log setup-password
```

```
Enter the switch name: <return>
```

```
The switch name entered is not recognized.
```

```
Choose from the following list:
```

```
sw1
```

```
sw2
```

```
cluster1::*> system switch ethernet log setup-password
```

```
Enter the switch name: sw1
```

```
RSA key fingerprint is e5:8b:c6:dc:e2:18:18:09:36:63:d9:63:dd:03:d9:cc
```

```
Do you want to continue? {y|n}::[n] y
```

```
Enter the password: <enter switch password>
```

```
Enter the password again: <enter switch password>
```

```
cluster1::*> system switch ethernet log setup-password
```

```
Enter the switch name: sw2
```

```
RSA key fingerprint is 57:49:86:a1:b9:80:6a:61:9a:86:8e:3c:e3:b7:1f:b1
```

```
Do you want to continue? {y|n}:: [n] y
```

```
Enter the password: <enter switch password>
```

```
Enter the password again: <enter switch password>
```

Followed by: `system switch ethernet log enable-collection`

```
cluster1::*> system switch ethernet log enable-collection
```

```
Do you want to enable cluster log collection for all nodes in the  
cluster?
```

```
{y|n}: [n] y
```

```
Enabling cluster switch log collection.
```

```
cluster1::*>
```



If any of these commands return an error, contact NetApp support.

27. Initiate the switch log collection feature: `system switch ethernet log collect -device *`

Wait for 10 minutes and then check that the log collection was successful using the command: `system switch ethernet log show`

```
cluster1::*> system switch ethernet log show
```

```
Log Collection Enabled: true
```

Index	Switch	Log Timestamp	Status
1	sw1 (b8:ce:f6:19:1b:42)	4/29/2022 03:05:25	complete
2	sw2 (b8:ce:f6:19:1b:96)	4/29/2022 03:07:42	complete

28. Change the privilege level back to admin: `set -privilege admin`

29. If you suppressed automatic case creation, reenable it by invoking an AutoSupport message: `system node autosupport invoke -node * -type all -message MAINT=END`

Replace NVIDIA SN2100 switches

Replace a NVIDIA SN2100 cluster switch

Replacing a defective NVIDIA SN2100 switch in a cluster network is a nondisruptive procedure (NDU).

Before you begin

The following conditions must exist before performing the switch replacement in the current environment and on the replacement switch.

- Existing cluster and network infrastructure:
 - The existing cluster must be verified as completely functional, with at least one fully connected cluster switch.
 - All cluster ports must be up.
 - All cluster logical interfaces (LIFs) must be up and on their home ports.
 - The ONTAP `cluster ping-cluster -node node1` command must indicate that basic connectivity and larger than PMTU communication are successful on all paths.
- NVIDIA SN2100 replacement switch:
 - Management network connectivity on the replacement switch must be functional.
 - Console access to the replacement switch must be in place.
 - The node connections are ports swp1 through swp14.
 - All Inter-Switch Link (ISL) ports must be disabled on ports swp15 and swp16.
 - The desired reference configuration file (RCF) and Cumulus operating system image switch must be loaded onto the switch.
 - Initial customization of the switch must be complete, as detailed in:

Any previous site customizations, such as STP, SNMP, and SSH, should be copied to the new switch.

You must execute the command for migrating a cluster LIF from the node where the cluster LIF is hosted.

About this task

The examples in this procedure use the following switch and node nomenclature:

- The names of the existing NVIDIA SN2100 switches are *sw1* and *sw2*.
- The name of the new NVIDIA SN2100 switch is *nsw2*.
- The node names are *node1* and *node2*.
- The cluster ports on each node are named *e3a* and *e3b*.
- The cluster LIF names are *node1_clus1* and *node1_clus2* for node1, and *node2_clus1* and *node2_clus2* for node2.
- The prompt for changes to all cluster nodes is `cluster1::*>`
- Breakout ports take the format: `swp[port]s[breakout port 0-3]`. For example, four breakout ports on `swp1` are *swp1s0*, *swp1s1*, *swp1s2*, and *swp1s3*.



The following procedure is based on the following cluster network topology:

```
cluster1::*> network port show -ipspace Cluster
```

```
Node: node1
```

```
Ignore
```

						Speed (Mbps)	Health
Health							
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
Status							
-----	-----	-----	----	----	-----	-----	-----

e3a	Cluster	Cluster		up	9000	auto/100000	healthy
false							
e3b	Cluster	Cluster		up	9000	auto/100000	healthy
false							

```
Node: node2
```

```
Ignore
```

						Speed (Mbps)	Health
Health							
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
Status							
-----	-----	-----	----	----	-----	-----	-----

e3a	Cluster	Cluster		up	9000	auto/100000	healthy
false							
e3b	Cluster	Cluster		up	9000	auto/100000	healthy
false							

```
cluster1::*> network interface show -vserver Cluster
```

	Logical	Status	Network	Current	
Current Is					
Vserver	Interface	Admin/Oper	Address/Mask	Node	Port
Home					
-----	-----	-----	-----	-----	-----
-----	-----	-----	-----	-----	-----
Cluster					
	node1_clus1	up/up	169.254.209.69/16	node1	e3a
true					
	node1_clus2	up/up	169.254.49.125/16	node1	e3b
true					
	node2_clus1	up/up	169.254.47.194/16	node2	e3a
true					
	node2_clus2	up/up	169.254.19.183/16	node2	e3b
true					

```
cluster1::*> network device-discovery show -protocol lldp
```

Node/	Local	Discovered			
Protocol	Port	Device (LLDP: ChassisID)	Interface	Platform	
-----	-----	-----	-----	-----	-----
-----	-----	-----	-----	-----	-----
node1	/lldp				
	e3a	sw1 (b8:ce:f6:19:1a:7e)	swp3	-	
	e3b	sw2 (b8:ce:f6:19:1b:96)	swp3	-	
node2	/lldp				
	e3a	sw1 (b8:ce:f6:19:1a:7e)	swp4	-	
	e3b	sw2 (b8:ce:f6:19:1b:96)	swp4	-	

```
cumulus@sw1:~$ net show lldp
```

LocalPort	Speed	Mode	RemoteHost	RemotePort
swp3	100G	Trunk/L2	sw2	e3a
swp4	100G	Trunk/L2	sw2	e3a
swp15	100G	BondMember	sw2	swp15
swp16	100G	BondMember	sw2	swp16

```
cumulus@sw2:~$ net show lldp
```

LocalPort	Speed	Mode	RemoteHost	RemotePort
swp3	100G	Trunk/L2	sw1	e3b
swp4	100G	Trunk/L2	sw1	e3b
swp15	100G	BondMember	sw1	swp15
swp16	100G	BondMember	sw1	swp16

Steps

1. If AutoSupport is enabled on this cluster, suppress automatic case creation by invoking an AutoSupport message: `system node autosupport invoke -node * -type all -message MAINT=xh`

where *x* is the duration of the maintenance window in hours.

2. Change the privilege level to advanced, entering *y* when prompted to continue: `set -privilege advanced`

The advanced prompt (**>*) appears.

3. Install the appropriate RCF and image on the switch, *nsw2*, and make any necessary site preparations.

If necessary, verify, download, and install the appropriate versions of the RCF and Cumulus software for the new switch. If you have verified that the new switch is correctly set up and does not need updates to the RCF and Cumulus software, continue to step 3. See [Setup and configure the NVIDIA SN2100 switches](#) for further details.

- a. You can download the applicable Cumulus software for your cluster switches from the *NVIDIA Support* site. Follow the steps on the Download page to download the Cumulus Linux for the version of ONTAP software you are installing.
 - b. The appropriate RCF is available from the [NVIDIA Cluster and Storage Switches](#) page. Follow the steps on the Download page to download the correct RCF for the version of ONTAP software you are installing.
4. On the new switch *nsw2*, log in as admin and shut down all of the ports that will be connected to the node cluster interfaces (ports *swp1* to *swp14*).

If the switch that you are replacing is not functional and is powered down, go to Step 4. The LIFs on the cluster nodes should have already failed over to the other cluster port for each node.

```
cumulus@nsw2:~$ net add interface swp1s0-3, swp2s0-3, swp3-14 link down
cumulus@nsw2:~$ net pending
cumulus@nsw2:~$ net commit
```

5. Disable auto-revert on the cluster LIFs: `network interface modify -vserver Cluster -lif * -auto-revert false`

```
cluster1::~*> network interface modify -vserver Cluster -lif * -auto
-revert false
```

Warning: Disabling the auto-revert feature of the cluster logical interface may effect the availability of your cluster network. Are you sure you want to continue? {y|n}: **y**

6. Shut down the ISL ports swp15 and swp16 on the SN2100 switch sw1:

```
cumulus@sw1:~$ net add interface swp15-16 link down
cumulus@sw1:~$ net pending
cumulus@sw1:~$ net commit
```

7. Remove all the cables from the SN2100 sw1 switch, and then connect them to the same ports on the SN2100 nsw2 switch.
8. Bring up the ISL ports swp15 and swp16 between the sw1 and nsw2 switches.

The following commands enable ISL ports swp15 and swp16 on switch sw1:

```
cumulus@sw1:~$ net del interface swp15-16 link down
cumulus@sw1:~$ net pending
cumulus@sw1:~$ net commit
```

The following example shows that the ISL ports are up on switch sw1:

```
cumulus@sw1:~$ net show interface
```

State	Name	Spd	MTU	Mode	LLDP	Summary
-----	-----	----	-----	-----	-----	

...						
...						
UP	swp15	100G	9216	BondMember	nsw2 (swp15)	Master:
	cluster_isl (UP)					
UP	swp16	100G	9216	BondMember	nsw2 (swp16)	Master:
	cluster_isl (UP)					

The following example shows that the ISL ports are up on switch nsw2:

```
cumulus@nsw2:~$ net show interface
```

State	Name	Spd	MTU	Mode	LLDP	Summary
-----	-----	----	-----	-----	-----	

...						
...						
UP	swp15	100G	9216	BondMember	sw1 (swp15)	Master:
	cluster_isl (UP)					
UP	swp16	100G	9216	BondMember	sw1 (swp16)	Master:
	cluster_isl (UP)					

9. Verify that port e3b is up on all nodes: `network port show -ipspace Cluster`

The output should be similar to the following:

```
cluster1::*> network port show -ipspace Cluster
```

```
Node: node1
```

```
Ignore
```

						Speed(Mbps)	Health
Health							
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
Status							
-----	-----	-----	-----	-----	-----	-----	-----
e3a	Cluster	Cluster		up	9000	auto/100000	healthy
false							
e3b	Cluster	Cluster		up	9000	auto/100000	healthy
false							

```
Node: node2
```

```
Ignore
```

						Speed(Mbps)	Health
Health							
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
Status							
-----	-----	-----	-----	-----	-----	-----	-----
e3a	Cluster	Cluster		up	9000	auto/100000	healthy
false							
e3b	Cluster	Cluster		up	9000	auto/100000	healthy
false							

10. The cluster ports on each node are now connected to cluster switches in the following way, from the nodes' perspective:

```
cluster1::*> network device-discovery show -protocol lldp
```

Node/ Protocol	Local Port	Discovered Device (LLDP: ChassisID)	Interface	Platform
node1	/lldp			
	e3a	sw1 (b8:ce:f6:19:1a:7e)	swp3	-
	e3b	nsw2 (b8:ce:f6:19:1b:b6)	swp3	-
node2	/lldp			
	e3a	sw1 (b8:ce:f6:19:1a:7e)	swp4	-
	e3b	nsw2 (b8:ce:f6:19:1b:b6)	swp4	-

11. Verify that all node cluster ports are up: `net show interface`

```
cumulus@nsw2:~$ net show interface
```

State	Name	Spd	MTU	Mode	LLDP	Summary
UP	swp3	100G	9216	Trunk/L2		Master:
	bridge(UP)					
UP	swp4	100G	9216	Trunk/L2		Master:
	bridge(UP)					
UP	swp15	100G	9216	BondMember	sw1 (swp15)	Master:
	cluster_isl(UP)					
UP	swp16	100G	9216	BondMember	sw1 (swp16)	Master:
	cluster_isl(UP)					

12. Verify that both nodes each have one connection to each switch: `net show lldp`

The following example shows the appropriate results for both switches:

```
cumulus@sw1:~$ net show lldp
```

LocalPort	Speed	Mode	RemoteHost	RemotePort
-----	-----	-----	-----	-----
swp3	100G	Trunk/L2	node1	e3a
swp4	100G	Trunk/L2	node2	e3a
swp15	100G	BondMember	nsw2	swp15
swp16	100G	BondMember	nsw2	swp16

```
cumulus@nsw2:~$ net show lldp
```

LocalPort	Speed	Mode	RemoteHost	RemotePort
-----	-----	-----	-----	-----
swp3	100G	Trunk/L2	node1	e3b
swp4	100G	Trunk/L2	node2	e3b
swp15	100G	BondMember	sw1	swp15
swp16	100G	BondMember	sw1	swp16

13. Enable auto-revert on the cluster LIFs: `cluster1::*> network interface modify -vserver Cluster -lif * -auto-revert true`

14. On switch nsw2, bring up the ports connected to the network ports of the nodes.

```
cumulus@nsw2:~$ net del interface swp1-14 link down
cumulus@nsw2:~$ net pending
cumulus@nsw2:~$ net commit
```

15. Display information about the nodes in a cluster: `cluster show`

This example shows that the node health for node1 and node2 in this cluster is true:

```
cluster1::*> cluster show
```

Node	Health	Eligibility
-----	-----	-----
node1	true	true
node2	true	true

16. Verify that all physical cluster ports are up: `network port show ipspace Cluster`


```
cluster1::*> network port show -ipspace Cluster
```

```
Node node1
```

```
Ignore
```

						Speed(Mbps)	Health
Health							
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
Status							
-----	-----	-----	-----	-----	-----	-----	-----

e3a	Cluster	Cluster		up	9000	auto/10000	healthy
false							
e3b	Cluster	Cluster		up	9000	auto/10000	healthy
false							

```
Node: node2
```

```
Ignore
```

						Speed(Mbps)	Health
Health							
Port	IPspace	Broadcast	Domain	Link	MTU	Admin/Oper	Status
Status							
-----	-----	-----	-----	-----	-----	-----	-----

e3a	Cluster	Cluster		up	9000	auto/10000	healthy
false							
e3b	Cluster	Cluster		up	9000	auto/10000	healthy
false							

17. Verify that the cluster network is healthy:

```
cumulus@sw1:~$ net show lldp
```

LocalPort	Speed	Mode	RemoteHost	RemotePort
-----	-----	-----	-----	-----
swp3	100G	Trunk/L2	node1	e3a
swp4	100G	Trunk/L2	node2	e3a
swp15	100G	BondMember	nsw2	swp15
swp16	100G	BondMember	nsw2	swp16

18. Enable the Ethernet switch health monitor log collection feature for collecting switch-related log files, using the commands: `system switch ethernet log setup-password` and `system switch ethernet log enable-collection`

Enter: `system switch ethernet log setup-password`

```
cluster1::*> system switch ethernet log setup-password
```

```
Enter the switch name: <return>
```

```
The switch name entered is not recognized.
```

```
Choose from the following list:
```

```
sw1
```

```
nsw2
```

```
cluster1::*> system switch ethernet log setup-password
```

```
Enter the switch name: sw1
```

```
RSA key fingerprint is e5:8b:c6:dc:e2:18:18:09:36:63:d9:63:dd:03:d9:cc
```

```
Do you want to continue? {y|n}::[n] y
```

```
Enter the password: <enter switch password>
```

```
Enter the password again: <enter switch password>
```

```
cluster1::*> system switch ethernet log setup-password
```

```
Enter the switch name: nsw2
```

```
RSA key fingerprint is 57:49:86:a1:b9:80:6a:61:9a:86:8e:3c:e3:b7:1f:b1
```

```
Do you want to continue? {y|n}:: [n] y
```

```
Enter the password: <enter switch password>
```

```
Enter the password again: <enter switch password>
```

Followed by: `system switch ethernet log enable-collection`

```
cluster1::*> system switch ethernet log enable-collection
```

```
Do you want to enable cluster log collection for all nodes in the  
cluster?
```

```
{y|n}: [n] y
```

```
Enabling cluster switch log collection.
```

```
cluster1::*>
```



If any of these commands return an error, contact NetApp support.

19. Initiate the switch log collection feature: `system switch ethernet log collect -device *`

Wait for 10 minutes and then check that the log collection was successful using the command: `system switch ethernet log show`

```
cluster1::*> system switch ethernet log show
```

```
Log Collection Enabled: true
```

Index	Switch	Log Timestamp	Status
1	sw1 (b8:ce:f6:19:1b:42)	4/29/2022 03:05:25	complete
2	nsw2 (b8:ce:f6:19:1b:96)	4/29/2022 03:07:42	complete

20. Change the privilege level back to admin: `set -privilege admin`

21. If you suppressed automatic case creation, re-enable it by invoking an AutoSupport message: `system node autosupport invoke -node * -type all -message MAINT=END`

Replace a NVIDIA SN2100 storage switch

You must be aware of certain configuration information, port connections and cabling requirements when you replace NVIDIA SN2100 storage switches.

Before you begin

You must verify that the following conditions exist before installing the Cumulus software and RCFs on a NVIDIA SN2100 storage switch:

- Your system can support NVIDIA SN2100 storage switches.
- You must have downloaded the applicable RCFs.
- The [Hardware Universe](#) provides full details of supported ports and their configurations.

About this task

The existing network configuration must have the following characteristics:

- Ensure that all troubleshooting steps have been completed to confirm that your switch needs replacing.
- Management connectivity must exist on both switches.



Make sure that all troubleshooting steps have been completed to confirm that your switch needs replacing.

The replacement NVIDIA SN2100 switch must have the following characteristics:

- Management network connectivity must be functional.
- Console access to the replacement switch must be in place.
- The appropriate RCF and Cumulus operating system image must be loaded onto the switch.
- Initial customization of the switch must be complete.

Procedure summary

This procedure replaces the second NVIDIA SN2100 storage switch sw2 with the new NVIDIA SN2100 switch nsw2. The two nodes are node1 and node2.

Steps to complete:

- Confirm the switch to be replaced is sw2.
- Disconnect the cables from switch sw2.
- Reconnect the cables to switch nsw2.
- Verify all device configurations on switch nsw2.

Steps

1. If AutoSupport is enabled on this cluster, suppress automatic case creation by invoking an AutoSupport message: `system node autosupport invoke -node * -type all - message MAINT=xh`

x is the duration of the maintenance window in hours.

2. Change the privilege level to advanced, entering **y** when prompted to continue: `set -privilege advanced`
3. Check on the health status of the storage node ports to make sure that there is connection to storage switch S1:

`storage port show -port-type ENET`

```
cluster1::*> storage port show -port-type ENET
```

Node	Port	Type	Mode	Speed (Gb/s)	State	Status	VLAN ID

node1	e3a	ENET	storage	100	enabled	online	30
	e3b	ENET	storage	0	enabled	offline	30
	e7a	ENET	storage	0	enabled	offline	30
	e7b	ENET	storage	100	enabled	online	30
node2	e3a	ENET	storage	100	enabled	online	30
	e3b	ENET	storage	0	enabled	offline	30
	e7a	ENET	storage	0	enabled	offline	30
	e7b	ENET	storage	100	enabled	online	30

```
cluster1::*>
```

4. Verify that storage switch sw1 is available: `network device-discovery show`

```
cluster1::*> network device-discovery show protocol lldp
```

Node/	Local	Discovered		
Protocol	Port	Device (LLDP: ChassisID)	Interface	Platform
-----	----	-----	-----	-----
node1/lldp				
	e3a	sw1 (b8:ce:f6:19:1b:42)	swp3	-
node2/lldp				
	e3a	sw1 (b8:ce:f6:19:1b:42)	swp4	-

```
cluster1::*>
```

- Run the `net show interface` command on the working switch to confirm that you can see both nodes and all shelves: `net show interface`

```
cumulus@sw1:~$ net show interface
```

State	Name	Spd	MTU	Mode	LLDP	Summary
-----	-----	----	-----	-----	-----	-----
...						
...						
UP	swp1	100G	9216	Trunk/L2	node1 (e3a)	Master:
	bridge(UP)					
UP	swp2	100G	9216	Trunk/L2	node2 (e3a)	Master:
	bridge(UP)					
UP	swp3	100G	9216	Trunk/L2	SHFFG1826000112 (e0b)	Master:
	bridge(UP)					
UP	swp4	100G	9216	Trunk/L2	SHFFG1826000112 (e0b)	Master:
	bridge(UP)					
UP	swp5	100G	9216	Trunk/L2	SHFFG1826000102 (e0b)	Master:
	bridge(UP)					
UP	swp6	100G	9216	Trunk/L2	SHFFG1826000102 (e0b)	Master:
	bridge(UP)					
...						
...						

- Verify the shelf ports in the storage system: `storage shelf port show -fields remote-device, remote-port`

```
cluster1::*> storage shelf port show -fields remote-device, remote-port
shelf    id  remote-port  remote-device
-----  --  -
3.20     0   swp3        sw1
3.20     1   -           -
3.20     2   swp4        sw1
3.20     3   -           -
3.30     0   swp5        sw1
3.20     1   -           -
3.30     2   swp6        sw1
3.20     3   -           -
cluster1::*>
```

7. Remove all cables attached to storage switch sw2.
8. Reconnect all cables to the replacement switch nsw2.
9. Recheck the health status of the storage node ports: `storage port show -port-type ENET`

```
cluster1::*> storage port show -port-type ENET
```

Node	Port	Type	Mode	Speed (Gb/s)	State	Status	VLAN ID
node1							
	e3a	ENET	storage	100	enabled	online	30
	e3b	ENET	storage	0	enabled	offline	30
	e7a	ENET	storage	0	enabled	offline	30
	e7b	ENET	storage	100	enabled	online	30
node2							
	e3a	ENET	storage	100	enabled	online	30
	e3b	ENET	storage	0	enabled	offline	30
	e7a	ENET	storage	0	enabled	offline	30
	e7b	ENET	storage	100	enabled	online	30

```
cluster1::*>
```

10. Verify that both switches are available: `net device-discovery show`

```
cluster1::*> network device-discovery show protocol lldp
```

Node/	Local	Discovered		
Protocol	Port	Device (LLDP: ChassisID)	Interface	Platform
-----	----	-----	-----	-----
node1/lldp				
	e3a	sw1 (b8:ce:f6:19:1b:96)	swp1	-
	e7b	nsw2 (b8:ce:f6:19:1a:7e)	swp1	-
node2/lldp				
	e3a	sw1 (b8:ce:f6:19:1b:96)	swp2	-
	e7b	nsw2 (b8:ce:f6:19:1a:7e)	swp2	-

```
cluster1::*>
```

11. Verify the shelf ports in the storage system: storage shelf port show -fields remote-device, remote-port

```
cluster1::*> storage shelf port show -fields remote-device, remote-port
```

shelf	id	remote-port	remote-device
-----	--	-----	-----
3.20	0	swp3	sw1
3.20	1	swp3	nsw2
3.20	2	swp4	sw1
3.20	3	swp4	nsw2
3.30	0	swp5	sw1
3.20	1	swp5	nsw2
3.30	2	swp6	sw1
3.20	3	swp6	nsw2

```
cluster1::*>
```

12. Enable the Ethernet switch health monitor log collection feature for collecting switch-related log files, using the two commands: system switch ethernet log setup-password and system switch ethernet log enable-collection

Enter: system switch ethernet log setup-password

```
cluster1::*> system switch ethernet log setup-password
```

```
Enter the switch name: <return>
```

```
The switch name entered is not recognized.
```

```
Choose from the following list:
```

```
sw1
```

```
nsw2
```

```
cluster1::*> system switch ethernet log setup-password
```

```
Enter the switch name: sw1
```

```
RSA key fingerprint is e5:8b:c6:dc:e2:18:18:09:36:63:d9:63:dd:03:d9:cc
```

```
Do you want to continue? {y|n}::[n] y
```

```
Enter the password: <enter switch password>
```

```
Enter the password again: <enter switch password>
```

```
cluster1::*> system switch ethernet log setup-password
```

```
Enter the switch name: nsw2
```

```
RSA key fingerprint is 57:49:86:a1:b9:80:6a:61:9a:86:8e:3c:e3:b7:1f:b1
```

```
Do you want to continue? {y|n}:: [n] y
```

```
Enter the password: <enter switch password>
```

```
Enter the password again: <enter switch password>
```

Followed by: `system switch ethernet log enable-collection`

```
cluster1::*> system switch ethernet log enable-collection
```

```
Do you want to enable cluster log collection for all nodes in the  
cluster?
```

```
{y|n}: [n] y
```

```
Enabling cluster switch log collection.
```

```
cluster1::*>
```



If any of these commands return an error, contact NetApp support.

13. Initiate the switch log collection feature: `system switch ethernet log collect -device *`

Wait for 10 minutes and then check that the log collection was successful using the command: `system switch ethernet log show`


```
cluster1::*> system switch ethernet log show
```

```
Log Collection Enabled: true
```

Index	Switch	Log Timestamp	Status
-----	-----	-----	-----
1	sw1 (b8:ce:f6:19:1b:42)	4/29/2022 03:05:25	complete
2	nsw2 (b8:ce:f6:19:1b:96)	4/29/2022 03:07:42	complete

14. Change the privilege level back to admin: `set -privilege admin`

15. If you suppressed automatic case creation, re-enable it by invoking an AutoSupport message: `system node autosupport invoke -node * -type all -message MAINT=END`

Copyright Information

Copyright © 2022 NetApp, Inc. All rights reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means-graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system- without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP "AS IS" AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

RESTRICTED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (c)(1)(ii) of the Rights in Technical Data and Computer Software clause at DFARS 252.277-7103 (October 1988) and FAR 52-227-19 (June 1987).

Trademark Information

NETAPP, the NETAPP logo, and the marks listed at <http://www.netapp.com/TM> are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.