

MINISTRY OF EDUCATION OF REPUBLIC OF MOLDOVA
TECHNICAL UNIVERSITY OF MOLDOVA
FACULTY OF COMPUTERS, INFORMATICS AND MICROELECTRONICS
SOFTWARE ENGINEERING DEPARTMENT

EMBEDDED SYSTEMS
LABORATORY WORK WORK #5.2

PID Control of a Servo-Driven Gate


During the preparation of this report, the author used various AI Tools such as ChatGPT, Gemini, Claude to generate/augment the content, generate the code and structure the directory. The resulting information was reviewed, validated, and adjusted to meet the requirements of the laboratory assignment.

Author: Timur CRAVTOV
std. gr. FAF-231

Verified by:
Alexei MARTÎNIUC
asist. univ



Chişinău, 2026



1 Objective and Technical Analysis

The objective of this laboratory work is to implement closed-loop PID control for a servo-driven gate using an ultrasonic distance sensor as feedback. Compared with the previous lab, the hardware layout remains the same, while the control strategy is upgraded from open-loop or threshold-based regulation to proportional-integral-derivative compensation.

The system is organized into three cooperating tasks: input acquisition, PID control, and state reporting. This keeps timing deterministic and separates user interaction from the control loop.

The main learning outcomes are:


- understanding the structure of a PID controller and its discrete-time implementation;
- converting a distance error into a bounded servo command;
- applying integral windup protection and output clamping;
- keeping a FreeRTOS-based control loop responsive under serial and keypad interaction;
- documenting the same electrical scheme used in Lab 5.1.

1.1 Specifications

Table 1 summarizes the main components, timing, and control constraints used for the PID experiment. These values reflect the practical limits of the hardware and the task schedule.

Table 1: Lab 5.2 Specifications

Item	Specification
MCU	Arduino Nano (ATmega328P)
Sensor	Ultrasonic distance sensor (TRIG/ECHO)
Actuator	Servo motor (PWM control)
Keypad	4x4 matrix keypad
Display	16x2 LCD via I2C + Teleplot serial
Control logic	Discrete PID with saturation
Task periods	Read: 40 ms, Filter: 80 ms, Display: 250 ms
Safe distance range	MIN_DISTANCE_MIN_CM to MIN_DISTANCE_MAX_CM



1.2 PID Control Theory

The control signal is computed from the distance error between the desired threshold and the measured distance:

$$e[k] = r[k] - y[k] \quad (1)$$

where $r[k]$ is the setpoint and $y[k]$ is the measured distance.

The discrete PID law used in the implementation is:

$$u[k] = K_p e[k] + K_i \sum_{i=0}^k e[i] \Delta t + K_d \frac{e[k] - e[k-1]}{\Delta t} \quad (2)$$

The output is then limited to the supported servo position range:

$$u_{sat}[k] = \min(\max(u[k], u_{min}), u_{max}) \quad (3)$$

This is important because the actuator should never be commanded outside its safe travel interval.

In practice, the integral term is clamped to prevent windup while the output is saturated. The control loop uses a fixed time step derived from the task period, which keeps the discrete PID stable and predictable even on a small MCU.


1.3 Discrete PID Considerations

A discrete controller depends on the sampling period, Δt . A larger Δt reduces CPU load but can make the loop sluggish or unstable. A smaller Δt improves responsiveness but amplifies noise, especially in the derivative term. For that reason, the derivative is computed from successive samples and its effect is bounded indirectly by the output clamp.

Integral windup is another key concern. When the actuator saturates, the error can persist and cause the integral term to grow without bound. Clamping the integral term and resetting it when the target is out of range prevents overshoot when the object re-enters the sensing region.

1.4 Control Objective

The controller keeps the servo closed when the object is out of range and opens the gate proportionally when the measured distance moves inside the configured threshold. That behavior gives the system a clear binary default state while still allowing smooth intermediate motion when the error is small.



2 System Design

2.1 Task-Based Architecture

The software is split into three tasks with fixed periods:

- **TaskRead** (40 ms): reads keypad input and updates the distance threshold;
- **TaskFilter** (80 ms): reads the ultrasonic sensor and executes PID control;
- **TaskDisplay** (250 ms): reports the current state over serial and Teleplot output.

This structure keeps the control calculation periodic and prevents input handling from delaying servo updates.

At the hardware level, the Arduino Nano is the central node. The keypad provides on-the-fly threshold updates, the ultrasonic sensor produces distance feedback, the servo receives PWM commands, and the LCD/serial output reports the current state. The diagram below reflects this end-to-end signal path and its separation from the timing-critical PID loop.

Shared state is updated by the control task and read by the display task inside a critical section. This ensures that the reported distance, PID error, and actuator output stay consistent across the user interface and Teleplot stream.

2.2 Control Flow

PID control loop: keypad threshold → distance measurement → error
calculation → PID update → bounded servo command


Figure 1: PID Control Loop for Lab 5.2

The controller follows the same flow on every cycle. If the target is outside the valid range, the actuator is returned to the fully closed position and the integral state is cleared to avoid stale control memory.

2.3 Electrical Schematic

The electrical scheme is intentionally kept the same as in Lab 5.1. The hardware topology uses the same Arduino Nano-based layout with the servo actuator, keypad, LCD, and ultrasonic sensor connected to the same logical blocks.

The improved circuit diagram emphasizes the wiring and power distribution, while the architecture diagram shows how data and control signals flow between modules.



All modules share a common ground, and the servo power rail should be stable to reduce measurement noise. Shorter signal paths help keep the ultrasonic echo line clean, which improves PID stability near the setpoint.




Figure 2: Hardware and architecture diagrams for the PID-controlled gate

The report keeps the same scheme because the assignment changes the control law, not the physical I/O arrangement. Only the software logic is extended to compute a PID command from sensor feedback.

2.4 Component Overview

2.4.1 Arduino Nano


The Arduino Nano (ATmega328P) provides the timing base for the PID loop and runs FreeRTOS tasks at fixed periods. Its limited SRAM encourages compact buffers and fixed-size state structures.

2.4.2 Ultrasonic Sensor

Distance is measured by time-of-flight. A trigger pulse emits an ultrasonic burst and the echo pulse width represents the round-trip travel time. The controller validates the measurement before using it in the PID calculation to avoid injecting invalid values into the loop.

2.4.3 Servo Motor

The servo actuator is driven by a PWM signal and accepts a bounded position range. The PID output is clamped to this range to avoid over-travel and to reduce the chance of stalling at mechanical limits.



2.4.4 Keypad Matrix

The 4x4 keypad is scanned as a row/column matrix and allows the user to update the threshold without reflashing the firmware. Sampling at a periodic rate provides basic debouncing behavior.

2.4.5 LCD and Serial Output

Status is displayed on a 16x2 LCD and mirrored to serial/Teleplot. This gives immediate feedback on distance, error, and actuator output while keeping the control task isolated from slower I/O.

2.4.6 FreeRTOS

FreeRTOS separates the input, control, and display paths into independent tasks. The scheduler ensures the PID loop runs at a consistent cadence, which is critical for discrete control stability.

2.5 Pin Assignment Summary

Table 2: Main Hardware Connections

Component	Pin(s)	Function
Servo actuator	D11	PWM output
Keypad rows	D9, D8, D7, D6	Input scanning
Keypad columns	D5, D4, D3, D2	Input scanning
LCD I2C bus	A4, A5	Display interface
Ultrasonic sensor	A0, A2	Distance feedback

3 Implementation and Results

3.1 Software Structure

The implementation uses shared state variables for measured distance, current servo angle, PID error, and output position. The control task updates these fields atomically and the display task reads them for reporting.

The main controller logic can be summarized as follows:

```

1 if (valid && distanceCm <= minDistanceCm) {
2     float error = setpoint - distanceCm;
3     pidIntegral = clampFloat(pidIntegral + error * dt,
4                               PID_INTEGRAL_MIN, PID_INTEGRAL_MAX);
5     float derivative = (error - lastError) / dt;
6     float control = PID_KP * error + PID_KI * pidIntegral + PID_KD * derivative;
7     int16_t command = clampInt16(SERVO_POS_MIN + roundToInt(control),

```



```

8 |                 SERVO_POS_MIN, SERVO_POS_MAX);
9 |     actuator->setPosition((uint8_t)command);
10| }

```

This structure shows the core PID computation, the integral limiter, and the final output saturation.

3.2 Timing Characteristics

Table 3: Control Loop Timing

Task	Period
TaskRead	40 ms
TaskFilter	80 ms
TaskDisplay	250 ms
Teleplot output	80 ms

The shorter control period keeps the servo responsive while the display task remains slower to reduce serial noise and processing overhead.


3.3 Observed Behavior

The controller produces smooth servo movement when the sensed distance crosses the active threshold. For stable targets, the proportional term dominates; for slowly drifting targets, the integral term removes steady-state error; and the derivative term damps sudden changes.

When the object leaves the control zone, the actuator returns to the closed position and the PID memory is reset. This prevents accumulated integral error from causing an overshoot when the target reappears.

3.4 Practical Notes

- The servo command is intentionally bounded to the safe travel range.
- Integral windup protection is required because the output may stay saturated for extended periods.
- The ultrasonic sensor reading is treated as invalid outside the configured physical range.
- The keypad provides a convenient way to adjust the threshold without recompiling firmware.



3.5 Measurement Noise and Filtering

Ultrasonic sensors are sensitive to surface angle, air turbulence, and electrical noise on the echo line. As a result, consecutive measurements can fluctuate even when the target is stationary. The control loop mitigates this by validating the range and by using a control period that is long enough to average out transient spikes. In practice, if the environment is noisy, a simple moving average or median filter can be added before the PID calculation to further reduce jitter.

3.6 PID Tuning Strategy

Manual tuning begins by increasing K_p until the system responds quickly without large oscillation. Next, a small K_i is introduced to remove steady-state error, and finally K_d is used to damp rapid changes. Because the actuator has a bounded range, gains must be selected with saturation in mind; otherwise, the servo will spend most of its time at the limits and the integral term will accumulate unnecessarily.

3.7 Telemetry and Observability

The serial output provides visibility into distance, error, and output position. This is useful for both tuning and validation. Observing the response curve helps confirm that the gate opens smoothly as the object approaches and returns to the closed position when the object moves away.


3.8 Limitations and Improvements

The system uses a single distance measurement and does not compensate for multipath reflections or environmental changes in the speed of sound. Future improvements could include sensor filtering, adaptive gain scheduling, or an automatic tuning method based on step-response identification.

4 Conclusion

This laboratory work implemented a discrete PID controller for a servo-driven gate and kept the same hardware layout as Lab 5.1. The result is a stable embedded control system with bounded actuator output, clear task separation, and simple operator input through the keypad.

The main achievement is the transition from fixed-position logic to feedback-based regulation. Compared with threshold-only control, the PID approach improves smoothness and reduces oscillation near the target distance.



Future improvements could include automatic gain tuning, sensor filtering for noisier environments, and a richer LCD user interface for live parameter adjustment.

References


- [1] K. J. Astrom and T. Hagglund, *PID Controllers: Theory, Design, and Tuning*, 2nd ed., Instrument Society of America, 1995.
- [2] FreeRTOS API Reference, <https://www.freertos.org/a00106.html>
- [3] Arduino Servo Library Reference, <https://www.arduino.cc/reference/en/libraries/servo/>
- [4] HC-SR04 Ultrasonic Sensor Datasheet, generic module reference.
- [5] Arduino Nano Documentation, <https://docs.arduino.cc/hardware/nano>
- [6] Keypad Library Reference, <https://playground.arduino.cc/Code/Keypad/>
- [7] LiquidCrystal I2C Library Reference, https://github.com/johnrickman/LiquidCrystal_I2C

A Source Code

Full source code for Lab 5.2 is available in the repository.

`actuator.h`

```
1 #pragma once
2
3 #include <Arduino.h>
4 #include <Servo.h>
5
6 // Configuration constants
7 constexpr uint8_t ACTUATOR_MIN = 0;
8 constexpr uint8_t ACTUATOR_MAX = 100;
9
10 // Abstract interface for analog actuators
11 class AnalogActuator {
12 public:
13     virtual void setPosition(uint8_t position) = 0;
14     virtual uint8_t getPosition() = 0;
15     virtual void begin() = 0;
```




```
16     virtual ~AnalogActuator() {}
17 };
18
19 // Concrete implementation for Servo-based actuator control
20 // Maps 0–100% to servo angle (0–180 degrees)
21 class ServoActuator : public AnalogActuator {
22     private:
23         uint8_t pin;
24         Servo servo;
25         uint8_t currentPosition; // 0–100%
26         uint8_t currentAngle;   // 0–180 degrees
27
28     public:
29         ServoActuator(uint8_t p);
30         void begin() override;
31         void setPosition(uint8_t position) override;
32         uint8_t getPosition() override;
33         uint8_t getAngle();
34 };
```

Listing 1: actuator.h - Actuator Interface

actuator.cpp


```
1 #include "actuator.h"
2
3 ServoActuator::ServoActuator(uint8_t p) : pin(p),
4     currentPosition(0), currentAngle(0) {}
5
6 void ServoActuator::begin() {
7     servo.attach(pin);
8     servo.write(0); // Start at 0 degrees
9 }
10
11 void ServoActuator::setPosition(uint8_t position) {
12     // Saturate to valid range
13     if (position > ACTUATOR_MAX) position = ACTUATOR_MAX;
14
15     currentPosition = position;
16     // Map 0–100% to 0–180 degrees
17     currentAngle = map(position, ACTUATOR_MIN, ACTUATOR_MAX, 0,
```



```
        180);  
17     servo.write(currentAngle);  
18 }  
19  
20 uint8_t ServoActuator::getPosition() {  
21     return currentPosition;  
22 }  
23  
24 uint8_t ServoActuator::getAngle() {  
25     return currentAngle;  
26 }
```

Listing 2: actuator.cpp - Actuator Implementation


```
tasks.h  
1 #ifndef TASKS_H  
2 #define TASKS_H  
3 #include "actuator.h"  
4 #include <Arduino_FreeRTOS.h>  
5 #include <sensors/distance.h>  
6  
7 // Task periods (ms)  
8 constexpr uint32_t TASK_READ_PERIOD    = 40;  
9 constexpr uint32_t TASK_CONTROL_PERIOD = 80;  
10 constexpr uint32_t TASK_DISPLAY_PERIOD = 250;  
11 constexpr uint32_t TASK_PLOT_PERIOD    = 80;  
12  
13 // Distance limits (cm)  
14 constexpr uint16_t MIN_DISTANCE_DEFAULT_CM = 15;  
15 constexpr uint16_t MIN_DISTANCE_MIN_CM     = 2;  
16 constexpr uint16_t MIN_DISTANCE_MAX_CM     = 400;  
17  
18 // Servo positions (%)  
19 constexpr uint8_t SERVO_POS_MIN    = 0;  
20 constexpr uint8_t SERVO_POS_MAX    = 40;  
21 constexpr uint8_t SERVO_POS_CLOSED = SERVO_POS_MIN;  
22 constexpr uint8_t SERVO_POS_OPEN   = SERVO_POS_MAX;  
23 constexpr uint8_t SERVO_POS_NEUTRAL = (SERVO_POS_MIN +  
    SERVO_POS_MAX) / 2;  
24
```



```

25 // Servo angle helpers (0–180 degrees)
26 constexpr uint8_t SERVO_ANGLE_MIN      = (uint8_t)((SERVO_POS_MIN
    * 180u) / ACTUATOR_MAX);
27 constexpr uint8_t SERVO_ANGLE_MAX      = (uint8_t)((SERVO_POS_MAX
    * 180u) / ACTUATOR_MAX);
28 constexpr uint8_t SERVO_ANGLE_NEUTRAL = (uint8_t)((
    SERVO_POS_NEUTRAL * 180u) / ACTUATOR_MAX);
29 constexpr uint8_t SERVO_ANGLE_DEADBAND = 5;
30
31 // Keep a small hysteresis to avoid gate chatter near threshold
32 constexpr uint8_t GATE_HYSTERESIS_CM = 2;
33 // Minimum time to keep the gate open after activation
34 constexpr uint16_t GATE_MIN_OPEN_MS = 600;
35
36 // Serial Plotter output toggle (prints only plot lines when
    true)
37 constexpr bool ENABLE_PLOTTER = true;
38
39 // PID tuning (start values; adjust on hardware)
40 constexpr float PID_KP          = 1.2f;
41 constexpr float PID_KI          = 0.02f;
42 constexpr float PID_KD          = 0.8f;
43 constexpr float PID_INTEGRAL_MIN = -120.0f;
44 constexpr float PID_INTEGRAL_MAX = 120.0f;
45 constexpr bool PID_INVERT_OUTPUT = false;
46
47 // Shared state variables (accessed by tasks)
48 extern volatile uint16_t measuredDistanceCm;
49 extern volatile uint16_t minDistanceCm;
50 extern volatile uint8_t  servoAngle;
51 extern volatile int16_t  pidErrorCm;
52 extern volatile uint8_t  pidOutputPos;
53 extern volatile bool     gateOpen;
54 extern volatile bool     sensorValid;
55 extern volatile char     lastKeyPressed;
56
57 // System state
58 struct SystemState {

```



```

59     uint16_t distanceCm;
60     uint16_t thresholdCm;
61     uint8_t  angle;
62     int16_t  errorCm;
63     uint8_t  outputPos;
64     bool     isOpen;
65     bool     isSensorValid;
66     char     key;
67 };
68 extern volatile SystemState sysState;
69
70 struct ControlContext {
71     ServoActuator* actuator;
72     DistanceSensor* sensor;
73 };
74
75 // Task function declarations
76 void TaskRead(void* pvParameters);
77 void TaskFilter(void* pvParameters);
78 void TaskDisplay(void* pvParameters);
79
80 #endif // TASKS_H

```


Listing 3: tasks.h - Task Interface

tasks.cpp

```

1  #include "tasks.h"
2  #include <Arduino.h>
3  #include <Arduino_FreeRTOS.h>
4  #include <avr/pgmspace.h>
5  #include <stdio.h>
6  #include <string.h>
7
8  // progmem strings
9  static const char STR_LINE0 []          PROGMEM = "\rD:%3u T:%3u %
    c  \n";
10 static const char STR_LINE0_INVALID []  PROGMEM = "\rD:--- T:%3u %
    c  \n";
11 static const char STR_LINE1 []          PROGMEM = "\rK:%c In:%-3s
    ";


```




```

12
13 // plotter format strings
14 static const char PLOT_DIST[]    PROGMEM = ">pos/dist:%d.%u\n";
15 static const char PLOT_SETPOINT[] PROGMEM = ">pos/setpoint:%u\n"
    ;
16 static const char PLOT_ERROR[]    PROGMEM = ">pid/error:%d.%u\n"
    ;
17 static const char PLOT_OUTPUT[]    PROGMEM = ">pid/output:%d\n";
18 static const char PLOT_VALID[]    PROGMEM = ">status/valid:%u\n"
    ;
19
20 // shared state variables
21 volatile uint16_t    measuredDistanceCm = 0;
22 volatile uint16_t    minDistanceCm      =
    MIN_DISTANCE_DEFAULT_CM;
23 volatile uint8_t     servoAngle         = 0;
24 volatile int16_t     pidErrorCm         = 0;
25 volatile uint8_t     pidOutputPos       = SERVO_POS_MIN;
26 volatile bool        gateOpen           = false;
27 volatile bool        sensorValid        = false;
28 volatile char        lastKeyPressed     = '_';
29 volatile SystemState sysState           = {0,
    MIN_DISTANCE_DEFAULT_CM, 0, 0,
30                                     SERVO_POS_MIN, false,
                                     false, '_' };
31
32 // keypad input buffer
33 static char    inputBuffer[4] = {0};
34 static uint8_t inputIndex     = 0;
35
36 // resets the input buffer
37 static inline void clearInputBuffer() {
38     inputIndex     = 0;
39     inputBuffer[0] = '\0';
40 }
41
42 // converts the buffer to an integer
43 static uint16_t parseInputBuffer() {

```



```
44     uint16_t value = 0;
45     for (uint8_t i = 0; i < inputIndex; i++) {
46         value = (uint16_t)(value * 10u + (uint16_t)(inputBuffer[
47             i] - '0'));
48     }
49     return value;
50 }
51 // bounds the threshold value
52 static inline uint16_t clampThreshold(uint16_t value) {
53     if (value < MIN_DISTANCE_MIN_CM) return MIN_DISTANCE_MIN_CM;
54     if (value > MIN_DISTANCE_MAX_CM) return MIN_DISTANCE_MAX_CM;
55     return value;
56 }
57
58 // bounds a float value
59 static inline float clampFloat(float value, float minValue,
60     float maxValue) {
61     if (value < minValue) return minValue;
62     if (value > maxValue) return maxValue;
63     return value;
64 }
65 // bounds an int16 value
66 static inline int16_t clampInt16(int16_t value, int16_t minValue
67     , int16_t maxValue) {
68     if (value < minValue) return minValue;
69     if (value > maxValue) return maxValue;
70     return value;
71 }
72 // rounds a float to the nearest int16
73 static inline int16_t roundToInt(float value) {
74     return (int16_t)(value + ((value >= 0.0f) ? 0.5f : -0.5f));
75 }
76
77 // fixed point moving average shift
78 #define EMA_SHIFT 3
```



```

79
80 // calculates exponential moving average step
81 static inline int16_t emaStep(int16_t smoothed, int16_t incoming
    ) {
82     return (int16_t)(smoothed + ((incoming - smoothed) >>
        EMA_SHIFT));
83 }
84
85 // prints fixed point value with one decimal
86 static void printFixed(const char* fmt_P, int16_t val_x10) {
87     int16_t intPart;
88     uint8_t fracPart;
89     if (val_x10 < 0) {
90         int16_t abs_x10 = (int16_t)(-val_x10);
91         intPart = (int16_t)(-(abs_x10 / 10));
92         fracPart = (uint8_t) ( abs_x10 % 10u);
93     } else {
94         intPart = (int16_t)(val_x10 / 10);
95         fracPart = (uint8_t) (val_x10 % 10u);
96     }
97     printf_P(fmt_P, (int)intPart, (unsigned)fracPart);
98 }
99
100 // pid variables
101 static float pidIntegral = 0.0f;
102 static float lastError   = 0.0f;
103
104 // reads serial inputs for system configuration
105 void TaskRead(void* pvParameters) {
106     (void)pvParameters;
107     while (true) {
108         char c = 0;
109         if (scanf("%c", &c) > 0 && c != '\0' && c != '\n' && c
            != '\r') {
110             lastKeyPressed = c;
111             sysState.key    = c;
112
113             if (c >= '0' && c <= '9') {


```





```

114         if (inputIndex < 3) {
115             inputBuffer[inputIndex++] = c;
116             inputBuffer[inputIndex] = '\0';
117         }
118     } else if (c == '#' || c == 'A') {
119         if (inputIndex > 0) {
120             minDistanceCm = clampThreshold(
121                 parseInputBuffer());
122             sysState.thresholdCm = minDistanceCm;
123             clearInputBuffer();
124         }
125     } else if (c == '*' || c == 'B') {
126         clearInputBuffer();
127     } else if (c == 'C') {
128         minDistanceCm = MIN_DISTANCE_DEFAULT_CM;
129         sysState.thresholdCm = minDistanceCm;
130         clearInputBuffer();
131     } else if (c == 'D') {
132         minDistanceCm = clampThreshold((uint16_t)
133             (minDistanceCm + 5u));
134         sysState.thresholdCm = minDistanceCm;
135         clearInputBuffer();
136     }
137 }
138 }
139
140 // executes sensor reading and pid control
141 void TaskFilter(void* pvParameters) {
142     ControlContext* ctx = static_cast<ControlContext*>(
143         pvParameters);
144     ServoActuator* actuator = ctx->actuator;
145     DistanceSensor* sensor = ctx->sensor;
146
147     // start fully closed
148     actuator->setPosition(SERVO_POS_MIN);
149     vTaskDelay(pdMS_TO_TICKS(300));

```



```
149     gateOpen    = false;
150     servoAngle = actuator->getAngle();
151
152     static bool controlActive    = false;
153     static uint32_t lastOpenMs   = 0;
154
155     while (true) {
156         const float rawDistance = sensor->readRaw();
157         const bool  valid       = (rawDistance > 0.5f) &&
158                                   (rawDistance <= (float)
159                                                  MIN_DISTANCE_MAX_CM);
159         const uint16_t distanceCm = valid ? (uint16_t)(
160             rawDistance + 0.5f) : 0u;
161
162         const uint32_t nowMs = millis();
163         const bool inRange = valid && (distanceCm <=
164             minDistanceCm);
165         const bool aboveClose = valid &&
166             (distanceCm > (uint16_t)(minDistanceCm +
167                                     GATE_HYSTERESIS_CM));
168         const bool holdOpen = controlActive &&
169             ((uint32_t)(nowMs - lastOpenMs) < GATE_MIN_OPEN_MS);
170
171         if (inRange) {
172             if (!controlActive) {
173                 controlActive = true;
174                 lastOpenMs = nowMs;
175             }
176         } else if (!valid || aboveClose) {
177             if (controlActive && (uint32_t)(nowMs - lastOpenMs)
178                 >= GATE_MIN_OPEN_MS) {
179                 controlActive = false;
180             }
181         }
182     }
183
184     // runs PID only while active and in range; holds last
185     // output otherwise
186     if (controlActive && inRange) {
```




```
181     const float setpoint = (float)minDistanceCm;
182     float error = setpoint - (float)distanceCm;
183
184     // zeroes error near threshold to stop micro-
185     // movements;
186     // integral is preserved so the servo can still
187     // reach SERVO_POS_MAX
188     if (error >= -1.0f && error <= 1.0f) {
189         error = 0.0f;
190     }
191
192     if (PID_INVERT_OUTPUT) error = -error;
193
194     const float dt = (float)TASK_CONTROL_PERIOD / 1000.0
195         f;
196     pidIntegral = clampFloat(pidIntegral + (error *
197         dt),
198         PID_INTEGRAL_MIN,
199         PID_INTEGRAL_MAX);
200     const float derivative = (error - lastError) / dt;
201     float control = (PID_KP * error)
202         + (PID_KI * pidIntegral)
203         + (PID_KD * derivative);
204
205     // zeroes out negligible control signals to keep
206     // servo still
207     if (control > -2.0f && control < 2.0f) {
208         control = 0.0f;
209     }
210
211     // command offset from SERVO_POS_MIN: zero control =
212     // fully closed,
213     // positive control opens toward SERVO_POS_MAX
214     int16_t command = (int16_t)SERVO_POS_MIN +
215         roundToInt(control);
216     command = clampInt16(command, SERVO_POS_MIN,
217         SERVO_POS_MAX);
218     if (holdOpen && command < SERVO_POS_OPEN) {
```



```

210         command = SERVO_POS_OPEN;
211     }
212     actuator->setPosition((uint8_t)command);
213
214     gateOpen      = (command > SERVO_POS_MIN);
215     lastError     = error;
216     pidErrorCm    = roundToInt(error);
217     pidOutputPos  = (uint8_t)command;
218 } else if (controlActive) {
219     if (holdOpen) {
220         actuator->setPosition(SERVO_POS_OPEN);
221         gateOpen = true;
222         pidOutputPos = SERVO_POS_OPEN;
223     } else {
224         actuator->setPosition(pidOutputPos);
225         gateOpen = (pidOutputPos > SERVO_POS_MIN);
226     }
227 } else {
228     // object out of range - drive fully closed, clear
229     pid memory
230     actuator->setPosition(SERVO_POS_MIN);
231     gateOpen      = false;
232     pidIntegral   = 0.0f;
233     lastError     = 0.0f;
234     pidErrorCm    = 0;
235     pidOutputPos  = SERVO_POS_MIN;
236 }
237
238 measuredDistanceCm = distanceCm;
239 sensorValid       = valid;
240 servoAngle        = actuator->getAngle();
241
242 sysState.distanceCm      = measuredDistanceCm;
243 sysState.thresholdCm    = minDistanceCm;
244 sysState.angle           = servoAngle;
245 sysState.errorCm         = pidErrorCm;
246 sysState.outputPos       = pidOutputPos;
247 sysState.isOpen          = gateOpen;


```




```

247     sysState.isSensorValid = sensorValid;
248
249     vTaskDelay(pdMS_TO_TICKS(TASK_CONTROL_PERIOD));
250 }
251 }
252
253 // displays output on serial and processes telemetry
254 void TaskDisplay(void* pvParameters) {
255     (void)pvParameters;
256
257     // moving average variables
258     static int16_t smoothDist_x10 = 0;
259     static int16_t smoothErr_x10  = 0;
260     static int16_t smoothOut      = 0;
261     static bool    smoothReady    = false;
262
263     while (true) {
264         // reads shared state
265         uint16_t dLocal, tLocal;
266         uint8_t  angleLocal, outLocal;
267         int16_t  errLocal;
268         bool     validLocal;
269         char     keyLocal;
270         char     localInput[4] = "____";
271
272         taskENTER_CRITICAL();
273         dLocal      = sysState.distanceCm;
274         tLocal      = sysState.thresholdCm;
275         angleLocal  = sysState.angle;
276         errLocal    = sysState.errorCm;
277         outLocal    = sysState.outputPos;
278         validLocal  = sysState.isSensorValid;
279         keyLocal    = sysState.key;
280         if (inputIndex > 0) {
281             strncpy(localInput, inputBuffer, 3);
282             localInput[3] = '\0';
283         }
284         taskEXIT_CRITICAL();

```



```
285
286     if (keyLocal < 32 || keyLocal > 126) keyLocal = '-';
287
288     // teleplot serial logic
289     if (ENABLEPLOTTER) {
290         if (validLocal) {
291             const int16_t dist_x10 = (int16_t)(dLocal * 10u)
292             ;
293             const int16_t err_x10  = (int16_t)(errLocal *
294             10);
295             // output relative to SERVO_POS_MIN: 0 = closed ,
296             positive = opening
297             const int16_t out = (int16_t)((int16_t)outLocal
298             - (int16_t)SERVO_POS_MIN);
299
300             if (!smoothReady) {
301                 smoothDist_x10 = dist_x10;
302                 smoothErr_x10  = err_x10;
303                 smoothOut      = out;
304                 smoothReady    = true;
305             } else {
306                 smoothDist_x10 = emaStep(smoothDist_x10 ,
307                 dist_x10);
308                 smoothErr_x10  = emaStep(smoothErr_x10 ,
309                 err_x10);
310                 smoothOut      = emaStep(smoothOut ,
311                 out);
312             }
313
314             printf_P(PLOT_DIST,  smoothDist_x10);
315             printf_P(PLOT_SETPPOINT, tLocal);
316             printf_P(PLOT_ERROR,  smoothErr_x10);
317             printf_P(PLOT_OUTPUT,  (int)smoothOut);
318             printf_P(PLOT_VALID,   1u);
319
320             } else {
321                 smoothReady = false;
322                 printf_P(PLOT_SETPPOINT, tLocal);
```



```

317         printf_P (PLOT_VALID,      0u);
318     }
319
320     vTaskDelay (pdMS_TO_TICKS (TASK_PLOT_PERIOD));
321     continue;
322 }
323
324 // text display logic
325 // '=' closed (at or near MIN), '>' opening above MIN +
    deadband
326 // '<' removed — servo never goes below SERVO_POS_MIN
327 char dirChar = '=';
328 if (angleLocal > (uint8_t)(SERVO_ANGLE_MIN +
    SERVO_ANGLE_DEADBAND)) {
329     dirChar = '>';
330 }
331
332 if (validLocal) {
333     printf_P (STR_LINE0, dLocal, tLocal, dirChar);
334 } else {
335     printf_P (STR_LINE0_INVALID, tLocal, dirChar);
336 }
337
338 printf_P (STR_LINE1, keyLocal, localInput);
339 printf_P (PSTR("\n\n"));
340
341 vTaskDelay (pdMS_TO_TICKS (TASK_DISPLAY_PERIOD));
342 }
343 }

```


Listing 4: tasks.cpp - Task Implementation

main.cpp


```

1 #include <Arduino.h>
2 #include <Arduino_FreeRTOS.h>
3 #include <Keypad.h>
4 #include <Wire.h>
5 #include <LiquidCrystal_I2C.h>
6 #include <lcd/LcdStdioManager.h>
7 #include <keypad/KeypadStdioManager.h>

```



```
8 #include "actuator.h"
9 #include <serialio/serialio.h>
10 #include <sensors/distance.h>
11 #include "tasks.h"
12
13 // LCD (I2C address 0x27, 16x2)
14 static LiquidCrystal_I2C lcd(0x27, 16, 2);
15
16 // Keypad pin configuration
17 static byte rowPins[4] = {9, 8, 7, 6};
18 static byte colPins[4] = {5, 4, 3, A1};
19
20 // Keypad layout (PROGMEM via Keypad library)
21 static const char keys[4][4] = {
22     {'1', '2', '3', 'A'},
23     {'4', '5', '6', 'B'},
24     {'7', '8', '9', 'C'},
25     {'*', '0', '#', 'D'}
26 };
27
28 static Keypad keypad(makeKeymap(keys), rowPins, colPins, 4, 4);
29
30 // Servo actuator on pin 11
31 static ServoActuator actuator(11);
32 // Ultrasonic sensor from nano simulation: TRIG=A0, ECHO=D2
33 static DistanceSensor distanceSensor(A0, 2);
34 static ControlContext controlContext = {&actuator, &
    distanceSensor};
35
36 void setup() {
37     Serial.begin(9600);
38     actuator.begin();
39     distanceSensor.init();
40
41     lcd.init();
42     lcd.backlight();
43
44     // STDIO: LCD output, Keypad input
```

```
45  static LcdStdioManager lcdManager;  
46  // lcdManager.setup(&lcd);  
47  KeypadStdioManager::setup(&keypad);  
48  
49  redirectSerialToStdio(false, true, true);  
50  
51  // FreeRTOS tasks (stack sizes tuned for Nano - 2KB RAM)  
52  xTaskCreate(TaskRead, "Read", 100, NULL, 1, NULL);  
53  xTaskCreate(TaskFilter, "Filter", 160, &controlContext, 2,  
54             NULL);  
55  xTaskCreate(TaskDisplay, "Disp", 140, NULL, 1, NULL);  
56  
57  // fprintf_P(stderr, PSTR("Ready\n"));  
58  vTaskStartScheduler();  
59  
60 void loop() {}
```

Listing 5: main.cpp - System Initialization