TECHNICAL REPORT

Vataleni PMSG + SSO Wind-Energy System

Self-contained Simulink implementation, oscillation study, mitigation and validation

Authoritative model: model/Vataleni_PMSG_SSO_Final.slx

Generated from fresh MATLAB/Simulink results - 13 August 2026

Executive summary

This report documents the repaired 5 MW averaged dq wind-energy model. The authoritative SLX contains the wind-turbine, PMSG rotor, machine-side control, DC link, grid-side control, PLL, grid-current dynamics, PCC algebra and measurement equations internally. It does not call custom Level-2 MATLAB S-Functions and it runs from a fresh MATLAB session without an initialization script.

The weak-grid disturbance changes short-circuit ratio (SCR) from 10 to 5 at 2 s. The fresh simulation identifies a dominant electrical-power oscillation at 4.8447 Hz. The matching nonlinear-state Jacobian mode is +0.04749 +/- j30.41449 per second, with negative damping ratio -0.00156. Reducing the PLL integral gain from 2.8 to 0.5 moves the tracked mode into the stable half-plane and reduces late-window power-oscillation RMS from 0.067754 pu to 2.657e-07 pu.

Item	Validated value
MATLAB / Simulink	R2025b / 25.2
Model	model/Vataleni_PMSG_SSO_Final.slx
Solver	ode4, fixed step, 0.0002 s
Simulation horizon	12 s
Custom S-Functions	0
Algebraic loops	0

1. Objective and study scope

The model studies converter-grid interaction in a full-converter permanent-magnet synchronous-generator wind turbine. It is intended for time-domain and small-signal investigation of sub-synchronous oscillation (SSO) under changing grid strength, and for a controlled comparison of a PLL-gain mitigation.

- Base rating: 5 MVA, 690 V line-line, 50 Hz.
- Plant representation: nonlinear averaged dq model; no switching ripple.
- Disturbance: SCR step from 10 to 5 at 2 s.
- Mitigation: PLL integral gain changes from 2.8 to 0.5 with all other case parameters held equal.

2. System architecture

The top-level diagram is organized left-to-right. Compact diagnostic vectors feed the logging interface without altering the physical signal paths. Every continuous state is an Integrator block; each equation set is stored in an embedded MATLAB Function block inside the SLX.




Figure 1. Authoritative top-level Simulink architecture.

Subsystem	Inputs	Outputs / states
Wind Turbine + PMSG	wind speed, machine iq	rotor speed, mechanical power/torque; omega_r
MSC Control	rotor speed	machine iq and reference; iq_m, speed PI state
DC Link	mechanical power, speed, grid power	vdc; capacitor-energy state
GSC Control	vdc, id, iq, mechanical power	vcd/vcq commands; three PI states
PLL	PCC vq, mitigation selector	angle, frequency deviation; angle and PI states
Grid Current	converter voltage, PLL frame, SCR	id/iq; two current states
PCC Interface	angle, id, iq, SCR	vd/vq, P/Q, voltage magnitude
Measurements	diagnostic vectors and time	35 logged engineering channels

3. Governing equations

3.1 Aerodynamics and rotor

The standard exponential power-coefficient fit is bounded to 0 <= Cp <= 0.50. Aerodynamic power is limited to 1.15 pu and torque follows from power divided by pu speed.

lambda = omega_r omega_base R / v_w ; P_m = 0.5 rho A Cp v_w^3 / S_base

d omega_r / dt = [T_m - i_qm - D(omega_r - 1)] / (2H)

3.2 Machine-side converter

i_qm,ref = Kp_speed(omega_r - 1) + xi_speed

d i_qm/dt = (i_qm,ref - i_qm)/tau_i ; d xi_speed/dt = Ki_speed(omega_r - 1)

The machine electrical inner loop is an averaged first-order torque-current channel. Machine d-axis current is zero in this reduced-order representation; switching-level machine voltage references are therefore outside the model fidelity.

3.3 DC link

d v_dc/dt = (P_m omega_r - P_grid) / [C_pu max(v_dc, 0.25)]

3.4 Grid-side converter

i_d,ref = P_m + Kp_dc(v_dc - v_dc,ref) + xi_dc ; i_q,ref = 0

v_cd = E + Kp_i(i_d,ref - i_d) + xi_id - X_f i_q

v_cq = Kp_i(i_q,ref - i_q) + xi_iq + X_f i_d

3.5 PLL and weak-grid interface

Delta omega_PLL = Kp_PLL v_q + xi_PLL ; d delta/dt = omega_base Delta omega_PLL

d xi_PLL/dt = Ki_PLL v_q ; Ki_PLL = 2.8 (base) or 0.5 (mitigated)

v_d = E cos(delta) + R_g i_d - X_g i_q ; v_q = -E sin(delta) + R_g i_q + X_g i_d

P = v_d i_d + v_q i_q ; Q = v_q i_d - v_d i_q

3.6 Grid current dynamics

d i_d/dt = omega_b/L_t [v_cd - E cos(delta) - R_t i_d + L_t(1+Delta omega_PLL)i_q]

d i_q/dt = omega_b/L_t [v_cq + E sin(delta) - R_t i_q - L_t(1+Delta omega_PLL)i_d]

4. Parameterization and initialization

Group	Parameter	Value
Base	S, Vll, f	5 MVA; 690 V; 50 Hz
Wind	rho, R, lambda_opt	1.225 kg/m3; 55 m; 6.3
Rotor	H, D	4.0 s; 0.02 pu
MSC	Kp/Ki speed; tau_i	2.0 / 1.0; 0.02 s
DC	C_pu; vdc_ref	0.08 s; 1.0 pu
GSC	Kp_i/Ki_i; Kp_dc/Ki_dc	0.30/20; 0.80/20
Filter	R_f; X_f	0.01 pu; 0.15 pu
Grid	E; X/R	1.0 pu; 10
PLL	Kp; Ki base/mitigated	0.01; 2.8 / 0.5

Initial conditions are the consistent SCR=10 power-flow solution for nominal wind and 1 pu rotor speed. Those numerical state values, scenario defaults, stop time and fixed step are saved inside the model. No callback, addpath command or base-workspace parameter structure is needed for standalone execution.

5. Numerical configuration

The final configuration uses fixed-step classical fourth-order Runge-Kutta (ode4), dt = 0.0002 s, and a 12 s horizon. The model contains eleven continuous states and no zero-crossing-dependent logic. The fixed step resolves the approximately 4.84 Hz SSO with more than one thousand points per cycle while preserving deterministic batch reproducibility.




Figure 2. Timestep sensitivity of the FFT-identified SSO frequency.

A fresh sweep over 1.0 ms, 0.5 ms, 0.2 ms and 0.1 ms gives 4.8370, 4.8370, 4.8447 and 4.8447 Hz respectively. The 0.2 ms result is converged to the 0.1 ms rerun at the reported precision.

6. Scenario definitions

Scenario	SCR	Wind	PLL Ki	Purpose
Baseline	10 -> 10	12 m/s	2.8	steady strong-grid reference
Wind step	10 -> 10	12 -> 10.5 m/s at 4 s	2.8	aerodynamic/control response
SSO before	10 -> 5 at 2 s	12 m/s	2.8	weak-grid instability
SSO after	10 -> 5 at 2 s	12 m/s	0.5	controlled mitigation comparison

7. Time-domain results




Figure 3. Baseline rotor speed, active power and DC-link voltage.




Figure 4. Weak-grid SSO response in power, DC-link voltage and q-axis grid current.




Figure 5. Generator speed, mechanical/electromagnetic torque and grid currents.




Figure 6. PCC dq voltage and active/reactive power.




Figure 7. Baseline, weak-grid SSO and mitigated active-power responses.

8. Frequency-domain and modal analysis

FFT analysis uses the simulated active-power channel after the configured analysis start. The nonlinear model is also linearized numerically by a centered finite-difference Jacobian of the exact eleven-state ODE at the case equilibrium. Prony analysis provides an independent damped-sinusoid estimate. No eigenvalues or spectral peaks are loaded from a cache.




Figure 8. FFT spectrum of the weak-grid active-power oscillation.




Figure 9. Eigenvalue map of the weak-grid state Jacobian.

Case	FFT (Hz)	Prony sigma (1/s)	Eigen real (1/s)	Eigen freq. (Hz)	Eigen damping
Before	4.8447	+0.05148	+0.04749	4.8406	-0.00156
After	1.8883	-1.39367	-1.39437	1.8923	+0.11648

9. Mitigation assessment




Figure 10. Active-power response before and after PLL-gain mitigation.




Figure 11. Spectral comparison before and after mitigation.




Figure 12. Eigenvalue comparison before and after mitigation.

Metric	Before	After	Change
SSO frequency FFT (Hz)	4.84467	1.88828	-2.95639
Prony frequency (Hz)	4.83487	1.89233	-2.94254
Prony damping ratio	-0.00169455	0.116418	+0.118112
Eigenvalue frequency (Hz)	4.84062	1.89234	-2.94827
Eigenvalue damping ratio	-0.00156147	0.116475	+0.118037
Power oscillation RMS (pu)	0.0677542	2.65677e-07	-0.067754
Peak current (pu)	0.97445	0.914417	-0.0600324
Vdc max deviation (pu)	0.044871	0.0148467	-0.0300243

The comparison supports the limited claim that the selected PLL integral-gain reduction stabilizes the tracked converter-grid mode for this parameter set. It is not evidence of universal robustness across turbine ratings, grid topologies, switching models or untested operating points.

10. Validation and portability

The validator starts with bdclose('all'), clear and clc. It opens and compiles the authoritative SLX without adding project scripts, executes its default simulation, audits S-Functions, callbacks, unresolved links, machine paths and algebraic loops, then regenerates baseline, SSO, mitigation, wind-step, figures and compact result exports. It throws an error unless all twenty checks pass.

- Core dynamics: embedded MATLAB Function blocks plus native Integrator, Step, Constant, Mux and routing blocks.
- Custom Level-2 MATLAB S-Functions in authoritative model: zero.
- Model callbacks: empty.
- Unresolved library links: zero.
- Algebraic loops: zero; no artificial loop-breaking Memory or Unit Delay blocks are required.
- Standalone default simulation: load_system followed by sim from a clean MATLAB process.

11. Limitations

- The converter and machine are averaged; semiconductor switching, PWM ripple and detailed magnetic saturation are excluded.
- The rotor is a single-mass inertia; shaft torsional modes are not represented.
- The machine-side electrical loop is reduced to a first-order q-axis torque-current response with id = 0.
- Mitigation is evaluated for the documented SCR step and nominal operating point, not a full grid-code envelope.
- The study is a model-based investigation and is not a substitute for field, controller-hardware or EMT validation.

12. Conclusions

The repaired SLX is a portable, self-contained implementation of the recovered nonlinear averaged model. The weak-grid case produces an internally consistent 4.84 Hz SSO identified by FFT, Prony and eigenanalysis. The tested PLL-gain mitigation changes the critical modal real part from positive to negative and materially reduces DC-link deviation, peak current and active-power oscillation for the controlled comparison. The model, scripts, figures, result tables and reports are regenerated from the same authoritative equations and scenario definitions.

Appendix A. Logged signal dictionary

#	Signal	#	Signal
1	wind_speed	19	cp
2	omega_r	20	lambda
3	torque_m	21	turbine_speed
4	power_m	22	electrical_rotor_speed
5	iq_machine	23	torque_e
6	vdc	24	id_machine
7	id_grid	25	iq_machine_reference
8	iq_grid	26	vcd_reference
9	power_e	27	vcq_reference
10	reactive_q	28	pll_frequency_hz
11	vd_pcc	29	sso_signal
12	vq_pcc	30	damping_gain
13	v_pcc	31	controller_command
14	pll_angle	32	grid_voltage_pu
15	ia	33	id_grid_reference
16	va	34	iq_grid_reference
17	current_pu	35	pll_ki_selected
18	scr		

Appendix B. Reproduction

Fresh validation command:

matlab -batch ”cd('<repo-root>'); run('validation/validate_project.m')”

Independent standalone simulation command:

matlab -batch ”cd('<repo-root>'); load_system('model/Vataleni_PMSG_SSO_Final.slx');

out=sim('Vataleni_PMSG_SSO_Final')”