



PicoMuon Detector

Setting up a

Raspberry Pi 4/5

Pico^μ

<https://ukraa.com/>

The UK Radio Astronomy Association

A charitable incorporated organisation

Registered charity in England and Wales No. 1123866



Table of Contents

.....	2
Set-up instructions.....	4
Raspberry Pi OS.....	5
RPi4 configuration.....	14
Headless access to RPi via VNC	20
License	23
Contact us	23

Set-up instructions

These instructions cover setting up your Raspberry Pi4 or Raspberry Pi 5 with a suitable operating system and ability to be remotely access via VNC.

It is recommended that you use a Raspberry Pi 4/5 with at least 2GB memory.

When using the Raspberry Pi Imager, remember to write down the **hostname** you use – this is used to view the web page with the results from your UKRAA PicoMuon detector.

Please keep the username as **pi** when using OS customisation within the Raspberry Pi Imager.


The instructions for accessing your Raspberry Pi heedlessly assume use of Windows PC and that the following two applications are preinstalled on that PC.

- PuTTY
- RealVNC Viewer


No information on installing these two applications is given in this text – there are numerous guides available on the internet.

Raspberry Pi OS


1. Download [Raspberry Pi Imager](#) for your operating system.




2. Run Raspberry Pi Imager.




3. Select **CHOOSE DEVICE** and then select your **Raspberry Pi device**.




4. Select **CHOOSE OS** and then select **Raspberry Pi OS (64bit)**.



5. Select **CHOOSE STORAGE** and select your **microSD card** for your RPi.



6. Select **NEXT**
7. You are presented with a **Use OS customisation?** window, select **EDIT SETTINGS**.



8. On the **GENERAL** page...

- Set **hostname** - set to whatever you want - but write it down, we will need it latter!
- Set **Username:** and **Password:**
 - Keep username as **pi**
 - set your own password
- Configure wireless LAN
 - if you wish to use you RPi wirelessly
 - Enter your wireless network's **SSID:**, **Password:** and **Wireless LAN country:**
- Set locale settings
 - set **Time zone:** and **Keyboard layout** to your preferences

OS Customisation

GENERAL

SERVICES

OPTIONS

☒ Set hostname: .local

☒ Set username and password

Username:

Password:

☒ Configure wireless LAN

SSID:

Password:

☒ Show password ☐ Hidden SSID

Wireless LAN country:


☒ Set locale settings

Time zone:

Keyboard layout:

SAVE

9. Select **SERVICES**
 - Keep as shown




The screenshot shows the 'OS Customisation' window with the 'SERVICES' tab selected. The 'GENERAL' tab is also visible. The 'SERVICES' tab contains the following options:

- ☒ Enable SSH
 - ☒ Use password authentication
 - ☐ Allow public-key authentication only
 - Set authorized_keys for 'pi':
 -

Below the radio buttons is a button labeled 'RUN SSH-KEYGEN'. At the bottom of the window is a large red 'SAVE' button.


10. Select **OPTIONS**

- Keep as shown




11. Select **SAVE** at bottom of window.


12. Now apply the customised OS settings by selecting **YES**.




13. You will be asked if you wish to proceed, select **YES**.




14. The operating system will now be written to the microSD card



15. and then verified, this take a bit of time...



16. When finished, you can remove the microSD card and select **CONTINUE** and close the **Raspberry Pi Imager**.




RPi4 configuration

Put the microSD card you have just created into your RPi4, connect the RPi to your LAN if necessary, insert the power cable and turn on.

Using PuTTY (<https://www.putty.org/>)

1. In **Host Name (or IP address)**, type the host name of your RPi that you wrote down earlier... and select **Open**




2. You will be presented with a PuTTY Security Alert - select **Accept**. You will now have a PuTTY terminal window.



3. Login as **pi** and enter your **password**
4. Now type the command below and press enter. This will update the RPi OS


sudo apt update



```
pi@RPi4-UKRAA: ~  
login as: pi  
pi@RPi4-UKRAA.local's password:  
Linux RPi4-UKRAA 6.6.51+rpt-rpi-v8 #1 SMP PREEMPT Debian 1:6.6.51-1+rpt3 (2024-10-08) aarch64  
  
The programs included with the Debian GNU/Linux system are free software;  
the exact distribution terms for each program are described in the  
individual files in /usr/share/doc/*/copyright.  
  
Debian GNU/Linux comes with ABSOLUTELY NO WARRANTY, to the extent  
permitted by applicable law.  
Last login: Tue Nov 19 13:44:32 2024  
  
Wi-Fi is currently blocked by rfkill.  
Use raspi-config to set the country before use.  
pi@RPi4-UKRAA:~ $ sudo apt update
```

5. Now type the command below and press enter. This will update any preinstalled software packages. You will be asked to type **y** to proceed.


sudo apt upgrade



```
pi@RPi4-UKRAA: ~  
Get:3 http://deb.debian.org/debian bookworm-updates InRelease [55.4 kB]  
Get:4 http://archive.raspberrypi.com/debian bookworm InRelease [39.3 kB]  
Get:5 http://deb.debian.org/debian-security bookworm-security/main arm64 Packages [235 kB]  
Get:6 http://deb.debian.org/debian-security bookworm-security/main armhf Packages [220 kB]  
Get:7 http://deb.debian.org/debian-security bookworm-security/main Translation-en [141 kB]  
Get:8 http://deb.debian.org/debian bookworm-updates/main arm64 Packages [8,844 B]  
Get:9 http://deb.debian.org/debian bookworm-updates/main armhf Packages [8,292 B]  
Get:10 http://deb.debian.org/debian bookworm-updates/main Translation-en [8,248 B]  
Get:11 http://archive.raspberrypi.com/debian bookworm/main arm64 Packages [520 kB]  
Get:12 http://archive.raspberrypi.com/debian bookworm/main armhf Packages [549 kB]  
Fetched 1,730 kB in 1s (1,625 kB/s)  
Reading package lists... Done  
Building dependency tree... Done  
Reading state information... Done  
50 packages can be upgraded. Run 'apt list --upgradable' to see them.  
pi@RPi4-UKRAA:~ $ sudo apt upgrade
```

6. You may be advised that you can remove **no longer required** packages. You can type the command below and press enter. Again, you will be asked to type **y** to proceed.

sudo apt autoremove




```
pi@RPi4-UKRAA: ~  
'/boot/initrd.img-6.6.62+rpt-rpi-v8' -> '/boot/firmware/initramfs8'  
update-initramfs: Generating /boot/initrd.img-6.6.62+rpt-rpi-2712  
'/boot/initrd.img-6.6.62+rpt-rpi-2712' -> '/boot/firmware/initramfs_2712'  
pi@RPi4-UKRAA:~ $ sudo apt update  
Hit:1 http://deb.debian.org/debian bookworm InRelease  
Hit:2 http://deb.debian.org/debian-security bookworm-security InRelease  
Hit:3 http://deb.debian.org/debian bookworm-updates InRelease  
Hit:4 http://archive.raspberrypi.com/debian bookworm InRelease  
Reading package lists... Done  
Building dependency tree... Done  
Reading state information... Done  
1 package can be upgraded. Run 'apt list --upgradable' to see it.  
pi@RPi4-UKRAA:~ $ sudo apt upgrade  
Reading package lists... Done  
Building dependency tree... Done  
Reading state information... Done  
Calculating upgrade... Done  
The following package was automatically installed and is no longer required:  
  libwlroots12  
Use 'sudo apt autoremove' to remove it.  
The following packages have been kept back:  
  raspberrypi-ui-mods  
0 upgraded, 0 newly installed, 0 to remove and 1 not upgraded.  
pi@RPi4-UKRAA:~ $ sudo apt autoremove
```


7. We can now set up VNC to access the RPi from our desktop PC. Type the command below and press enter. We will be presented with the RPi configuration tool.

sudo raspi-config

8. Select **3 Interface Options** and selecting **Select** and press enter.




9. Now navigate down to **I3 VNC** and selecting **Select** and press enter.




10. Select **Yes** and press enter to enable the VNC Server.



11. VNC server will now be enabled, press enter.



12. Finish with the Configuration Tool by selecting **Finish** and press enter.



```
pi@RPi4-UKRAA: ~
Raspberry Pi 4 Model B Rev 1.5, 4GB


Raspberry Pi Software Configuration Tool (raspi-config)

1 System Options      Configure system settings
2 Display Options     Configure display settings
3 Interface Options   Configure connections to peripherals
4 Performance Options Configure performance settings
5 Localisation Options Configure language and regional settings
6 Advanced Options    Configure advanced settings
8 Update              Update this tool to the latest version
9 About raspi-config  Information about this configuration tool

<Select>                <Finish>
```

13. Reboot the RPi, type the command below and press enter. This will close the PuTTY connection. You can close the Putty window.

sudo reboot



```
PuTTY (inactive)

Hit:3 http://deb.debian.org/debian-security bookworm-security InRelease
Hit:4 http://deb.debian.org/debian bookworm-updates InRelease
Reading package lists... Done
Building dependency tree... Done
Reading state information... Done
1 package can be upgraded. Run 'apt list --upgradable' to see it.
pi@RPi4-UKRAA:~ $ sudo apt upgrade
Reading package lists... Done
Building dependency tree... Done
Reading state information... Done
Calculating upgrade... Done
The following packages have been kept back:
  raspberrypi-ui-mods
0 upgraded, 0 newly installed, 0 to remove and 1 not upgraded.
pi@RPi4-UKRAA:~ $ sudo raspi-config
Created symlink /etc/systemd/system/multi-user.target.wants/wayvnc.service → /lib/systemd/system/wayvnc.service.
pi@RPi4-UKRAA:~ $ sudo reboot now

Broadcast message from root@RPi4-UKRAA on pts/1 (Sat 2024-12-28 17:55:47 GMT):


The system will reboot now!

pi@RPi4-UKRAA:~ $
```


Headless access to RPi via VNC

Using a VNC program like RealVNC (<https://www.realvnc.com/en/>), connect to your RPi using your desktop PC...


1. Create a **New connections** (CTRL-N) and enter the hostname into the **VNC Server:** box, add friendly name in the **Name** box and select **OK**.




2. Open this VNC connection to your RPi; you will get a **VNC server not recognised** window from RealVNC. Select **Continue**



3. You will now get an **Authentication** window from RealVNC, enter your **Username** and **Password** details and select **Remember password** to make it easier to login in future.



4. You are now remotely accessing your RPi from your desktop PC...



License

MIT License

Copyright (c) 2024 UKRAA

Permission is hereby granted, free of charge, to any person obtaining a copy of this software and associated documentation files (the **Software**), to deal in the Software without restriction, including without limitation the rights to use, copy, modify, merge, publish, distribute, sublicense, and/or sell copies of the Software, and to permit persons to whom the Software is furnished to do so, subject to the following conditions:

The above copyright notice and this permission notice shall be included in all copies or substantial portions of the Software.

THE SOFTWARE IS PROVIDED **AS IS**, WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT. IN NO EVENT SHALL THE AUTHORS OR COPYRIGHT HOLDERS BE LIABLE FOR ANY CLAIM, DAMAGES OR OTHER LIABILITY, WHETHER IN AN ACTION OF CONTRACT, TORT OR OTHERWISE, ARISING FROM, OUT OF OR IN CONNECTION WITH THE SOFTWARE OR THE USE OR OTHER DEALINGS IN THE SOFTWARE.

Contact us

Please send an e-mail to picomuon@ukraa.com

