



BMM150

Magnetometer BMM150

Professional electronic component

v1.0
2025-07-17
Rev. A

PRODUCT OVERVIEW

The BMM150 is a compact, low-power triaxial geomagnetic sensor from Bosch Sensortec. It delivers precise magnetic field measurements on three axes and supports I²C/SPI interfaces for easy integration with platforms like Arduino, ESP32, and Raspberry Pi. Its built-in compensation algorithms and support for sensor fusion make it ideal for navigation, robotics, and wearable applications.

PRODUCT VIEWS

TOP VIEW



Top View

Component placement and connectors

BOTTOM VIEW



Bottom View

Underside components and connections

KEY TECHNICAL SPECIFICATIONS

POWER SUPPLY

Operating Voltage:

3.3V

Supply Current:

170μA

CONNECTIVITY

Interfaces:

I²C, SPI

Connector:

Qwiic + Pin Headers

TECHNICAL FEATURES

Axes: 3 (X, Y, Z)	Measurement Range: ±1300 μT
Resolution: ~0.3 μT	Power Consumption: Ultra-low power consumption for battery-operated devices
Interfaces: I ² C and SPI	Operating Voltage (VDD / VDDIO): 3.3 V (regulated internal voltage for sensor operation)
Input Voltage via VCC Pin: 3.6–6.0 V (through onboard voltage regulator)	Operating Temperature: Wide operating range suitable for various environments
Additional Signals:	DRDY (Data Ready)
INT (Programmable Interrupt)	

TECHNICAL SPECIFICATIONS

TYPICAL APPLICATIONS

APPLICATION	DESCRIPTION
Electronic Compass	Detects Earth's magnetic field to determine the device orientation.
Inertial Navigation (INS)	Integrates with accelerometers and gyroscopes to improve position and orientation estimation.
Augmented Reality (AR)	Dynamically adjusts AR content on smart devices based on precise orientation data.
Metal Detection / Proximity Sensing	Monitors magnetic field variations to detect metallic objects and machinery anomalies.
Mobile Robotics and Drones	Provides reliable heading information, essential for indoor navigation and autonomous operation.
Wearables and Portable Devices	Enhances personal navigation in smartwatches, fitness trackers, and other portable devices.
Indoor Geolocation	Improves indoor positioning accuracy by compensating for sensor drift and interference.

HARDWARE DOCUMENTATION

MECHANICAL DIMENSIONS



Physical dimensions and mounting specifications (measurements in millimeters)

SYSTEM TOPOLOGY



Connection topology and system integration diagram

Click image to open in full size

COMPONENT REFERENCE

REF.	DESCRIPTION
IC1	BMM150 Magnetometer
U1	AP2112K 3V3 Regulator
L1	Power On LED
SW1	Dip Switch for Mode and Address Selector
J1	QWIIC Connector (JST 1mm for I2C)
J2	QWIIC Connector (JST 1mm for I2C)
J3	JST Connector 1mm Pitch for SPI
JP1	2.54mm Castellated Holes

CIRCUIT SCHEMATIC

**Circuit Schematic**

Complete circuit schematic showing all component connections

[View Complete Schematic PDF](#)

PIN DESCRIPTION

Detailed pin assignment and electrical specifications

SIGNAL DESCRIPTION

SIGNAL	DESCRIPTION
VCC	Power supply
GND	Ground
SCL	I ² C clock
SDA	I ² C data
SDO / ADDR	SPI MISO / I ² C address select
CS	SPI chip-select (active LOW) / must be HIGH for I ² C mode
PS	Protocol select (LOW=I ² C, HIGH=SPI)
DRDY	Data-Ready flag (new data available)
INT	Programmable interrupt output (e.g. threshold, flip-over)

PIN CONFIGURATION LAYOUT

Physical connector layout and pin positioning



Pin Configuration Layout

Complete pin configuration diagram showing all connectors, pin assignments, and electrical connections for proper integration

© 2025 UNIT Electronics México
Technical document automatically generated

BMM150 v1.0
Professional Technical Datasheet

Date: 2025-07-17
For commercial distribution