

| Designation | Capacitance | Voltage | Temp | Size | Lead Spacing | Brand | Series | Notes |
|---------------|-------------|-------------|------|-------|--------------|-----------|--------|---|
| (1) 1 | 3.3uF | 50v | 85 | 5x11 | 3mm | RG Allen | TR | between ch select and ch A comp switch |
| (2) 4 | 3.3uF | 25v | 85 | 5x11 | n/a | RG Allen | NT | bodge on ch B gain switch |
| (3) 7 | 3.3uF | 50v | 85 | 5x11 | 5mm | RG Allen | TR | connected to ch B volume knob |
| (4) 7 | 3.3uF | 50v | 85 | 5x11 | 5mm | RG Allen | TR | connected to pin 3 of TL604CP |
| (5) 11 | 3.3uF | 50v | 85 | 5x11 | 2.5mm | RG Allen | TR | connected to pin 3 of TL604CP |
| (6) Small 4 | 3.3uF | 50v | 85 | 5x11 | 2.5mm | RG Allen | TR | just behind 120hz knob |
| (7) Small 4 | 3.3uF | 50v | 85 | 5x11 | 2.5mm | RG Allen | TR | just behind previous cap |
| (8) 19 | 220uF | 25v | 85 | 10x15 | 5mm | RG Allen | NT | 3 inline connected to headphone port |
| (9) 19 | 220uF | 25v | 85 | 10x15 | 5mm | RG Allen | NT | 3 inline connected to headphone port |
| (10) 19 | 220uF | 25v | 85 | 10x15 | 5mm | RG Allen | NT | 3 inline connected to headphone port |
| (11) 1 | 220uF | 25v | 85 | 10x15 | 6mm | RG Allen | NT | mid left of board |
| (12) Mid | 2200uF | 50v | 85 | 18x40 | 46mm | Panasonic | SU | big axial on the mid left of board |
| (13) Mid | 2200uF | 50v | 85 | 18x40 | 46mm | Panasonic | SU | big axial on the middle of board |
| (14) 18 | 220uF | 50v | 85 | 12x20 | 5mm | Panasonic | S | large blue radial on left of board |
| (15) 24 | 220uF | 50v | 85 | 12x20 | 5mm | Panasonic | S | large blue radial on left of board |
| (16) Mid | 3.3uF | 50v | 85 | 5x11 | 6mm | RG Allen | TR | to the upper right of mid axial |
| (17) Mid | 220uF | 25v | 85 | 10x15 | 5mm | RG Allen | NT | to right of mid axial |
| (18) Mid | 3.3uF | 50v | 85 | 5x11 | 2.5mm | RG Allen | TR | to right of previous capacitor |
| (19) Small 8 | 3.3uF | 50v | 85 | 5x11 | 2.5mm | RG Allen | TR | near ext right speaker port |
| (20) Small 19 | 3.3uF | 50v | 85 | 5x11 | 2.5mm | RG Allen | TR | near ext left speaker port |
| (21) Small 23 | 3.3uF | 50v | 85 | 5x11 | 2.5mm | RG Allen | TR | just above mid axial |
| (22) 32 | 3.3uF | 50v | 85 | 5x11 | 2.5mm | RG Allen | TR | topmost capacitor above mid blue radial |
| (23) 32 | 3.3uF | 50v | 85 | 5x11 | 2.5mm | RG Allen | TR | middle capacitor above mid blue radial |
| (24) 32 | 3.3uF | 50v | 85 | 5x11 | 2.5mm | RG Allen | TR | lower capacitor above mid blue radial |
| (25) 27 | 3.3uF | 50v | 85 | 5x11 | 5mm | RG Allen | TR | left in front of return port |
| (26) 28 | 3.3uF | 50v | 85 | 5x11 | 2.5mm | RG Allen | TR | right in front of return port |
| (27) 29 | 3.3uF | 50v | 85 | 5x11 | 2.5mm | RG Allen | TR | between send and return ports |
| (28) 28 | 3.3uF | 50v | 85 | 5x11 | 2.5mm | RG Allen | TR | in front of previous capacitor |
| (29) 29 | 3.3uF | 50v | 85 | 5x11 | 2.5mm | RG Allen | TR | below send port |
| (30) 29 | 3.3uF | 25v | 85 | 5x11 | 2.5mm | RG Allen | TR | below previous capacitor |
| (31) 29 | 3.3uF | 25v | 85 | 5x11 | 5mm | RG Allen | TR | to right of previous capacitor |
| (32) 29 | 220uF | 25v | 85 | 10x15 | 5mm | RG Allen | NT | right of send port |
| (33) 30 | 220uF | 25v | 85 | 10x15 | 5mm | RG Allen | NT | left of aux in port |
| Board | GK 60049A | KALEX 94V 0 | K368 | 5387 | | | | |