Synology RT1900ac as router on Cablenet

Fiber behind a Huawei ONT · DHCP + VLAN 42 · optional Pi-hole DNS · Oct 2026

Cabling

Device	Synology port
Huawei OptiXstar HG8010Hv6 (fiber modem, no router)	**WAN**
Computer	**LAN 1**
Raspberry Pi / wired devices	**LAN 1 or LAN 2** (not LAN 3 or 4)

Key values

SRM address	**`http://192.168.1.1:8000`**
Internet connection	Automatic (DHCP), **no** username/password, no PPPoE
VLAN ID for Internet	**42**

1. Sign in and operation mode

1. ☐ Open **`http://192.168.1.1:8000`** and sign in.
2. ☐ Operation mode: **Wireless Router** (not Access Point).
3. ☐ External access to SRM: **Disabled**.

2. Internet connection

1. ☐ **Network Center → Internet → Connection**.
2. ☐ Connection type **Automatic**. Default gateway: **Enabled**.

3. VLAN 42 (required)

1. ☐ Open **ISP Settings (IPTV & VoIP)**.
2. ☐ Tick **Enable IPTV/VoIP**, mode **Manual**.
3. ☐ Top section (Internet only): **VID = 42**, priority **0**.
4. ☐ Leave LAN 3 and LAN 4 empty. Do **not** choose an ISP profile such as M1-Fiber.
5. ☐ **OK**, then **Apply**. Wait about **1 minute**.

4. Check

1. ☐ Status shows the Internet connection as connected.
2. ☐ A web page not seen before loads.

5. Pi-hole for the whole network (optional)

1. ☐ Network Center → Internet → Connection → DNS server manually: preferred **`192.168.1.9`** (your Pi-hole), alternative **`9.9.9.9`**. Apply.
2. ☐ Reserve a fixed address for the Pi-hole in the DHCP settings using its MAC address.
3. ☐ Wi-Fi: same name and password as the old router.

Troubleshooting

Problem	What to try
No Internet / no WAN address	ONT in the **WAN** port? VLAN 42 saved? Else enter the old router's **WAN MAC** by hand under ISP Settings (do not use “Clone”).
Wired device not reachable	Use **LAN 1 or LAN 2**. LAN 3/4 may be separated by the IPTV/VoIP setting.
SRM page not reachable	Set your computer to **`169.254.1.2`**, mask **`255.255.0.0`**, open **`http://169.254.1.1:8000`**.
Need the old router's settings	Connect it only to your computer; disconnect the Synology (both use 192.168.1.1).

Notes (no passwords here)

_____

_____