Vivante Programming:

VGLite®

Vector Graphics API

Document Revision 2.06

29 June 2023

This document, for use with the VGLite Graphics API release versions from document date and is compatible with VGLite Driver V4 and

Vivante Vector Graphics IP including

GCNanoUltraV, GCNanoLiteV (V1311p), GCNanoV, GC355 and GC555.

Legal Notices

COPYRIGHT INFORMATION

This document contains proprietary information of Vivante Corporation and VeriSilicon Holdings Co., Ltd. They reserve the right to make changes to any products herein at any time without notice and do not assume any responsibility or liability arising out of the application or use of any product described herein, except as expressly agreed to in writing by Vivante and/or VeriSilicon; nor does the purchase or use of a product from Vivante or VeriSilicon convey a license under any patent rights, copyrights, trademark rights, or any other of the intellectual property rights of Vivante, VeriSilicon or third parties.

DISCLOSURE/RE-DISTRIBUTION LIMITATIONS

The information contained in this Vivante proprietary copyright document may be re-distributed by Vivante and VeriSilicon customer SoC vendors who have licensed the related core IP, with the understanding that the material be re-packaged/re-branded as a licensee (SoC vendor) written/labeled document. In the adapted document please identify the technology and features described in this document using the Vivante trademark and include a reference to the copyright owner, for example: "This section describes the Vivante® GPU and contains copyright material disclosed with permission of VeriSilicon®."
(VeriSilicon Distribution **LEVEL A: PROPRIETARY INFORMATION**)

TRADEMARK ACKNOWLEDGMENT

VeriSilicon® and the VeriSilicon logo design are the trademarks or the registered trademarks of VeriSilicon Holdings Co., Ltd. Vivante® is a registered trademark of Vivante Corporation. All other brand and product names may be trademarks of their respective companies.

For our current distributors, sales offices, design resource centers, and product information, visit our web page located at http://www.verisilicon.com.

Table of Contents

LEGAL NOTICES **2**
TABLE OF CONTENTS **3**
LIST OF FIGURES **7**
LIST OF TABLES **7**
1 INTRODUCTION **8**
1.1 Vivante VGLite Graphics API 8
1.2 API Function Group 8
1.3 API Files 9
1.4 Hardware Versions 9
2 COMMON PARAMETERS AND ERROR VALUES **10**
2.1 Common Parameters 10
2.2 Enumeration used for Error Reporting 11
2.2.1 vg_lite_error_t Enumeration 11
3 HARDWARE PRODUCT AND FEATURE INFORMATION **12**
3.1 Enumerations for Product and Feature Queries 12
3.1.1 vg_lite_feature_t Enumeration 12
3.2 Structures for Product and Feature Queries 13
3.2.1 vg_lite_info_t Structure 13
3.3 Functions for Product and Feature Queries 14
vg_lite_get_product_info 14
vg_lite_get_info 15
vg_lite_get_register 15
vg_lite_query_feature 16
vg_lite_get_mem_size 16
4 API CONTROL **17**
4.1 Context Initialization and Control Functions 17
vg_lite_init 17
vg_lite_close 18
vg_lite_finish 18
vg_lite_flush 18
vg_lite_set_command_buffer_size 19
vg_lite_set_command_buffer 19
vg_lite_set_tess_buffer 20
5 PIXEL BUFFERS **21**
5.1 Pixel Buffer Alignment 21
5.2 Pixel Cache 21
5.3 Internal Representation 21
5.4 Pixel Buffer Enumerations 22
5.4.1 vg_lite_buffer_format_t Enumeration 22
5.4.2 vg_lite_buffer_layout_t Enumeration 29
5.4.3 vg_lite_compress_mode_t Enumeration 29
5.4.4 vg_lite_gamma_conversion_t Enumeration 29
5.4.5 vg_lite_index_endian_t Enumeration 29
5.4.6 vg_lite_image_mode_t Enumeration 30
5.4.7 vg_lite_map_flag_t Enumeration 30
5.4.8 vg_lite_paint_type_t Enumeration 30

5.4.9 vg_lite_transparency_t Enumeration 31
5.4.10 vg_lite_swizzle_t Enumeration 31
5.4.11 vg_lite_yuv2rgb_t Enumeration 31
5.5 Pixel Buffer Structures 32
5.5.1 vg_lite_buffer_t Structure 32
5.5.2 vg_lite_fc_buffer_t Structure 33
5.5.3 vg_lite_yuvinfo_t Structure 33
5.6 Pixel Buffer Functions 34
vg_lite_allocate 34
vg_lite_free 35
vg_lite_upload_buffer 35
vg_lite_map 36
vg_lite_unmap 36
vg_lite_flush_mapped_buffer 37
vg_lite_set_CLUT 37
vg_lite_enable_dither 38
vg_lite_disable_dither 38
vg_lite_set_gamma 38
6 MATRICES 39
6.1 Matrix Control Float Parameter Type 39
6.2 Matrix Control Structures 39
6.2.1 vg_lite_matrix_t Structure 39
6.2.2 vg_lite_pixel_channel_enable_t Structure 39
6.3 Matrix Control Functions 40
vg_lite_identity 40
vg_lite_set_pixel_matrix 40
vg_lite_rotate 41
vg_lite_scale 41
vg_lite_translate 42
7 BLITS FOR COMPOSITING AND BLENDING 43
7.1 BLIT Enumerations 43
7.1.1 vg_lite_blend_t Enumeration 43
7.1.2 vg_lite_color_t Parameter 47
7.1.3 vg_lite_color_transform_t Structure 47
7.1.4 vg_lite_filter_t Enumeration 47
7.1.5 vg_lite_global_alpha_t Enumeration 48
7.1.6 vg_lite_mask_operation_t Enumeration 48
7.1.7 vg_lite_orientation_t Enumeration 48
7.2 BLIT Structures 49
7.2.1 vg_lite_buffer_t Structure 49
7.2.2 vg_lite_color_key_t Structure 49
7.2.3 vg_lite_color_key4_t Structure 49
7.2.4 vg_lite_matrix_t Structure 50
7.2.5 vg_lite_path_t Structure 50
7.2.6 vg_lite_rectangle_t Structure 50
7.2.7 vg_lite_point_t Structure 50
7.2.8 vg_lite_point4_t Structure 50
7.3 BLIT Functions 51
vg_lite_blit 51
vg_lite_blit2 53
vg_lite_blit_rect 55

vg_lite_get_transform_matrix 57
vg_lite_clear 57
vg_lite_set_color_key 58
vg_lite_gaussian_filter 59
7.4 Blit/Draw Extended Functions 60
vg_lite_set_premultiply 60
vg_lite_enable_scissor 60
vg_lite_disable_scissor 60
vg_lite_set_scissor 61
vg_lite_scissor_rects 61
vg_lite_disable_color_transform 62
vg_lite_enable_color_transform 62
vg_lite_set_color_transform 62
vg_lite_enable_masklayer 63
vg_lite_disable_masklayer 63
vg_lite_create_masklayer 64
vg_lite_fill_masklayer 64
vg_lite_blend_masklayer 65
vg_lite_set_masklayer 65
vg_lite_render_masklayer 66
vg_lite_destroy_masklayer 67
vg_lite_set_mirror 67
vg_lite_source_global_alpha 68
vg_lite_dest_global_alpha 68
8 VECTOR PATH CONTROL 69
8.1 Vector Path Enumerations 69
8.1.1 vg_lite_format_t Enumeration 69
8.1.2 vg_lite_quality_t Enumeration 69
8.2 Vector Path Structures 70
8.2.1 vg_lite_hw_memory Structure 70
8.2.2 vg_lite_path_t Structure 71
8.3 Vector Path Functions 73
vg_lite_get_path_length 73
vg_lite_append_path 74
vg_lite_init_path 75
vg_lite_init_arc_path 76
vg_lite_upload_path 77
vg_lite_clear_path 77
8.4 Vector Path Opcodes for Plotting Paths 78
9 VECTOR BASED DRAW OPERATIONS 81
9.1 Draw and Gradient Enumerations 81
9.1.1 vg_lite_blend_t Enumeration 81
9.1.2 vg_lite_color_t Parameter 81
9.1.3 vg_lite_fill_t Enumeration 81
9.1.4 vg_lite_filter_t Enumeration 81
9.1.5 vg_lite_gradient_spreadmode_t Enumeration 82
9.1.6 vg_lite_pattern_mode_t Enumeration 82
9.1.7 vg_lite_radial_gradient_spreadmode_t Enumeration 82
9.2 Draw and Gradient Structures 83
9.2.1 vg_lite_buffer_t Structure 83
9.2.2 vg_lite_color_ramp_t Structure 83

9.2.3 vg_lite_linear_gradient_t Structure 84
9.2.4 vg_lite_ext_linear_gradient Structure 84
9.2.5 vg_lite_linear_gradient_parameter Structure 85
9.2.6 vg_lite_matrix_t Structure 85
9.2.7 vg_lite_path_t Structure 85
9.2.8 vg_lite_radial_gradient_parameter_t Structure 86
9.2.9 vg_lite_radial_gradient_t Structure 87
9.3 Draw Functions 88
vg_lite_draw 88
vg_lite_draw_grad 89
vg_lite_draw_radial_grad 90
vg_lite_draw_pattern 91
9.4 Linear Gradient Initialization and Control Functions 93
vg_lite_init_grad 93
vg_lite_clear_grad 93
vg_lite_set_grad 94
vg_lite_get_grad_matrix 95
vg_lite_update_grad 95
9.5 Linear Gradient Extended Functions 96
vg_lite_set_linear_grad 96
vg_lite_get_linear_grad_matrix 97
vg_lite_draw_linear_grad 98
vg_lite_update_linear_grad 99
vg_lite_clear_linear_grad 99
9.6 Radial Gradient Functions 100
vg_lite_set_radial_grad 100
vg_lite_update_radial_grad 101
vg_lite_get_radial_grad_matrix 101
vg_lite_clear_radial_grad 102
10 STROKE OPERATIONS 103
10.1 Stroke Enumerations 103
10.1.1 vg_lite_cap_style_t Enumeration 103
10.1.2 vg_lite_path_type_t Enumeration 103
10.1.3 vg_lite_join_style_t Enumeration 104
10.2 Stroke Structures 105
10.2.1 vg_lite_path_t Structure 105
10.2.2 vg_lite_path_point_t Structure 105
10.2.3 vg_lite_stroke_t Structure 106
10.2.4 vg_lite_sub_path_t Structure 107
10.3 Stroke Functions 108
vg_lite_set_path_type 108
vg_lite_set_stroke 109
vg_lite_update_stroke 110
11 DEPRECATED AND RENAMED APIS 111
11.1 Deprecated vg_lite Syntax 112
vg_lite_perspective *(deprecated)* 112
vg_lite_set_dither *(deprecated)* 112
vg_lite_set_scissor *(deprecated)* 112
vg_lite_enable_premultiply *(deprecated)* 112
vg_lite_disable_premultiply *(deprecated)* 112

12 VGLITE API PROGRAMMING EXAMPLES 113
12.1 vg_lite_clear Example 113
12.2 vg_lite_blit Example 114
12.3 vg_lite_draw Example 115
12.4 vg_lite_draw_gradient Example 116
12.5 vg_lite_draw_pattern Example 117
12.6 Vector-based Font Rendering Example 118
DOCUMENT REVISION HISTORY 120

List of Figures

Figure 1. Example using vg_lite_clear 113
Figure 2. Example using vg_lite_blit. 114
Figure 3. Example using vg_lite_draw_gradient 116
Figure 4. Example using vg_lite_draw_pattern 117
Figure 5. Example using Vector Based Font Rendering 119
Figure 6. Example with Vector Based Font Rendering Upscaled 8X. 119

List of Tables

Table 1. Common Parameter Types 10
Table 2. Image Source Buffer Start Address and Stride Alignment Summary 28
Table 3. Porter Duff Operators and Related vg_lite_blend_t enum Values 43
Table 4. Vector Path Data Opcodes 78
Table 5. Vector Path Data Opcodes for Arc Paths 79

1 Introduction

Vivante's platform independent VGLite Graphics API (Application Programming Interface) is designed to support 2D vector and 2D raster-based operations for rendering interactive user interface that may include menus, fonts, curves, and images. Its goal is to provide the maximum 2D vector/raster rendering performance, while keeping the memory footprint to the minimum. The Vivante VGLite Graphics API allows users to implement customized applications for mobile or IoT devices that include Vivante Vector Graphics IP.

1.1 Vivante VGLite Graphics API

The Vivante VGLite Graphics API is used to control the Vivante vector graphics hardware units, which provide accelerated vector and raster operations.

The Vivante VGLite API is developed for use with Vivante GCNanoLiteV, GCNanoUltraV, GCNanoV, GC355 and GC555 hardware. GC355 and GC555 support Khronos OpenVG 1.1 feature set, while GCNanoLiteV, GCNanoUltraV and GCNanoV have a feature set smaller than that required to pass Khronos OpenVG CTS.

The VGLite API driver V4 is a complete new design and implementation of the driver (from 2023Q1) to support the new generation 2.5D GPU (GC555), as well as the previous 2.5D GPU releases (GC255, GC265, GC355). The new V4 driver supports the new and improved VGLite API (version 3.0), and can generate the most CPU efficient, customized driver build for a specific 2.5D GPU release based on the hardware feature set.

VGLite API supported features include: Porter-Duff Blending, Gradient Controls, Fast Clear, Arbitrary Rotations, Path Filling rules, Path painting, and Pattern Path Filling.

By default, VGLite API driver V4 supports one implicit global application context in single thread. VGLite V4 driver does not support multi-threaded application which is not suitable for embedded IoT devices.

1.2 API Function Group

The Vivante VGLite Graphics API has been designed to have independent function groups. It is permissible for user to use only one of the function groups in the VGLite application.

- **Initialization** – Used for initializing hardware and software structures.
- **Blit API** – Used for the raster part of rendering.
- **Draw API** – Used for 2D vector-based draw operations.

1.3 API Files

For customers with access to source:

The Vivante VGLite Graphics API functions are defined in the header file **`VGLite/inc/vg_lite.h`**.

All VGLite application used enumerations and data types are also defined in **`VGLite/inc/vg_lite.h`**.

1.4 Hardware Versions

The Vivante VGLite API is compatible with a range of Vivante Vector Graphics IPs including: GCNanoLiteV, GCNanoUltraV, GCNanoV, GC355 and GC555.

Note that a specific hardware version has customized feature set which may limit hardware support for some VGLite API options. The VGLite application can use vg_lite_query_feature API to query specific VGLite feature availability.

Users can also check the **VGLite/VGLite/vg_lite_options.h** file which includes CHIPID, REVISION, CID to identify specific HW releases, and gcFEATURE_VG_* macros to define the feature set for the HW release.

The gcFEATURE_VG_* macro values (except a few SW features) should NOT be changed. Otherwise, the VGLite driver will not function correctly on the specific HW release. Users can change the “SW Features” macro values to disable some software features, unnecessary error checks, or enable VGLite API trace for debug purposes.

2 Common Parameters and Error Values

2.1 Common Parameters

Vivante VGLite Graphics API uses a naming convention scheme wherein definitions are preceded by '**vg_lite**'.

Below is the list of most proprietary defined types and structures in the drivers. Not all may be used in the API functions.

Table 1. Common Parameter Types

Name	Typedef	Value
vg_lite_bool_t	int	A signed 32-bit integer 0: FALSE; 1: TRUE.
vg_lite_int8_t	char	A signed 8-bit integer
vg_lite_uint8_t	unsigned char	An unsigned 8-bit integer
vg_lite_int16_t	short	A signed 16-bit integer
vg_lite_uint16_t	unsigned short	An unsigned 16-bit integer
vg_lite_int32_t	int	A signed 32-bit integer
vg_lite_uint32_t	unsigned int	An unsigned 32-bit integer
vg_lite_uint64_t	unsigned long long	An unsigned 64-bit integer
vg_lite_float_t	float	A 32-bit single precision floating point number
vg_lite_double_t	double	A 64-bit double precision floating point number
vg_lite_char_t	char	A signed 8-bit integer
vg_lite_string	char*	A pointer to a character string
vg_lite_pointer	void*	A generic address pointer (void *). On 32-bit OS, it is a 32-bit address pointer. On 64-bit OS, it is a 64-bit address pointer.
vg_lite_void	void	The void type
vg_lite_color_t	vg_lite_uint32_t	A 32-bit color value The color value specifies the color used in various functions. The color is formed using 8-bit RGBA channels. The red channel is in the lower 8-bit of the color value, followed by the green and blue channels. The alpha channel is in the upper 8-bit of the color value. **A8R8G8B8**: 31:24 = A, 23:16 = R, 15:8 = G, 7:0 = B For L8 target formats, the RGB color is converted to L8 by using the default ITU-R BT.709 conversion rules.
VG_LITE_S8	enum vg_lite_format_t	A signed 8-bit integer coordinate
VG_LITE_S16	enum vg_lite_format_t	A signed 16 bit integer coordinate
VG_LITE_S32	enum vg_lite_format_t	A signed 32-bit integer coordinate
VG_LITE_FP32	enum vg_lite_format_t	A 32-bit floating point coordinate

2.2 Enumeration used for Error Reporting

2.2.1 vg_lite_error_t Enumeration

Most functions in the API include an error status via the **vg_lite_error_t** enumeration. API functions return the status of the command and will report **VG_LITE_SUCCESS** if successful with no errors. Possible error values include the values in the table below.

Used in many functions, including initialization, flush, blit, draw, gradient and pattern functions.

vg_lite_error_t String Values	Description
VG_LITE_GENERIC_IO	Cannot communicate with the kernel driver
VG_LITE_INVALID_ARGUMENT	Invalid argument specified
VG_LITE_MULTI_THREAD_FAIL	Multi-thread/tasks fail *(available from June 2020)*
VG_LITE_NO_CONTEXT	No context specified
VG_LITE_NOT_SUPPORT	Function call not supported. Hardware support not available.
VG_LITE_OUT_OF_MEMORY	Out of memory (driver heap)
VG_LITE_OUT_OF_RESOURCES	Out of resources (OS heap)
VG_LITE_SUCCESS	Successful with no errors
VG_LITE_TIMEOUT	Timeout
VG_LITE_ALREADY_EXISTS	Object already exists *(available from August 2021)*
VG_LITE_NOT_ALIGNED	Data alignment error *(available from August 2021)*

3 Hardware Product and Feature Information

These query functions can be used to identify the product and its key features, and to get VGLite driver information.

3.1 Enumerations for Product and Feature Queries

3.1.1 vg_lite_feature_t Enumeration

The following feature values may be queried for availability in compatible hardware. *(expanded March 2023 to support additional hardware for driver V4)*

Used in information functions: vg_lite_query_feature.

vg_lite_feature_t String Values	Description
gcFEATURE_BIT_VG_16PIXELS_ALIGN	Require 16 pixels aligned for input pixel buffer
gcFEATURE_BIT_VG_24BIT	RGB888 or RGBA5658 formats support
gcFEATURE_BIT_VG_24BIT_PLANAR	24 bit planar formats support
gcFEATURE_BIT_VG_AYUV_INPUT	AYUV input format support
gcFEATURE_BIT_VG_BORDER_CULLING	Border culling support
gcFEATURE_BIT_VG_COLOR_KEY	Color key support.
gcFEATURE_BIT_VG_COLOR_TRANSFORMATION	Color transform support.
gcFEATURE_BIT_VG_DEC_COMPRESS	DEC compression format output support
gcFEATURE_BIT_VG_DITHER	Dither support
gcFEATURE_BIT_VG_DOUBLE_IMAGE	Support two image source inputs
gcFEATURE_BIT_VG_FLEXA	FLEXA interface support
gcFEATURE_BIT_VG_GAMMA	Gamma support
gcFEATURE_BIT_VG_GAUSSIAN_BLUR	Gaussian blur sampling support
gcFEATURE_BIT_VG_GLOBAL_ALPHA	Global alpha support
gcFEATURE_BIT_VG_HW_PREMULTIPLY	HW supports alpha premultiply for image
gcFEATURE_BIT_VG_IM_DEC_INPUT	DEC compressed format input support
gcFEATURE_BIT_VG_IM_FASTCLEAR	Fast Clear support
gcFEATURE_BIT_VG_IM_INDEX_FORMAT	Index format support for image
gcFEATURE_BIT_VG_IM_INPUT	Blit and draw API support
gcFEATURE_BIT_VG_IM_REPEAT_REFLECT	Image repeat reflect mode support
gcFEATURE_BIT_VG_INDEX_ENDIAN	Index format endian support
gcFEATURE_BIT_VG_LINEAR_GRADIENT_EXT	Support for extended linear gradient capabilities
gcFEATURE_BIT_VG_LVGL_SUPPORT	LVGL blend mode support
gcFEATURE_BIT_VG_MASK	Mask support
gcFEATURE_BIT_VG_MIRROR	Mirror support
gcFEATURE_BIT_VG_NEW_BLEND_MODE	New blend mode DARKEN/LIGHTEN support
gcFEATURE_BIT_VG_NEW_IMAGE_INDEX	New CLUT image index support

vg_lite_feature_t String Values	Description
gcFEATURE_BIT_VG_PARALLEL_PATHS	New parallel path HW support
gcFEATURE_BIT_VG_PE_CLEAR	Pixel engine clear support
gcFEATURE_BIT_VG_PIXEL_MATRIX	Pixel matrix support
gcFEATURE_BIT_VG_QUALITY_8X	8x anti-aliasing path support
gcFEATURE_BIT_VG_RADIAL_GRADIENT	Radial gradient support
gcFEATURE_BIT_VG_RECTANGLE_TILED_OUT	Rectangle tiled output support
gcFEATURE_BIT_VG_RGBA2_FORMAT	RGBA2222 format support
gcFEATURE_BIT_VG_RGBA8_ETC2_EAC	ETC2/EAC compressed image format support
gcFEATURE_BIT_VG_SCISSOR	Scissor support
gcFEATURE_BIT_VG_SRC_PREMULTIPLIED	Source image alpha premultiplied
gcFEATURE_BIT_VG_STENCIL	Stencil image mode support
gcFEATURE_BIT_VG_STRIPE_MODE	Stripe mode support
gcFEATURE_BIT_VG_TESSELLATION_TILED_OUT	Tessellation tiled output support
gcFEATURE_BIT_VG_USE_DST	Read destination pixel support
gcFEATURE_BIT_VG_YUV_INPUT	YUV input format support
gcFEATURE_BIT_VG_YUV_OUTPUT	YUV format output support
gcFEATURE_BIT_VG_YUV_TILED_INPUT	YUV tiled input format support
gcFEATURE_BIT_VG_YUY2_INPUT	YUY2 input format support

3.2 Structures for Product and Feature Queries

3.2.1 vg_lite_info_t Structure

This structure is used to query VGLite driver information.

Used in function: vg_lite_get_info_t.

vg_lite_info_t Members	Type	Description
api_version	vg_lite_uint32_t	VGLite API version
header_version	vg_lite_uint32_t	VGLite header version
release_version	vg_lite_uint32_t	VGLite driver release version
reserved	vg_lite_uint32_t	Reserved for future use

3.3 Functions for Product and Feature Queries

vg_lite_get_product_info

Description:
This function is used to identify the VGLite compatible product.

Syntax:

```
vg_lite_uint32_t vg_lite_get_product_info (
    vg_lite_char              *name
    vg_lite_uint32_t          *chip_id
    vg_lite_uint32_t          *chip_rev
);
```

Parameters:

***name**	Character array to store the name of the chip.
***chip_id**	Stores an ID number for the chip.
***chip_rev**	Stores a revision number for the chip.

vg_lite_get_info

Description:
This function is used to query the VGLite driver information.

Syntax:

```
vg_lite_error_t vg_lite_get_info (
    vg_lite_info_t              *info
);
```

Parameters:

***info**	Points to the VGLite driver information structure which includes the API version, header version, and release version.

vg_lite_get_register

Description:
This function can be used to read a Vivante Vector Graphics register value given the AHB Byte address of a register. Refer to Vivante Vector Graphics Accessible Register specification documents compatible with your IP for register descriptions. The value range of AHB/APB accessible addresses for VGLite cores is usually 0x0 to 0x1FF and 0xA00 to 0xA7F.

Syntax:

```
vg_lite_error_t vg_lite_get_register (
    vg_lite_uint32_t            address
    vg_lite_uint32_t            *result
);
```

Parameters:

address	Byte Address of the register whose value you want.
***result**	The registers value.

vg_lite_query_feature

Description:
This function is used to query if a specific feature is available.

Syntax:

```
vg_lite_uint32_t vg_lite_query_feature (
    vg_lite_feature_t          feature
);
```

Parameters:

feature	Feature being queried, as detailed in enum vg_lite_feature_t.

Returns:
Either the feature is not supported (0) or supported (1).

vg_lite_get_mem_size

Description:
This function queries whether or not there is any remaining allocated contiguous video memory. *(available from June 2020)*

Syntax:

```
vg_lite_error_t vg_lite_get_mem_size(
    vg_lite_uint32_t           *size
);
```

Parameters:

size	Pointer to the remaining allocated contiguous video memory.

Returns:
Returns VG_LITE_SUCCESS if the query is successful and memory is available. Returns VG_LITE_NO_CONTEXT if the driver is not initialized, or there is no available memory.

4 API Control

Before calling any VGLite API function, the application must initialize the VGLite implicit (global) context by calling *vg_lite_init()*, which will fill in a features table, reset the fast-clear buffer, reset the compositing target buffer, as well as allocate the command and tessellation buffers.

The VGLite driver only supports one current context and one thread to issue commands to the Vivante Vector Graphics hardware. The VGLite driver does not support multiple concurrent contexts running simultaneously in multiple threads/processes, as the VGLite kernel driver does not support context switching. A VGLite application can only use a single context at any time to issue commands to the Vivante Vector Graphics hardware. If a VGLite application needs to switch contexts, **vg_lite_close()** should be called to close the current context in the current thread, then **vg_lite_init()** can be called to initialize a new context either in the current thread or from another thread/process.

4.1 Context Initialization and Control Functions

vg_lite_init

Description:

This function initializes the memory and data structures needed for VGLite draw/blit functions, by allocating memory for the command buffer and a tessellation buffer of the specified size. The tessellation buffer width & height must be a multiple of 16. The tessellation window can be specified based on the amount of memory available in the system and the desired performance. A smaller window can have a lower memory footprint but may result in lower performance. The minimum window that can be used for tessellation is 16x16. If the height or width is less than 0, then no tessellation buffer is created, thus it can be used in a blit-only case.

If this would be the first context that accesses the hardware, the hardware will be turned on and initialized. If a new context needs to be initialized**, vg_lite_close** must be called to close the current context. Otherwise, **`vg_lite_init`** will return an error.

Syntax:

```
vg_lite_error_t vg_lite_init (
    vg_lite_int32_t             tess_width,
    vg_lite_int32_t             tess_height
);
```

Parameters:

tess_width	Width of tessellation window. Value should be a multiple of 16; minimum width is 16 pixels, maximum cannot be greater than frame width. If less than or equal to 0, then no tessellation buffer is created, in which case the function is used for a blit init.
tess_height	Height of tessellation window. Value should be a multiple of 16; minimum height is 16 pixels, maximum cannot be greater than frame height. If less than or equal to 0, then no tessellation buffer is created, in which case the function is used for a blit init.

vg_lite_close

Description:
This function will deallocate all the resource and free up all the memory that was initialized earlier by the **vg_lite_init** function. It will also turn OFF the hardware automatically if this was the only active context.

Syntax:

```
vg_lite_error_t vg_lite_close (
    void
);
```

vg_lite_finish

Description:
This function explicitly submits the command buffer to the GPU and waits for it to complete.

Syntax:

```
vg_lite_error_t vg_lite_finish (
    void
);
```

vg_lite_flush

Description:
This function explicitly submits the command buffer to the GPU without waiting for it to complete. *(From Dec 2019, return type is vg_lite_error_t, previously was void.)*

Syntax:

```
vg_lite_error_t vg_lite_flush (
    void
);
```

Returns:
Returns VG_LITE_SUCCESS if the flush is successful. See vg_lite_error_t enum for other return codes.

vg_lite_set_command_buffer_size

Description:
This function is optional. If used, call it before **vg_lite_init** if you want to change the command buffer size. *(available from March 2020)*

This function is useful for devices where memory is limited and less than the default. The VGLite Command buffer is set to 32K by default, so that VGLite applications can render more complex paths with better performance. This function can be used to adjust the command buffer size to fit specific application and system/device requirements.

Syntax:

```
vg_lite_error_t vg_lite_set_command_buffer_size (
    vg_lite_uint32_t            size
);
```

Parameters:

size	Size of the VGLite Command buffer. Default is 64K.

vg_lite_set_command_buffer

Description:
This function sets a user-defined external memory buffer (physical, 64-byte aligned) as the VGLite command buffer. By default, the VGLite driver allocates a static command buffer internally. Thus, it is not necessary for an application to allocate and set the command buffer. This function is only used for devices where an application needs to allocate the command buffer dynamically. *(from December 2021)*

Syntax:

```
vg_lite_error_t vg_lite_set_command_buffer (
    vg_lite_uint32_t            physical,
    vg_lite_uint32_t            size
);
```

Parameters:

physical	The physical address of a memory buffer. The address must be 64-byte aligned.
size	The size of memory buffer. The size must be 128-byte aligned.

Returns:
Returns VG_LITE_SUCCESS if the command buffer set is successful. See vg_lite_error_t enum for other return codes.

vg_lite_set_tess_buffer

Description:
This function specifies a memory buffer from an application as the VGLite driver's tessellation buffer. By default, the VGLite driver allocates a static tessellation buffer internally. Thus, it is not necessary for an application to allocate and set the tessellation buffer. This function is only used for devices where the application needs to allocate the tessellation buffer dynamically. *(from December 2021)*

Syntax:

```
vg_lite_error_t vg_lite_set_tess_buffer (
    vg_lite_uint32_t            physical,
    vg_lite_uint32_t            size
);
```

Parameters:

physical	The physical address of a tessellation buffer. The address must be 64-byte aligned.
size	The size of tessellation buffer. tessellation buffer size = target buffer's height * 128B.

Returns:
Returns VG_LITE_SUCCESS if the tessellation buffer set is successful. See vg_lite_error_t enum for other return codes.

5 Pixel Buffers

5.1 Pixel Buffer Alignment

The VGLite hardware requires the pixel buffer start address and stride to be properly byte aligned to work correctly. The start address and stride alignment requirement for a pixel buffer depends on the specific pixel format, and gcFEATURE_VG_16PIXELS_ALIGNED value (0/1) in vg_lite_options.h file.

Refer to the Alignment Notes Table 2: Image Source Start Address and Stride Alignment Summary later in this document.

5.2 Pixel Cache

The Vivante Imaging Engine (IM) includes two fully associative caches. Each cache has 8 lines, each line has 64 bytes. In this case, one cache line can hold either a 4x4-pixel Tile or a 16x1-pixel row.

5.3 Internal Representation

For non 32-bit color formats, each pixel will be extended to 32-bits as such:

If the source and destination formats have the same color format, but differ in the number of bits per color channel, the source channel is multiplied by $(2^d - 1)/(2^s - 1)$ and rounded to the nearest integer, where:

d is the number of bits in the destination channel
s is the number of bits in the source channel

Example: a b11111 5-bit source channel gets converted to an 8-bit destination b11111000.
The YUV formats are internally converted to RGB. Pixel selection is unified for all formats by using the LSB of the coordinate.

5.4 Pixel Buffer Enumerations

5.4.1 vg_lite_buffer_format_t Enumeration

This enumeration specifies the color format to use for a buffer. This applies to both Image and Render Target. Formats include supported swizzles for RGB. For YUV swizzles, use the related values and parameters in vg_lite_swizzle_t.

Application can use vg_lite_query_feature API to determine support for some hardware dependent formats. For example, related vg_lite_feature_t enum values include gcFEATURE_BIT_VG_RGBA2_FORMAT and gcFEATURE_BIT_VG_IM_INDEX_FORMAT.

NOTE: See Alignment Notes Table 2 following the value descriptions for alignment requirements summary for the image formats. *(alignment column refined March 2023)*

Used in structure: vg_lite_buffer_t.
See also vg_lite_blit, vg_lite_clear, vg_lite_draw.

vg_lite_buffer_format_t String Value	Description	Supported as Source	Supported as Dest	gcFEATURE_VG_16PIXELS_ALIGNED Value: Bytes
VG_LITE_ABGR8888	32-bit ABGR format with 8 bits per color channel. Alpha is in bits 7:0, blue in bits 15:8, green in bits 23:16, and the red channel is in bits 31:24. 31:24 / 23:16 / 15:8 / 7:0 **ABGR8888**: R / G / B / A	Yes	Yes	0: 4B 1: 64B
VG_LITE_ARGB8888	32-bit ARGB format with 8 bits per color channel. Alpha is in bits 7:0, red in bits 15:8, green in bits 23:16, and the blue channel is in bits 31:24. 31:24 / 23:16 / 15:8 / 7:0 **ARGB8888**: B / G / R / A	Yes	Yes	0: 4B 1: 64B
VG_LITE_BGRA8888	32-bit BGRA format with 8 bits per color channel. Blue in bits 7:0, green in bits 15:8, red is in bits 23:16, and the alpha channel is in bits 31:24. 31:24 / 23:16 / 15:8 / 7:0 **BGRA8888**: A / R / G / B	Yes	Yes	0: 4B 1: 64B
VG_LITE_RGBA8888	32-bit RGBA format with 8 bits per color channel. Red is in bits 7:0, green in bits 15:8, blue in bits 23:16, and the alpha channel is in bits 31:24. 31:24 / 23:16 / 15:8 / 7:0 **RGBA8888**: A / B / G / R	Yes	Yes	0: 4B 1: 64B
VG_LITE_BGRX8888	32-bit BGRX format with 8 bits per color channel. Blue in bits 7:0, green in bits 15:8, red is in bits 23:16, and the X channel is in bits 31:24. 31:24 / 23:16 / 15:8 / 7:0 **BGRX8888**: X / R / G / B	Yes	Yes	0: 4B 1: 64B

vg_lite_buffer_format_t String Value	Description	Supported as Source	Supported as Dest	gcFEATURE_VG_16PIXELS_ALIGNED Value: Bytes
VG_LITE_RGBX8888	32-bit RGBX format with 8 bits per color channel. Red is in bits 7:0, green in bits 15:8, blue in bits 23:16, and the X channel is in bits 31:24. RGBX8888: 31:24 X, 23:16 B, 15:8 G, 7:0 R	Yes	Yes	0: 4B 1: 64B
VG_LITE_XBGR8888	32-bit XBGR format with 8 bits per color channel. X channel is in bits 7:0, blue in bits 15:8, green in bits 23:16, and the red channel is in bits 31:24. XBGR8888: 31:24 R, 23:16 G, 15:8 B, 7:0 X	Yes	Yes	0: 4B 1: 64B
VG_LITE_XRGB8888	32-bit XRGB format with 8 bits per color channel. X channel is in bits 7:0, red in bits 15:8, green in bits 23:16, and the blue channel is in bits 31:24. XRGB8888: 31:24 B, 23:16 G, 15:8 R, 7:0 X	Yes	Yes	0: 4B 1: 64B
VG_LITE_ABGR1555	16-bit ABGR format with 5 bits per color channel and one bit alpha. Alpha channel is in bit 0:0, blue in bits 5:1, green in bits 10:6 and the red channel is in bits 15:11. ABGR5551: 15:11 R, 10:6 G, 5:1 B, 0:0 A	Yes	Yes	0: 4B 1: 32B
VG_LITE_ARGB1555	16-bit ARGB format with 5 bits per color channel and one bit alpha. The alpha channel is bit 0:0, red in bits 5:1, green in bits 10:6 and the blue channel is in bits 15:11. ARGB5551: 15:11 B, 10:6 G, 5:1 R, 0:0 A	Yes	Yes	0: 4B 1: 32B
VG_LITE_BGRA5551	16-bit BGRA format with 5 bits per color channel and one bit alpha. Blue is in bit 4:0, green in bits 9:5,red in bits 14:0 and the alpha channel is bit 15:15. BGRA5551: 15:15 A, 14:10 R, 9:5 G, 4:0 B	Yes	Yes	0: 4B 1: 32B
VG_LITE_RGBA5551	16-bit RGBA format with 5 bits per color channel and one bit alpha. Red is in bit 4:0, green in bits 9:5, blue in bits 14:0 and the alpha channel is bit 15:15. RGBA5551: 15:15 A, 14:10 B, 9:5 G, 4:0 R	Yes	Yes	0: 4B 1: 32B
VG_LITE_BGR565	16-bit BGR format with 5 and 6 bits per color channel. Blue is in bits 4:0, green in bits 10:5 and the red channel is in bits 15:11. BGR565: 15:11 R, 10:5 G, 4:0 B	Yes	Yes	0: 4B 1: 32B

vg_lite_buffer_format_t String Value	Description	Supported as Source	Supported as Dest	gcFEATURE_VG_16PIXELS_ALIGNED Value: Bytes
VG_LITE_RGB565	16-bit RGB format with 5 or 6 bits per color channel. Red is in bits 4:0, green in bits 10:5 and the blue channel is in bits 15:11. RGB565: 15:11 B, 10:5 G, 4:0 R	Yes	Yes	0: 4B 1: 32B
VG_LITE_ABGR4444	16-bit ABGR format with 4 bits per color channel. Alpha is in bits 3:0, blue in bits 7:4, green in bits 11:8 and the red channel is in bits 15:12. ABGR4444: 15:12 R, 11:8 G, 7:4 B, 3:0 A	Yes	Yes	0: 4B 1: 32B
VG_LITE_ARGB4444	16-bit ARGB format with 4 bits per color channel. Alpha is in bits 3:0, red in bits 7:4, green in bits 11:8 and the blue channel is in bits 15:12. ARGB4444: 15:12 B, 11:8 G, 7:4 R, 3:0 A	Yes	Yes	0: 4B 1: 32B
VG_LITE_BGRA4444	16-bit BGRA format with 4 bits per color channel. Red is in bits 11:8, green in bits 7:4, blue in bits 3:0 and the alpha channel is in bits 15:12. BGRA4444: 15:12 A, 11:8 R, 7:4 G, 3:0 B	Yes	Yes	0: 4B 1: 32B
VG_LITE_RGBA4444	16-bit RGBA format with 4 bits per color channel. Red is in bits 3:0, green in bits 7:4, blue in bits 11:8 and the alpha channel is in bits 15:12. RGBA4444: 15:12 A, 11:8 B, 7:4 G, 3:0 R	Yes	Yes	0: 4B 1: 32B
VG_LITE_YUY2 VG_LITE_YUYV	Packed YUV format, 32-bit for 2 pixels. Y0 is in bits 7:0 and V0 is in bits 31:23. (available for Source IMAGE only) YUY2: 31:24 V0, 23:16 Y1, 15:8 U0, 7:0 Y0; V2, Y3, U2, Y2	Yes	No	0: 4B 1: 32B
VG_LITE_A4	4-bit alpha format. There are no RGB values. A4: 3:0 A	Yes	No	0: 4B 1: 8B
VG_LITE_A8	8-bit alpha format. There are no RGB values. A8: 7:0 A	Yes	Yes	0: 4B 1: 16B

<table>
<tr><th>Hardware dependent formats for vg_lite_buffer_format_t</th><th>Description</th><th>Supported as Source</th><th>Supported as Dest</th><th>gcFEATURE_VG_16PIXELS_ALIGNED Value: Bytes</th></tr>
<tr><td>VG_LITE_ABGR2222</td><td>8-bit BGRA format with 2 bits per color channel. Alpha is in bits 1:0, blue in bits 3:2, green in bits 5:4 and the red channel is in bits 7:6.<table><tr><td></td><td>7:6</td><td>5:4</td><td>3:2</td><td>1:0</td></tr><tr><td>ABGR2222</td><td>R</td><td>G</td><td>B</td><td>A</td></tr></table></td><td>Yes</td><td>Yes</td><td>0: 4B
1: 16B</td></tr>
<tr><td>VG_LITE_ARGB2222</td><td>8-bit BGRA format with 2 bits per color channel. Alpha is in bits 1:0, red in bits 3:2,green in bits 5:4 and the blue channel is in bits 7:6.<table><tr><td></td><td>7:6</td><td>5:4</td><td>3:2</td><td>1:0</td></tr><tr><td>ARGB2222</td><td>B</td><td>G</td><td>R</td><td>A</td></tr></table></td><td>Yes</td><td>Yes</td><td>0: 4B
1: 16B</td></tr>
<tr><td>VG_LITE_BGRA2222</td><td>8-bit BGRA format with 2 bits per color channel. Blue is in bits 1:0, green in bits 3:2, red in bits 5:4 and the alpha channel is in bits 7:6.<table><tr><td></td><td>7:6</td><td>5:4</td><td>3:2</td><td>1:0</td></tr><tr><td>BGRA2222</td><td>A</td><td>R</td><td>G</td><td>B</td></tr></table></td><td>Yes</td><td>Yes</td><td>0: 4B
1: 16B</td></tr>
<tr><td>VG_LITE_RGBA2222</td><td>8-bit RGBA format with 2 bits per color channel. Red is in bits 1:0, green in bits 3:2, blue in bits 5:4 and the alpha channel is in bits 7:6.<table><tr><td></td><td>7:6</td><td>5:4</td><td>3:2</td><td>1:0</td></tr><tr><td>RGBA2222</td><td>A</td><td>B</td><td>G</td><td>R</td></tr></table></td><td>Yes</td><td>Yes</td><td>0: 4B
1: 16B</td></tr>
<tr><td>VG_LITE_INDEX_1</td><td>1-bit index format.</td><td>Yes</td><td>No</td><td>8</td></tr>
<tr><td>VG_LITE_INDEX_2</td><td>2-bit index format.</td><td>Yes</td><td>No</td><td>8</td></tr>
<tr><td>VG_LITE_INDEX_4</td><td>4-bit index format.</td><td>Yes</td><td>No</td><td>8</td></tr>
<tr><td>VG_LITE_INDEX_8</td><td>8-bit index format.</td><td>Yes</td><td>No</td><td>8</td></tr>
<tr><td>VG_LITE_NV12_TILED</td><td>Supertiled (8x8 pixels), planar YUV format, 96-bit for 4 pixels. Y plane is 32 bits for 4 pixels and is organized in 64 pixel super tiles (8x8 Y); UV plane is 64 bits for 4 pixels. Pixels are organized in super tiles are (4x4 UV pairs). (available for Source IMAGE only on supporting hardware)<table><tr><td></td><td>31:24</td><td>23:16</td><td>15:8</td><td>7:0</td></tr><tr><td>Y Buffer</td><td>Y3</td><td>Y2</td><td>Y1</td><td>Y0</td></tr><tr><td>Y Buffer</td><td>...</td><td></td><td></td><td></td></tr><tr><td></td><td>31:24</td><td>23:16</td><td>15:8</td><td>7:0</td></tr><tr><td rowspan="3">UV Buffer</td><td>V1</td><td>U1</td><td>V0</td><td>U0</td></tr><tr><td>V3</td><td>U3</td><td>V2</td><td>U2</td></tr><tr><td>...</td><td></td><td></td><td></td></tr></table></td><td>Yes</td><td>No</td><td>Y: 16 Bytes

UV: 8 Bytes</td></tr>
</table>

Hardware dependent formats for vg_lite_buffer_format_t	Description	Supported as Source	Supported as Dest	gcFEATURE_VG_16PIXELS_ALIGNED Value: Bytes
VG_LITE_ANV12_TILED	Pixel organization as NV12_TILED but with an Alpha Buffer, also supertiled. (available for Source IMAGE only on supporting hardware) **Alpha Buffer**: 31:24 / 23:16 / 15:8 / 7:0; A3 A2 A1 A0; ... **Y Buffer Y Buffer**: 31:24 / 23:16 / 15:8 / 7:0; Y3 Y2 Y1 Y0; ... **UV Buffer**: 31:24 / 23:16 / 15:8 / 7:0; V1 U1 V0 U0; V3 U3 V2 U2; ...	Yes	No	A, Y: 16 Bytes UV: 8 Bytes
VG_LITE_AYUY2_TILED	Supertiled (8x8) and packed YUV format with separate tiled Alpha Buffer. Y0 is in bits 7:0 and V is in bits 31:23. (available for Source IMAGE only on supporting hardware) **Alpha Buffer**: 31:24 / 23:16 / 15:8 / 7:0; A3 A2 A1 A0; ... **YUY2 Buffer**: 31:24 / 23:16 / 15:8 / 7:0; V0 Y1 U0 Y0; V2 Y3 U2 Y2; V4 Y5 U4 Y4	Yes	No	32 Bytes
VG_LITE_RGB888	24-bit RGB format with 8 bits per color channel. Red is in bits 7:0, green in bits 15:8, blue in bits 23:16. **RGB888**: 23:16 B / 15:8 G / 7:0 R	Yes	Yes	0: 4B 1: 32B
VG_LITE_BGR888	24-bit RGB format with 8 bits per color channel. Blue is in bits 7:0, green in bits 15:8, red in bits 23:16. **BGR888**: 23:16 R / 15:8 G / 7:0 B	Yes	Yes	0: 4B 1: 32B
VG_LITE_ARGB8565	24-bit RGBA format with 4 and 5 bits per color channel. Alpha channel is in bit 7:0, red in bits 12:8, green in bits 18:13 and the blue in bits 23:19. **ARGB8565**: 23:19 B / 18:13 G / 12:8 R / 7:0 A	Yes	Yes	0: 4B 1: 32B
VG_LITE_BGRA5658	24-bit RGBA format with 4 and 5 bits per color channel. Blue is in bits 4:0, green in bits 10:5, red in bits 15:11,alpha channel is in bit 23:16. **BGRA5658**: 23:16 A / 15:11 R / 10:5 G / 4:0 B	Yes	Yes	0: 4B 1: 32B

Hardware dependent formats for vg_lite_buffer_format_t	Description	Supported as Source	Supported as Dest	gcFEATURE_VG_16PIXELS_ALIGNED Value: Bytes
VG_LITE_ABGR8565	24-bit RGBA format with 4 and 5 bits per color channel. Alpha channel is in bit 7:0, blue in bits 12:8, green in bits 18:13 and the red in bits 23:19. **ABGR8565**: 23:19 R, 18:13 G, 12:8 B, 7:0 A	Yes	Yes	0: 4B 1: 32B
VG_LITE_RGBA5658	24-bit RGBA format with 4 and 5 bits per color channel. Red is in bits 4:0, green in bits 10:5, blue in bits 15:11 and the alpha channel is in bits 23:16 **RGBA5658**: 23:16 A, 15:11 B, 10:5 G, 4:0 R	Yes	Yes	0: 4B 1: 32B

5.4.1.1.1 Alignment Notes

Source Image Alignment Requirement

The buffer start address and stride byte-alignment requirement for a pixel depends on the specific pixel format, and gcFEATURE_VG_16PIXELS_ALIGNED value (0/1) in vg_lite_options.h file.

Table 2. Image Source Buffer Start Address and Stride Alignment Summary

(Start Address / Stride column updated for some formats March 2023)

Image Format	Bits per pixel	Start Address & Stride Alignment Requirement in Bytes	Supported for Source IMAGE	Supported for Destination
VG_LITE_INDEX1	1	8B	Yes	
VG_LITE_INDEX2	2	8B	Yes	
VG_LITE_INDEX4	4	8B	Yes	
VG_LITE_INDEX8	8	16B	Yes	
VG_LITE_A4	4	4B / 8B	Yes	
VG_LITE_A8	8	4B / 16B	Yes	Yes
VG_LITE_L8	8	4B / 16B	Yes	Yes
VG_LITE_ARGB2222 group	8	4B / 16B	Yes	Yes
VG_LITE_RGB565 group	16	4B / 32B	Yes	Yes
VG_LITE_ARGB1555 group	16	4B / 32B	Yes	Yes
VG_LITE_ARGB4444 group	16	4B / 32B	Yes	Yes
VG_LITE_YUY2/UYVY	16	4B / 32B	Yes	
VG_LITE_ARGB8888/XRGB8888 group	32	4B / 64B	Yes	Yes
VG_LITE_ARGB8565/RGB888 group	32	4B / 64B	Yes	Yes
VG_LITE_NV12_TILED	Tile 4x4	Y: 16B UV: 8B	Yes	
VG_LITE_ANV12_TILED	Tile 4x4	Y: 16B UV: 8B	Yes	
VG_LITE_AYUY2_TILED	Tile 4x4	32B	Yes	

VGLite hardware requires the raster image width to be a multiple of 16 pixels for linear gradient and radial gradient operations. This requirement applies to all image formats. Therefore, the user needs to pad an arbitrary image width to a multiple of 16 pixels for VGLite linear gradient and radial gradient APIs.

Destination Alignment Requirement

- For Pixel Engine (PE) destination, the alignment should be 64B for all tiled (4x4) formats.
- Alignment may also be limited by the alignment requirements of backend modules such as DC (Display Controller).

5.4.2 vg_lite_buffer_layout_t Enumeration

Specifies the buffer data layout in memory.

Used in structure: vg_lite_buffer.

vg_lite_buffer_layout_t String Value	Description
VG_LITE_LINEAR	Linear (scanline) layout.
VG_LITE_TILED	Data is organized in 4x4 pixel tiles. Note: for this layout, the buffer start address and stride need to be 64 byte aligned.

5.4.3 vg_lite_compress_mode_t Enumeration

Specifies the DECNano comprssion mode. *(from March 2023)*

Used in structure: vg_lite_buffer_t.

vg_lite_compress_mode_t String Value	Description
VG_LITE_DEC_DISABLE	Disable compression.
VG_LITE_DEC_NON_SAMPLE	compression ratio is 1.6 for ARGB8888, 2.0 for XRGB8888
VG_LITE_DEC_HSAMPLE	compression ratio is 2.0 for ARGB8888, 2.6 for XRGB8888
VG_LITE_DEC_HV_SAMPLE	compression ratio is 2.6 for ARGB8888, 4.0 for XRGB8888

5.4.4 vg_lite_gamma_conversion_t Enumeration

Specifies the gamma conversion mode. *(from Sept 2022)*

Used in function: vg_lite_set_gamma.

vg_lite_gamma_conversion_t String Value	Description
VG_LITE_GAMMA_NO_CONVERSION	Leave color as is.
VG_LITE_GAMMA_LINEAR	Convert from sRGB to linear.
VG_LITE_GAMMA_NON_LINEAR	Convert from linear to sRGB space.

5.4.5 vg_lite_index_endian_t Enumeration

Specifies the endian order parsing mode for index formats. *(from March 2023)*

Used in structure: vg_lite_buffer_t.

vg_lite_index_endian_t String Value	Description
VG_LITE_INDEX_ENDIAN_LITTLE_ENDIAN	Parse the index pixel from low to high, when using index1, the parsing order is bit0~bit7. when using index2, the parsing order is bit0:1,bit2:3,bit4:5.bit6:7. when using index4, the parsing order is bit0:3,bit4:7.

VG_LITE_INDEX_ENDIAN_BIG_ENDIAN	Parse the index pixel from low to high, when using index1, the parsing order is bit7~bit0. when using index2, the parsing order is bit7:6,bit5:4,bit3:2.bit1:0. when using index4, the parsing order is bit4:7,bit0:3.

5.4.6 vg_lite_image_mode_t Enumeration

Specifies how an image is rendered onto a buffer. *(prior to Sept 2022 name was vg_lite_buffer_image_mode_t)*

Used in structure: vg_lite_buffer_t.

vg_lite_image_mode_t String Value	Description
VG_LITE_ZERO	
VG_LITE_NORMAL_IMAGE_MODE	Image drawn with blending mode
VG_LITE_MULTIPLY_IMAGE_MODE	Image is multiplied with paint color
VG_LITE_STENCIL_MODE	
VG_LITE_NONE_IMAGE_MODE	Image input is ignored
VG_LITE_RECOLOR_MODE	

5.4.7 vg_lite_map_flag_t Enumeration

Specifies whether mapping is for user memory or the DMA buffer. *(from March 2023)*

Used in function: vg_lite_map.

vg_lite_map_flag_t String Value	Description
VG_LITE_MAP_USER_MEMORY	Mapping is for user memory.
VG_LITE_MAP_DMABUF	Mapping is for the DMA buffer.

5.4.8 vg_lite_paint_type_t Enumeration

Specifies paint type. *(from May 2023)*

Used in structure: vg_lite_buffer_t.

vg_lite_paint_type_t String Value	Description
VG_LITE_PAINT_ZERO	
VG_LITE_PAINT_COLOR	Color
VG_LITE_PAINT_LINEAR_GRADIENT	Linear Gradient
VG_LITE_PAINT_RADIAL_GRADIENT	Radial Gradient
VG_LITE_PAINT_PATTERN	Pattern

5.4.9 vg_lite_transparency_t Enumeration

Specifies the transparency mode for a buffer. *(prior to Sept 2022 name was vg_lite_buffer_transparency_mode_t)*

Used in structure: vg_lite_buffer.

vg_lite_transparency_t String Value	Description
VG_LITE_IMAGE_OPAQUE	Opaque image: all image pixels are copied to the VG PE for rasterization
VG_LITE_IMAGE_TRANSPARENT	Transparent image: only the non-transparent image pixels are copied to the VG PE. Note: this mode is only valid when IMAGE_MODE (vg_lite_image_mode_t) is either VG_LITE_NORMAL_IMAGE_MODE or VG_LITE_MULTIPLY_IMAGE_MODE.

5.4.10 vg_lite_swizzle_t Enumeration

This enumeration specifies the swizzle for the UV components of YUV data.

Used in structure: vg_lite_yuvinfo.

vg_lite_swizzle_t String Value	Description
VG_LITE_SWIZZLE_UV	U in lower bits, V in upper bits
VG_LITE_SWIZZLE_VU	V in lower bits, U in upper bits

5.4.11 vg_lite_yuv2rgb_t Enumeration

This enumeration specifies the standard for conversion of YUV data to RGB data.

Used in structure: vg_lite_yuvinfo.

vg_lite_yuv2rgb_t String Value	Description
VG_LITE_YUV601	YUV Converting with ITC.BT-601 standard
VG_LITE_YUV709	YUV Converting with ITC.BT-709 standard

5.5 Pixel Buffer Structures

5.5.1 vg_lite_buffer_t Structure

This structure defines the buffer layout for a VGLite image or memory data.

Used in structures: vg_lite_linear_gradient_t, vg_lite_radial_gradient_t.
Used in init functions: vg_lite_allocate, vg_lite_free, vg_lite_upload_buffer, vg_lite_map, vg_lite_unmap.
Used in blit functions: vg_lite_blit, vg_lite_blit_rect, vg_lite_clear, vg_lite_create_masklayer, vg_lite_fill_masklayer, vg_lite_blend_masklayer, vg_lite_set_masklayer, vg_lite_render_masklayer, vg_lite_destroy_masklayer,
Used in draw functions: vg_lite_draw, vg_lite_draw_pattern, vg_lite_draw_grad, vg_lite_draw_radial_grad.

vg_lite_buffer_t Members	Type	Description
width	vg_lite_int32_t	Width of buffer in pixels
height	vg_lite_int32_t	Height of buffer in pixels
stride	vg_lite_int32_t	Stride in bytes
tiled	vg_lite_buffer_layout_t	Linear or tiled format for buffer enum
format	vg_lite_buffer_format_t	color format enum
handle	vg_lite_pointer	memory handle
memory	vg_lite_pointer	pointer to the start address of the memory
address	vg_lite_uint32_t	GPU address
yuv	vg_lite_yuvinfo_t	YUV format info struct
image_mode	vg_lite_image_mode_t	Blit image mode enum
transparency_mode	vg_lite_transparency_t	Image transparency mode enum
fc_enable	vg_lite_int8_t	Enable Image fast clear
fc_buffer[3]	vg_lite_fc_buffer_t	Three (3) fast clear buffers, reserved YUV format *(from March 2023)*
compress_mode	vg_lite_compress_mode	Compression mode *(from March 2023)*
index_endian	vg_lite_index_endian_t	Big/Little Endian setting for index formats *(from March 2023)*
paintType	vg_lite_paint_type_t	Paint type enum *(from May 2023)*

5.5.2 vg_lite_fc_buffer_t Structure

This structure defines the organization of a fast clear buffer. *(from March 2023)*

Used in structure: vg_lite_buffer_t.

vg_lite_fc_buffer_t Members	Type	Description
width	vg_lite_int32_t	Width of buffer in pixels
height	vg_lite_int32_t	Height of buffer in pixels
stride	vg_lite_int32_t	Stride in bytes
handle	vg_lite_pointer	memory handle as allocated by the VGLite kernel
memory	vg_lite_pointer	logical pointer to the start address of the memory for the CPU
address	vg_lite_uint32_t	address to the buffer's memory for the GPU hardware
color	vg_lite_uint32_t	The fast clear color value

5.5.3 vg_lite_yuvinfo_t Structure

This structure defines the organization of VGLite YUV data.

Used in structure: vg_lite_buffer_t.

vg_lite_yuvinfo_t Members	Type	Description
swizzle	vg_lite_swizzle_t	UV swizzle enum
yuv2rgb	vg_lite_yuv2rgb_t	YUV conversion standard enum
uv_planar	vg_lite_uint32_t	UV (U) planar address for GPU, generated by driver
v_planar	vg_lite_uint32_t	V planar address for GPU, generated by driver
alpha_planar	vg_lite_uint32_t	Alpha planar address for GPU, generated by driver
uv_stride	vg_lite_uint32_t	UV (U) stride in bytes
v_stride	vg_lite_uint32_t	V planar stride in bytes
alpha_stride	vg_lite_uint32_t	Alpha stride in bytes
uv_height	vg_lite_uint32_t	UV (U) height in pixels
v_height	vg_lite_uint32_t	V stride in bytes
uv_memory	vg_lite_pointer	Logical pointer to the UV (U) planar memory
v_memory	vg_lite_pointer	Logical pointer to the V planar memory
uv_handle	vg_lite_pointer	Memory handle of the UV (U) planar, generated by driver
v_handle	vg_lite_pointer	Memory handle of the V planar, generated by driver

5.6 Pixel Buffer Functions

vg_lite_allocate

Description:
This function is used to allocate a buffer before using it in either blit or draw functions.

In order for the hardware to access some memory, like a source image or a target buffer, it needs to be allocated first. The supplied vg_lite_buffer_t structure needs to be initialized with the size (width and height) and format of the requested buffer. If the stride is set to zero, this function will fill it in. The only input parameter to this function is the pointer to the buffer structure. If the structure has all the information needed, appropriate memory will be allocated for the buffer.

This function will call the kernel to actually allocate the memory. The memory handle, logical address, and hardware addresses in the vg_lite_buffer_t structure will be filled in by the kernel.

Alignment Note: Though Vivante Vector Graphics hardware has an alignment requirement of 64 bytes, the VGLite Driver sets alignment to 128 bytes for render target buffer to conform to the alignment requirement of Vivante Display Controller. For source image buffer alignment requirement, see Alignment Notes Table 3 following the vg_lite_buffer_format_t value descriptions.

Syntax:

```
vg_lite_error_t vg_lite_allocate (
    vg_lite_buffer_t          *buffer
);
```

Parameters:

***buffer**	Pointer to the buffer that holds the size and format of the buffer being allocated. Either the memory or address field needs to be set to a non-zero value to map either a logical or physical address into hardware accessible memory.

Returns:
VG_LITE_SUCCESS if the allocating contiguous buffer is allocated successfully.
VG_LITE_OUT_OF_RESOURCES if there is insufficient memory in the host OS heap for the buffer
VG_LITE_OUT_OF_MEMORY if allocation of a contiguous buffer failed.

vg_lite_free

Description:
This function is used to deallocate the buffer that was previously allocated. This will free up the memory for that buffer.

Syntax:

```
vg_lite_error_t vg_lite_free (
    vg_lite_buffer_t            *buffer
);
```

Parameters:

***buffer**	Pointer to a buffer structure that was filled in by vg_lite_allocate.

vg_lite_upload_buffer

Description:
The function uploads the pixel data to a GPU memory buffer object. Note that the format of the data (pixel) to be uploaded must be the same as described in the buffer object. The input data memory buffer should contain enough data to be uploaded to the GPU buffer pointed by the input parameter "buffer". *(replaces deprecated vg_lite_buffer_upload from Sept 2022)*

Note: Vivante Vector Graphics IP only uses data[0] and stride[0] as it does not support planar YUV formats.

Syntax:

```
vg_lite_error_t vg_lite_upload_buffer (
    vg_lite_buffer_t            *buffer,
    vg_lite_uint8_t             *data[3],
    vg_lite_uint32_t            stride[3]
);
```

Parameters:

***buffer**	Pointer to a buffer structure that was filled in by vg_lite_allocate.
***data[3]**	Pointer to pixel data. For YUV format, there may be up to 3 pointers.
stride[3]	Stride for the pixel data.

vg_lite_map

Description:
This function is used to map the memory appropriately for a particular buffer. For some operating systems, it will be used to get proper translation to physical or logical address of the buffer needed by the GPU.

If you want the use a frame buffer directly as a target buffer, you need to wrap a vg_lite_buffer_t structure around it and call the kernel to map the supplied logical or physical address into hardware accessible memory. For example, if you know the logical address of the frame buffer, set the memory field of the vg_lite_buffer_t structure with that address and call this function. If you know the physical address, set the memory field to NULL and program the address field with the physical address.

Syntax:

```
vg_lite_error_t vg_lite_map (
    vg_lite_buffer_t           *buffer,
    vg_lite_map_flag_t         flag,
    int32_t                    fd
);
```

Parameters:

***buffer**	Pointer to a buffer structure that was filled in by vg_lite_allocate.
flag	Enum vg_lite_map_flag_t value which specifies whether mapping is for user memory or DMA buffer. *(from March 2023)*
fd	File descriptor for dma_buf if flag is VG_LITE_MAP_DMABUF. Otherwise this parameter is ignored. *(from March 2023)*

vg_lite_unmap

Description:
This function unmaps the buffer and frees any memory resources allocated by a previous call to vg_lite_map.

Syntax:

```
vg_lite_error_t vg_lite_unmap (
    vg_lite_buffer_t           *buffer
);
```

Parameters:

***buffer**	Pointer to a buffer structure that was filled in by vg_lite_map.

vg_lite_flush_mapped_buffer

Description:
This function flushes the CPU cache for the mapped buffer to make sure the buffer contents are written to GPU memory.

Syntax:

```
vg_lite_error_t vg_lite_flush_mapped_buffer (
    vg_lite_buffer_t           *buffer
);
```

Parameters:

***buffer**	Pointer to a buffer structure that was filled in by vg_lite_map.

vg_lite_set_CLUT

Description:
This function sets the Color Lookup Table (CLUT) in context state for index color image. Once the CLUT is set (Not NULL), the image pixel color for index format image rendering is obtained from the Color Lookup Table (CLUT) according to the pixel's color index value.

Note: Available only for IP with Indexed color support.

Syntax:

```
vg_lite_error_t vg_lite_set_CLUT (
    vg_lite_uint32_t            count,
    vg_lite_uint32_t            *colors
);
```

Parameters:

count	This is the count of the colors in the color look up table. For INDEX_1, there can be up to 2 colors in the table; For INDEX_2, there can be up to 4 colors in the table; For INDEX_4, there can be up to 16 colors in the table; For INDEX_8, there can be up to 256 colors in the table.
***colors**	The Color Lookup Table (CLUT) pointed by "colors" will be stored in the context and programmed to the command buffer when needed. The CLUT will not take effect until the command buffer is submitted to HW. The color is in ARGB format with A located in the upper bits. Note: The VGLite driver does not validate the CLUT contents from application.

Returns:
VG_LITE_SUCCESS since no checking is done.

vg_lite_enable_dither

Description:
This function is used to enable the dither function. Dither is turned off by default.
Application can use VGLite API vg_lite_query_feature(gcFEATURE_BIT_VG_DITHER) to determine HW support for dither.

Syntax:

```
vg_lite_error_t vg_lite_enable_dither (
);
```

Parameters: None

vg_lite_disable_dither

Description:
This function is used to disable the dither function. Dither is turned off by default.

Syntax:

```
vg_lite_error_t vg_lite_disable_dither (
);
```

Parameters: None

vg_lite_set_gamma

Description:
This function sets a gamma value.
Application can use VGLite API vg_lite_query_feature(gcFEATURE_BIT_VG_GAMMA) to determine HW support for gamma.

Syntax:

```
vg_lite_error_t vg_lite_set_gamma (
    vg_lite_gamma_conversion_t    gamma_value
);
```

Parameters:

gamma_value	Sets a gamma value. See enum vg_lite_gamma_conversion_t.

6 Matrices

This part of the API provides matrix controls.

Note: All the transformations in the driver/API are actually the final plane/surface coordinate system. There is no transformation of different coordinate systems with VGLite.

6.1 Matrix Control Float Parameter Type

Name	Typedef	Value
vg_lite_float_t	float	A single precision floating point number

vg_lite_pixel_matrix_t[20]	vg_lite_float_t	Pixel transform matrix m[20] which transforms each pixel as follows:
		`|a'|  |m0  m1  m2  m3  m4 |  |a|`
		`|r'|  |m5  m6  m7  m8  m9 |  |r|`
		`|g'| = |m10 m11 m12 m13 m14|.|g|`
		`|b'|  |m15 m16 m17 m18 m19|  |b|`
		`|1 |  |0   0   0   0   1  |  |1|`

6.2 Matrix Control Structures

6.2.1 vg_lite_matrix_t Structure

This structure defines a 3x3 float matrix.

Used in structures: vg_lite_linear_gradient_t, vg_lite_radial_gradient_t.
Used in blit functions: vg_lite_blit, vg_lite_blit_rect.
Used in function: vg_lite_render_masklayer.
Used in draw functions: vg_lite_draw, vg_lite_draw_grad, vg_lite_draw_radial_grad, vg_lite_draw_pattern, vg_lite_identity, vg_lite_scale, vg_lite_translate.

vg_lite_matrix_t Members	Type	Description
m[3][3]	vg_lite_float_t	3x3 matrix, in [row] [column] order

6.2.2 vg_lite_pixel_channel_enable_t Structure

This structure provides enable disable flags for hardware pixel channels A,R,G,B.

Used in function: vg_lite_set_pixel_matrix_t.

vg_lite_pixel_channel_enable_t Members	Type	Description
enable_a	vg_lite_uint8_t	Enable A channel
enable_b	vg_lite_uint8_t	Enable B channel
enable_g	vg_lite_uint8_t	Enable G channel
enable_r	vg_lite_uint8_t	Enable R channel

6.3 Matrix Control Functions

vg_lite_identity

Description:
This function loads an identity matrix into a matrix variable.

Syntax:

```
vg_lite_error_t vg_lite_identity (
    vg_lite_matrix_t            *matrix,
);
```

Parameters:

***matrix**	Pointer to the vg_lite_matrix_t structure that will be loaded with an identity matrix

vg_lite_set_pixel_matrix

Description:
This function sets up a pixel transform matrix m[20] which transforms each pixel as follows:

```
|a'|   |m0  m1  m2  m3  m4 | |a|
|r'|   |m5  m6  m7  m8  m9 | |r|
|g'| = |m10 m11 m12 m13 m14|.|g|
|b'|   |m15 m16 m17 m18 m19| |b|
|1 |   |0   0   0   0   1  | |1|
```

The pixel transform for the A, R, G, B channels can be enabled/disabled individually with the channel parameter.

Applications can use VGLite API vg_lite_query_feature (gcFEATURE_BIT_VG_PIXEL_MATRIX) to determine HW support for gaussian blur.

Syntax:

```
vg_lite_error_t vg_lite_set_pixel_matrix (
    vg_lite_pixel_matrix_t          matrix,
    vg_lite_pixel_channel_enable_t  *channel
);
```

Parameters:

matrix	Specifies the vg_lite_pixel_matrix_t pixel transform matrix that will be loaded
***channel**	Pointer to the vg_lite_pixel_channel_enable_t structure used to enable/disable individual channels.

vg_lite_rotate

Description:
This function rotates a matrix a specified number of degrees.

Syntax:

```
vg_lite_error_t vg_lite_rotate (
    vg_lite_float_t             degrees,
    vg_lite_matrix_t            *matrix
);
```

Parameters:

degrees	Number of degrees to rotate the matrix. Positive numbers rotate clockwise. The coordinates for the transformation are given in the surface coordinate system (top-to-bottom orientation). Rotations with positive angles are in the clockwise direction
***matrix**	Pointer to the vg_lite_matrix_t structure that will be rotated.

vg_lite_scale

Description:
This function scales a matrix in both horizontal and vertical directions.

Syntax:

```
vg_lite_error_t vg_lite_scale (
    vg_lite_float_t             scale_x,
    vg_lite_float_t             scale_y,
    vg_lite_matrix_t            *matrix
);
```

Parameters:

scale_x	Horizontal scale.
scale_y	Vertical scale.
***matrix**	Pointer to the vg_lite_matrix_t structure that will be scaled.

vg_lite_translate

Description:
This function translates a matrix to a new location.

Syntax:

```
vg_lite_error_t vg_lite_translate (
    vg_lite_float_t             x,
    vg_lite_float_t             y,
    vg_lite_matrix_t            *matrix
);
```

Parameters:

x	X location of the transformation.
y	Y location of the transformation.
***matrix**	Pointer to the vg_lite_matrix_t structure that will be translated.

7 Blits for Compositing and Blending

This part of the API performs the hardware accelerated blit operations.

Compositing rules describes how two areas are combined to form a single area. Blending rules describes how combining the colors of the overlapping areas are combined. VGLite supports two blending operations and a subset of the Porter-Duff operations [PD84]. The Porter-Duff operators assume the pixels have the alpha associated (pre-multiplied), i.e., pixels are premultiplied prior to the blending operation. Note that GC555, GC355 and some GCNanoUltraV hardware supports alpha premultiply for RGB image, but GCNanoLiteV does not.

The source image is copied to the destination window with a specified matrix that can include translation, rotation, scaling, and perspective correction.

- The blit function can be used with or without the blend mode.
- The blit function can be used with or without specifying any color value.
- The blit function can be used for color conversion with an identity matrix and appropriate formats specified for the source and the destination buffers. In this case do not specify blend mode and color value.

7.1 BLIT Enumerations

7.1.1 vg_lite_blend_t Enumeration

This enumeration defines the blending modes supported by some VGLite API functions. S and D represent source and destination color channels and Sa and Da represent the source and destination alpha channels.

Reference: Thomas Porter and Tom Duff. Compositing digital images. *SIGGRAPH Comput. Graph.*, 18(3):253–259, January 1984.

Table 3. Porter Duff Operators and Related vg_lite_blend_t enum Values

Sf/Df	0	1	Sa	1 - Sa
0	clear (n/a)	dst (n/a)	dst-in VG_LITE_BLEND_DST_IN	dst-out VG_LITE_BLEND_SUBTRACT
1	src VG_LITE_BLEND_NONE	plus VG_LITE_BLEND_ADDITIVE	…	src-over VG_LITE_BLEND_SRC_OVER
Da	src-in VG_LITE_BLEND_SRC_IN	…	…	src-atop(n/a)
1 - Da	src-out (n/a)	dst-over VG_LITE_BLEND_DST_OVER	dst-atop (n/a)	xor (n/a)

Used in blit functions: vg_lite_blit, vg_lite_blit2, vg_lite_blit_rect.
Used in draw functions: vg_lite_draw, vg_lite_draw_grad, vg_lite_draw_radial_grad, vg_lite_draw_pattern.

Colors are shown at 100% and 50% opacity.

vg_lite_blend_t String Values	Description
VG_LITE_BLEND_ADDITIVE	**S + D** Plus 50% = Result  Porter Duff Compositing Mode: plus
VG_LITE_BLEND_DST_IN	**Sa * D** DstIn DstIn 50% = Result  Porter Duff Compositing Mode: dst-in
VG_LITE_BLEND_DST_OVER	**(1 – Da) * S + D** DstOver 50% = Result  Porter Duff Compositing Mode: dst-over

vg_lite_blend_t String Values	Description
VG_LITE_BLEND_MULTIPLY	**S * (1 – Da) + D * (1 – Sa) + S * D** = Result  Blending Mode: mathematical multiply. (see https://www.w3.org/TR/compositing-1/#blendingmultiply) make white transparent for diagrams/text
VG_LITE_BLEND_NONE	**S, no blending** = Result  Porter Duff Compositing Mode: src
VG_LITE_BLEND_SCREEN	**S + D – S * D** = Result  Blending Mode: mathematical screen. (see https://www.w3.org/TR/compositing-1/#blendingscreen) make black transparent for diagrams/text

vg_lite_blend_t String Values	Description
VG_LITE_BLEND_SRC_IN	**Da * S** = Result SrcIn 50%  Porter Duff Compositing Mode: src-in, also known as clipping
VG_LITE_BLEND_SRC_OVER	**S + (1 - Sa) * D** = Result SrcOver 50%  Porter Duff Compositing Mode: src-over
VG_LITE_BLEND_SUBTRACT	**D * (1 – S)** = Result DestOut 50%  Porter Duff Compositing Mode: dst-out
VG_LITE_BLEND_SUBTRACT_LVGL	**D – S** *(from March 2023)*
VG_LITE_BLEND_NORMAL_LVGL	**S * Sa + (1 - Sa) * D** *(from March 2023)*
VG_LITE_BLEND_ADDITIVE_LVGL	**(S + D) * Sa + D * (1 - Sa)** *(from March 2023)*
VG_LITE_BLEND_MULTIPLY_LVGL	**(S * D) * Sa + D * (1 - Sa)** *(from March 2023)*
VG_LITE_BLEND_PREMULTIPLY_SRC_OVER	**S * Sa + (1 - Sa) * D.** Not a standard OVG blend mode, only supported with GCNanoUltraV *(from March 2023)*

7.1.2 vg_lite_color_t Parameter

The common parameter vg_lite_color_t is described in Section 1.4. LINK to Common Parameter Types.

7.1.3 vg_lite_color_transform_t Structure

Specifies the pixel color_transform values for scale and bias.

Used in functions: vg_lite_set_color_transform.

vg_lite_color_transform_t Members	Type	Description
a_scale	vg_lite_float_t	Scale value for alpha.
a_bias	vg_lite_float_t	Bias value for alpha.
r_scale	vg_lite_float_t	Scale value for red.
r_bias	vg_lite_float_t	Bias value for red.
g_scale	vg_lite_float_t	Scale value for gree.
g_bias	vg_lite_float_t	Bias value for gree.
b_scale	vg_lite_float_t	Scale value for blue.
b_bias	vg_lite_float_t	Bias value for blue.

7.1.4 vg_lite_filter_t Enumeration

Specifies the sample filtering mode in VGLite blit and draw APIs.

Used in blit functions: vg_lite_blit, vg_lite_blit_rect,
Used in draw functions: vg_lite_draw_radial_grad, vg_lite_draw_pattern.

vg_lite_filter_t String Values	Description
VG_LITE_FILTER_POINT	Fetch only the nearest image pixel.
VG_LITE_FILTER_LINEAR	Use linear interpolation along horizontal line.
VG_LITE_FILTER_BI_LINEAR	Use a 2x2 box around the image pixel and perform an interpolation.
VG_LITE_FILTER_GAUSSIAN	Perform 3x3 gaussian blur with the convolution for image pixel. *(from March 2023)*

7.1.5 vg_lite_global_alpha_t Enumeration

Specifies the global alpha mode in VGLite blit APIs.

Used in blit function: vg_lite_dest_global_alpha.

vg_lite_global_alpha_t String Values	Description
VG_LITE_NORMAL	= 0: Use original src/dst alpha value.
VG_LITE_GLOBAL	Use global src/dst alpha value to replace original src/dst alpha value.
VG_LITE_SCALED	Multiply global src/dst alpha value and original src/dst alpha value.

7.1.6 vg_lite_mask_operation_t Enumeration

Specifies the mask operation mode in VGLite blit APIs.

Used in functions: vg_lite_blend_masklayer, vg_lite_render_masklayer.

vg_lite_mask_operation_t String Values	Description
VG_LITE_CLEAR_MASK	This operation sets all mask values in the region of interest to 0, ignoring the new mask layer.
VG_LITE_FILL_MASK	This operation sets all mask values in the region of interest to 1, ignoring the new mask layer.
VG_LITE_SET_MASK	This operation copies values in the region of interest from the new mask layer, overwriting the previous mask values.
VG_LITE_UNION_MASK	This operation replaces the previous mask in the region of interest by its union with the new mask layer. The resulting values are always greater than or equal to their previous value.
VG_LITE_INTERSECT_MASK	This operation replaces the previous mask in the region of interest by its intersection with the new mask layer. The resulting mask values are always less than or equal to their previous value.
VG_LITE_SUBTRACT_MASK	This operation subtracts the new mask from the previous mask and replaces the previous mask in the region of interest by the resulting mask. The resulting values are always less than or equal to their previous value.

7.1.7 vg_lite_orientation_t Enumeration

Specifies the mirror orientation in VGLite blit APIs.

Used in functions: vg_lite_set_mirror.

vg_lite_orientation_t String Values	Description
VG_LITE_ORIENTATION_TOP_BOTTOM	Target output orientation is from top to bottom (default).
VG_LITE_ORIENTATION_BOTTOM_TOP	Target output orientation is from bottom to top.

7.2 BLIT Structures

7.2.1 vg_lite_buffer_t Structure

Defined under Pixel Buffer Structures. LINK to vg_lite_buffer_t structure.

7.2.2 vg_lite_color_key_t Structure

A “color key” have two sections, where each section contains R,G,B channels which are noted as high_rgb and low_rgb respectively. *(from April 2022)*

When the enable value is true, the color key specified is effective and the alpha value is used to replace the alpha channel of the destination pixel when its RGB channels are in range [low_rgb, high_rgb]. After the color key is used in the current frame, if the color key is not needed for the next frame, it should be disabled before the next frame.

Used in structure: vg_lite_color_key4_t.

vg_lite_color_key_t Members	Type	Description
enable	vg_lite_uint8_t	When set (true), this color key is enabled.
low_r	vg_lite_uint8_t	The R channel of low_rgb.
low_g	vg_lite_uint8_t	The G channel of low_rgb.
low_b	vg_lite_uint8_t	The B channel of low_rgb.
alpha	vg_lite_uint8_t	The alpha channel to replace the destination pixel alpha channel.
high_r	vg_lite_uint8_t	The R channel of high_rgb.
high_g	vg_lite_uint8_t	The G channel of high_rgb.
high_b	vg_lite_uint8_t	The B channel of high_rgb.

7.2.3 vg_lite_color_key4_t Structure

The priority order is: color_key_0 > color_key_1 > color_key_2 > color_key_3. *(from April 2022)*

Used in blit function: vg_lite_set_color_key

vg_lite_color_key4_t Members	Type	Description
color_key_0		high_rgb_0, low_rgb_0, alpha_0, enable_0
color_key_1		high_rgb_1, low_rgb_1, alpha_1, enable_1
color_key_2		high_rgb_2, low_rgb_2, alpha_2, enable_2
color_key_3		high_rgb_3, low_rgb_3, alpha_3, enable_3

7.2.4 vg_lite_matrix_t Structure

Defined under Matrix Control Structures LINK to vg_lite_matrix_t structure.

7.2.5 vg_lite_path_t Structure

Defined under Vector Path Structures. LINK to vg_lite_path_t structure.

7.2.6 vg_lite_rectangle_t Structure

This structure defines the organization of a rectangle of VGLite data.

Used in blit function: vg_lite_clear.

vg_lite_rectangle_t Members	Type	Description
x	vg_lite_int32_t	X Origin of rectangle, left coordinate in pixels
y	vg_lite_int32_t	Y Origin of rectangle, top coordinate in pixels
width	vg_lite_int32_t	X Width of rectangle in pixels
height	vg_lite_int32_t	Y Height of rectangle in pixels

7.2.7 vg_lite_point_t Structure

This structure defines a 2D Point. *(from March 2021)*

Used in structure: vg_lite_point4_t.

vg_lite_point_t Members	Type	Description
x	vg_lite_int32_t	X value of coordinate
y	vg_lite_int32_t	Y value of coordinate

7.2.8 vg_lite_point4_t Structure

This structure defines four 2D points that form a polygon. The points are defined by structure vg_lite_point_t. *(from March 2021)*

Used in blit function: vg_lite_get_transform_matrix.

vg_lite_point4_t Members	Type	Description
vg_lite_point[4]	vg_lite_int32_t each	a set of four points

7.3 BLIT Functions

vg_lite_blit

Description:

This is the blit function. The blit operation is performed using a source and a destination buffer. The source and destination buffer structures are defined using the vg_lite_buffer_t structure. Blit copies a source image to the destination window with a specified matrix that can include translation, rotation, scaling, and perspective correction. Note that vg_lite_buffer_t does not support coverage sample anti-aliasing so the destination buffer edge may not be smooth especially with a rotation matrix. VGLite path rendering can be used to achieve high quality coverage sample anti-aliasing (16X, 8X, 4X) rendering effect.

Notes:

- The blit function can be used with or without the blend function (vg_lite_blend_t).
- The blit function can be used with or without specifying any color value (vg_lite_color_t) .
- The blit function can be used for color conversion with an identity matrix and appropriate formats specified for the source and the destination buffers. In this case do not specify blend mode and color value.

Syntax:

```
vg_lite_error_t vg_lite_blit (
    vg_lite_buffer_t          *target,
    vg_lite_buffer_t          *source,
    vg_lite_matrix_t          *matrix,
    vg_lite_blend_t           blend,
    vg_lite_color_t           color,
    vg_lite_filter_t          filter
);
```

Parameters:

***target**	Points to the vg_lite_buffer_t structure which defines the destination buffer. See Image Source Alignment Requirement for valid destination color formats for the blit functions.
***source**	Points to the vg_lite_buffer_t structure for the source buffer. All color formats available in the vg_lite_buffer_format_t enum are valid source formats for the blit function.
***matrix**	Points to a vg_lite_matrix_t structure that defines the 3x3 transformation matrix of source pixels into the target. If matrix is NULL, an identity matrix is assumed, meaning the source will be copied directly on the target at (0,0) location.

blend	Specifies one of the enum vg_lite_blend_t values for hardware supported blend modes to be applied to each image pixel. If no blending is required, set this value to VG_LITE_BLEND_NONE (0). Note: If the “matrix” parameter is specified with rotation or perspective, and the “blend" parameter is specified as VG_LITE_BLEND_NONE, VG_LITE_BLEND_SRC_IN, or VG_LITE_BLEND_DST_IN, the VGLite driver will overwrite the application’s setting for the BLIT operation as follows: • If gcFEATURE_BIT_VG_BORDER_CULLING (vg_lite_feature_t) is supported, the transparency mode will always be set to TRANSPARENT. • If gcFEATURE_BIT_VG_BORDER_CULLING (vg_lite_feature_t) is not supported, the blend mode will always be set to VG_LITE_BLEND_SRC_OVER. This is due to some limitations in the VGLite hardware.
color	If non-zero, this color value is used as a mix color. The mix color gets multiplied with each source pixel before blending happens. If you don't need a mix color, set the color parameter to 0.
filter	Specifies the filter type. All formats available in the vg_lite_filter_t enum are valid formats for this function. A value of zero (0) indicates VG_LITE_FILTER_POINT.

vg_lite_blit2

Description:

This is the blit function for use with two sources. The blit2 operation is performed using two source buffers and one destination buffer. The source and destination buffer structures are defined using the vg_lite_buffer_t structure. Source0 and Source1 are first blended according to the blend mode with a specific transformation matrix for each image. Source1 is used as the source while Source0 is used as dest and is directly output to the render target buffer.

The specified matrices can include translation, rotation, scaling, and perspective correction. Note that vg_lite_buffer_t does not support coverage sample anti-aliasing so the destination buffer edge may not be smooth especially with a rotation matrix. VGLite path rendering can be used to achieve high quality coverage sample anti-aliasing (16X, 8X, 4X) rendering effect.

Application can use VGLite API vg_lite_query_feature(gcFEATURE_BIT_VG_DOUBLE_IMAGE) to determine HW support for double image.

Notes:

- The vg_lite_blit function can be used for color conversion for Source0 or Source1 before merging sources with vg_lite_blit2.

Syntax:

```
vg_lite_error_t vg_lite_blit2 (
    vg_lite_buffer_t          *target,
    vg_lite_buffer_t          *source0,
    vg_lite_buffer_t          *source1,
    vg_lite_matrix_t          *matrix0,
    vg_lite_matrix_t          *matrix1,
    vg_lite_blend_t           blend,
    vg_lite_filter_t          filter
);
```

Parameters:

***target**	Points to the vg_lite_buffer_t structure which defines the destination buffer. See Image Source Alignment Requirement for valid destination color formats for the blit functions.
***source0, *source1**	Points to the vg_lite_buffer_t structure for the source0 and source1 buffers. All color formats available in the vg_lite_buffer_format_t enum are valid source formats for the blit functions.
***matrix0, *matrix1**	Points to a vg_lite_matrix_t structure that defines the 3x3 transformation matrix0 for the source0 pixels and matrix1 for the source1 pixels. If matrix0 and matrix1 are both NULL, the identity matrix is assumed, meaning the blending result of Source0 and Source1 is copied directly on the target at location(0,0).

blend

Specifies one of the enum vg_lite_blend_t values for hardware supported blend modes to be applied to each image pixel. If no blending is required, set this value to VG_LITE_BLEND_NONE (0).

Note: If the “matrix” parameter is specified with rotation or perspective, and the “blend" parameter is specified as VG_LITE_BLEND_NONE, VG_LITE_BLEND_SRC_IN, or VG_LITE_BLEND_DST_IN, the VGLite driver will overwrite the application’s setting for the BLIT operation as follows:

- If gcFEATURE_BIT_VG_BORDER_CULLING (vg_lite_feature_t) is supported, the transparency mode will always be set to TRANSPARENT.
- If gcFEATURE_BIT_VG_BORDER_CULLING (vg_lite_feature_t) is not supported, the blend mode will always be set to VG_LITE_BLEND_SRC_OVER.

This is due to some limitations in the VGLite hardware.

filter

Specifies the filter type. All formats available in the vg_lite_filter_t enum are valid formats for this function. A value of zero (0) indicates VG_LITE_FILTER_POINT.

vg_lite_blit_rect

Description:

This is the blit rectangle function. The blit operation is performed using a source and a destination buffer. The source and destination buffer structures are defined using the vg_lite_buffer_t structure. Blit copies a source image to the destination window with a specified matrix that can include translation, rotation, scaling, and perspective correction. Note that vg_lite_buffer_t does not support coverage sample anti-aliasing so the destination buffer edge may not be smooth especially with a rotation matrix. VGLite path rendering can be used to achieve high quality coverage sample anti-aliasing (16X, 8X, 4X) rendering effect.

Notes:

- The blit_rect function can be used with or without the blend function (vg_lite_blend_t).
- The blit_rect function can be used with or without specifying any color value (vg_lite_color_t) .
- The blit_rect function can be used for color conversion with an identity matrix and appropriate formats specified for the source and destination buffers. In this case do not specify blend mode and color value.
- *The vg_lite_blit_rect rectangle start origin point is always (0,0) for hardware versions prior to GCNanoLiteV 1311p which do not support a non-zero rectangle origin.*

Syntax:

```
vg_lite_error_t vg_lite_blit_rect (
    vg_lite_buffer_t          *target,
    vg_lite_buffer_t          *source,
    vg_lite_rectangle_t       *rect,
    vg_lite_matrix_t          *matrix,
    vg_lite_blend_t           blend,
    vg_lite_color_t           color,
    vg_lite_filter_t          filter
);
```

Parameters:

***target**	Points to the vg_lite_buffer_t structure which defines the destination buffer. See Source Image Alignment Requirement for valid destination color formats for the blit_rect functions.
***source**	Points to the vg_lite_buffer_t structure for the source buffer. All color formats available in the vg_lite_buffer_format_t enum are valid source formats for the blit_rect function.
***rect**	Specifies the rectangle area (x, y, width, height) of the source image to blit. Note: Non-zero source origins are supported.
***matrix**	Points to a vg_lite_matrix_t structure that defines the 3x3 transformation matrix of source pixels into the target. If matrix is NULL, an identity matrix is assumed, meaning the source will be copied directly on the target at 0,0 location.

blend	Specifies one of the enum vg_lite_blend_t values for hardware supported blend modes to be applied to each image pixel. If no blending is required, set this value to VG_LITE_BLEND_NONE (0). Note: If the “matrix” parameter is specified with rotation or perspective, and the “blend" parameter is specified as VG_LITE_BLEND_NONE, VG_LITE_BLEND_SRC_IN, or VG_LITE_BLEND_DST_IN, the VGLite driver will overwrite the application’s setting for the BLIT operation as follows: • If gcFEATURE_BIT_VG_BORDER_CULLING (vg_lite_feature_t) is supported, the transparency mode will always be set to TRANSPARENT. • If gcFEATURE_BIT_VG_BORDER_CULLING (vg_lite_feature_t) is not supported, the blend mode will always be set to VG_LITE_BLEND_SRC_OVER. This is due to some limitations in the VGLite hardware.
color	If non-zero, this color value is used as a mix color. The mix color gets multiplied with each source pixel before blending happens. If you don't need a mix color, set the color parameter to 0.
filter	Specifies the filter type. All formats available in the vg_lite_filter_t enum are valid formats for this function. A value of zero (0) indicates VG_LITE_FILTER_POINT.

vg_lite_get_transform_matrix

Description:
This function generates a 3x3 homogenous transform matrix from 4 source coordinates and 4 target coordinates. *(from March 2021)*

Syntax:

```
vg_lite_error_t vg_lite_get_transform_matrix (
    vg_lite_point4_t            src,
    vg_lite_point4_t            dst,
    vg_lite_matrix_t            *mat
);
```

Parameters:

src	Pointer to a set of four 2D points that form a source polygon.
dst	Pointer to a set of four 2D points that form a destination polygon.
mat	Output parameter, pointer to a 3x3 homogenous matrix that transforms the source polygon to a destination polygon.

vg_lite_clear

Description:
This function performs the clear operation, clearing/filling the specified buffer (entire buffer or partial rectangle in a buffer) with an explicit color.

Syntax:

```
vg_lite_error_t vg_lite_clear (
    vg_lite_buffer_t            *target,
    vg_lite_rectangle_t         *rect,
    vg_lite_color_t             color
);
```

Parameters:

***target**	Pointer to the vg_lite_buffer_t structure for the destination buffer. All color formats available in the vg_lite_buffer_format_t enum are valid destination formats for the clear function.
***rect**	Pointer to a vg_lite_rectangle_t structure that specifies the area to be filled. If the rectangle is NULL, the entire target buffer will be filled with the specified color.
color	Clear color, as specified in the vg_lite_color_t enum which is the color value to use for filling the buffer. If the buffer is in L8 format, the RGBA color will be converted into a luminance value.

vg_lite_set_color_key

Description:

This function sets a color key. Color key can be used for blit or for draw pattern operations. *(from April 2022)*

A "color key" have two sections, where each section contains R,G,B channels which are noted as high_rgb and low_rgb respectively.

When the vg_lite_color_key_t structure value enable is true, the color key specified is effective and the alpha value is used to replace the alpha channel of the destination pixel when its RGB channels are within range [low_rgb, high_rgb]. After the color key is used in the current frame, if the color key is not needed for the next frame, it should be disabled before the next frame.

Hardware support for color key is not available for GCNanoLiteV. Application can use VGLite API vg_lite_query_feature(gcFEATURE_BIT_VG_COLOR_KEY) to determine HW support for color key.

Syntax:

```
vg_lite_error_t vg_lite_set_color_key (
    vg_lite_color_key4_t          colorkey
);
```

Parameters:

colorkey	A color key as defined by vg_lite_color_key4_t. There are 4 groups of color key states: - color_key_0: high_rgb_0, low_rgb_0, alpha_0, enable_0. - color_key_1: high_rgb_1, low_rgb_1, alpha_1, enable_1. - color_key_2: high_rgb_2, low_rgb_2, alpha_2, enable_2. - color_key_3: high_rgb_3, low_rgb_3, alpha_3, enable_3. The priority order of these states is: color_key_0 > color_key_1 > color_key_2 > color_key_3.

Return:

VG_LITE_SUCCESS if successful. Otherwise VG_LITE_NOT_SUPPORT if color key is not supported in hardware.

vg_lite_gaussian_filter

Description:
This function sets 3x3 gaussian blur weighted values to filter an image pixel. *(from March 2023)*

The parameters w0, w1, w2 define a 3x3 gaussian blur weight matrix as:

```
| w2  w1  w2 |
| w1  w0  w1 |
| w2  w1  w2 |
```

The sum of the 9 kernel weights must be 1.0 to avoid convolution overflow (w0 + 4*w1 + 4*w2 = 1.0).
The 3x3 weight matrix applies to a 3x3 pixel block:

```
| pixel[i-1][j-1]   pixel[i][j-1]   pixel[i+1][j-1]|
| pixel[i-1][j]     pixel[i][j]     pixel[i+1][j]  |
| pixel[i-1][j+1]   pixel[i][j+1]   pixel[i+1][j+1]|
```

With the following dot product equation:

```
color[i][j] = w2*pixel[i-1][j-1] + w1*pixel[i][j-1] + w2*pixel[i+1][j-1]
            + w1*pixel[i-1][j]   + w0*pixel[i][j]   + w1*pixel[i+1][j]
            + w2*pixel[i-1][j+1] + w1*pixel[i][j+1] + w2*pixel[i+1][j+1];
```

Applications can use VGLite API vg_lite_query_feature (gcFEATURE_BIT_VG_GAUSSIAN_BLUR) to determine HW support for gaussian blur.

Syntax:

```
vg_lite_error_t vg_lite_gaussian_filter (
    vg_lite_float_t          w0
    vg_lite_float_t          w1
    vg_lite_float_t          w2
);
```

Parameters:

w0, w1, w2 w0, w1, w2 define a 3x3 gaussian blur weighted matrix as:

```
| w2  w1  w2 |
| w1  w0  w1 |
| w2  w1  w2 |
```

Return:
VG_LITE_SUCCESS if successful. Otherwise VG_LITE_NOT_SUPPORT if gaussian blur is not supported in hardware.

7.4 Blit/Draw Extended Functions

The following BLIT or DRAW related functions typically require GC355 or GC555 hardware, and are not available for all Vivante Vector Graphics hardware configurations.

Applications can use VGLite API vg_lite_query_feature to determine HW support for the related functionality.

vg_lite_set_premultiply

Description:
This function will set source and destination image premultiply states. *(from Sept 2022, parameters modified Dec 2022, requires GC355 or GC555 hardware)*

Applications can use VGLite API vg_lite_query_feature (gcFEATURE_BIT_VG_HW_PREMULTIPLY) to determine HW support for premultiply.

Syntax:

```
vg_lite_error_t vg_lite_set_premultiply (
    vg_lite_uint8_t                src_premult,
    vg_lite_uint8_t                dst_premult,
);
```

Parameters:

src_premult	Specify whether the source image is premultiply or not.
dst_premult	Enable/disable destination image premultiply.

vg_lite_enable_scissor

Description:
This function enables scissor operations for a render targets boundary. *(from March 2020, modified August 2020, requires GC355 or GC555 hardware)*

Applications can use VGLite API vg_lite_query_feature (gcFEATURE_BIT_VG_SCISSOR) to determine HW support for scissoring. Support is available with GC355 and GC555.

Syntax:

```
vg_lite_error_t vg_lite_enable_scissor (
    void
);
```

vg_lite_disable_scissor

Description:

This function disables scissor operations for a render targets boundary. *(from March 2020, modified August 2020, requires GC355 or GC555 hardware)*

Syntax:

```
vg_lite_error_t vg_lite_disable_scissor (
      void
  );
```

vg_lite_set_scissor

Description:
This function is used to set a scissor rectangle for the render target.
(from March 2023, requires GC355 or GC555 hardware)

Syntax:

```
vg_lite_error_t vg_lite_set_scissor (
    vg_lite_int32_t              x,
    vg_lite_int32_t              y,
    vg_lite_int32_t              right,
    vg_lite_int32_t              bottom
);
```

Parameters:

x	X Origin of rectangle, left coordinate in pixels
y	Y Origin of rectangle, top coordinate in pixels
right	X rightmost pixel of rectangle
bottom	Y bottom pixel of rectangle

vg_lite_scissor_rects

Description:
This function is used to set scissor regions and update scissor layer through these regions.
(from August 2022, requires GC355 or GC555 hardware)

Syntax:

```
vg_lite_error_t vg_lite_scissor_rects (
    vg_lite_uint32_t             nums,
    vg_lite_rectangle_t          rect[]
);
```

Parameters:

nums	Number of scissor rectangles.
rect[]	The scissor rectangle array.

vg_lite_disable_color_transform

Description:
This function is used to disable color transformation. By default, color transform is turned off. *(from Sept 2022, only for GC355 and GC555 hardware)*

Applications can use VGLite API vg_lite_query_feature (gcFEATURE_BIT_VG_COLOR_TRANSFORMATION) to determine HW support for color transformation. Support is available with GC355 and GC555.

Syntax:

```
vg_lite_error_t vg_lite_disable_color_transform (
);
```

Parameters: None

vg_lite_enable_color_transform

Description:
This function is used to enable color transformation. By default, color transform is turned off. *(from Sept 2022, only for GC355 and GC555 hardware)*

Syntax:

```
vg_lite_error_t vg_lite_enable_color_transform (
);
```

Parameters: None

vg_lite_set_color_transform

Description:
This function is used to set pixel scale and bias values for color transformation for each pixel channel. *(from August 2022, only for GC355 and GC555 hardware)*

Syntax:

```
vg_lite_error_t vg_lite_set_color_transform (
    vg_lite_color_transform_t     *values
);
```

Parameters:

***values**	Pointer to the color transformation values to set. See enum vg_lite_color_transform_t.

vg_lite_enable_masklayer

Description:
This function controls the availability of mask functionality. Mask is turned off by default. *(from August -Sept 2022, requires GC555 hardware)*

Applications can use VGLite API vg_lite_query_feature (gcFEATURE_BIT_VG_MASK) to determine HW support for mask. The blit and draw mask functions below require GC555 hardware support. These functions were introduced in August 2022 and syntax or name further refined in September 2022.

Syntax:

```
vg_lite_error_t vg_lite_enable_masklayer (
    void
  );
```

vg_lite_disable_masklayer

Description:
This function controls the availability of mask functionality. Mask is turned off by default. *(from August -Sept 2022, requires GC555 hardware, prior to Sept 2022 name was vg_lite_disable_mask_layer)*

Syntax:

```
vg_lite_error_t vg_lite_disable_masklayer (
    void
);
```

vg_lite_create_masklayer

Description:
This function creates a mask layer with the specified width and height. The mask format defaults to A8 and the default mask value is 255. *(from August 2022-Sept, requires GC555 hardware)*

Syntax:

```
vg_lite_error_t vg_lite_create_masklayer (
    vg_lite_buffer_t              *masklayer,
    vg_lite_uint32_t              width,
    vg_lite_uint32_t              height
);
```

Parameters:

***masklayer**	Points to the address of the buffer of the mask layer to be created.
width	Mask layer width (in pixels).
height	Mask layer height (in pixels).

vg_lite_fill_masklayer

Description:
This function sets the values of a given mask layer within a given rectangular region to a given value. The value must be between 0 and 255. *(from August-Sept 2022, requires GC555 hardware)*

Syntax:

```
vg_lite_error_t vg_lite_fill_masklayer (
    vg_lite_buffer_t              *masklayer,
    vg_lite_rectangle_t           *rect,
    vg_lite_uint8_t               value
);
```

Parameters:

***masklayer**	Points to the address of the buffer of the mask layer to be filled.
***rect**	The rectangle area (x, y, width, height) to be filled with value.
value	The value of the fill area. The value must be between 0 and 255.

vg_lite_blend_masklayer

Description:
This function blends the specified area of the source mask layer with the destination mask layer according to an vg_lite_mask_operation_t enumeration value, to create a blended destination mask layer. *(from August-Sept 2022, requires GC555 hardware)*

Syntax:

```
vg_lite_error_t vg_lite_blend_masklayer (
    vg_lite_buffer_t              *dst_masklayer,
    vg_lite_buffer_t              *src_masklayer,
    vg_lite_mask_operation        operation,
    vg_lite_rectangle_t           *rect,
);
```

Parameters:

***dst_masklayer**	Points to the address of the buffer of the destination mask layer.
***src_masklayer**	Points to the address of the buffer of the source mask layer.
operation	Blending mode to be applied to each image pixel, as defined by enum vg_lite_mask_operation_t.
***rect**	The rectangle area (x, y, width, height) of the blend operation.

vg_lite_set_masklayer

Description:
This function sets the given mask layer to the hardware. *(from August-Sept 2022, requires GC555 hardware)*

Syntax:

```
vg_lite_error_t vg_lite_set_masklayer (
    vg_lite_buffer_t              *masklayer
);
```

Parameters:

***masklayer**	Points to the address of the buffer of the mask layer to be set.

vg_lite_render_masklayer

Description:
This function draws the mask layer according to the specified path, color and matrix information. *(from August-Sept 2022, requires GC555 hardware)*

Syntax:

```
vg_lite_error_t vg_lite_render_masklayer (
    vg_lite_buffer_t              *masklayer,
    vg_lite_mask_operation        operation,
    vg_lite_path_t                *path,
    vg_lite_fill_t                fill_rule,
    vg_lite_color_t               color,
    vg_lite_matrix_t              *matrix
);
```

Parameters:

***masklayer**	Points to the address of the buffer of the destination mask layer.
operation	Blending mode to be applied to each image pixel, as defined by enum vg_lite_mask_operation_t.
***path**	Pointer to the vg_lite_path_t structure containing path data which describes the path to draw. Refer to the section on Vector Path Data Opcodes in this document for opcode detail.
fill_rule	Specifies the vg_lite_fill_t enum value for the fill rule for the path.
color	Specifies the color vg_lite_color_t RGBA value to be applied to each pixel drawn by the path.
***matrix**	Points to a vg_lite_matrix_t structure that defines the 3x3 transformation matrix of the path. If matrix is NULL, an identity matrix is assumed, meaning the source will be copied directly on the target at 0,0 location. which is usually a bad idea since the path can be anything.

vg_lite_destroy_masklayer

Description:
This function is used to free a mask layer. *(from August-Sept 2022, requires GC555 hardware)*

Syntax:

```
vg_lite_error_t vg_lite_destroy_masklayer (
    vg_lite_buffer_t              masklayer
);
```

Parameters:

***masklayer**	Points to the address of the buffer of the mask layer to be destroyed.

vg_lite_set_mirror

Description:
This function is used to control mirror functionality. By default, mirror is turned off and the default output orientation is from top to bottom. *(from August 2022, only for GC555 hardware)*

Application can use VGLite API vg_lite_query_feature (gcFEATURE_BIT_VG_MIRROR) to determine HW support for mirror. Mirror functions require GC555 hardware.

Syntax:

```
vg_lite_error_t vg_lite_set_mirror (
    vg_lite_orientation_t         orientation
);
```

Parameters:

orientation	The orientation mode as defined by enum vg_lite_orientation_t.

Returns:
VG_LITE_SUCCESS or VG_LITE_NOT_SUPPORT if not supported.

vg_lite_source_global_alpha

Description:
This function will set image/source global alpha and return a status error code. *(from June 2021, requires GCNanoUltraV or GC555 hardware)*

Application can use VGLite API vg_lite_query_feature (gcFEATURE_BIT_VG_GLOBAL_ALPHA) to determine HW support for global alpha. The global alpha BLIT related functions require GCNanoUltraV or GC555 hardware.

Syntax:

```
vg_lite_error_t vg_lite_source_global_alpha (
    vg_lite_global_alpha_t        alpha_mode,
    vg_lite_uint8_t               alpha_value
);
```

Parameters:

alpha_mode	Global alpha mode value. See enum vg_lite_global_alpha_t.
alpha_value	The image/source global alpha value to set.

Returns:
VG_LITE_SUCCESS or VG_LITE_NOT_SUPPORT if global alpha is not supported.

vg_lite_dest_global_alpha

Description:
This function will set destination global alpha and return a status error code. *(from June 2021, requires GCNanoUltraV or GC555 hardware)*

Syntax:

```
vg_lite_error_t vg_lite_dest_global_alpha (
    vg_lite_global_alpha_t        alpha_mode,
    vg_lite_uint8_t               alpha_value
);
```

Parameters:

alpha_mode	Global alpha mode value. See enum vg_lite_global_alpha_t.
alpha_value	The destination global alpha value to set.

Returns:
VG_LITE_SUCCESS or VG_LITE_NOT_SUPPORT if global alpha is not supported.

8 Vector Path Control

8.1 Vector Path Enumerations

8.1.1 vg_lite_format_t Enumeration

Values for vg_lite_format_t are defined in the table Common Parameter Types. LINK to Common Parameters table.

If vg_lite_format_t	Path data alignment in array should be:
VG_LITE_S8	8 bit
VG_LITE_S16	2 bytes
VG_LITE_S32	4 bytes

8.1.2 vg_lite_quality_t Enumeration

Specifies the level of hardware assisted anti-aliasing.

Used in structure: vg_lite_path_t.
Used in functions: vg_lite_init_path, vg_lite_init_arc_path.

vg_lite_quality_t String Values	Description
VG_LITE_HIGH	High quality: 16x coverage sample anti-aliasing
VG_LITE_UPPER	Upper quality: 8x coverage sample anti-aliasing. Use vg_lite_query_feature to determine availability of 8x CSAA (feature enum value gcFEATURE_BIT_VG_QUALITY_8X. *(deprecated from June 2020, available with supported hardware from August 2022)*
VG_LITE_MEDIUM	Medium quality: 4x coverage sample anti-aliasing
VG_LITE_LOW	Low quality: no anti-aliasing

8.2 Vector Path Structures

8.2.1 vg_lite_hw_memory Structure

This structure simply records the memory allocation info by kernel.

Used in structure: vg_lite_path_t.

vg_lite_hw_memory_t Members	Type	Description
handle	vg_lite_pointer	GPU memory object handle
memory	vg_lite_pointer	Logical memory address
address	vg_lite_uint32_t	GPU memory address
bytes	vg_lite_uint32_t	Size of memory
property	vg_lite_uint32_t	Bit 0 is used for path upload: 0: Disable path data uploading (always embedded into command buffer). 1: Enable auto path data uploading.

8.2.2 vg_lite_path_t Structure

This structure describes VGLite path data.
Path data is composed of op codes and coordinates. The format for op codes is always VG_LITE_S8. Refer to the section on Vector Path Data Opcodes in this document for opcode detail.

Used in init functions: vg_lite_init_path, vg_lite_init_arc_path, vg_lite_upload_path, vg_lite_clear_path, vg_lite_append_path.
Used in function: vg_lite_render_masklayer.
Used in draw functions: vg_lite_draw, vg_lite_draw_grad, vg_lite_draw_radial_grad, vg_lite_draw_pattern.

vg_lite_path_t Members	Type	Description
bounding_box[4]	vg_lite_float_t	bounding box for path [0] left [1] top [2] right [3] bottom
quality	vg_lite_quality_t	enum for quality hint for the path, anti-aliasing level
format	vg_lite_format_t	enum for coordinate format. The coordinates may have these formats: If vg_lite_format_t / Path data alignment in array should be: VG_LITE_S8 / 8 bit VG_LITE_S16 / 2 bytes VG_LITE_S32 / 4 bytes
uploaded	vg_lite_hw_memory_t	struct with path data that has been uploaded into GPU addressable memory
path_length	vg_lite_uint32_t	number of bytes in the path data
path	vg_lite_pointer	pointer to the physical description of the path
path_changed	vg_lite_int8_t	0: not changed; 1: changed.
pdata_internal	vg_lite_int8_t	0: path data memory is allocated by application; 1: path data memory is allocated by driver.
path_type	vg_lite_path_type_t	The draw path type as specified in enum vg_lite_path_type_t. *(added for stroke control, from March 2022)*
*stroke	vg_lite_stroke_t	As defined by structure vg_lite_stroke_t *(added for stroke control, from March 2022)*
stroke_path	vg_lite_pointer	Pointer to the physical description of the stroke path. *(added for stroke control, from March 2022)*
stroke_size	vg_lite_uint32_t	Number of bytes in the stroke path data. *(added for stroke control, from March 2022)*
stroke_color	vg_lite_color_t	The stroke path fill color. *(from Sept 2022)*
add_end	vg_lite_int8_t	Flag that add end_path in driver *(from March 2023)*

Special Notes for Path Objects:

- Endianness has no impact, as it is aligned against the boundaries.

- Multiple contiguous op codes should be packed by the size of the specified data format. E.g., by 2 bytes for VG_LITE_S16 or by 4 bytes for VG_LITE_S32.
    - For example, since opcodes are 8-bits (1 byte), for 16-bit (2 byte) or 32-bit (4 byte) data types:

```
…
<opcode1_that_needs_data>
<align_to_data_size>
<data_for_opcode1>
<opcode2_that_doesnt_need_data>
<opcode3_that_needs_data>
<align_to_data_size>
<data_for_opcode3>
…
```

- Path data in the array should always be 1-, 2, or 4-byte aligned, depending on the format:
    - For example, for 32-bit (4 byte) data types:

```
…
<opcode1_that_needs_data>
<pad to 4 bytes>
<4 byte data_for_opcode1>
<opcode2_that_doesnt_need_data>
<opcode3_that_needs_data>
<pad to 4 bytes>
<4 byte data_for_opcode3>
…
```

8.3 Vector Path Functions

When using a small tessellation window and depending on a path's size, a path might be uploaded to the hardware multiple times because the hardware scanline convert path with the provided tessellation window size, so VGLite path rendering performance might go down. So it is better to set the tessellation buffer size to the most common path size, for example if you only render 24-pt fonts, you can set the tessellation buffer to be 24x24.

All the RGBA color formats available in the vg_lite_buffer_format_t are supported as the destination buffer for the draw function.

vg_lite_get_path_length

Description:
This function calculates the path command buffer length (in bytes).

The application is responsible for allocating a buffer according to the buffer length calculated with this function. Then the buffer is used by the path as a command buffer. The VGLite driver does not allocate the path command buffer.

Syntax:

```
vg_lite_uint32_t vg_lite_get_path_length (
    vg_lite_uint8_t          *opcode,
    vg_lite_uint32_t         count,
    vg_lite_format_t         format
);
```

Parameters:

***opcode**	Pointer to the opcode array to use to construct the path. *(*opcode from March 2023)*
count	The opcode count.
format	The coordinate data format. All formats available for vg_lite_format_t are valid formats for this function.

vg_lite_append_path

Description:
This function assembles the command buffer for the path. The command buffer is allocated by the application and assigned to the path. This function makes the final GPU command buffer for the path based on the input opcodes (cmd) and coordinates (data). Note that the application is responsible to allocate a buffer large enough for the path. *(from Jan 2022, returns a vg_lite_error_t status code)*

Syntax:

```
vg_lite_error_t vg_lite_append_path (
    vg_lite_path_t              *path
    vg_lite_uint8_t             *opcode,
    vg_lite_pointer             data,
    vg_lite_uint32_t            seg_count
);
```

Parameters:

***path**	Pointer to the vg_lite_path_t structure with the path definition.
***opcode**	Pointer to the opcode array to use to construct the path. *(*opcode from March 2023)*
data	Pointer to the coordinate data array to use to construct the path.
seg_count	The opcode count.

Returns:
Returns VG_LITE_SUCCESS if successful. See vg_lite_error_t enum for other return codes.

vg_lite_init_path

Description:
This function initializes a path definition with specified values. *(From Dec 2019 returns vg_lite_error_t, previous was void.)*

Syntax:

```
vg_lite_error_t vg_lite_init_path (
    vg_lite_path_t              *path,
    vg_lite_format_t            format,
    vg_lite_quality_t           quality,
    vg_lite_uint32_t            length,
    vg_lite_pointer             *data,
    vg_lite_float_t             min_x,
    vg_lite_float_t             min_y,
    vg_lite_float_t             max_x,
    vg_lite_float_t             max_y
);
```

Parameters:

***path**	Pointer to the vg_lite_path_t structure for the path object to be initialized with the member values specified.
format	The coordinate data format. All formats available in the vg_lite_format_t enum are valid formats for this function.
quality	The quality for the path object. All formats available in the vg_lite_quality_t enum are valid formats for this function.
length	The length of the path data (in bytes).
***data**	Pointer to path data.
min_x **min_y** **max_x** **max_y**	Minimum and maximum x and y values specifying the bounding box of the path.

Returns:
Returns VG_LITE_SUCCESS if successful. See vg_lite_error_t enum for other return codes.

vg_lite_init_arc_path

Description:
This function initializes an arc path definition with specified values. *(from February 2021)*

Syntax:

```
vg_lite_error_t vg_lite_init_arc_path (
    vg_lite_path_t              *path,
    vg_lite_format_t            format,
    vg_lite_quality_t           quality,
    vg_lite_uint32_t            length,
    vg_lite_pointer             *data,
    vg_lite_float_t             min_x,
    vg_lite_float_t             min_y,
    vg_lite_float_t             max_x,
    vg_lite_float_t             max_y
);
```

Parameters:

***path**	Pointer to the vg_lite_path_t structure for the path object to be initialized with the member values specified.
format	The coordinate data format. The vg_lite_format_t enum value should be FP32.
quality	The quality for the path object. All formats available in the vg_lite_quality_t enum are valid formats for this function.
length	The length of the path data (in bytes).
***data**	Pointer to path data.
min_x **min_y** **max_x** **max_y**	Minimum and maximum x and y values specifying the bounding box of the path.

Returns:
Returns VG_LITE_SUCCESS if successful. See vg_lite_error_t enum for other return codes.

vg_lite_upload_path

Description:
This function is used to upload a path to GPU memory.

In normal cases, the VGLite driver will copy any path data into a command buffer structure during runtime. This does take some time if there are many paths to be rendered. Also, in an embedded system the path data won't change - so it makes sense to upload the path data into GPU memory in such a form that the GPU can directly access it. This function will signal the driver to allocate a buffer that will contain the path data and the required command buffer header and footer data for the GPU to access the data directly. Call vg_lite_clear_path to free this buffer after the path is used.

Syntax:

```
vg_lite_error_t vg_lite_upload_path (
    vg_lite_path_t              *path
);
```

Parameters:

***path**	Pointer to a vg_lite_path_t structure that contains the path to be uploaded.

Returns:
VG_LITE_OUT_OF_MEMORY if not enough GPU memory is available for buffer allocation.

vg_lite_clear_path

Description:
This function will clear and reset path member values. If the path has been uploaded, it frees the GPU memory allocated when uploading the path. *(From Dec 2019 returns vg_lite_error_t, previous was void.)*

Syntax:

```
Vg_lite_error_t vg_lite_clear_path (
    vg_lite_path_t              *path
);
```

Parameters:

***path**	Pointer to the vg_lite_path_t path definition to be cleared.

Returns:
Returns VG_LITE_SUCCESS if successful. See vg_lite_error_t enum for other return codes.

8.4 Vector Path Opcodes for Plotting Paths

The following opcodes are path drawing commands available for vector path data.

A Path operation is submitted to the GPU as [Opcode | Coordinates]. The Operation code is stored as a VG_LITE_S8 while the Coordinates are specified via vg_lite_format_t.

Table 4. Vector Path Data Opcodes

Opcode	Arguments	Description
0x00	None	END. Finish tessellation. Close any open path.
0x02	(x,y)	MOVE. Move to the given vertex. Close any open path. $start_x = x$ $start_y = y$
0x03	(Δx,Δy)	MOVE_REL. Move to the given relative point. Close any open path. $start_x = start_x + \Delta x$ $start_y = start_y + \Delta y$
0x04	(x,y)	LINE. Draw a line to the given point. $Line(start_x, start_y, x, y)$ $start_x = x$ $start_y = y$
0x05	(Δx,Δy)	LINE_REL. Draw a line to the given relative point. $x = start_x + \Delta x$ $y = start_y + \Delta y$ $Line(start_x, start_y, x, y)$ $start_x = x$ $start_y = y$
0x06	(cx,cy) (x,y)	QUAD. Draw a quadratic curve to the given end point using the specified control point. $Quad(start_x, start_y, cx, cy, x, y)$ $start_x = x$ $start_y = y$
0x07	(Δcx,Δcy) (Δx,Δy)	QUAD_REL. Draw a quadratic curve to the given relative end point using the specified relative control point. $cx = start_x + \Delta cx$ $cy = start_y + \Delta cy$ $x = start_x + \Delta x$ $y = start_y + \Delta y$ $Quad(start_x, start_y, cx, cy, x, y)$ $start_x = x$ $start_y = y$

Opcode	Arguments	Description
0x08	(cx_1,cy_1) (cx_2,cy_2) (x,y)	CUBIC. Draw a cubic curve to the given end point using the specified control points. $Cubic(start_x, start_y, cx_1, cy_1, cx_2, cy_2, x, y)$ $start_x = x$ $start_y = y$
0x09	(Δcx_1,Δcy_1) (Δcx_2,Δcy_2) (Δx,Δy)	CUBIC_REL. Draw a cubic curve to the given relative end point using the specified relative control points. $cx_1 = start_x + \Delta cx_1$ $cy_1 = start_y + \Delta cy_1$ $cx_2 = start_x + \Delta cx_2$ $cy_2 = start_y + \Delta cy_2$ $x = start_x + \Delta x$ $y = start_y + \Delta y$ $Cubic(start_x, start_y, cx_1, cy_1, cx_2, cy_2, x, y)$ $start_x = x$ $start_y = y$

The following Opcodes for arc paths are available *(from February 2021).* Note:CW and CCW for clockwise and counter-clockwise.

Table 5. Vector Path Data Opcodes for Arc Paths

Opcode for Arc Paths	Arguments	Description
0x0A	(rh,rv,rot,x,y)	SCCWARC. Draw a small CCW Arc to the given end point using the specified radius and rotation angle. $\boldsymbol{SCCWARC(rh, rv, rot, x, y)}$ $\boldsymbol{start_x = x}$ $\boldsymbol{start_y = y}$
0x0B	(rh,rv,rot,x,y)	SCCWARC_REL. Draw a small CCW Arc to the given relative end point using the specified radius and rotation angle. $x = start_x + \Delta x$ $y = start_y + \Delta y$ $SCCWARC(rh, rv, rot, x, y)$ $start_x = x$ $start_y = y$
0x0C	(rh,rv,rot,x,y)	SCWARC. Draw a small CW Arc to the given end point using the specified radius and rotation angle. $SCWARC(rh, rv, rot, x, y)$ $start_x = x$ $start_y = y$

Opcode for Arc Paths	Arguments	Description
0x0D	(rh,rv,rot,x,y)	SCWARC_REL. Draw a small CW Arc to the given relative end point using the specified radius and rotation angle. $x = start_x + \Delta x$ $y = start_y + \Delta y$ $SCWARC(rh, rv, rot, x, y)$ $start_x = x$ $start_y = y$
0x0E	(rh,rv,rot,x,y)	LCCWARC. Draw a large CCW Arc to the given end point using the specified radius and rotation angle. $LCCWARC(rh, rv, rot, x, y)$ $start_x = x$ $start_y = y$
0x0F	(rh,rv,rot,x,y)	LCCWARC_REL. Draw a large CCW Arc to the given relative end point using the specified radius and rotation angle. $x = start_x + \Delta x$ $y = start_y + \Delta y$ $LCCWARC(rh, rv, rot, x, y)$ $start_x = x$ $start_y = y$
0x10	(rh,rv,rot,x,y)	LCWARC. Draw a large CW Arc to the given end point using the specified radius and rotation angle. $LCWARC(rh, rv, rot, x, y)$ $start_x = x$ $start_y = y$
0x11	(rh,rv,rot,x,y)	LCWARC_REL. Draw a large CW Arc to the given relative end point using the specified radius and rotation angle. $x = start_x + \Delta x$ $y = start_y + \Delta y$ $LCWARC(rh, rv, rot, x, y)$ $start_x = x$ $start_y = y$

9 Vector Based Draw Operations

This part of the API performs the hardware accelerated draw operations.

9.1 Draw and Gradient Enumerations

9.1.1 vg_lite_blend_t Enumeration

This enumeration is detailed under the Blit section. LINK to vg_lite_blend_t enumeration.

9.1.2 vg_lite_color_t Parameter

The common parameter vg_lite_color_t is described in Section 1.4 Common Parameter Types.
LINK to vg_lite_color_t color parameter description.

9.1.3 vg_lite_fill_t Enumeration

This enumeration is used to specify the fill rule to use. For drawing any path, the hardware supports both non-zero and odd-even fill rules.
To determine whether any point is contained inside an object, imagine drawing a line from that point out to infinity in any direction such that the line does not cross any vertex of the path. For each edge that is crossed by the line, add 1 to the counter if the edge is crossed from left to right, as seen by an observer walking across the line towards infinity, and subtract 1 if the edge crossed from right to left. In this way, each region of the plane will receive an integer value.
The non-zero fill rule says that a point is inside the shape if the resulting sum is not equal to zero. The even/odd rule says that a point is inside the shape if the resulting sum is odd, regardless of sign.

Used in function: vg_lite_render_masklayer.
Used in draw functions: vg_lite_draw, vg_lite_draw_grad, vg_lite_draw_radial_grad, vg_lite_draw_pattern.

vg_lite_fill_t String Values	Description
VG_LITE_FILL_NON_ZERO	Non-zero fill rule. A pixel is drawn if it crosses at least one path pixel.
VG_LITE_FILL_EVEN_ODD	Even-odd fill rule. A pixel is drawn if it crosses an odd number of path pixels.

9.1.4 vg_lite_filter_t Enumeration

Defined under Blit. LINK to vg_lite_filter_t enumeration.

9.1.5 vg_lite_gradient_spreadmode_t Enumeration

Defines the gradient padding mode. Matches OpenVG enum VGColorRampSpreadMode *(from March 2023, replaces vg_lite_radial_gradient_spreadmode,requires GC355 hardware)*

Used in structure: vg_lite_radial_gradient_t.

vg_lite_gradient_spreadmode_t String Values	Description
VG_LITE_GRADIENT_SPREAD_FILL	
VG_LITE_GRADIENT_SPREAD_PAD	
VG_LITE_GRADIENT_SPREAD_REPEAT	
VG_LITE_GRADIENT_SPREAD_REFLECT	

9.1.6 vg_lite_pattern_mode_t Enumeration

Defines how the region outside the image pattern is filled for the path.

Used in function: vg_lite_draw_grad, vg_lite_draw_pattern.

vg_lite_pattern_mode_t String Values	Description
VG_LITE_PATTERN_COLOR	Pixels outside the bounds of the source image should be taken as the color
VG_LITE_PATTERN_PAD	Pixels outside the bounds of the source image should be taken as having the same color as the closest edge pixel. The color of the pattern border is expanded to fill the region outside the pattern.
VG_LITE_PATTERN_REPEAT	Pixels outside the bounds of the source image should be repeated indefinitely in all directions. *(from March 2023)*
VG_LITE_PATTERN_REFLECT	Pixels outside the bounds of the source image should be reflected indefinitely in all directions. *(from March 2023)*

9.1.7 vg_lite_radial_gradient_spreadmode_t Enumeration

(Deprecated March 2023) use vg_lite_gradient_spreadmode_t. Defines the radial gradient padding mode. *(from Nov 2020, requires GC355 hardware)*

Used in structure: vg_lite_radial_gradient_t.

vg_lite_radial_gradient_spreadmode_t String Values	Description
VG_LITE_RADIAL_GRADIENT_SPREAD_FILL = 0	
VG_LITE_RADIAL_GRADIENT_SPREAD_PAD	
VG_LITE_RADIAL_GRADIENT_SPREAD_REPEAT	
VG_LITE_RADIAL_GRADIENT_SPREAD_REFLECT	

9.2 Draw and Gradient Structures

9.2.1 vg_lite_buffer_t Structure

Defined under Pixel Buffer Structures. LINK to vg_lite_buffer_t structure.

9.2.2 vg_lite_color_ramp_t Structure

This structure defines the stops for the radial gradient. The five parameters provide the offset and color for the stop. Each stop is defined by a set of floating point values which specify the offset and the sRGBA color and alpha values. Color channel values are in the form of a non-premultiplied (R, G, B, alpha) quad. All parameters are in the range of [0,1]. The red, green, blue, alpha value of [0, 1] is mapped to an 8-bit pixel value [0, 255]. *(from November 2020, requires GC355 hardware)*

The define for the max number of radial gradient stops is #define MAX_COLOR_RAMP_STOPS 256.

Used in radial gradient structure: vg_lite_radial_gradient_t.

vg_lite_color_ramp_t Members	Type	Description
stop	vg_lite_float_t	Offset value for the color stop
red	vg_lite_float_t	Red color channel value for the color stop
green	vg_lite_float_t	Green color channel value for the color stop
blue	vg_lite_float_t	Blue color channel value for the color stop
alpha	vg_lite_float_t	Alpha color channel value for the color stop

9.2.3 vg_lite_linear_gradient_t Structure

This structure defines the organization of a linear gradient in VGLite data. The linear gradient is applied to filling a path. It will generate a 256x1 image according to the specified settings.

Used in init and draw functions: vg_lite_init_grad, vg_lite_set_grad, vg_lite_update_grad, vg_lite_get_grad_matrix, vg_lite_clear_grad, vg_lite_draw_grad.

vg_lite_linear_gradient_t Constants	**Type**	**Description**
VLC_MAX_GRADIENT_STOPS	vg_lite_int32_t	Constant. Maximum number of gradient colors = 16.
vg_lite_linear_gradient_t Members	**Type**	**Description**
colors[VLC_MAX_GRADIENT_STOPS]	vg_lite_uint32_t	Color array for the gradient
count	vg_lite_uint32_t	Number of colors
stops[VLC_MAX_GRADIENT_STOPS]	vg_lite_uint32_t	Number of color stops, from 0 to 255
matrix	vg_lite_matrix_t	Struct for the matrix to transform the gradient color ramp
image	vg_lite_buffer_t	Image object struct to represent the color ramp

9.2.4 vg_lite_ext_linear_gradient Structure

This structure defines the organization of the extended parameters possible for a linear gradient. *(from April 2022)*

Used in functions: vg_lite_draw_linear_grad.

vg_lite_ext_linear_gradient_t Members	**Type**	**Description**
count	vg_lite_uint32_t	Count of colors, up to 256.
matrix	vg_lite_matrix_t	The matrix to transform the gradient.
image	vg_lite_buffer_t	The image for rendering as gradient pattern.
linear_grad	vg_lite_linear_gradient_parameter_t	Linear gradient parameters. Includes center point, focal point and radius.
ramp_length	vg_lite_uint32_t	Color ramp length for gradient paints provided to the driver
color_ramp[VLC_MAX_COLOR_RAMP_STOPS]	vg_lite_color_ramp_t	Color ramp parameter for gradient paints provided to the driver
converted_length	vg_lite_uint32_t	Converted internal color ramp length.
converted_ramp[VLC_MAX_COLOR_RAMP_STOPS+2]	vg_lite_color_ramp_t	Converted internal color ramp.
pre-multiplied	vg_lite_uint8_t	If this value is set to 1, the color value of color_ramp will be multiplied by the alpha value of color_ramp.
spread_mode	vg_lite_radial_gradient_spreadmode_t	The spread mode that is applied to the pixels out of the image after transformed.

9.2.5 vg_lite_linear_gradient_parameter Structure

This structure defines radial direction for a linear gradient. *(from April 2022)*

Line0 connects point (X0, Y0) to point (X1, Y1) and represents the radial direction of the linear gradient.

Line1 is a line perpendicular to line0 which passes through point (X0, Y0).

Line2 is a line perpendicular to line0 which passes through point (X1, Y1)

The linear gradient paint is applied at the intersection of the path fill area and the plane starting from line 1 and ending at line 2.

Used in structure: vg_lite_ext_linear_gradient.
Used in functions: vg_lite_set_linear_grad.

vg_lite_linear_gradient_parameter_t Members	Type	Description
X0	vg_lite_float_t	X origin of linear gradient radial direction.
Y0	vg_lite_float_t	Y origin of linear gradient radial direction.
X1	vg_lite_float_t	X end point of linear gradient radial direction.
Y1	vg_lite_float_t	Y end point of linear gradient radial direction.

9.2.6 vg_lite_matrix_t Structure

Defined under Matrix Structures. LINK to vg_lite_matrix_t structure.

9.2.7 vg_lite_path_t Structure

Defined under Vector Path Structures. LINK to vg_lite_path_t structure.

9.2.8 vg_lite_radial_gradient_parameter_t Structure

This structure defines the gradient radius and the X and Y coordinates for the center and focal points of the gradient.
(from November 2020, requires GC355 or GC555 hardware)

Used in radial gradient structure: vg_lite_radial_gradient_t.

vg_lite_radial_gradient_parameter_t Members	Type	Description *(member order updated from August 2021)*
cx	vg_lite_float_t	Coordinates x and y of the gradient color center point.  Center point refers to the center of the gradient color.
cy	vg_lite_float_t	
r	vg_lite_float_t	Radius of the gradient. 
fx	vg_lite_float_t	Coordinates x and y of the gradient color focal point  Focal point refers to the center of the gradient color.
fy	vg_lite_float_t	

9.2.9 vg_lite_radial_gradient_t Structure

This structure defines the application of the radial gradient to fill a path. *(from November 2020, requires GC355 or GC555 hardware).*

Used in radial gradient functions: vg_lite_draw_grad, vg_lite_set_radial_grad, vg_lite_update_radial_grad, vg_lite_get_radial_grad, vg_lite_clear_radial_grad

vg_lite_radial_gradient_t Members	Type	Description
count	vg_lite_uint32_t	Count of colors, up to 256
matrix	vg_lite_matrix_t	Structure which specifies the transform matrix for the gradient
image	vg_lite_buffer_t	Structure which specifies the image for rendering as a gradient pattern
radial_grad	vg_lite_radial_gradient_parameter_t	Structure which specifies the location of the gradient's center point (cx, cy), focal point(fx, fy) and radius(r)
ramp_length	vg_lite_uint32_t	Color ramp parameters for gradient paints provided to the driver
color_ramp[VLC_MAX_COLOR_RAMP_STOPS]	vg_lite_color_ramp_t	Structure which specifies the color ramp.
converted_length	vg_lite_uint32_t	Converted internal color ramp
converted_ramp[VLC_MAX_COLOR_RAMP_STOPS+2]	vg_lite_color_ramp_t	Structure which specifies the Internal color ramp.
pre_multiplied	vg_lite_uint32_t	If this value is set to 1, the color value of color_ramp will be multiplied by the alpha value of color_ramp.
spread_mode	vg_lite_radial_gradient_spreadmode_t	Enum which specifies the tiling mode that is applied to the pixels out of the image after transformation.

9.3 Draw Functions

vg_lite_draw

Description:
Performs a hardware accelerated 2D vector draw operation.
The size of the tessellation buffer can be specified, and that size will be aligned to the minimum required alignment of the hardware by the kernel. If you make the tessellation buffer smaller, less memory will be allocated, but a path might be sent down to the hardware multiple times because the hardware will walk the target with the provided tessellation window size, so performance might be lower. It is good practice to set the tessellation buffer size to the most common path size. For example, if all you do is render up to 24-pt fonts, you can set the tessellation buffer to be 24x24.

Notes:

- All the color formats available in the vg_lite_buffer_format_t enum are supported as the destination buffer for the draw function.
- Strokes are not supported by the hardware. They need to be converted to paths before being used in the draw API.

Syntax:

```
vg_lite_error_t vg_lite_draw (
    vg_lite_buffer_t            *target,
    vg_lite_path_t              *path,
    vg_lite_fill_t              fill_rule,
    vg_lite_matrix_t            *matrix,
    vg_lite_blend_t             blend,
    vg_lite_color_t             color
);
```

Parameters:

***target**	Pointer to the vg_lite_buffer_t structure for the destination buffer. All color formats available in the vg_lite_buffer_format_t enum are valid destination formats for the draw function.
***path**	Pointer to the vg_lite_path_t structure containing path data which describes the path to draw. Refer to the section on Vector Path Data Opcodes in this document for opcode detail.
fill_rule	Specifies the vg_lite_fill_t enum value for the fill rule for the path.
***matrix**	Pointer to a vg_lite_matrix_t structure that defines the **affine** transformation matrix of the path. If matrix is NULL, an identity matrix is assumed. **Note:** non-affine transformation is not supported for vg_lite_draw, so a perspective transformation matrix has no effect on path.
blend	Select one of the hardware supported blend modes in the vg_lite_blend_t enum to be applied to each drawn pixel. If no blending is required, set this value to VG_LITE_BLEND_NONE (0).
color	The color applied to each pixel drawn by the path.

vg_lite_draw_grad

Description:
This function is used to fill a path with a gradient according to specified fill rules. The specified path will be transformed according to the selected matrix and filled with the gradient.

Syntax:

```
vg_lite_error_t vg_lite_draw_grad (
    vg_lite_buffer_t            *target,
    vg_lite_path_t              *path,
    vg_lite_fill_t              fill_rule,
    vg_lite_matrix_t            *matrix,
    vg_lite_linear_gradient_t   *grad,
    vg_lite_blend_t             blend
);
```

Parameters:

***target**	Pointer to the vg_lite_buffer_t structure containing data describing the target path.
***path**	Pointer to the vg_lite_path_t structure containing path data which describes the path to draw for the linear gradient. Refer to the section on Vector Path Data Opcodes in this document for opcode detail.
fill_rule	Specifies the vg_lite_fill_t enum value for the fill rule for the path.
***matrix**	Pointer to a vg_lite_matrix_t structure that defines the 3x3 transformation matrix of the path. If matrix is NULL, an identity matrix is assumed which is usually a bad idea since the path can be anything.
***grad**	Pointer to the vg_lite_linear_gradient_t structure which contains the values to be used to fill the path.
blend	Specified the blend mode in the vg_lite_blend_t enum to be applied to each drawn pixel. If no blending is required, set this value to VG_LITE_BLEND_NONE (0).

vg_lite_draw_radial_grad

Description:

This function is used to fill a path with a radial gradient according to specified fill rules. The specified path will be transformed according to the selected matrix and filled with the gradient.

Application can use VGLite API vg_lite_query_feature (gcFEATURE_BIT_VG_RADIAL_GRADIENT) to determine HW support for radial gradient.

Syntax:

```
vg_lite_error_t vg_lite_draw_radial_grad (
    vg_lite_buffer_t            *target,
    vg_lite_path_t              *path,
    vg_lite_fill_t              fill_rule,
    vg_lite_matrix_t            *path_matrix,
    vg_lite_radial_gradient_t   *grad,
    vg_lite_color_t             paint_color,
    vg_lite_blend_t             blend,
    vg_lite_filter_t            filter
);
```

Parameters:

***target**	Pointer to the vg_lite_buffer_t structure containing data describing the target path.
***path**	Pointer to the vg_lite_path_t structure containing path data which describes the path to draw for the linear gradient. Refer to the section on Vector Path Data Opcodes in this document for opcode detail.
fill_rule	Specifies the vg_lite_fill_t enum value for the fill rule for the path.
***path_matrix**	Pointer to a vg_lite_matrix_t structure that defines the 3x3 transformation matrix of the path. If matrix is NULL, an identity matrix is assumed which is usually a bad idea since the path can be anything.
***grad**	Pointer to the vg_lite_radial_gradient_t structure which contains the values to be used to fill the path. Note: grad->image.image_mode does not support VG_LITE_MULTIPLY_IMAGE_MODE.
paint_color	Specifies the paint color vg_lite_color_t RGBA value to be applied by VG_LITE_RADIAL_GRADIENT_SPREAD_FILL, which set by function vg_lite_set_radial_grad. When pixels are out of the image after transformation, this paint_color is applied to them. See also enum vg_lite_radial_gradient_spreadmode_t.
blend	Specifies the blend mode in the vg_lite_blend_t enum to be applied to each drawn pixel. If no blending is required, set this value to VG_LITE_BLEND_NONE (0).
filter	Specified the filter mode vg_lite_filter_t enum value to be applied to each drawn pixel. If no filtering is required, set this value to VG_LITE_BLEND_POINT (0).

vg_lite_draw_pattern

Description:

This function fills a path with an image pattern. The path will be transformed according to the specified matrix and filled with the transformed image pattern.

Syntax:

```
vg_lite_error_t vg_lite_draw_pattern (
    vg_lite_buffer_t            *target,
    vg_lite_path_t              *path,
    vg_lite_fill_t              fill_rule,
    vg_lite_matrix_t            *path_matrix,
    vg_lite_buffer_t            *pattern_image,
    vg_lite_matrix_t            *pattern_matrix,
    vg_lite_blend_t             blend,
    vg_lite_pattern_mode_t      pattern_mode,
    vg_lite_color_t             pattern_color,
    vg_lite_color_t             color,
    vg_lite_filter_t            filter
);
```

Parameters:

***target**	Pointer to the vg_lite_buffer_t structure that defines the path to draw.
***path**	Pointer to the vg_lite_path_t structure containing path data which describes the path to draw. Refer to the section on Vector Path Data Opcodes in this document for opcode detail.
fill_rule	Specifies the vg_lite_fill_t enum value for the fill rule for the path.
***path_matrix**	Pointer to a vg_lite_matrix_t structure that defines the 3x3 transformation matrix of the path. If matrix is NULL, an identity matrix is assumed, which is usually a bad idea since the path can be anything.
***pattern_image**	Pointer to the vg_lite_buffer_t structure that describes the image pattern. Note: pattern_image->image_mode does not support VG_LITE_MULTIPLY_IMAGE_MODE in this API.
***pattern_matrix**	Pointer to a vg_lite_matrix_t structure that defines the 3x3 transformation matrix of the source pixels into the target. If matrix is NULL, an identity matrix is assumed, meaning the source will be copied directly onto the target at 0,0 location.
blend	Specifies one of the vg_lite_blend_t enum values for hardware supported blend modes to be applied to each drawn pixel in the image. If no blending is required, set this value to VG_LITE_BLEND_NONE (0).
pattern_mode	Specifies the vg_lite_pattern_mode_t value which defines how the region outside the image pattern is to be filled.
pattern_color	Specifies a 32bpp ARGB color (vg_lite_color_t) to be applied to the fill outside the image pattern area when the pattern_mode value is VG_LITE_PATTERN_COLOR. *(from Dec 2019, type now vg_lite_color_t, previously was uint32_t)*

color	Specifies a 32bpp ARGB color (vg_lite_color_t) to be applied as a mix color. If non-zero, the mix color value gets multiplied with each source pixel before blending happens. If a mix color is not needed, set the color parameter to 0. *(from May 2023)*
filter	Specifies the filter type. All formats available in the vg_lite_filter_t enum are valid formats for this function. A value of zero (0) indicates VG_LITE_FILTER_POINT.

9.4 Linear Gradient Initialization and Control Functions

This part of the API performs linear gradient operations.
A color gradient (color progression, color ramp) is a smooth transition between a set of colors (color stops) that is done along a line (linear, or axial color gradient) or radially, along concentric circles (radial color gradient). The color transition is done by linear interpolation between two consecutive color stops.

Note: VGLite supports linear color gradients for GCNanoLiteV and GCNanoUltraV. Both linear and radial gradients are supported with GC355 and GC555.

vg_lite_init_grad

Description:
This function initializes the internal buffer for the linear gradient object with default settings for rendering.

Syntax:

```
vg_lite_error_t vg_lite_init_grad (
    vg_lite_linear_gradient_t       *grad,
);
```

Parameters:

***grad**	Pointer to the vg_lite_linear_gradient_t structure which defines the gradient to be initialized. Default values are used.

vg_lite_clear_grad

Description:
This function is used to clear the values of a linear gradient object and free the image buffer's memory.

Syntax:

```
vg_lite_error_t vg_lite_clear_grad (
    vg_lite_linear_gradient_t   *grad,
);
```

Parameters:

***grad**	Pointer to the vg_lite_linear_gradient_t structure which is to be cleared.

vg_lite_set_grad

Description:
This function is used to set values for the members of the vg_lite_linear_gradient_t structure.

Note: **vg_lite_set_grad** API adopts the following rules to set the default gradient colors if the input parameters are incomplete or invalid.

a. If no valid stops have been specified (e.g., due to an empty input array, out-of-range, or out-of-order stops), a stop at 0 with (R, G, B, α) color (0.0, 0.0, 0.0, 1.0) (opaque black) and a stop at 1 with color (1.0, 1.0, 1.0, 1.0) (opaque white) are implicitly defined.
b. If at least one valid stop has been specified, but none has been defined with an offset of 0, an implicit stop is added with an offset of 0 and the same color as the first user-defined stop.
c. If at least one valid stop has been specified, but none has been defined with an offset of 1, an implicit stop is added with an offset of 1 and the same color as the last user-defined stop.

Syntax:

```
vg_lite_error_t vg_lite_set_grad (
    vg_lite_linear_gradient_t   *grad,
    vg_lite_uint32_t            count,
    vg_lite_uint32_t            *colors,
    vg_lite_uint32_t            *stops
);
```

Parameters:

***grad**	Pointer to the vg_lite_linear_gradient_t structure to be set.
count	This is the count of the colors in the linear gradient. The maximum color stop count is defined by VLC_MAX_GRAD which is 16.
***colors**	Specifies the color array for the gradient stops. The color is in ARGB8888 format with alpha in the upper byte.
***stops**	Pointer to the gradient stop offset.

Returns:
Always returns VG_LITE_SUCCESS.

vg_lite_get_grad_matrix

Description:

This function is used to get a pointer to the gradient object's transformation matrix. This allows an application to manipulate the matrix to facilitate correct rendering of the gradient path.

Syntax:

```
vg_lite_error_t vg_lite_get_grad_matrix (
    vg_lite_linear_gradient_t   *grad,
);
```

Parameters:

***grad**	Pointer to the vg_lite_linear_gradient_t structure which contains the matrix to be retrieved.

vg_lite_update_grad

Description:

This function is used to update or generate values for an image object that is going to be rendered. The vg_lite_linear_gradient_t object has an image buffer which is used to render the gradient pattern. The image buffer will be created or updated with the corresponding grad parameters.

Syntax:

```
vg_lite_error_t vg_lite_update_grad (
    vg_lite_linear_gradient_t   *grad,
);
```

Parameters:

***grad**	Pointer to the vg_lite_linear_gradient_t structure which contains the update values to be used for the object to be rendered.

9.5 Linear Gradient Extended Functions

The following functions are available only with IP which includes hardware support for extended linear gradient capabilities, such as GC355 and GC555. These functions are not available with GCNanoLiteV, GCNanoUltraV or GCNanoV.

Applications can use VGLite API vg_lite_query_feature(gcFEATURE_BIT_VG_LINEAR_GRADIENT_EXT) to determine HW support for linear gradient.

vg_lite_set_linear_grad

Description:

This function is used to set the values which define the linear gradient. *(from April 2022)*

Syntax:

```
vg_lite_error_t vg_lite_set_linear_grad (
    vg_lite_ext_linear_gradient_t          *grad,
    vg_lite_uint32_t                       count,
    vg_lite_color_ramp_t                   *color_ramp,
    vg_lite_linear_gradient_parameter_t    grad_param,
    vg_lite_radial_gradient_spreadmode_t   spread_mode,
    vg_lite_uint8_t                        pre_mult
);
```

Parameters:

***grad**	Pointer to the vg_lite_ext_linear_gradient_t structure which is to be set.
count	Count of the colors in the gradient. The maxmum color stop count is defined by MAX_COLOR_RAMP_STOPS, which is currently 256.
***color_ramp**	This is the stop for the linear gradient. The number of parameters is 5, and gives the offset and color of the stop. Each stop is defined by a floating-point offset value and four floating-point values containing the sRGBA color and alpha value associated with each stop, in the form of a non-premultiplied (R, G, B, alpha) quad. And the range of all parameters in it is [0,1].
grad_param	Gradient parameters as specified in structure vg_lite_linear_gradient_parameter_t.
spread_mode	The tiling mode applied to the pixels out of the paint after transformation. Uses the same spread mode enumeration types as radial gradient. See vg_lite_radial_gradient_spreadmode_t enum.
pre_mult	This parameter controls whether color and alpha values are interpolated in premultiplied or non-premultiplied form.

Returns:

Returns VG_LITE_INVALID_ARGUMENTS to indicate the parameters are wrong.

vg_lite_get_linear_grad_matrix

Description:
This function returns a pointer to an extended linear gradient object's matrix. *(from March 2023)*

Syntax:

```
vg_lite_matrix_t* vg_lite_get_linear_grad_matrix (
    vg_lite_ext_linear_gradient_t   *grad,
);
```

Parameters:

***grad**	Pointer to the vg_lite_ext_linear_gradient_t structure

Returns:
Returns a pointer to a vg_lite_matrix_t for the specified extended linear gradient.

vg_lite_draw_linear_grad

Description:

This function is used to fill a path with a linear gradient according to specified fill rules. The specified path will be transformed according to the selected matrix and filled with the transformed linear gradient. *(from April 2022)*

Syntax:

```
vg_lite_error_t vg_lite_draw_linear_grad (
    vg_lite_buffer_t                *target,
    vg_lite_path_t                  *path,
    vg_lite_fill_t                  fill_rule,
    vg_lite_matrix_t                *path_matrix,
    vg_lite_ext_linear_gradient_t   *grad,
    vg_lite_color_t                 paint_color,
    vg_lite_blend_t                 blend,
    vg_lite_filter_t                filter
);
```

Parameters:

***target**	Pointer to the vg_lite_buffer_t structure containing data describing the target path.
***path**	Pointer to the vg_lite_path_t structure containing path data which describes the path to draw for the linear gradient. Refer to the section on Vector Path Data Opcodes in this document for opcode detail.
fill_rule	Specifies the vg_lite_fill_t enum value for the fill rule for the path.
***path_matrix**	Pointer to a vg_lite_matrix_t structure that defines the 3x3 transformation matrix of the path. If matrix is NULL, an identity matrix is assumed which is usually a bad idea since the path can be anything.
***grad**	Pointer to the vg_lite_ext_linear_gradient_t structure which contains the values to be used to fill the path. Note: grad->image.image_mode does not support VG_LITE_MULTIPLY_IMAGE_MODE.
paint_color	Specifies the paint color vg_lite_color_t RGBA value to be applied by VG_LITE_RADIAL_GRADIENT_SPREAD_FILL, which set by function vg_lite_set_linear_grad. When pixels are out of the image after transformation, this paint_color is applied to them. See also enum vg_lite_radial_gradient_spreadmode_t.
blend	Specifies the blend mode in the vg_lite_blend_t enum to be applied to each drawn pixel. If no blending is required, set this value to VG_LITE_BLEND_NONE (0).
filter	Specified the filter mode vg_lite_filter_t enum value to be applied to each drawn pixel. If no filtering is required, set this value to VG_LITE_BLEND_POINT (0).

vg_lite_update_linear_grad

Description:
This function is used to update or generate the corresponding image object to render. *(from April 2022)*

The vg_lite_ext_linear_gradient_t object has an image buffer which is used to render the linear gradient paint. The image buffer will be created/updated according to the specified grad parameters.

Syntax:

```
vg_lite_error_t vg_lite_update_linear_grad (
    vg_lite_ext_linear_gradient_t   *grad,
);
```

Parameters:

***grad**	Pointer to the vg_lite_ext_linear_gradient_t structure which is to be updated or created.

vg_lite_clear_linear_grad

Description:
This function is used to clear the linear gradient object. This will reset the grad members and free the image buffer's memory. *(from April 2022)*

Syntax:

```
vg_lite_error_t vg_lite_clear_linear_grad (
    vg_lite_ext_linear_gradient_t    *grad,
);
```

Parameters:

***grad**	Pointer to the vg_lite_ext_linear_gradient_t structure which is to be cleared.

9.6 Radial Gradient Functions

The following functions are available only with IP which supports radial gradients, such as GC355 and GC555. These functions are not available with GCNanoLiteV, or GCNanoUltraV or GCNanoV. Note: There is no init function required for radial gradients. Buffer initialization is done through the vg_lite_update_radial_grad function. *(from Nov 2020, requires GC355 or GC555 hardware)*

vg_lite_set_radial_grad

Description:
This function is used to set the values for the radial linear gradient definition. *(from November 2020, requires GC355 or GC555 hardware*

Syntax:

```
vg_lite_error_t vg_lite_set_radial_grad (
    vg_lite_radial_gradient_t              *grad,
    vg_lite_uint32_t                       count,
    vg_lite_color_ramp_t                   *color_ramp,
    vg_lite_radial_gradient_parameter_t    grad_param,
    vg_lite_radial_gradient_spreadmode_t   spread_mode,
    vg_lite_uint8_t                        pre_mult
);
```

Parameters:

***grad**	Pointer to the vg_lite_radial_gradient_t structure for the radial gradient which will be set
count	This is the count of the color stops in the gradient. The maximum color stop count is defined by MAX_COLOR_RAMP_STOPS, which is currently 256.
***color_ramp**	Pointer to the vg_lite_color_ramp_t structure which defines the stops for the radial gradient. The five parameters provide the offset and color for the stop. Each stop is defined by a set of floating point values which specify the offset and the sRGBA color and alpha values. Color channel values are in the form of a non-premultiplied (R, G, B, alpha) quad. All parameters are in the range of [0,1]. The red, green, blue, alpha value of [0, 1] is mapped to an 8-bit pixel value [0, 255].
grad_param	The radial gradient parameters are supplied as a vector of 5 floats in the order {cx,cy,fx,fy,r}. Parameters(cx,cy) specify the center point, (fx,fy) the focal point and r the radius. See struct vg_lite_radial_gradient_parameter_t.
spread_mode	The tiling mode that is applied to pixels out of the paint after transformation. See enum vg_lite_radial_gradient_spreadmode_t.
pre_mult	Controls whether color and alpha values are interpolated in premultiplied or non-premultiplied form. If this value is set to 1, the color value of vgColorRamp will be multipled by the alpha value of vgColorRamp.

Returns:
Returns VG_LITE_INVALID_ARGUMENTS to indicate the parameters are wrong.

vg_lite_update_radial_grad

Description:
This function is used to update or generate values for an image object that is going to be rendered. The vg_lite_radial_gradient_t object has an image buffer which is used to render the gradient pattern. The image buffer will be created or updated with the corresponding gradient parameters. *(from November 2020, requires GC355 or GC555 hardware)*

Syntax:

```
vg_lite_error_t vg_lite_update_radial_grad (
    vg_lite_radial_gradient_t   *grad,
);
```

Parameters:

***grad**	Pointer to the vg_lite_radial_gradient_t structure which contains the update values to be used for the object to be rendered.

vg_lite_get_radial_grad_matrix

Description:
This function is used to get a pointer to the radial gradient object's transformation matrix. This allows an application to manipulate the matrix to facilitate correct rendering of the gradient path. *(from Nov 2020, requires GC355 or GC555 hardware)*

Syntax:

```
vg_lite_error_t vg_lite_get_radial_grad_matrix (
    vg_lite_radial_gradient_t    *grad,
);
```

Parameters:

***grad**	Pointer to the vg_lite_radial_gradient_t structure which contains the matrix to be retrieved.

vg_lite_clear_radial_grad

Description:

This function is used to clear the values of a radial gradient object and free the image buffer's memory. *(from Nov 2020, requires GC355 or GC555 hardware)*

Syntax:

```
vg_lite_error_t vg_lite_clear_radial_grad (
    vg_lite_radial_gradient_t   *grad,
);
```

Parameters:

***grad**	Pointer to the vg_lite_radial_gradient_t structure which is to be cleared.

10 Stroke Operations

This part of the API performs stroke operations. *(from March 2022)*

10.1 Stroke Enumerations

10.1.1 vg_lite_cap_style_t Enumeration

Defines the style of cap at the end of a stroke. *(from March 2022)*

Used in structure: vg_lite_stroke_t.
Used in function: vg_lite_set_stroke.

vg_lite_cap_style_t String Values	Description
VG_LITE_CAP_BUTT	The Butt end cap style terminates each segment with a line perpendicular to the tangent at each endpoint.
VG_LITE_CAP_ROUND	The Round end cap style appends a semicircle with a diameter equal to the line width centered around each endpoint.
VG_LITE_CAP_SQUARE	The Square end cap style appends a rectangle with two sides of length equal to the line width perpendicular to the tangent, and two sides of length equal to half the line width parallel to the tangent, at each endpoint.

10.1.2 vg_lite_path_type_t Enumeration

Defines the type of draw path. *(from March 2022)*

Used in structure: vg_lite_path_t, vg_lite_stroke_t.
Used in function: vg_lite_set_path_type.

vg_lite_path_type_t String Values	Description
VG_LITE_DRAW_FILL_PATH	Draw path is fill.
VG_LITE_DRAW_STROKE_PATH	Draw path is stroke.
VG_LITE_DRAW_FILL_STROKE_PATH	Draw path is both fill and stroke.

10.1.3 vg_lite_join_style_t Enumeration

Defines the type of styles available for line joints. *(from March 2022)*

Used in structure: vg_lite_stroke_t.
Used in function: vg_lite_set_stroke.

vg_lite_join_style_t String Values	Description
VG_LITE_JOIN_MITER	The Miter join style appends a trapezoid with one vertex at the intersection point of the two original lines, two adjacent vertices at the outer endpoints of the two “fattened” lines and a fourth vertex at the extrapolated intersection point of the outer perimeters of the two “fattened” lines.
VG_LITE_JOIN_ROUND	The Round join style appends a wedge-shaped portion of a circle, centered at the intersection point of the two original lines, having a radius equal to half the line width.
VG_LITE_JOIN_BEVEL	The Bevel join style appends a triangle with two vertices at the outer endpoints of the two "fattened” lines and a third vertex at the intersection point of the two original lines.

10.2 Stroke Structures

10.2.1 vg_lite_path_t Structure

Defined under Vector Path Structures. LINK to vg_lite_path_t structure.
(additional members added for stroke from March 2022)

10.2.2 vg_lite_path_point_t Structure

The structure vg_lite_path_point_ptr points to a vg_lite_path_point structure which provides path detail. *(from March 2022)*

Used (vg_lite_path_point_ptr) in structures: vg_lite_path_point_t, vg_lite_stroke_conversion. vg_lite_sub_path_t.

vg_lite_path_point_t Members	Type	Description
x	vg_lite_float_t	X coordinate
y	vg_lite_float_t	Y coordinate
flatten_flag	vg_lite_uint8_t	Flatten flag for flattened path
curve_type	vg_lite_uint8_t	Curve type for the stroke path
tangentX	vg_lite_float_t	X tangent (Note: #define centerX tangent)
tangentY	vg_lite_float_t	Y tangent (Note: #define centerX tangent)
length	vg_lite_float_t	Line length
prev	vg_lite_path_point_ptr	Pointer to the previous point node

10.2.3 vg_lite_stroke_t Structure

The structure provides stroke parameters and pointers to temp storage for a stroke sub path. Refer to function vg_lite_set_stroke parameter descriptions for additional description for some members. *(from March 2022)*

Used in structure: vg_lite_path_t.

vg_lite_stroke_t Members	Type	Description
cap_style	vg_lite_cap_style_t	Stroke cap style
join_style	vg_lite_join_style_t	Stroke joint style
line_width	vg_lite_float_t	Stroke line width
miter_limit	vg_lite_float_t	Stroke miter limit
*dash_pattern	vg_lite_float_t	Pointer to stroke dash pattern
pattern_count	vg_lite_uint32_t	Number of dash pattern repetitions
dash_phase	vg_lite_float_t	Stroke dash phrase
dash_length	vg_lite_float_t	Stroke dash initial length
dash_index	vg_lite_uint32_t	Stroke dash initial index
half_width	vg_lite_float_t	Half line width
pattern_length	vg_lite_float_t	Total length of stroke dash patterns.
miter_square	vg_lite_float_t	For fast checking
path_points	vg_lite_path_point_ptr	Temp storage for stroke sub path
path_end	vg_lite_path_point_ptr	Temp storage for stroke sub path
point_count	unint32_t	Temp storage for stroke sub path
left_point	vg_lite_path_point_ptr	Temp storage for stroke sub path
right_pont	vg_lite_path_point_ptr	Temp storage for stroke sub path
stroke_points	vg_lite_path_point_ptr	Temp storage for stroke sub path
stroke_end	vg_lite_path_point_ptr	Temp storage for stroke sub path
stroke_count	vg_lite_uint32_t	Temp storage for stroke sub path
stroke_paths	vg_lite_sub_path_ptr	
last_stroke	vg_lite_sub_path_ptr	
need_swing	vg_lite_uint8_t	
swing_handling	vg_lite_uint32_t	
swing_ccw	vg_lite_uint8_t	
swing_deltax	vg_lite_float_t	
swing_deltay	vg_lite_float_t	
swing_start	vg_lite_path_point_ptr	
swing_stroke	vg_lite_path_point_ptr	
swing_length	vg_lite_float_t	
swing_centlen	vg_lite_float_t	

vg_lite_stroke_t Members	Type	Description
swing_count	vg_lite_uint32_t	
stroke_length	vg_lite_float_t	
stroke_size	vg_lite_uint32_t	
fattened	vg_lite_uint8_t	the stroke line is fat line.
closed	vg_lite_uint8_t	

10.2.4 vg_lite_sub_path_t Structure

The structure vg_lite_sub_path_ptr points to a vg_lite_sub_path structure which provides sub path detail and a pointer to the next sub path. *(from March 2022)*

Used in structure: vg_lite_stroke_conversion.

vg_lite_path_point_t Members	Type	Description
next	vg_lite_sub_path_ptr	Pointer to the next sub path
point_count	vg_lite_uint32_t	Number of points in the sub path
point_list	vg_lite_path_point_ptr	Pointer to the point list.
end_point	vg_lite_path_point_ptr	Pointer to the last point.
closed	vg_lite_uint8_t	Indicates whether or not the path is closed.
length	vg_lite_float_t	Length of the sub path.

10.3 Stroke Functions

All return vg_lite_error_t status.

vg_lite_set_path_type

Description:
This function sets the path type. *(from March 2022*

Syntax:

```
vg_lite_error_t vg_lite_set_path_type (
    vg_lite_path_t              *path,
    vg_lite_path_type_t         path_type
);
```

Parameters:

***path**	Pointer to the vg_lite_path_t structure that describes the path.
path_type	Pointer to a vg_lite_path_type_t structure that describes the path type.

vg_lite_set_stroke

Description:
This function uses input parameters to set stroke attributes. *(from March 2022*

Syntax:

```
vg_lite_error_t vg_lite_set_stroke (
    vg_lite_path_t              *path,
    vg_lite_cap_style_t         cap_style,
    vg_lite_join_style_t        join_style,
    vg_lite_float_t             line_width,
    vg_lite_float_t             miter_limit,
    vg_lite_float_t             *dash_pattern,
    vg_lite_uint32_t            pattern_count,
    vg_lite_float_t             dash_phase,
    vg_lite_color_t             color
);
```

Parameters:

***path**	Pointer to the vg_lite_path_t structure that describes the path.
cap_style	The end cap style defined by the vg_lite_cap_style_t enum.
join_style	The line join style defined by the vg_lite_join_style_t enum.
line_width	The line width of the stroke path. A line width less than or equal to 0 prevents stroking from taking place.
miter_limit	When stroking using the Miter stroke vg_lite_join_style_t, the miter length (i.e., the length between the intersection points of the inner and outer perimeters of the two “fattened” lines) is compared to the product of the user-set miter limit and the line width. If the miter length exceeds this product, the Miter join is not drawn and a Bevel join is substituted. Note: Miter limit values less than 1 are silently clamped to 1.
***dash_pattern**	Pointer to a dash pattern which consists of a sequence of lengths of alternating "on" and "off" dash segments. The first value of the dash array defines the length, in user coordinates, of the first "on" dash segment. The second value defines the length of the following "off" segment. Each subsequent pair of values defines one "on" and one "off" segment. Note: If the dash pattern has an odd number of elements, the final element is ignored.
pattern_count	The count of dash on/off segments.
dash_phase	Defines the starting point in the dash pattern that is associated with the start of the first segment of the path. For example, if the dash pattern is [10 20 30 40] and the dash phase is 35, the path will be stroked with an "on" segment of length 25 (skipping the first "on" segment of length 10, the following "off" segment of length 20, and the first 5 units of the next "on" segment), followed by an "off" segment of length 40. The pattern will then repeat from the beginning, with an “on” segment of length 10, an "off" segment of length 20, an "on" segment of length 30.
color	The stroke color.

vg_lite_update_stroke

Description:
This function uses the path and stroke attributes as specified with function vg_lite_set_stroke to update the stroke path's parameters and generate stroke path data. *(from March 2022*

Syntax:

```
vg_lite_error_t vg_lite_update_stroke (
    vg_lite_path_t              *path,
);
```

Parameters:

***path**	Pointer to the vg_lite_path_t structure that describes the path.

11 Deprecated and Renamed APIs

The following functions are deprecated and are either obsolete or replaced by a more efficient implementation. Their use is discouraged and will produce unpredictable behaviors.

The names of some functions, enums and structures were modified during code refinements in 2022Q3. If the parameters did not change, the deprecated syntax detail is not provided below. Changes to enums and structs are not mentioned here, instead refer to the item itself.

Deprecated or Renamed API	Recommended Replacement API	Source file	Date Deprecated
vg_lite_perspective	n/a	vg_lite.h	August 2022
vg_lite_set_dither	vg_lite_enable_dither vg_lite_disable_dither	vg_lite.h	August 2022
vg_lite_set_scissor	vg_lite_enable_scissor vg_lite_disable_scissor	vg_lite.h	August 2022
vg_lite_append_path	vg_lite_path_append	vg_lite.h	Sept 2022
vg_lite_path_calc_length	vg_lite_get_path_length	vg_lite.h	Sept 2022
vg_lite_set_image_global_alpha	vg_lite_set_source_global_alpha	vg_lite.h	Sept 2022
vg_lite_dest_global_alpha	vg_lite_set_dest_global_alpha	vg_lite.h	Sept 2022
vg_lite_mem_avail	vg_lite_get_mem_size	vg_lite.h	Sept 2022
vg_lite_enable_premultiply	vg_lite_set_premulitply	vg_lite.h	Dec 2022
vg_lite_disable_premultiply	vg_lite_set_premulitply	vg_lite.h	Dec 2022
vg_lite_radial_gradient_spreadmode_t enum	vg_lite_gradient_spreadmode_t enum	vg_lite.h	March 2023
API Name Refinement	***(no change to parameters)***		
vg_lite_buffer_upload	vg_lite_upload_buffer_	vg_lite.h	Sept 2022
vg_lite_*mask*	*most vg_lite_*mask_layer*	vg_lite.h	Sept 2022
vg_lite_*_grad	vg_lite_*_gradient *(parameters unchanged)*	vg_lite.h	Sept 2022
vg_lite_*_radial_grad*	vg_lite_*_rad_grad*	vg_lite.h	Sept 2022
vg_lite_buffer_image_mode_t	vg_lite_image_mode_t	vg_lite.h	Sept 2022
vg_lite_transparency_mode_t	vg_lite_buffer_transparency_t	vg_lite.h	Sept 2022
vg_lite_set_update_stroke	vg_lite_update_stroke	vg_lite.h	Sept 2022
vg_lite_set_draw_path_type	vg_lite_set_path_type	vg_lite.h	Sept 2022

11.1 Deprecated vg_lite Syntax

Syntax for deprecated functions is provided below for reference. Note: this list does not include items renamed during code refinement of Sept 2022.

vg_lite_perspective *(deprecated)*

Syntax:

```
void vg_lite_perspective (
     vg_lite_float_t             px,
     vg_lite_float_t             py,
     vg_lite_matrix_t            *matrix
);
```

vg_lite_set_dither *(deprecated)*

Syntax:

```
vg_lite_error_t vg_lite_set_dither (
     int                 enable
);
```

vg_lite_set_scissor *(deprecated)*

Syntax:

```
vg_lite_error_t vg_lite_set_scissor (
    int32_t                 x,
    int32_t                 y,
    int32_t                 width,
    int32_t                 height
);
```

vg_lite_enable_premultiply *(deprecated)*

Syntax:

```
vg_lite_error_t vg_lite_enable_premultiply (
      void
  );
```

vg_lite_disable_premultiply *(deprecated)*

Syntax:

```
vg_lite_error_t vg_lite_disable_premultiply (
      void
  );
```

12 VGLite API Programming Examples

12.1 vg_lite_clear Example

The **Conformance/samples/clear/clear.c** test program demonstrates the basic flow of a VGLite application program and the usage of the vg_lite_clear API. First, the program initializes the VGLite API with:

```
error = vg_lite_init(0, 0);
```

Note that as the tessellation buffer width and height are defined as (0, 0) in this vg_lite_init API call, this program cannot use the path rendering vg_lite_draw APIs. Only clear and blit APIs can be used in this program.

After initialization, the program allocates a 256x256 render buffer with a format of VG_LITE_RGB565.

```
buffer.width  = 256;
buffer.height = 256;
buffer.format = VG_LITE_RGB565;
error = vg_lite_allocate(&buffer);
fb = &buffer;
```

It clears the entire render buffer with blue color first with the vg_lite_clear API.

```
error = vg_lite_clear(fb, NULL, 0xFFFF0000);
```

Then it clears a 64x64 square at the position (64, 64) relative to the top-left origin of the render buffer.

```
vg_lite_rectangle_t rect = { 64, 64, 64, 64 };
error = vg_lite_clear(fb, &rect, 0xFF0000FF);
```

After that, it calls vg_lite_finish to flush the commands to Vivante Vector Graphics hardware and then frees up the allocated render buffer. Finally, it calls vg_lite_close to destroy the VGLite context which is initialized by vg_lite_init.

```
vg_lite_finish();
vg_lite_free(&buffer);
vg_lite_close();
```



Figure 1. Example using vg_lite_clear

12.2 vg_lite_blit Example

The **Conformance/samples/ui/main.c** test program demonstrates the usage of the vg_lite_blit API. It clears a 320x480 render buffer with blue background color first, then it blits six 256x256 icon images to six different positions in the render buffer with a blit matrix for each icon. The blit matrix scales the original icon image to a proper size and translates the scaled icon to the right position in the render buffer. The vg_lite_blit API call is set as VG_LITE_BLEND_SRC_OVER so the icon image pixels with alpha value 0xFF cover the background blue color.

```
vg_lite_blit(fb, &icons[icon_id], &icon_matrix, VG_LITE_BLEND_SRC_OVER, 0,
                 VG_LITE_FILTER_POINT);
```



Figure 2. Example using vg_lite_blit.

12.3 vg_lite_draw Example

The **Conformance/samples/ui/main.c** test program also demonstrates the usage of the vg_lite_draw API with which draws a highlighted rectangle on the top-right icon in above image. The program defines a path (path_data[]) for a 10x10 square bounding box, and it sets up a proper "highlight_matrix" to translate/scale the 10x10 square to cover the top-right icon. The vg_lite_draw API call uses blend parameter VG_LITE_BLEND_SRC_OVER and blend color 0x22444488 (alpha value 0x22) to draw a semi-transparent rectangle on the top-right icon.

```
static char path_data[] = {
    2,  0,  0,          // moveto    0,  0
    4, 10,  0,          // lineto   10,  0
    4, 10, 10,          // lineto   10, 10
    4, 0,  10,          // lineto    0, 10
    0,                  // end
};
static vg_lite_path_t path = {
    {-10, -10, 10, 10}, // bounding box left, top, right, bottom
    VG_LITE_HIGH,       // quality
    VG_LITE_S8,         // -128 to 127 coordinate range
    {0},                // uploaded
    sizeof(path_data),  // path length
    path_data,          // path data
    1                   // path changed
};

error = vg_lite_draw(fb, &path, VG_LITE_FILL_EVEN_ODD, &highlight_matrix,
                VG_LITE_BLEND_SRC_OVER, 0x22444488);
```

After the vg_lite_draw call, vg_lite_clear_path(&path) is called to free and reset the path data.

12.4 vg_lite_draw_gradient Example

The **Conformance/samples/linearGrad/linearGrad.c** test program demonstrates the usage of the vg_lite_draw_grad API. It defines 5 colors (black, red, green, blue, white) in ramps[] and 5 stops in stops[] which are used for gradient color transition. It calls the following to setup the color gradient image.

```
vg_lite_uint32_t ramps[] = {0xff000000, 0xffff0000, 0xff00ff00, 0xff0000ff, 0xffffffff};
vg_lite_uint32_t stops[] = {0, 66, 122, 200, 255};
vg_lite_set_grad(&grad, 5, ramps, stops);
vg_lite_update_grad(&grad);
```

Note that the "colors" parameter (ramps[]) in vg_lite_set_grad API must be in ARGB8888 format with alpha at the higher byte.

It also sets up the gradient transformation matrix "matGrad" with a proper scale factor and 30 degree rotation.

```
matGrad = vg_lite_get_grad_matrix(&grad);
vg_lite_identity(matGrad);
vg_lite_rotate(30.0f, matGrad);
```

Then it calls:

```
vg_lite_draw_grad(fb, &path, VG_LITE_FILL_EVEN_ODD, &matPath, &grad, VG_LITE_BLEND_NONE);
```

with a ploygon path and color gradient image/matrix so that it generates the rendering effect as illustrated in the image below.

After the draw gradient API, it calls:

```
vg_lite_finish();
vg_lite_clear_grad(&grad);
```

to flush the VGLite commands and clean up the gradient image buffer.



Figure 3. Example using vg_lite_draw_gradient

12.5 vg_lite_draw_pattern Example

The **Conformance/samples/patternFill/patternFill.c** test program demonstrates the usage of the vg_lite_draw_pattern API. It defines a vg_lite_path_t path for a convex polygon shape as shown below, and loads an image file "landscape.raw" with which to fill the polygon interior area.

It also defines two matrices, one named “matrix” for the image, another named “matPath” for the “path”. The image matrix rotates the image 33 degrees clockwise based on the image center.

```
vg_lite_identity(&matrix);
vg_lite_translate(fb_width / 2.0f, fb_height / 4.0f, &matrix);
vg_lite_rotate(33.0f, &matrix);
vg_lite_scale(0.4f, 0.4f, &matrix);
vg_lite_translate(fb_width / -2.0f, fb_height / -4.0f, &matrix);

vg_lite_identity(&matPath);
vg_lite_translate(fb_width / 2.0f, fb_height / 4.0f, &matPath);
vg_lite_scale(10, 10, &matPath);
```

Then it calls vg_lite_draw_pattern API two times with different parameters to draw the polygon twice.

```
error = vg_lite_draw_pattern(fb, &path, VG_LITE_FILL_EVEN_ODD, &matPath, &image, &matrix,
                  VG_LITE_BLEND_NONE, VG_LITE_PATTERN_COLOR, 0xffaabbcc,
                  VG_LITE_FILTER_POINT);

error = vg_lite_draw_pattern(fb, &path, VG_LITE_FILL_EVEN_ODD, &matPath, &image, &matrix,
                  VG_LITE_BLEND_NONE, VG_LITE_PATTERN_PAD, 0xffaabbcc,
                  VG_LITE_FILTER_POINT);
```

With the vg_lite_pattern_mode_t setting of VG_LITE_PATTERN_COLOR, the polygon area outside the pattern image of the upper polygon is filled with color 0xffaabbcc. With the vg_lite_pattern_mode_t setting of VG_LITE_PATTERN_PAD, the polygon area outside the pattern image of the lower polygon is filled with the border pixel color of the pattern image.



Figure 4. Example using vg_lite_draw_pattern

12.6 Vector-based Font Rendering Example

The **`Conformance/samples/glyphs2/glyphs2.c`** test program demonstrates vector-based font rendering with the `vg_lite_draw` API, which is capable of drawing quadratic curves and cubic curves based on end point and control point coordinates in the path data. The font path data can be generated by using a third-party font engine that can produce VGLite path data directly, or by using VeriSilicon's VGLite tools to convert other formats of font data, such as SVG, etc., to VGLite path data. Here is an example of path data for the character "~" (ASCII code 126):

```
float ascii_font_126[] =
{
    2,15.984375,20.273438,
    4,16.296875,20.476563,
    6,15.781250,21.351563,14.921875,21.992188,
    6,13.953125,22.710938,13.046875,22.710938,
    6,12.375000,22.710938,10.898438,22.203125,
    6,9.421875,21.695313,8.656250,21.695313,
    6,7.937500,21.695313,7.375000,22.117188,
    6,7.015625,22.382813,6.421875,23.117188,
    4,6.109375,22.914063,
    6,7.593750,20.664063,9.453125,20.664063,
    6,10.156250,20.664063,11.492188,21.140625,
    6,12.828125,21.617188,13.531250,21.617188,
    6,14.921875,21.617188,15.984375,20.273438,
    0
};
```

The first integer in each line is the path opcode, followed by the coordinates for each opcode. As listed in Section 8.4, opcode (2, x, y) moves the current position to (x, y); opcode (4, x, y) draws a line from the current position to (x, y); opcode (6, cx, cy, x, y) draws a quadratic curve from the current position to the given end point (x, y) using the specified control point (cx, cy).

The program calls:

```
error = vg_lite_init(256, 256);
```

to initialize VGLite with a 256x256 path tessellation buffer, then allocates a 320x320 render buffer with the format VG_LITE_RGBA8888. The size of the tessellation buffer is big enough to cover the font character bounding box.

The program renders the path for each character in the string "Hello,\nVerisilicon!" in a loop with calls to:

```
/* Draw the path using the matrix.*/
error = vg_lite_draw(fb, &path, VG_LITE_FILL_EVEN_ODD, &matrix, VG_LITE_BLEND_NONE,
                     0xFF0000FF);
```

The character's vector path is rendered without blending (VG_LITE_BLEND_NONE). The path interior is filled with the color red (0xFF0000FF).

Figure 5. Example using Vector Based Font Rendering

To demonstrate the smooth curve of vector-based path rendering with any scale factor, the program renders a single character “H” with a scaled size of 8X using following API calls.

```
vg_lite_identity(&matrix);
vg_lite_translate(startX, startY, &matrix);
vg_lite_scale(8.0, 8.0, &matrix);
error = vg_lite_draw(fb, &path, VG_LITE_FILL_EVEN_ODD, &matrix, VG_LITE_BLEND_NONE,
                     0xFF0000FF);
```

The following image example shows the resulting vector path rendering of character “H”.

Figure 6. Example with Vector Based Font Rendering Upscaled 8X.

Document Revision History

This section describes top level differences between document revisions:

Document Revision	Date	Compatible SW Release	Notes
2.06	2023-06-29	VGLite from June 2023 *(690729)*	Section 9.2.5: update vg_lite_linear_gradient_parameter structure text to indicate perpendicular instead of parallel lines.
2.05	2023-05-22	VGLite from May 2023 *(677579)*	Section 5.4.8 and 5.5.1: Add enum vg_lite_paint_type. Section 9.5: Add color parameter to vg_lite_draw pattern.
2.04	2023-04-13	VGLite from March 2023 *(640414)*	Section 9.5: Correct typo in function name vg_lite_get_linear_grad_matrix and parameter description.
2.03	2023-03-17	VGLite from March 2023 *(640414)*	Section 1.1: Refine text in second paragraph. Section 7.1.1: Add more blend modes, correct formula for SUBTRACT. Sections 7.4, 7.5, 7.6, 9.5, 9.6: Heading text refined. Section 8.2.2: add description for member add_end. Various: remove numerical enum values. Miscellaneous refinements.
2.02	2023-03-15	VGLite from March 2023 *(639839)*	Various: inline history removed. Section 1.1: Add note re V4 driver. Section 1.4: revised. Section 3.3.1: feature enum values added. Section 5.1: paragraph 1 revised. Section 5.4.1: column added for alignment notes. Section 5.4.1.1: revised Section 5.4.3: add enum vg_lite_map_flag. Section 5.4: add enums compress_mode, index_endian Section 5.5: add struct vg_lite_fc_buffer_t Section 5.5.1: add members to structure, update transparency_mode member name. Section 5.6: add function vg_lite_flush_mapped_buffer; add parameters to function vg_lite_map flag, fd. Section 6.3: return now vg_lite_error_t, was void Section 7.1.3: Add gaussian value for vg_lite_filter_t enum Section 7.3: correct syntax typo for blend in vg_lite_blit_rect. Sections 7.4, 7.5, 7.6: arrangement modified Section 7.6: change global_alpha parameter alpha_value to vg_lite_unit8_t, was 32. Section 8.2.2: add member add_end Section 8.3: vg_lite_get_path, vg_lite_append_path *cmd now *opcode, *data now data. Section 9.5: add function vg_lite_get_linear_grad_matrix. Miscellaneous refinements. Section 9.1.5: Add 2 values for enum vg_lite_pattern_mode.

2.01	2022-12-09	VGLite from December 2022 *(603862)*	Section 7.4.1: Change parameters for VGLite API vg_lite_error_t vg_lite_set_premultiply (vg_lite_uint8_t ~~src_enable~~ src_premult, vg_lite_uint8_t ~~dst_enable~~ dst_premult~~, vg_lite_uint8_t lerp_enable~~) Section 9.3, 9.4: add note to disable VG_LITE_MULTIPLY_IMAGE_MODE support in the following three APIs. – vg_lite_draw_pattern – vg_lite_draw_linear_gradient – vg_lite_draw_radial_gradient Section 11: deprecate vg_lite_enable_premultiply, vg_lite_disable_premultiply. Some wording refinements. Update document template and related format refinements.
2.00	2022-10-03	VGLite from September 2022 *(560435)*	Update for API version 3.0 to add support for GC555 functionality. Various: add vg_lite prefix to more common parameter types Section 5.6: Add function vg_lite_set_gamma. Section 7.4.1: Add function vg_lite_set_premulitply. Section 7.4.3: Added vg_lite_enable_color_transform, vg_lite_disable_color_transform, vg_lite_set_color_transform. Section 8.2.2, 9.2.4 and 9.2.9: undate variable names for structures. Section 11: List renamed functions.
1.20	2022-08-15	VGLite from August 2022	Section 3.1.1: add enum values gcFEATURE_BIT_VG_MASK, gcFEATURE_BIT_VG_QUALITY_8X, gcFEATURE_BIT_VG_MIRROR. Section 5.6: add vg_lite_enable_dither, vg_lite_disable_dither; deprecate vg_lite_set_dither. Section 7.1.5: add enum vg_lite_mask_operation_t. Section 7.1.6: add enum vg_lite_orientation_t. Section 7.3: revise reference to color_key compatible cores. Section 7.4.2: add vg_lite_scissor_rects; deprecate vg_lite_set_scissor. Section 7.4.3: add vg_lite_enable_mask, vg_lite_create_mask_layer, vg_lite_fill_mask_layer, vg_lite_blend_mask_layer, vg_lite_set_mask_layer, vg_lite_generate_mask_layer_by_path, vg_lite_destroy_mask_layer. Section 7.4.5: add vg_lite_set_mirror., Section 8.1.2: update description for VG_LITE_UPPER value. Section 11 added. Template updated. Miscellaneous Refinements.
1.19	2022-04-18	VGLite from April 2022	Format refinements. Template changed, no change to text content.

1.19	2022-04-15	VGLite from April 2022	Various: adjustments for GC555. Section 2.2, Table 1: add VG_LITE_FP32 enum value for vg_lite_format_t. Section 3.1: Add enum values gcFFEATURE_BIT_LINEAR_GRADIENT_EXT, gcFEATURE_BIT_VG_COLOR_KEY. Section 6.1: add vg_lite_pixel_matrix_t[20] Section 6.2.2 : add struct vg_lite_pixel_channel_enable_t. Section 6.3: add function vg_lite_set_pixel_matrix_t. Section 7.2: Add struct vg_lite_color_key_t, vg_lite_color_key4_t Section 7.3: Add function vg_lite_set_color_key. Section 7.4: Add vg_lite_disable_scissor, vg_lite_set_scissor. Section 9.2: Add struct vg_lite_linear_gradient_parameter, vg_lite_linear_gradient_ext. Section 9.4: vg_lite_set_linear_grad, vg_lite_update_linear_grad, vg_lite_clear_linear_grad, vg_lite_draw_linear_gradient. Miscellaneous refinements
1.18	2022-04-01	VGLite from March 2022	Section 8.2: Added members to vg_lite_path_t. Section 10: Added for stroke. Section 10.1: Add enums vg_lite_cap_style, vg_lite_draw_path_type, vg_lite_join_style. Section 10.2: Add struct vg_lite_path_point, vg_lite_sub_path, vg_lite_stroke_conversion, vg_lite_path. Section 10.3: Add function vg_lit_set_stroke, vg_lite_update_stroke, vg_lite_set_draw_path_type.
1.17	2022-03-03	VGLite from March 2022	Legal Notices and throughout: update branding and layout to include VeriSilicon. Sections 1.1 and 1.4: update references for newer hardware Section 3.1: Add vg_lite_feature enum values update gcFEATURE_BIT_VG_YUV_OUTPUT, gcFEATURE_BIT_VG_DOUBLE_IMAGE. Section 5.1: Remove last paragraph Section 5.4 Alignment notes expand text, Table 2 Rename table, refine column heading text, for dest remove last sentence of first bullet. Section 7.1: Refine vg_lite_blend_t Section 7.3: Add vg_lite_blit2.
1.16	2022-01-20	VGLite from January 2022	Section 8.3: vg_lite_path_append now returns vg_lite_error_t.
1.15	2021-12-01	VGLite from December 2021	Section 4.1: Add functions vg_lite_set_command_buffer and vg_lite_set_ts_buffer.
1.14	2021-10-25	VGLite from October 2021	Section 3.1: Add vg_lite_feature enum values gcFEATURE_BIT_VG_DITHER Section 5.4: Add 24bit color formats. Section 5.6: Add vg_lite_set_dither.
1.13	2021-10-19	VGLite from August 2021	Section 5.4: Add three values for enum type vg_lite_buffer_format_t: NV12_TILED, ANV12_TILED AYUY2_TILED.
1.12	2021-08-17	VGLite from August 2021	Section 2.2: Add two values for enum type vg_lite_error_t. Section 5.6: Function vg_lite_set_CLUT description modified. Section 9.2: Adjust vg_lite_radial_gradient_parameter_t the member order of structure.

1.11	2021-05-25	VGLite from June 2021	Section 3.1: Add vg_lite_feature enum values gcFEATURE_BIT_VG_GLOBAL_ALPHA and gcFEATURE_BIT_VG_IM_FASTCLEAR Section 7.1: Add enum vg_lite_global_alpha_t. Section 7.3: Add APIs vg_lite_set_image_global_alpha, vg_lite_set_dest_global_alpha
1.10	2021-04-07	VGLite from April 2021	Section 9.2: Add images for members of vg_lite_radial_gradient_parameter_t. Miscellaneous refinements.
1.09	2021-03-10	VGLite from March 2021	Section 7.2: Add structs vg_lite_point, vg_lite_point4_t. Section 7.3: Add API vg_lite_get_transform_matrix.
1.08	2021-03-03	VGLite from February 2021	Section 8.3: Add vg_lite_init_arc_path API. Section 8.4: Add Opcodes for arc paths.
1.07	2021-02-05	VGLite as previous (November 2020)	Legal Notices: Distribution Level changed B to A. Section 1, 1.1 and 1.4 and various: Add GCNanoUltraV
1.06	2020-12-15	VGLite as previous (November 2020)	Section 5.1 and 5.4, Alignment Notes: Refine alignment discussion.
1.04	2020-08-11	VGLite as of pre-release (August 2020) and GCNanoLiteV HW from V1311p	Section 7: – Add note re premulitply support in hardware Section 7.4: section created - Add vg_lite_enable/disable_premulitply - Modify vg_lite_enable/disable_scissor Change parameters for vg_lite_set_scissor function to use width, height instead of right, bottom.
1.03	2020-05-21	VGLite as of pre-release 2.0.17 (June 2020) and GCNanoLiteV HW from V1311p	Correct sw version. Legal Notices: Distribution Level changed A to B. Section 3.3: added vg_lite_mem_avail Section 8.1: deprecate vg_lite_quality_t.VG_LITE_UPPER value
1.02	2020-04-20	VGLite as of pre-release sw (April 2020) and GCNanoLiteV HW from V1311p	Section 7.3: vg_lite_blit and vg_lite_blit_rect blend parameter, note expanded.
1.01	2020-03-27	VGLite as of pre-release sw (March 2020) and GCNanoLiteV HW from V1311p	Section 3.1: Add vg_lite_feature_t enum values for scissor, ARGB2 and border culling. Section 4.1: Add vg_lite_set_command_buffer_size. Section 5.1 and 5.4: add notes re alignment for tiled data. Section 7.3: Expand notes for vg_lite_blit* description and blend parameter; add 3 scissor functions. Add more hyperlinks to enums and structures. Miscellaneous refinements. Distribution Level now A.
1.00	2019-12-24	VGLite as of sw (December 2019) and GCNanoLiteV HW from V1311p	initial version for sw with GCNanoLiteV 1311p