

Single Channel DC Power Supply

PDS-E Series



EmailSupport: service@szmatrix.com



Features

- Set voltage and current in two ways: digital keyboard and knob
- Voltage 1mV and current 1mA resolution,high precision display
- 9 sets of voltage and current storage call functions
- The appearance is fashionable and small, affordable,cost-effective ultra-high
- Intelligent temperature controlled fan
- List sequence output
- Battery charging warning function, setting upper and lower limits for voltage and current
- Lock key function

Applications

- Experimental technique
- Electronic maintenance
- Aging test
- DIY

Optional SENSE ☐ RS-232 ☐

Model		Voltage	Current	Power	Ripple
PDS-2030E		0~20V	0~30A	600W	10mVrms
PDS-3020E		0~30V	0~20A	600W	10mVrms
PDS-6010E		0~60V	0~10A	600W	10mVrms
PDS-1560E		0~15V	0~60A	900W	10mVrms
PDS-3030E		0~30V	0~30A	900W	10mVrms
PDS-6015E		0~60V	0~15A	900W	10mVrms
PDS-8010E		0~80V	0~11A	880W	15mVrms
PDS-15006E		0~150V	0~6A	900W	15mVrms
Rated input voltage		AV220V/110V±10%			
Transformer mode		Switch power supply			
Load regulation rate	Voltage	≤0.1%+20mV			
	Current	≤0.1%+5mA			
Power regulation rate	Voltage	≤0.1%+20mV			
	Current	≤0.1%+5mA			
Setting resolution	Voltage	1mV			
	Current	1mA			
Setting accuracy	Voltage	≤0.1%+10mV			
	Current	≤0.3%+10mA			
Readback resolution	Voltage	1mV			
	Current	1mA			
Readback accuracy	Voltage	≤0.1%+10mV			
	Current	≤0.3%+10mA			
Temperature	Operating	0 to 40°C≤85R.H.			
	Storage	-15 to 70°C≤85 R.H.			
Product size(W*H*D)	mm	214*108*305			
Net weight	kg	4.5			

Link to download the manual: <https://wendy4197.github.io/MATRIX/PDS-E-UserManual.pdf>