A11 Box - Parts to Buy

United Control Box, wiring rev 0.7 (direct wired; no terminal blocks, only the L / N busbars)
Enclosure: bought 800 × 1000 × 250, swing door

Already have: breakers, EMI filter, contactor, VFD, PSUs, drives (with ALM), E-stop (1 NC + block below), ON/OFF, connectors, NPN NO sensors, fan, Schuko, earth bar.

	BOUGHT		
☑	Enclosure 800 W × 1000 H × 250 D mm, steel, swing door hinged on the left, mounting plate included, no removable panels	x1	wall mount
☑	Relay Finder 55.34.9.024.0000 + socket (RXZE2S114M look-alike), 24 V DC (K1: pole 1 latch, 2 spare, 3 empty gap, 4 → KM1 coil; AC15 350 VA ≥ 200 VA coil inrush)	x1	in socket
☑	Fuse holder RT18-32 (or RT14) 1P, DIN rail, for 10 × 38 mm fuse links (F1, F2)	x2	DIN
☑	Fuse link 10 × 38 mm (RO15) gG 2 A: use these for F1 and F2	x2 + spares	-
☑	Fuse link 10 × 38 mm aM 2 A: do NOT use for F1 / F2 (aM = motor short-circuit only, no overload protection)	-	spare / return
☑	230 V busbar 160 × 16 × 42 mm, 12 points, on insulators: XL (switched L) and XN (all N); vertical, right of the right vertical duct	x2	screws to plate
☑	Earth bar, copper 150 × 25 mm on two 17 mm red insulators, 4 points: PE 1 and PE 2, linked by wire 138. Up to 2 conductors per point (owner decision; IEC 60204-1 asks for one protective conductor per point - a 12-point bar removes the deviation)	x2	bottom wall
☑	Slotted wire duct 40 W × 60 H with cover, 2 m	x2	screws to plate
	ENCLOSURE & MOUNTING		
☐	DIN rail TS35 × 7.5, slotted: one 330 mm piece (row A, right of the plate-mounted EMI filter)	0.5 m	screws to plate
☐	DIN rail end stops	x4	DIN
☐	Slotted wire duct 40 W × 60 H with cover, 2 m: the third length (motor lane VM shortened to 455 mm; cut list in A11_Enclosure_Selection.md)	x1	screws to plate
☐	DIN rail earth clamp, M6 stud	x1	DIN
☐	Door earth strap, braided ≥ 6 mm², 2 m, M6 lugs (door stud → earth bar, through the hinge loop)	x1	-
☐	M6 earth stud kit (bolt, 2 nuts, serrated washers): body (wire 139) and plate (wire 141), only where the enclosure has none	x2	body / plate
☐	Cable gland M20, nylon, IP68 (mains + pump cord)	x2	bottom wall
☐	Recommended (IP 54 against router dust): filter fan Rittal SK 3238.124 24 V DC + outlet filter SK 3238.200, cut-outs 124 × 124	x1 + x1	side walls
	EMC (spindle cable W1 and stepper motor cables)		
☐	EMC shield clamp (saddle) for Ø 8–12 mm, screwed to the plate: W1 at the power lane (wire 127)	x1	plate
☐	HDC-HA metal hood + metal housing with EMC cable gland (360° shield): spindle connector X1, both halves	x1 set	bottom wall
☐	EMC cable gland (brass, 360° shield) at the spindle motor terminal box	x1	spindle
☐	Shield clamps for the motor cables at the drives (LiYCY braid to the plate)	x3	plate
	CONTROL PARTS		
☐	RichAuto A11E kit (handheld + board + 50-pin cable) - 24 V DC 3 A	x1	standoffs
☐	Optional: diode module Schneider RXM040W (6–250 V DC) - only if your socket has a module slot and is a genuine RXZE2S114M (C11)	x1	in socket
☐	22 mm LED pilot lamp 24 V DC - yellow / green / red	x1 each	door
☐	NC contact block Schneider ZB2-BE102 (or the clone's 1 NC block) clipped onto the E-stop base: NC2 → A11 X7	x1	door
☐	GX16-5 plug with pins 3-4 bridged: dummy plug when the tool setter is unplugged (over-travel is in the X7 loop)	x1	XT
	WIRE - colours IEC 60204-1 (3D routing in the 800-wide enclosure, 121 conductors, +10 % +15 cm each, rounded up)		
☐	0.5 mm² H05V-K dark blue (+24 V, DC control, signals)	32 m	
☐	0.5 mm² H05V-K blue/white (0 V)	10 m	
☐	Control cable LiYY 3 × 0.5, cores twisted (5V / PULSE / DIR, 1 per axis)	3 m	
☐	Control cable LiYCY 4 × 1.0 shielded (drive → motor connector, 1 per axis; also for the motor side)	4 m	motor lane
☐	Shielded cable 4G1.5, e.g. ÖLFLEX CLASSIC 110 CY (W1: VFD → spindle connector)	2 m	power lane
☐	1.5 mm² H07V-K black (L to the PSUs / outlet, 48 V +/−)	5 m	
☐	1.5 mm² H07V-K light blue (N)	3 m	
☐	1.5 mm² H07V-K red (KM1 coil circuit, 230 V AC control)	2 m	
☐	1.5 mm² silicone, black, heat resistant (braking resistor)	3 m	
☐	1.5 mm² H07V-K green/yellow	6 m	
☐	2.5 mm² H07V-K black (L)	3 m	
☐	2.5 mm² H07V-K light blue (N)	3 m	
☐	2.5 mm² H07V-K dark blue (+24 V PSU → F1 / F2)	2 m	
☐	2.5 mm² H07V-K green/yellow	3 m	
☐	4 mm² H07V-K black (L, supply path behind QF0)	4 m	
☐	4 mm² H07V-K light blue (N, supply path behind QF0)	2 m	
☐	4 mm² H07V-K green/yellow	4 m	
	FINISHING & TOOLS		
☐	Insulated ferrules: 0.5 ×100, 1.0 ×50, 1.5 ×100, 2.5 ×50, 4 ×50	1 box each	
☐	Twin ferrules: 2 × 0.5 ×50, 2 × 1.5 ×10, 2 × 2.5 ×10, 2 × 4 ×10 (EMI filter LOAD L: 105 + 111)	1 box each	
☐	Wire number markers 0-9, for 0.5-4 mm²	1 set	
☐	Spiral wrap 10 mm (door hinge loop)	1 m	
☐	Knock-out punches / step drill: 16.2 (GX16), 20.5 (M20), 22.5 (door devices); nibbler or jigsaw for 2 × 124 × 124	if needed	bottom wall / door
	DECIDE BEFORE ORDERING		

☐	Check that the EMI filter LOAD L terminal takes 105 + 111 as a 2 × 4 mm² twin ferrule (supply path is 4 mm², C14 resolved).	-
☐	48 V drive feeds in 2.5 mm² instead of 1.5 (or fuse each drive)	black 4 m

Lengths: 3D duct routes ±15-20 %, Verification/A11_Wire_Lengths_rev07.csv; regenerate with make_parts_list.py.