

MT514 Pages

Item No.	Item name	Remark
01	Current remaining energy	
02	Current remaining credit	
03	Current remaining days	
04	Cumulative total forward active energy	No decimal
05	Current month consumption energy	
06	Current step tariff value	
07	Current step tariff No.	
08	Maximum current limit	Detect single phase
09	Current month consumption credit	
10	Current step number	
11~19	Current step1~9 value	If no value, display NULL
20	Current step tariff number	
21~30	Current step tariff1~10 value	
31	Current date	
32	Current time	12 hours format A-: Morning P-:Afternoon
33	Current week day	1~7
34	Remain credit alarm limit 1	
35	Remain credit alarm limit 2	
36	Remain credit alarm limit 3	
37	Hoarding threshold	
38	Overdraft threshold not friendly	
39	Active pulse constant	
40	Reactive pulse constant	
41	Serial number of vending system	

42	Customer number high 8 digits	
43	Customer number middle 6 digits	
44	Customer number low 6 digits	
45	Meter number high 4 digits	
46	Meter number high 8 digits	
47	Meter number high 8 digits	
48	Remain days alarm limit	
49	Cycle display interval	Unit: seconds
50	Cycle display items number	
51	Actual power on days current month	
52	Average day consumption of last month	
53	Total purchase credit	
54	Purchase times	
55	Terminal cover open times	Unit: kWh
56~57	Latest terminal cover open date and time	If there is no event, it will display: NULL
58	Power off times	
59~60	Latest power off date and time	If there is no event, it will display: NULL
61~72	Last 1~12 month: active energy of each month	
73~108	Last1~12month: Max Demand, happen date and time	
109	Current reverse active energy	
110~113	Alarm reasons	Details please check the note1
114~116	Trip reasons	Details please check the note2
117	The left time of open cover the relay don't open	Unit: second
118	Power on times	
119~120	Latest power on date and time	
121	Unbalance limit	
122	The left time of buzzer alarm suspended	

123	The time limit of buzzer alarm suspended	
124	Maximum power limit	
125	Actual continuous over MPL seconds	
127	Actual trip times in one cycle when over MPL	
128	Actual left time of trip when over MPL	
129	Low voltage limit value	
131	Phase A voltage	
132	Phase B voltage	
133	Phase C voltage	
134	Phase A current	
135	Phase B current	
136	Phase C current	
137	Current of neutral line	
138	Phase A fundamental wave voltage	
139	Phase B fundamental wave voltage	
140	Phase C fundamental wave voltage	
141	Phase A fundamental wave current	
142	Phase B fundamental wave current	
143	Phase C fundamental wave current	
144	Total active power	
145	Phase A active power	
146	Phase B active power	
147	Phase C active power	
148	Last 1 minute phase A average power	
149	Last 1 minute phase B average power	
150	Last 1 minute phase C average power	
151	Reactive power	
152	Phase A reactive power	
153	Phase B reactive power	

154	Phase C reactive power	
155	Total power factor	
156	Phase A power factor	
157	Phase B power factor	
158	Phase C power factor	
159	Frequency	
160	Phase disorder happen times	
161~162	The latest phase disorder happen date and time	
163	Reverse happen times	
164~165	The latest reverse happen date and time	
166	Phase loss happen times	
167~168	The latest phase loss happen date and time	
169	Over voltage and low voltage happen times	
170~171	The latest over voltage and low voltage happen date and time	
172	Unbalance happen times	
173~174	The latest unbalance happen date and time	
175	When the latest unbalance happen the unbalance limit	
176	When the latest unbalance happen phase A active power	
177	When the latest unbalance happen phase B active power	
178	When the latest unbalance happen phase C active power	
179	The relay trip times because of the remain credit using up	
180~181	The latest relay trip date and time because of the remain credit using up	
182	Reset happen times	
183~184	The latest reset happen date and time	

185	External battery low voltage happen times	
186~187	The latest external battery low voltage happen date and time	
188	Magnetic disturbance happen times	
189~190	The latest magnetic disturbance happen date and time	
191	Over MPL happen times	
192~193	The latest over MPL happen date and time	
194	Meter cover open times	
195~196	The latest meter cover open date and time	
197	Partially missing neutral happen times	
198~199	The last time partially missing neutral happen date and time	
200	Demand period	
201	Demand period number	
202	Buzzer voice last time	Unit:0.01 seconds
203	Buzzer pause voice last time	Unit:0.01 seconds
204	Software test finish time	
205	Software version	
206	Hardware version	
207	Current terminal cover status	
208	Total overdraft credit	
209	Total overdraft energy	
210	Power direction	Details please check note 3
211	Communication address high 2 digits	
212	Communication address middle 8 digits	
213	Communication address low 1 digits	
214	Billing date	
215	Friendly start time	
216	Friendly finish time	

217	Weekend	From left to right: Saturday Friday Thursday Wednesday Tuesday Monday Sunday 0 means weekend, even no energy the relay will not open 1 means work day
218	Prepayment indication	Bit0: 1 means the meter has been open account Bit 1: 1 means the meter has been changed meter(data from change meter card) Bit 2:1 means the meter has been canceled account Bit 3: 1 means the meter has been changed Bit 7: already insert installation card
219	Friendly indication and TOU holiday indication	Bit0:1 means friendly day Bit1:1 means friendly time Bit2:1 means weekend Bit3:1 means TOU holiday
220	Offset cover steps	
221~230	Offset value cover from 0~9	
231	TOU tariff number	
232~239	TOU tariff1~8 value	
240~241	TOU time interval switch date and time	
242~243	TOU tariff switch date and time	
244~245	Step switch date and time	
246~247	Step tariff switch date and time	
248~249	Offset switch date and time	
250~252	Each phase total active energy	

253	Left time when pressing the parameter setting button	
254	Protocol of optical	
255	Protocol of RS485	
256	Average power factor	
257	relay control status	Disconnect: force relay disconnect Connect: force relay connect NULL: no force control
258	Force relay control status left time	
259	Over voltage limit	
260	Standby steps number	
261~269	Standby step1~9 value	
270	Standby step tariff number	
271~280	Standby step tariff 1~10 value	
281~290	Standby offset value	
291	Standby TOU number	
292~299	Standby TOU tariff1~8 value	
300~307	Meter mode word 0~7	The details please check note 4.
308	Friendly day number	
309	Next friendly date	YY MM DD, if no display NULL
310~339	Friendly day	
340	Actual power on days last month	
341~342	Open account card insetting date and time	
343	Open account credit	
344~352	Last 3 times purchase record	
353~355	Mend card last charge data and time value	
356~357	Cancel account card insetting date and time	
358	Remain credit before insetting cancel account card	
359~360	Change meter card inserting date and time	

361	Remain credit of change meter card	
362~363	Inset card to remove open cover trip date and time	
364	Inset card to remove open cover trip operator No.	
365~366	Last 1 time remote charge date and time	
367	Last 1 time remote charge credit	
368	Maintenance card insert times	
369-370	Last 1 time maintenance card inset date and time	
372	Friendly time overdraft limit	
373	Load profile record interval	
374	Special radio fees	The default one is .002
375	Special radio energy limit	The default one is 45kWh
376	Special tariff 1	The default one is 0.006EGP
377	Special tariff energy 1	The default one is 10kWh
378	Special tariff 2	The default one is 0.003EGP
379	Special tariff energy 2	The default one is 10kWh
380	No consumption for one month the deduct credit	The default one is 3EGP
381	Current month deduction of special radio fees	
382	Current month deduction of special tariff 1	
383	Current month deduction of special tariff 2	
384	Total deduction of special radio fees	
385	Total deduction of special tariff 1	
386	Total deduction of special tariff 2	
387	Total No consumption for one month the deduct credit	
388	Prepayment mode consumption energy	
389	Postpaid mode consumption energy	
390	Prepayment and postpaid indication	Prepayment: PrEPAY ; Credit: POST PAY
391	Current step tariff table No.	

392	Standby step tariff table No.	
393~395	Reverse energy of phase A/B/C	
396	Reactive energy of quadrant 1	
397	Reactive energy of quadrant 2	
398	Reactive energy of quadrant 3	
399	Reactive energy of quadrant 4	
400	The time of no action switch off LCD	
401	Actual max power limit switch times every day	
402~465	Max power limit switch list(current)	Format: Hour time, current value
466	Billing times	
467~478	Last 1~12 month total active energy	Less than 9999999.9kWh
479~490	Last 1~12 month active energy of each month	
491-502	Last 1~12 month total active energy	More than 9999999.9kWh
503~504	Active power demand starting date and time	
509~510	Current demand starting date and time	
511~513	Current month the maximum power demand and happen date and time	
535~537	Current month the Max current demand and happen date and time	
538	Total maximum demand kW	
539	Total maximum demand A	
540	Relay error happen times	
541-542	The latest relay error happen date and time	
543	Relay error kWh	
544	Consumption energy when missing neutral	
545	Standby offset value actual used number	
550	Current TOU tariff value	
551	Current TOU holiday total number	
552	Current TOU week table No.	
553	Current TOU daily table No.	

554	Current TOU tariff No.	
555	Current TOU time interval number	
556~569	Current TOU daily table display	
570	Current TOU week table	
571	Current TOU season number	
572-585	Details of season table	
591-598	Consumption energy of each tariff	
601-612	Last 1~12 each month power factor	
599	Q1+Q2	
600	Q3+Q4	
613	Q1+13	
614	Q2+Q4	
615	Q1+Q2+Q3+Q4	
616-618	Phase angle of A/B/C	
619	Angle between phase A voltage and phase B voltage	
620	Angle between phase A voltage and phase C voltage	
621	One phase with current without voltage happen times	
622~623	One phase with current without voltage happen date and time	
624	Calculate neutral current	
625	Totally missing neutral times	
626-627	The last time totally missing neutral happen date and time	
628-630	When change meter the old meter number	
631	Total energy when latest open terminal cover happen	
632	Total consumption when latest power off happen	
633	Total consumption when latest power on happen	

634	Total consumption when latest open top cover happen	
635	Total consumption when latest strong magnetic alarm happen(reserve)	
636	Total consumption when latest battery alarm happen	
637	Total consumption when latest relay error happen	
638	Total consumption when latest reverse happen	
639	Total consumption when latest phases disorder happen	
640	Total consumption when latest loss phase happen	
641	Total consumption when latest total missing neutral happen	
642	Total consumption when latest partial missing neutral happen	
643	Total consumption when latest missing voltage happen	
645	Consumption during Wrong phase sequence	
646	Total consumption during one phase with current without voltage	
647	Total consumption during phase loss	
648	Total consumption money during relay error	
649	This month reactive energy	
650~661	Last 1~12 month reactive energy	
662	Reactive rollover number	
663	Billing offset numbers	
664~673	Current billing offset table	
674	Overdraft energy	
675	Overdraft credit	
676	Average power factor one year	
677	Monthly consumption limit 1	
678	Monthly consumption limit 2	

679	Monthly special fee	
680	Currently monthly overdraft limit	
681	Monthly remain credit after deduct special fee	
682	Monthly overdraft active limit	
683	Buzzer keep silent start time	
684	Buzzer keep silent end time	

Meter Errors

Error Code	Description
01	Data cannot be read
02~30	Data frame verification error
31~35	32K read card data frame verification error
36	32kB card index error
37	32kB card password protect area CRC check error
38	32kB card set area CRC check error
39	32KB card password check error
40	Card type error
41	The meter type data is not 3 phase in the card
42	Cannot support prepay fee
43	Vending system serial number error
44	Purchase credit too more over 999999.99
45	Customer No error
46	Meter No error (this card already turn back other customers information)
47	Meter No error (when need judge the meter number in the card or the meter number in the charge card or mend card is not right)

48	Preset energy of each phase over 10000000kWh
49	Credit is more than 999999.99
50	Initialization card return data error
51~55	Pull out card too early before the meter finishing reading
57	Pull out card too early, when insetting 32K read card
58	Pull out card too early, when copy the data from meter to card
59	Pull out card too early, when copy the data from card to meter
60~63	CPU Card approved error
64	32kB card user No error
70	The lead seal button is not be pressed
71	Status error, the meter cannot accept purchase card before open account
72	The meter is already cancel account
73	Relay check of last time is not finish
74	Address back to card over the Max address(check and reading card)
75	The meter has been open account cannot accept setting card
76	Reserved
77	Reserved
78	Data back to card is bad position(the first 64 byte of CPU Card)
79	Data back to card is bad position(over 0x3D0)
80	The value in the card add the remain credit in the meter is more than hoarding threshold or more than 999999.99
81	Purchase times error: times in the card is more than times in the meter
82	Purchase times error: times in the card is less than times in the meter
83	Terminal cover is not covered well when removing open cover alarm
84	Meter cover is not covered well when removing open cover alarm

85	Meter cover and terminal cover are not covered well when removing open cover alarm
86	The lead seal button is not pressed when copy the data from meter to card
87	The lead seal button is not pressed when copy the data from card to meter
88	Pull out card too early when copy data from meter to card and the meter number is different
89	Pull out card too early when copy data from card to meter and the meter number is different.
90	Still over MPL when removing over MPL alarm
91	Over limit time
92	Not 32KB change card(old meter is till good meter)
93	Event still exist
94	Not 32KB change card(old meter is damaged meter)
95	Not press the program button when inset change card
96	The firmware of old meter is too old
97	The change meter card already used
98	Pull out too early when inset change meter card