US 20240219581A1

(19) **United States**

(12) **Patent Application Publication** (10) **Pub. No.: US 2024/0219581 A1**

Clare et al. (43) **Pub. Date: Jul. 4, 2024**

(54) **MULTIPATH MITIGATION FOR GNSS LOCATION DETERMINATION USING DUAL ANTENNAS**

(71) Applicant: **Trimble Inc.**, Westminster, CO (US)

(72) Inventors: **Adam Clare**, Westminster, CO (US); **Shawn Weisenburger**, Westminster, CO (US); **Greg Wallace**, San Francisco, CA (US)

(73) Assignee: **Trimble Inc.**, Westminster, CO (US)

(21) Appl. No.: **18/091,675**

(22) Filed: **Dec. 30, 2022**

Publication Classification

(51) **Int. Cl.**


G01S 19/43	(2006.01)
G01S 19/22	(2006.01)
G01S 19/29	(2006.01)

(52) **U.S. Cl.**

CPC ***G01S 19/43*** (2013.01); ***G01S 19/22*** (2013.01); ***G01S 19/29*** (2013.01)

(57) **ABSTRACT**

A device for determining coordinates of a location can include two GNSS receiver antennas positioned in fixed relation to each other and separated by a short baseline. Signals received from the two receiver antennas can be processed to estimate a degree to a multipath effect may be impairing reliability of observables extracted from the received signals. Where both antennas observe signals at the same carrier frequency from the same satellite, each antenna can determine a carrier phase, and a single-difference carrier phase (SDCP) can be computed and used to estimate multipath effects. Where both antennas observe signals at two (or more) carrier frequencies from the same satellite, a "geometry-free" SDCP can be computed and used to estimate multipath effects. Observations of different satellites can be weighted based on the estimated multipath effects.






FIG. 1




FIG. 2A




FIG. 2B



300
208a
208b
312a
RECEIVER MODULE
RECEIVER MODULE
312b
INERTIAL MEASUREMENT UNIT
SIGNAL PROCESSING ENGINE
COMMUNICATION INTERFACE
322
320
324
USER INTERFACE
326

FIG. 3



400
402
Receive signals from satellites at antenna 1
404
Receive signals from satellites at antenna 2
406
Extract observables for antenna 1, including carrier phase, for each satellite
408
Extract observables for antenna 2, including carrier phase, for each satellite
414
Compute single-difference carrier phase (SDCP)
416
Assign weight to observations based on SDCP
418
Determine location of antenna(s) using observables and weights

FIG. 4



SDCP (meter)
-25.410
-25.420
-25.430
-25.440
-25.450
-25.460
-25.470
-25.480
03:40
03:50
04:00
04:10
04:20
04:30
04:40
time
502
510
512

FIG. 5



SDCP (meter)
3.340
3.320
3.300
3.280
3.260
3.240
3.220
3.200
3.180
3.160
3.140
3.120
3.100
16:20
16:40
17:00
17:20
17:40
18:00
18:20
18:40
19:00
19:20
time

FIG. 6



700
702
Receive signals from satellites at antenna 1, at multiple frequencies
704
Receive signals from satellites at antenna 2, at multiple frequencies
706
Extract observables for antenna 1, including carrier phase, for each satellite and frequency
708
Extract observables for antenna 2, including carrier phase, for each satellite and frequency
714
Compute SDCP at each frequency
716
Compute geometry-free SDCP for two frequencies
718
Assign weight to observations based on geometry-free SDCP
720
Determine location of antenna(s) using observables and weights

FIG. 7



G01 Geo Free GPS L1 GPS L2
800
Centimetre
Time (hours)
G01 Geo Free GPS L1 GPS L5
810
Centimetre
Time (hours)
G01 Geo Free GPS L2 GPS L5
820
Centimetre
Time (hours)

FIG. 8



Geometry Free Observations
900
G10
G21
G25
G31
G32
0.08
0.06
0.04
0.02
0
-0.02
-0.04
0
50
100
150
200
250
300
350
400
Absolute Value of Geometry Free Observations
910
G10
G21
G25
G31
G32
0.08
0.06
0.04
0.02
0
0
50
100
150
200
250
300
350
400

FIG. 9



Threshold example
1000
G10
G21
G25
G31
G32
Mean
Median
Fixed Threshold
0.07
0.06
0.05
0.04
0.03
0.02
0.01
0
0
50
100
150
200
250
300
350
400
1030
1010
1020

FIG. 10



Sigmoid
1100
Scale Factor to Observation Noise
Geometry Free Value
2
1.9
1.8
1.7
1.6
1.5
1.4
1.3
1.2
1.1
1
0
0.01
0.02
0.03
0.04
0.05
0.06
0.07
0.08
0.09
0.1

FIG. 11



East
1202
1200
1204
North
1212
1210
1214
Up
1222
1220
1224
Horizontal
1234
1232
1230
(cm)
Time (hours)

FIG. 12

MULTIPATH MITIGATION FOR GNSS LOCATION DETERMINATION USING DUAL ANTENNAS

CROSS-REFERENCES TO RELATED APPLICATIONS

[0001] The present disclosure is related to U.S. Patent Application No._____(Attorney Docket No. 089730-061900US-1316442), filed of even date herewith, the disclosure of which is incorporated herein by reference.

TECHNICAL FIELD

[0002] The present disclosure relates generally to location determination using a global navigation satellite system (GNSS) and in particular to multipath mitigation for GNSS location determination using dual receiver antennas.

BACKGROUND

[0003] Global navigation satellite systems (GNSS) include various constellations of satellites orbiting the earth. Examples include the Global Positioning System (GPS) (operated by the United States), GLONASS (operated by Russia), Galileo (operated by the European Space Agency), and BeiDou (operated by China). Each satellite emits signals that include satellite identifiers, ephemeris data (indicative of the location and health of the satellite), and timestamps. A GNSS receiver unit can receive signals from multiple satellites in one or more constellations and use the timestamps to determine the propagation delay time from the satellite to the receiver. Given signals from at least three or four satellites (depending on the particular receiver design), a location (typically expressed as a set of coordinates that can include a latitude, a longitude, and/or an altitude), can be triangulated. Signals from more than a minimum number of satellites can be used to improve accuracy of the location.

[0004] Location determination using GNSS is subject to various sources of error, including variable delays in the ionosphere and/or troposphere, clock synchronization errors, ephemeris errors, and multipath errors (where the signal may not take a direct path to the receiver). Accuracy of location determination using GNSS triangulation techniques is often limited to a few meters under open sky conditions and becomes worse under limited-view conditions.

[0005] Various techniques have been developed to improve accuracy of GNSS location determination. For example, real-time kinematic positioning (RTK) is commonly used in surveying and certain other applications where improved accuracy is desired. RTK uses phase tracking of the GNSS carrier wave in addition to the information content of the signal to enhance location accuracy. RTK generally requires two receivers: a "base" unit located at a fixed position and a "rover" unit, each of which has a GNSS receiver system that is capable of determining the phase of the carrier wave in addition to the information content of the signal. In surveying applications, for example, the base unit is placed in an open area with a clear view of the sky and remains stationary, allowing a location fix to be determined and maintained. The rover unit is moved about the survey site to determine locations of various points of interest. The base unit transmits its observed carrier phase information to the rover unit, and the rover unit can use this additional input in generating its own location estimates. RTK can achieve location accuracy on the order of 1 cm under favorable conditions. Precise point positioning (PPP) is another technique that uses carrier phase in addition to the information content of the signal in determining a location. Unlike RTK, PPP does not require a base unit, but centimeter-level accuracy may require that the receiver remain stationary for a sufficient period of time, which can be on the order of minutes.

[0006] Techniques such as RTK and PPP can substantially improve accuracy of GNSS location measurements. However, multipath errors in particular remain a limiting factor for the precision of GNSS location measurements.

SUMMARY

[0007] Embodiments described herein relate to location-determining devices and other GNSS receiver systems that include two GNSS receiver antennas positioned in fixed relation to each other and separated by a short baseline (which can be any length short enough that atmospheric effects can be treated as being the same for both antennas, for example, lengths up to a few meters). Signals received from the two receiver antennas can be processed using techniques described herein to estimate a degree to a multipath effect may be impairing reliability of observables extracted from the received signals. In some embodiments where both antennas observe signals at the same carrier frequency from the same GNSS satellite, each antenna can determine a carrier phase, and a single-difference carrier phase (SDCP) can be computed, e.g., by subtracting the carrier phase observables from the two antennas. Due to the short baseline, the SDCP is dominated by multipath effects and geometric offset between the antennas. Correcting for the geometric offset (e.g., based on available information about antenna and satellite positions) can provide an estimate of the degree to which the observations are affected by multipath. In some embodiments where both antennas observe signals at two (or more) carrier frequencies from the same GNSS satellite, a "geometry-free" SDCP can be computed, e.g., by subtracting SDCPs determined for different frequencies. The geometry-free SDCP can provide an estimate of the degree to which the observations are affected by multipath. The degree of multipath effect estimated from a given SDCP (including a geometry-free SDCP) can be used to assign a weight to the corresponding observations, with observations having a higher degree of multipath effect being assigned lower weight (or discarded entirely). The weights assigned to different observations can be used when determining location of one (or both) of the antennas using signals from multiple GNSS satellites, thereby providing mitigation of multipath errors.

[0008] Some embodiments relate to methods of determining location of a receiver system having a first antenna and a second antenna mounted on a movable structure in fixed locations relative to each other and defining a baseline. For example, the first antenna and the second antenna can receive global navigation satellite system (GNSS) signals from a plurality of GNSS satellites. For each received GNSS signal, the receiver system can: extract a first set of observables from the GNSS signal as received by the first antenna, the first set of observables including a first carrier phase; extract a second set of observables from the GNSS signal as received by the second antenna, the second set of observables including a second carrier phase; and compute a single difference carrier phase (SDCP) between the first carrier

phase and the second carrier phase. The receiver system can assign a weight for each GNSS satellite based at least in part on the SDCP computed for each received GNSS signal and can determine a location of the receiver system using the first and second sets of observables extracted from the received GNSS signals and the weights.

[0009] In some embodiments, assigning a weight for each GNSS satellite can include: determining an orientation of the first antenna and the second antenna (e.g., using an inertial measurement unit mounted to the receiver system in a fixed position relative to the first and second antennas); determining a geometric offset between the first antenna and the second antenna based at least in part on the orientation of the first antenna and the second antenna; subtracting the geometric offset from the first SDCP to produce a modified SDCP; and using the modified SDCP to estimate a multipath effect, where the weight is determined using the estimated multipath effect. For example, the weight decreases with increasing estimated multipath effect.

[0010] In some embodiments, assigning a weight for each GNSS satellite can include: performing a real-time kinematic (RTK) location determination using the first antenna and the second antenna; determining a residual for each GNSS satellite based on a result of the RTK location determination; and assigning a weight for each GNSS satellite based on the residuals.

[0011] In some embodiments, assigning a weight for each GNSS satellite can include estimating a multipath contribution to the SDCP and determining the weight based on the multipath contribution, for instance by applying a sigmoid function to the multipath contribution.

[0012] Some embodiments relate to methods of determining location of a receiver system having a first antenna and a second antenna mounted on a movable structure in fixed locations relative to each other and defining a baseline. For example, a receiver system can receive global navigation satellite system (GNSS) signals from a plurality of GNSS satellites at a first antenna and a second antenna of the receiver system, where the first antenna and the second antenna are mounted to the receiver system in a fixed relative position and define a baseline, and where the GNSS signals include a plurality of GNSS signals having different frequencies. The receiver system can extract a first set of observables from each GNSS signal received at the first antenna, the first set of observables including a first carrier phase of each received GNSS signal at each of the different frequencies, and can extract a second set of observables from each GNSS signal received at the second antenna, the second set of observables including a second carrier phase of each received GNSS signal at of the different frequencies. For each GNSS satellite and frequency, the receiver system can compute a frequency-specific single difference carrier phase (SDCP) between the first carrier phase and the second carrier phase. The receiver system can also computer, for each GNSS satellite, a geometry-free SDCP based on the frequency-specific SDCPs at two different frequencies. The receiver system can assign respective weights to the observations from each GNSS satellite based at least in part on the geometry-free SDCP and can determine a location of the receiver system using the first and second sets of observables of the received GNSS signals and the weights. For instance, the receiver system can perform a real-time kinematic (RTK) analysis using information extracted from the GNSS signals received at the first antenna and additional information received from a base unit.

[0013] In some embodiments, assigning the weight can include estimating a multipath contribution to the geometry-free SDCP and determining the weight based on the multipath contribution, wherein the weight decreases as the multipath contribution increases. For instance, assigning the weight can include applying a sigmoid function to the multipath contribution. In some embodiments, a weight of zero can be assigned if the multipath contribution exceeds a particular threshold.

[0014] Certain embodiments relate to systems for determining location. For example, the system can include a movable structure (such as a survey pole, a vehicle, or other rigid body that can be moved about to different locations); a first antenna and a second antenna mounted to the movable structure at a fixed baseline distance apart (e.g., less than a few meters, or less than a meter, down to a few centimeters) and configured to receive global navigation satellite system (GNSS) signals from each of a plurality of GNSS satellites; receiver circuitry coupled to the first antenna and the second antenna; and a signal processing engine coupled to the receiver circuitry. The receiver circuitry can be configured to extract a first set of observables from a first GNSS signal from a first one of the GNSS satellites as received by the first antenna and a second set of observables from the first GNSS signal as received by the second antenna, wherein the first set of observables includes a first carrier phase and the second set of observables includes a second carrier phase. The signal processing engine can be configured to: compute a first single difference carrier phase (SDCP) between the second carrier phase and the first carrier phase; assign a weight to the first and second sets of observables based at least in part on the first SDCP; and determine a location of the movable structure using the weight and the first and second sets of observables.

[0015] In some embodiments, the signal processing engine can be configured such that assigning the weight to the first and second sets of observables includes: estimating a multipath contribution to the first SDCP; and determining the weight based on the multipath contribution, wherein the weight decreases as the multipath contribution increases. In some embodiments, a weight of zero can be assigned if the multipath contribution exceeds a particular threshold.

[0016] In some embodiments, the system can also include an inertial measurement unit (IMU) coupled to the signal processing engine and configured to determine an orientation of the first antenna and the second antenna. The signal processing engine can be configured such that assigning the weight includes: determining a geometric offset between the first antenna and the second antenna based at least in part on the orientation of the first antenna and the second antenna; subtracting the geometric offset from the first SDCP to produce a modified SDCP; and using the modified SDCP to estimate a multipath effect, where the weight is determined using the estimated multipath effect.

[0017] In some embodiments, the receiver circuitry can be configured to extract a third set of observables from a second GNSS signal from the first one of the GNSS satellites as received by the first antenna and a fourth set of observables from the second GNSS signal as received by the second antenna, wherein the second GNSS signal has a frequency different from a frequency of the first GNSS signal, wherein the third set of observables includes a third carrier phase and

the fourth set of observables includes a fourth carrier phase. The signal processing engine can be configured to: compute a second single difference carrier phase (SDCP) between the third carrier phase and the fourth carrier phase; compute a geometry-free SDCP from the first SDCP and the second SDCP; and assign a weight to the first, second, third, and fourth sets of observables based at least in part on the geometry-free SDCP; and determine the location of the movable structure using the weight and the first, second, third, and fourth sets of observables. For example, the signal processing engine can be configured such that assigning the weight to the first, second, third, and fourth sets of observables includes: estimating a multipath contribution to the geometry-free SDCP; and determining the weight based on the multipath contribution, wherein the weight decreases as the multipath contribution increases.

[0018] In some embodiments, the signal processing engine can be configured to determine a threshold using respective geometry-free SDCPs computed for a plurality of GNSS satellites and to assign a respective weight to observables from each of the GNSS satellites based on the threshold. The receiver circuitry can be configured such that determining the location of the movable structure is based in part on the respective weights.

[0019] The following detailed description, together with the accompanying drawings, will provide a better understanding of the nature and advantages of the claimed invention.

BRIEF DESCRIPTION OF THE DRAWINGS

[0020] FIG. **1** shows a simplified diagram of a location-determining system according to some embodiments.

[0021] FIGS. **2**A and **2**B show views of a location-measuring device according to some embodiments, with FIG. **2**A showing a simplified side view and FIG. **2**B showing a simplified cross-section view.

[0022] FIG. **3** shows a simplified block diagram of a GNSS receiver system according to some embodiments.

[0023] FIG. **4** shows a flow diagram of a process for determining a location of an antenna according to some embodiments.

[0024] FIG. **5** shows a graph of a single-difference carrier phase (SDCP) computed according to some embodiments for a series of observations of the same satellite across a period of time.

[0025] FIG. **6** shows another graph of SDCP computed according to some embodiments for a series of observations of the same satellite across a period of time.

[0026] FIG. **7** is a flow diagram of a process for determining a location of an antenna according to some embodiments.

[0027] FIG. **8** shows graphs of geometry-free SDCPs obtained from observations of a GNSS satellite at multiple frequencies according to some embodiments.

[0028] FIG. **9** shows graphs of geometry-free SDCP obtained from various satellites using the process of FIG. **7** according to some embodiments.

[0029] FIG. **10** shows a graph of thresholds that can be defined from the geometry-free SDCP observations of FIG. **9** according to some embodiments.

[0030] FIG. **11** shows a graph of a sigmoid function that can be used to assign weights to observations according to some embodiments.

[0031] FIG. **12** shows graphs of errors in locations determined using a conventional process and a process according to some embodiments.

DETAILED DESCRIPTION

[0032] The following description of exemplary embodiments of the invention is presented for the purpose of illustration and description. It is not intended to be exhaustive or to limit the claimed invention to the precise form described, and persons skilled in the art will appreciate that many modifications and variations are possible. The embodiments have been chosen and described in order to best explain the principles of the invention and its practical applications to thereby enable others skilled in the art to best make and use the invention in various embodiments and with various modifications as are suited to the particular use contemplated.

[0033] Embodiments described herein relate to location determination using global navigation satellite system (GNSS) signals. As used herein, GNSS refers generally to any constellation of satellites that broadcast signals receivable by an antenna. A GNSS receiver system, which generally includes an antenna and appropriately-configured receiver and signal processing circuitry, can determine a location of the antenna using signals received by the antenna from multiple satellites. Examples of GNSS include the Global Positioning System (GPS) (operated by the United States), GLONASS (operated by Russia), Galileo (operated by the European Space Agency), and/or BeiDou (operated by China). GNSS satellites may transmit signals at one or more frequencies (or wavelengths). For instance, all GPS satellites currently broadcast at frequencies referred to as "L**1**" (1575.42 MHz, wavelength about 0.19 m) and "L**2**" (1227.60 MHz, wavelength about 0.24 m); some also broadcast at "L**5**" (1176.45 MHZ, wavelength about 0.25 m). A given GNSS receiver system may be configured to detect and process signals from any or all of these or other GNSS satellites and may use conventional or other techniques to extract a location measurement from received satellite signals based on code phase and other data encoded in the signal (e.g., ephemeris data indicating satellite locations); other information such as carrier phase, Doppler shift, and the like may also be exploited. For example, where two GNSS receiver systems capable of determining carrier phase are available, real-time kinematics (RTK) can be used to produce a high-precision location estimate. Other techniques, such as precise point positioning (PPP), can also be used. A location determined using GNSS signals can be expressed in various formats, including coordinates indicating latitude, longitude, and/or altitude.

[0034] Embodiments described herein relate to location-determining devices and other GNSS receiver systems that include two antennas positioned in fixed relation to each other and separated by a short baseline. A "short" baseline can be of any length short enough that atmospheric effects can be treated as being the same for both antennas, for example, lengths up to a few meters. Shorter baselines, e.g., around 10 to 30 cm, may be more convenient for portable units. GNSS signals received from the two antennas can be processed using techniques described herein to estimate a degree to which multipath effects may be impairing reliability of observables extracted from the signals. In some embodiments where both antennas observe signals at the same carrier frequency from the same GNSS satellite, each

antenna can determine a carrier phase, and a single-difference carrier phase (SDCP) can be computed, e.g., by subtracting the carrier phase observables from the two antennas. Due to the short baseline, the SDCP is dominated by multipath and geometric effects. Correcting for the geometric offset (e.g., based on available information about antenna and satellite positions) can provide an estimate of the degree to which the observations are affected by multipath. In some embodiments where both antennas receive signals at two or more carrier frequencies from the same GNSS satellite, a "geometry-free" SDCP can be computed, e.g., by subtracting SDCPs determined for different frequencies. The geometry-free SDCP can provide an estimate of the degree to which the observations are affected by multipath. The degree of multipath effect estimated from a given SDCP (including a geometry-free SDCP) can be used to assign a weight to the corresponding observations, with observations having a higher degree of multipath effect being assigned lower weight (or discarded entirely). The weights assigned to different observations can be used when determining location of one (or both) of the antennas using signals from multiple GNSS satellites, thereby providing mitigation of multipath errors.

[0035] FIG. **1** shows a simplified diagram of a location-determining system **100** according to some embodiments. System **100** includes a base unit **102** and a rover unit **104** that can be used to measure locations in an area **110**. Each of base unit **102** and rover unit **104** can be equipped with one or more antennas to receive GNSS signals from satellites **140**. In the example shown, base unit **102** has GNSS antennas **106***a*, **106***b*, and rover unit **104** has GNSS antennas **108***a*, **108***b*. Base unit **102** can be placed at a convenient location within area **110** and remain in that location for the duration of a survey operation (e.g., minutes, hours, days, depending on the application). The location of base unit **102** can be selected to avoid obstructions such as tree **116**, providing a clear view of the sky. In particular, base unit **102** can have a direct communication path to receive signals from GNSS satellites **140** located in orbit. The particular number of GNSS satellites **140** with which base unit **102** communicates can be at least three, at least four, or a larger number. Those skilled in the art will appreciate that GNSS satellites **140** are generally not in geostationary orbits and may move relative to base unit **102**; base unit **102** may receive signals from different combinations of GNSS satellites **140** at different times. Ideally, base unit **102** is located in a place where it is able to continually receive signals from a sufficient number of GNSS satellites **140** to establish and maintain a high-quality location fix for as long as the survey operation continues. Base unit **102** can remain at a fixed location while rover unit **104** is moved around to different locations within area **110** to obtain location measurements. In some embodiments, base unit **102** and rover unit **104** can support high-precision location determination techniques, including carrier phase detection. Real-time kinematics (RTK) can be used to determine the location of rover unit **104** with high precision, and base unit **102** can communicate with rover unit **104** to implement RTK. Other techniques, such as precise point positioning (PPP), can also be used, and a base unit is not required. In some implementations, base unit **102** may use PPP to determine its own location while rover unit **104** implements RTK using carrier phase data and/or other information provided by base unit **102**. Accordingly, base unit **104** can include a radio-frequency (RF) communication antenna **114**, and rover unit **104** can include a RF communication antenna **112**. Antennas **114** and **112** can support wireless communication (e.g., in the UHF band) between base unit **102** and rover unit **104**.

[0036] As rover unit **104** is moved around within area **110**, the GNSS signal quality may be affected by obstructions such as tree **116**. In particular, rover unit **104** may be susceptible to multipath effects, in which some (or all) of the GNSS signals bounce off an obstruction rather than taking a direct path from a satellite **140** to receiver antennas **108***a*, **108***b* of rover unit **104**. Such effects can introduce error that reduces the accuracy of the location determined from the GNSS signals. As described below, antennas **108***a*, **108***b* in rover unit **104** (and/or antennas **106***a*, **106***b* in base unit **102**) can be used to estimate the degree of multipath effects, and the estimate can be used in mitigation of such effects.

[0037] FIG. **2**A shows a simplified side view of a location-measuring device **200** according to some embodiments. Location-measuring device **200** can be used to implement rover unit **104** or base unit **102** of system **100** of FIG. **1**. In some embodiments, each of rover unit **104** and base unit **102** can be an instance of location-measuring device **200**, with the difference being in operation rather than hardware components. Location measuring device **200** can include a pole **202** and an electronics module **204** mounted at a top end **207** of pole **202**. Bottom end **205** of pole **202** can be placed on the ground to support device **200**, and pole **202** can be long enough to elevate electronics module **204** to a desired height above ground level. If desired, the length of pole **202** can be adjustable. Although not shown in FIG. **2**, pole **202** can include or be attached to tripod legs, spikes, cleats, or other structures to further stabilize pole **202** during location measurements.

[0038] FIG. **2**B shows a simplified cross-section view of electronics module **204**, through line **2**B of FIG. **2**A. Electronics module **204** can have a housing **220**, within which are mounted two GNSS antennas **208***a*, **208***b* having the same configuration. Each of antennas **208***a*, **208***b* can be sized and shaped to receive GNSS signals at one or more frequencies. In some embodiments, antennas **208***a*, **208***b* can also be used to determine a carrier phase of the GNSS signal, e.g., using known techniques. Antennas **208***a*, **208***b* can be oriented in the same direction and separated by a baseline distance (d), which is fixed for a particular electronics module. Distance d can be any distance short enough that atmospheric effects can be treated as being the same for both antennas, for example, distances up to a few meters. In some embodiments, d can be 30 cm or less, which can provide a convenient form factor for devices intended to be hand-carried by a user. In some embodiments, distance d can be 10 cm. A midpoint **210** between antennas **208***a*, **208***b* can be aligned with the top end **207** of pole **202**. In addition to antennas **208***a*, **208***b*, electronics module **204** can also include other components disposed within housing **220**, such as receiver circuitry, signal processing engine(s), an inertial measurement unit, communication circuitry to communicate with a base unit (or rover unit), battery or other power source, and so on. The size and shape of housing **220** can be varied as desired, provided that there is sufficient space to house the relevant components.

[0039] FIG. **3** shows a simplified block diagram of a GNSS receiver system **300**, such as location-measuring device **200** according to some embodiments. In various embodiments, some or all components of GNSS receiver

system **300** can be included in electronics module **204** of FIGS. **2**A and **2**B. As shown in FIG. **3**, GNSS receiver system **300** can include antennas **208***a*, **208***b*; receiver modules **312***a*, **312***b*; a signal processing engine **320**; an inertial measurement unit **322**; a base unit interface component **324**; and a user interface component **326**.

[0040] Antennas **208***a*, **208***b* can be of the same size and configuration and tuned (or tunable) to GNSS signal frequencies. As described above, antennas **208***a*, **208***b* can be mounted in fixed relation to each other and oriented in the same direction, separated by a baseline distance d. Receiver modules **312***a*, **312***b* can be coupled to antennas **208***a*, **208***b* and can include electronic circuitry to amplify received GNSS signals, determine carrier phase, convert signals to baseband, and extract data from the signals. In some embodiments, some or all of the circuitry of receiver modules **312***a*, **312***b* can be shared between the two antennas. In particular, receiver modules **312***a*, **312***b* may share a common clock. If desired, both antennas **208***a*, **208***b* can be operated using a single receiver module. A particular implementation of antennas **208***a*, **208***b* and receiver modules **312***a*, **312***b* is not relevant to understanding the present disclosure; conventional or other implementations can be used.

[0041] Signal processing engine **320** can include logic circuitry (e.g., fixed-function ASIC and/or a programmable microprocessor or microcontroller) configured to perform signal processing operations on data provided by receiver modules **312***a*, **312***b*. For instance, signal processing engine **320** can be configured to determine a location (e.g., latitude, longitude, and altitude) based on the data provided by receiver modules **312***a*, **312***b*. Examples of techniques that can be implemented in signal processing engine **320** are described below.

[0042] Communication interface **324** can include RF communication circuitry, antennas and the like, which can be of conventional or other design. In some embodiments, communication interface **324** can be operated to provide data from a base unit (e.g., base unit **102** of FIG. **1**) to a rover unit (e.g., rover unit **104**) of FIG. **1**. For instance, in embodiments where signal processing engine **320** of rover unit **104** implements RTK, communication interface **324** can be used to obtain carrier phase data and any other relevant data from base unit **102**.

[0043] Inertial measurement unit (IMU) **322** can include a combination of sensors such as accelerometers, gyroscopes, compass, or the like, which can be of conventional or other design. In some embodiments, IMU **322** can be used to determine and provide a spatial orientation (e.g., pitch, roll, yaw) of electronics module **204**. The spatial orientation provided by IMU **322** can be used in determining the location of a virtual antenna (e.g., as described below) and/or the base of pole **202**.

[0044] User interface **326** can include components such as buttons, dials, keypad, display, touch screen, speakers, microphones, or the like to enable a user to interact with GNSS receiver system **300**. For instance, a user may be able to initiate a location measurement using a button and/or read a location measurement using a display. These and/or other interactions can be supported. In some embodiments, GNSS receiver system **300** may be remotely operable and can include a communication interface to exchange signals with a remote control device. Wired or wireless communication protocols can be used, and a particular scheme for control input and data output is not relevant to understanding the present disclosure.

[0045] It will be appreciated that location-measuring device **200** and GNSS receiver system **300** are illustrative and that variations or modifications are possible. Receiver systems can have any desired form factor, provided that the two antennas can be accommodated. For example, the antennas may be mounted in fixed relation to each other on a vehicle or other movable structure or object and can be but need not be disposed inside a common housing. In addition, some or all components of GNSS receiver system **300** can be located remotely from other components. For instance, the signal processing engine may be housed in a separate device that communicates via wired or wireless channels with a device that includes the antennas, receiver modules, and IMU.

[0046] According to some embodiments, signal processing engine **320** can be configured (e.g., by programming and/or by design of suitable logic circuits) to perform a single-difference carrier phase (SDCP) computation using signals received by antennas **208***a*, **208***b*. Where multiple GNSS carrier frequencies are receivable by antennas **208***a*, **208***b*, a geometry-free SDCP computation can be performed. Results of the SDCP computation or geometry-free SDCP computation can be used to estimate a degree of multipath effect and assign weights to observations from different GNSS satellites. The weighted observations can be used for determining the location of antenna **208***a* and/or antenna **208***b*. Examples of location determining processes incorporating short-baseline SDCP computations will now be described.

[0047] FIG. **4** shows a flow diagram of a process **400** for determining a location of an antenna according to some embodiments. Process **400** can be implemented in GNSS receiver system **300** or other device or system having two antennas ("antenna **1**" and "antenna **2**") mounted in fixed relation to each other with a short baseline. Process **400** assumes that a location of GNSS receiver system **300** has already been estimated (e.g., using conventional GNSS techniques); however, the estimate may include error or uncertainty on the order of several meters. Process **400** can be used to reduce such error or uncertainty, e.g., to 10 cm or less in some embodiments.

[0048] At blocks **402** and **404**, antenna **1** (e.g., antenna **208***a*) and antenna **2** (e.g., antenna **208***b*) can each receive signals from GNSS satellites, including any or all GNSS satellites that are in view of the antennas at a given time. At blocks **406** and **408**, observables for each antenna can be extracted from the received signals. (As used herein, an "observation" refers to a set of observables for a particular antenna from a particular GNSS satellite at a particular frequency.) The observables can include any data or information that can be extracted from a GNSS signal and used in determining a distance to the GNSS satellite that was the source of the signal. Examples include a code observable, a Doppler observable, and a carrier phase observable (denoted herein as Φ_f^A, where A identifies an antenna and f identifies a frequency), all of which can be obtained using a suitably configured antenna and receiver. Observables can be extracted independently for each antenna, satellite, and frequency.

[0049] At block **414**, a single difference carrier phase (SDCP), represented as $\Delta\Phi_f^{1,2}$ can be computed using sig-

nals from the same satellite having the same frequency received by the two antennas. More specifically, SDCP can be defined as $\Delta\Phi_f^{1,2}=\Phi_f^1-\Phi_f^2$. It should be understood that SDCP can be computed for any pair of observations (i.e., any instance where both antennas concurrently receive signals from the same satellite at the same frequency).

[0050] According to some embodiments, SDCP can be used to estimate a degree to which different observations may be affected by multipath. For instance, for a single GNSS satellite transmitting at a frequency f, the carrier phase observable for an antenna A can be expressed as:

$$\Phi_f^A = \rho + \delta\rho + cdt + cdT + \lambda N - I_f + T + m_f^A + \epsilon, \quad (1)$$

where ρ is the geometric range from the satellite to the receiver and the other terms represent various sources of error: δρ represents orbital error (due to satellite not being exactly in the nominal location); cdt represents a receiver clock bias; cdT represents a satellite clock bias; Δ is the wavelength of the GNSS carrier; N represents an ambiguity in the number of wavelengths between the satellite and the antenna; I_f represents ionosphere-induced error for frequency f; T represents troposphere-induced error; m_f^A represents multipath error for antenna A at frequency f; and ϵ represents random noise. Computing SDCP has the effect of cancelling out some of these sources of error. For instance, due to the short baseline between antennas **1** and **2**, ionospheric and tropospheric errors (I_f and T in Eq. (1)) can be assumed to be the same for both antennas. Since both antennas are receiving from the same satellite, the satellite clock bias (cdT in Eq. (1)) is the same for both antennas. Assuming the receivers for both antennas operate from a common clock, the clock bias (cdt in Eq. (1)) is also the same for both antennas. Accordingly, in some embodiments

$$\Delta\Phi_f^{1,2} = \Phi_f^1 - \Phi_f^2 = \Delta\rho + \lambda\Delta N + \Delta m_f^{1,2} + \epsilon, \quad (2)$$

where Δρ is the difference in geometric range between the two antennas (also referred to herein as a "geometric offset"); λΔN represents the difference in ambiguity; $\Delta m_f^{1,2}$ is the difference in the multipath error; and ϵ again represents random noise.

[0051] It should be noted that, even for a short baseline, the difference in multipath error cannot be assumed to be small. Since multipath effects are strongly location-dependent, two antennas separated by a short baseline distance can experience different multipath effects. It should also be understood that $\Delta m_f^{1,2}$ does not measure the multipath error for any given antenna or frequency; it is used here as an indicator of a degree to which multipath may be affecting the observables for a given observation (and/or any location computations that use those observables).

[0052] In some embodiments, block **414** can include computing SDCPs for multiple pairs of observations (up to and including every pair of observations). At block **416**, weights can be assigned to the observations based on the SDCPs computed at block **414**. In some embodiments, weights can be assigned such that observations associated with small $\Delta m_f^{1,2}$ are given higher weight than observations associated with large $\Delta m_f^{1,2}$.

[0053] As indicated in Eq. (2), the SDCP includes contributions from several error sources, and it is desirable to isolate the contribution of $\Delta m_f^{1,2}$ to the SDCP in order to assign weights. In some embodiments, isolating $\Delta m_f^{1,2}$ can be done by compensating for the geometric offset Δρ, treating λΔN as a constant.

[0054] By way of example, FIG. **5** shows a graph **500** of SDCP $\Delta\Phi_f^{1,2}$ for a series of observations of the same satellite across a period of time according to some embodiments; the observations were obtained using a dual-antenna device with a baseline of 10 cm that remained at a fixed location during the observations. The SDCP has an offset from zero that is attributable to the ambiguity difference λΔN and can be ignored. The SDCP also shifts systematically over time; this general trend is indicated by line **502**. This systematic shift is a result of gradual changes in Δρ as the position of the satellite relative to the antennas changes with time. Based on estimated locations of the antennas and satellite, Δρ can be estimated and removed using a geometric transform. In some embodiments, orientation data from IMU **322** can be used to determine an orientation (in three-dimensional space) of the baseline between antenna **1** and antenna **2**. For instance, the orientation data from IMU **322** can include roll, pitch and yaw angles defined relative to compass north (e.g., as determined by magnetic compass) and down (e.g., as determined by gravitational acceleration). Since the antennas are in fixed locations relative to the IMU, the roll, pitch, and yaw angles can be used to determine the spatial orientation of the baseline. Given the approximate positions of the antenna and satellite, Δρ can be estimated by triangulation and removed from $\Delta\Phi_f^{1,2}$. (For a baseline distance d, Δρ is between −d and +d.)

[0055] Accordingly, $\Delta m_f^{1,2}$ can be used to assign weights to observations. In some embodiments, observations for which $\Delta m_f^{1,2}$ *is large can be assigned low (or zero) weight while observations for which* $\Delta m_f^{1,2}$ is small can be assigned high weight. For example, a sigmoid function can be used, with the weight decreasing from 1 to 0 once $\Delta m_f^{1,2}$ exceeds a selected threshold. As another example, a hard threshold can be applied and observations for which $\Delta m_f^{1,2}$ exceeds a selected threshold can be discarded (or assigned a weight of 0). In some embodiments, the same weight is assigned to both observations of a given pair, since $\Delta m_f^{1,2}$ does not indicate which antenna is the source of error.

[0056] Once Δρ is removed, remaining variation between data points is assumed to be dominated by multipath effect $\Delta m_f^{1,2}$. As can be seen in FIG. **5**, the multipath effect is highly variable. For instance, in region **510**, $\Delta m_f^{1,2}$ is small, while in region **512**, $\Delta m_f^{1,2}$ is significantly larger. This is due to movement of the satellite across the sky relative to the antenna; the signal paths from the same satellite at different times may encounter different obstacles (or no obstacles). In some embodiments, $\Delta m_f^{1,2}$ does not indicate which antenna is the source of error; instead, $\Delta m_f^{1,2}$ indicates the degree to which multipath is affecting reliability of the observables: higher $\Delta m_f^{1,2}$ indicates less reliable observables and vice versa.

[0057] As a more specific example, Δρ between antenna **1** and antenna **2** can be estimated by performing an RTK computation between antenna **1** and antenna **2**, using one of the antennas as the "base" and the other as the "rover." As is known in the art, RTK uses the SDCP between the two antennas and uses a priori estimates of the variance or standard deviation of each antenna to assign weights to

observations from different satellites. These a priori estimates can be a function of signal-to-noise ratio, satellite elevation angle, and a calibrated model of antenna behavior; conventional or other techniques can be used. In some embodiments, weights can be assigned based on a geometry-free analysis (e.g., as described below with reference to FIGS. **7-11**), rather than relying on a priori estimates. Regardless of how weights are assigned, the RTK computation between antenna **1** and antenna **2** provides, among other outputs, an estimated "inter-vector" distance (e.g., Δx, Δy, and Δz) between antenna **1** and antenna **2**. In this case, the actual baseline d between antenna **1** and antenna **2** is known (and fixed), and data from the IMU can be used to determine expected Δx, Δy, and Δz. A residual for each satellite can be defined as the difference between the estimated inter-vector distance and the actual baseline. The residual provides an indication of the relative reliability of different satellites (larger residual implies lower reliability), which can be used to define weights for each satellite.

[0058] At block **418**, a location of one or both of the antennas can be determined using the observables and weights for observations of multiple GNSS satellites (at one frequency or multiple frequencies). The same observations used to compute SDCP and assign weights can also be used for location determination. In various embodiments, determining the location of an antenna can include observing multiple GNSS satellites and extracting observables for each satellite, determining a distance to each satellite using the set of observables, and computing a location of the antenna using triangulation of the distances and/or other techniques. All of the observations can be used, with different observations being given different weights. The weight for each observation can be the weight assigned at block **416**. (In some embodiments, the weight assigned to an observation at block **416** can be subsequently modified based on other available indicia of absolute or relative reliability of that observation.) In some embodiments, RTK, PPP, or other high-precision GNSS location-determination techniques can be incorporated into the location determination for the antenna, using the weights assigned at block **416**. A location can be determined for either antenna or for both antennas. Where RTK is used, the same base unit can provide reference data for both antennas.

[0059] In some embodiments, the location of a receiver containing the antennas can be determined by determining a location for each antenna and averaging the locations or by combining observables from both antennas and applying GNSS location-determining techniques to the combined observables. Examples of suitable processes are described in above-referenced U.S. Patent Application No._____(Attorney Docket No. 089730-061900US-1316442).

[0060] As noted above, process **400** can use an estimation of the difference in geometric range between the two antennas ($\Delta\varphi$ in order to isolate the contribution of multipath error ($\Delta m_f^{1,2}$) to the SDCP ($\Delta\Phi_f^{1,2}$). Another approach can collect observations over a period of time while location-measuring device **200** remains in a fixed position and orientation, thereby producing a data set of the kind shown in FIG. **5**. A fitting procedure can be applied to determine a trend line **502**, allowing the contribution of multipath error to be isolated. However, in some cases, the effect of the changing geometric offset may predominate over the multipath effect. By way of example, FIG. **6** shows another graph **600** of SDCP $\Delta\Phi_f^{1,2}$ for a series of observations of the same satellite across a period of time according to some embodiments using a dual-antenna device with a baseline of 10 cm that remained at a fixed location during the observations. In this example the multipath effect creates only small excursions from the time-dependent variation of $\Delta\rho$. While process **400** can still be used, it may be desirable to use additional observations to remove or reduce the contribution of geometry offset to the SDCP.

[0061] FIG. **7** is a flow diagram of a process **700** for determining a location of an antenna according to some embodiments. Process **700** can be implemented in GNSS receiver system **300** or other device or system having two antennas ("antenna **1**" and "antenna **2**") mounted in fixed relation to each other with a short baseline. Process **700** can use observations at two or more different frequencies to remove the effect of antenna geometry; the result is referred to as "geometry-free SDCP." Process **700** assumes that each satellite broadcasts at two or more frequencies. The L**1**, L**2**, and L**5** frequencies used by existing GPS satellites are used herein as an example, but any set of two or more available frequencies may be used.

[0062] At blocks **702** and **704**, antenna **1** (e.g., antenna **208***a*) and antenna **2** (e.g., antenna **208***b*) can each receive signals from GNSS satellites, including any or all GNSS satellites that are in view of the antennas at a given time, at multiple frequencies. At blocks **706** and **708**, observables for each antenna can be extracted from the received signals from each satellite and frequency. As in process **400**, the observables can include any data or information that can be extracted from a GNSS signal and used in determining a distance to the GNSS satellite that was the source of the signal, including the code, Doppler, and carrier phase observables as mentioned above. Observables can be extracted independently for each antenna, satellite, and frequency. In some embodiments, blocks **702-708** for a given frequency can be identical to blocks **402-408** of process **400**.

[0063] At block **714**, for each frequency f, an SDCP $\Delta\Phi_f^{1,2}$ can be computed using signals from the same satellite having frequency f for the two antennas by subtracting Φ_f^2 from Φ_f^1. In some embodiments, block **714** for a given frequency can be identical to block **414** of process **400**.

[0064] At block **716**, a geometry-free SDCP, denoted as $\Delta\Phi_{f1,f2}^{1,2}$ can be computed by subtracting the SDCPs computed at block **714** for two different frequencies. Thus, for example, for the L**1** and L**2** GPS frequencies, $\Delta\Phi_{L1,L2}^{1,2}$==Δ**101** $_{L1}^{1,2}-\Delta\Phi_{L2}^{1,2}$. From Eq. (2), it follows that

$$\Delta\Phi_{L1,L2}^{1,2}=\Delta\Phi_{L1}^{1,2}-\Delta\Phi_{L2}^{1,2}= \tag{3}$$
$$\left(\Delta\rho_{L1}^{1,2}-\Delta\rho_{L2}^{1,2}\right)+\lambda\left(\Delta N_{L1}^{1,2}-\Delta N_{L2}^{1,2}\right)+\lambda\left(\Delta m_{L1}^{1,2}-\Delta m_{L2}^{1,2}\right)+\epsilon,$$

where ϵ represents random noise. Where the observations at both frequencies are made using the same pair of antennas and the same satellite (and the antennas are assumed to remain in a fixed position during the observations), $\Delta\rho_{L1}^{1,2}=\Delta\rho_{L2}^{1,2}$, and Eq. (3) reduces to:

$$\Delta\Phi_{L1,L2}^{1,2}=\lambda\Delta N_{L1,L2}^{1,2}+\Delta m_{L1,L2}^{1,2}+\epsilon'. \tag{4}$$

Similarly to Eq. (2), Eq. (4) obtains in the case of two antennas with a short baseline and a common receiver clock. The residual multipath term $\Delta m_{L1,L2}^{1,2}$ is not expected to be zero since it is not expected that multipath effects are the same across antennas or frequencies. In some embodiments, a geometry-free SDCP can be computed for multiple pairs of observations (up to and including every pair of observations).

[0065] Similarly to process **400**, the residual multipath term can be used to identify observations (i.e., sets of observables) where multipath effect is likely to be significant. As with $\Delta m_f^{1,2}$ in process **400**, residual multipath term $\Delta m_{L1,L2}^{1,2}$ does indicate which antenna or frequency is the source of error; instead, $\Delta m_{L1,L2}^{1,2}$ indicates a degree to which multipath may be affecting the observables for a given observation (and/or any location computations that use those observables).

[0066] At block **718**, weights can be assigned to the observations based on the geometry-free SDCPs computed at block **716**. In some embodiments, observations for which $\Delta m_{L1,L2}^{1,2}$ is large can be assigned low (or zero) weight while observations for which $\Delta m_{L1,L2}^{1,2}$ can be assigned high weight. For example, a sigmoid function can be used, with the weight decreasing from 1 to 0 once $\Delta m_{L1,L2}^{1,2}$ exceeds a selected threshold. As another example, a hard threshold can be applied and observations for which $\Delta m_{L1,L2}^{1,2}$ exceeds a selected threshold can be discarded (or assigned a weight of 0). In some embodiments, the same weight is assigned to all observations that contributed to a given geometry-free SDCP, since $\Delta m_{L1,L2}^{1,2}$ does not indicate which antenna or frequency is the source of error. Additional examples of assigning weights are described below.

[0067] At block **720**, a location of one or both of the antennas can be determined based on the observables and weights for observations of multiple GNSS satellites (at one frequency or multiple frequencies). The same observations used to compute geometry-free SDCP and assign weights can also be used for location determination. Similarly to block **418** of process **400**, determining the location of an antenna can include observing multiple GNSS satellites and extracting observables for each satellite, determining a distance to each satellite using the set of observables, and computing a location of the antenna using triangulation of the distances and/or other techniques All of the observations can be used, with different observations being given different weights. The weight for each observation can be the weight assigned at block **718**. (In some embodiments, the weight assigned to an observation at block **718** can be subsequently modified based on other available indicia of absolute or relative reliability of that observation.) In some embodiments, RTK, PPP, or other high-precision GNSS location-determination techniques can be incorporated into the location determination for each antenna. A location can be determined for either or both antennas. Where RTK is used, the same base unit can provide data for both antennas.

[0068] In some embodiments, the location of a receiver containing the antennas can be determined by determining a location for each antenna and averaging the locations or by combining observables from both antennas and applying GNSS location-determining techniques to the combined observables. Examples of suitable processes are described in above-referenced U.S. Patent Application No._____(Attorney Docket No. 089730-061900US-1316442).

[0069] In some embodiments, process **700** can be performed using more than two frequencies. For example, if a GPS satellite broadcasts at frequencies L**1**, L**2**, and L**5**, three geometry-free SDCPs can be computed using two antennas: $\Delta\Phi_{L1,L2}^{1,2}=\Delta\Phi_{L1}^{1,2}-\Delta\Phi_{L2}^{1,2}$; $\Delta\Phi_{L1,L5}^{1,2}=\Delta\Phi_{L1}^{1,2}-\Delta\Phi_{L5}^{1,2}$; and $\Delta\Phi_{L2,L5}^{1,2}=\Delta\Phi_{L2}^{1,2}-\Delta\Phi_{L5}^{1,2}$. Additional information about the effect of multipath can be inferred from these parameters. For instance, if $\Delta m_{L1,L5}^{1,2}$ is small while $\Delta m_{L1,L2}^{1,2}$ and $\Delta m_{L2,L5}^{1,2}$ is large, this may suggest that the L**2** signal is experiencing multipath error. Assignment of weights at block **718** can incorporate this information, e.g., de-weighting the observations from a satellite at a particular frequency (L**2** in this example) relative to other observations from the same satellite.

[0070] FIG. **8** shows graphs **800**, **810**, **820** of geometry-free SDCPs obtained from observations of a GPS satellite at frequencies L**1**, L**2**, and L**5**, using a receiver unit similar to device **200** and an implementation of process **700**. Graph **800** shows $\Delta\Phi_{L1,L2}^{1,2}$; graph **810** shows $\Delta\Phi_{L1,L5}^{1,2}$; and graph **820** shows $\Delta\Phi_{L2,L5}^{1,2}$ as functions of time. (There is a gap where the satellite was not visible to the antenna.) The oscillations reflect the time-varying magnitude of multipath effects.

[0071] According to various embodiments, weights can be assigned based on the relative reliability of signals from different satellites. FIG. **9** shows graphs **900**, **910** of geometry-free SDCP obtained from various satellites (G**10**, G**21**, G**25**, G**31**, G**32**) using process **700** according to some embodiments. In graph **900**, the geometry-free SDCP is plotted as a function of time. In graph **910**, the absolute value of geometry-free SDCP for the same set of observations is plotted. In this example, satellites G**10** and G**31** are experiencing multipath, which appears as a sinusoidal effect that is larger than for other satellites.

[0072] FIG. **10** shows a graph **1000** of thresholds that can be defined from the geometry-free SDCP observations of FIG. **9** according to some embodiments. A "mean threshold" **1010** is defined by computing the mean of geometry-free SDCP across all satellites, which changes with each set of observations. A "median threshold" **1020** is defined by computing the median of geometry-free SDCP across all satellites, which also changes with each set of observations. A "fixed threshold" **1030** can be chosen, e.g., based on analysis of large sets of observations. Any one of these thresholds, or a combination thereof, can be used. For instance, a predefined fixed threshold may be used if the median or mean of current observations exceeds the predefined fixed threshold, or the lowest of mean, median, and fixed threshold may be used in any given instance.

[0073] In some embodiments, the weight for a given observation can be assigned based on the difference between the geometry-free SDCP and the threshold. Any observation for which the geometry-free SDCP is below threshold can be assigned a weight of 1. For observations with geometry-free SDCP above threshold, a de-weighting can be applied, such that the weight decreases with increasing geometry-free SDCP. As just one example, FIG. **11** shows a graph **1100** of a sigmoid function that can be used to assign weights according to some embodiments. The x-axis is the difference $\Delta\Phi_{f1,f2}^{1,2}-Z$, where Z is a threshold that can be chosen based on mean, median or fixed values as described above. The y-axis is a noise parameter that, in this example, is inversely proportional to weight. Other weighting functions can be substituted for the sigmoid function of graph **1100**.

[0074] Other techniques for assigning weights to observations based on geometry-free SDCP can also be used. For example, a moving window (rather than a single set of observations) can be used to define the mean or median geometry-free SDCP. Standard deviation or variance of the observations can be analyzed instead of just mean or median. In some embodiments, large data sets can be collected and analyzed to generate a lookup table of weight values (e.g., based on the difference between observed geometry-free SDCP and a threshold parameter that may be dynamically defined), and weights can be assigned using the lookup table.

[0075] To illustrate the effectiveness of SDCP-based weighting techniques of the kind described herein, FIG. **12** shows graphs **1200**, **1210**, **1220**, **1230** of GPS errors for location determination using: (1) a conventional RTK technique with a single rover antenna (lines **1202**, **1212**, **1222**, **1232**); and (2) a weighted RTK technique using an implementation of process **700** (lines **1204**, **1214**, **1224** **1234**) with GPS L**1** and L**2** frequencies. Location errors are plotted as a function of time for an east-west (longitude) direction (graph **1200**); a north-south (latitude) direction (graph **1210**); a vertical direction (graph **1220**); and a net horizontal error (graph **1230**). In this example, the use of observation weighting based on geometry-free SDCP can reduce horizontal RTK errors from greater than 8 cm to under 4 cm in some spots and can reduce vertical error by 2 to 4 cm. Accordingly, a process such as process **400** or process **700** can help improve reliability of GNSS location measurements.

[0076] While the invention has been described with reference to specific embodiments, those skilled in the art will appreciate that variations and modifications are possible. Any algorithms and techniques for determining location of an antenna (or receiver) using GNSS satellite data can be used, and any number or combination of GNSS observations can be incorporated into the location determination. In some embodiments, signals can be obtained at multiple frequencies (e.g., any or all of the L**1**, L**2**, and L**5** frequencies used in GPS signals), and observables extracted from signals at different frequencies can be combined. The particular physical structures of the antennas can be implemented as desired, provided that the antennas are sized and shaped such that they can be mounted with a short baseline. Having the same physical configuration for both antennas can improve reliability of the measurements.

[0077] In some embodiments, a geometry-free SDCP analysis (e.g., as described above with reference to FIGS. **7-11**) can be used to obtain initial weights for each satellite. These weights can be applied to an RTK process between the two antennas as described above with reference to FIG. **4** (instead of using a priori weights). Residuals from the RTK process can then be used to assign weights to observations for an RTK process with the base unit.

[0078] Location measurements determined using techniques described herein have a variety of applications. Depending on the particular application, location data can be output to a user, stored in a computer-readable storage medium, inserted as an annotation in a map or other survey record, and so on.

[0079] In some embodiments, dual-antenna systems can be implemented in tilted-pole survey systems. As described above, an inertial measurement unit in the survey pole can determine an orientation of the pole, and location measurements can be modified to account for tilt or rotation of the pole. Where RTK is used, dual-antenna systems can be included in the rover unit and/or the base unit, and techniques described herein can be applied. In the case of a base unit, which may remain in a fixed location for an extended period of time (minutes, hours, or days), PPP or similar techniques can be used to reduce the location error. A location of a rover unit can be determined using RTK with reference to the base unit. Signal processing circuitry can be disposed in the rover unit and/or the base unit as desired.

[0080] Dual-antenna systems can also be implemented in other applications where highly accurate location determination is desired. For example, a pair of GNSS receiver antennas can be mounted on a vehicle at a fixed baseline distance from each other (e.g., 20 cm up to 2-3 meters), and techniques described herein may be applied. The improved accuracy can be beneficial in applications such as autonomous vehicles.

[0081] While various circuits and components are described herein with reference to particular blocks, it is to be understood that these blocks are defined for convenience of description and are not intended to imply a particular physical arrangement of component parts. The blocks need not correspond to physically distinct components, and the same physical components can be used to implement aspects of multiple blocks. Components described as dedicated or fixed-function circuits can be configured to perform operations by providing a suitable arrangement of circuit components (e.g., logic gates, registers, switches, etc.); automated design tools can be used to generate appropriate arrangements of circuit components implementing operations described herein. Components described as processors or microprocessors can be configured to perform operations described herein by providing suitable program code. Various blocks might or might not be reconfigurable depending on how the initial configuration is obtained. Embodiments of the present invention can be realized in a variety of apparatus including electronic devices implemented using a combination of circuitry and software.

[0082] All processes described herein are also illustrative and can be modified. Operations can be performed in a different order from that described, to the extent that logic permits; operations described above may be omitted or combined; and operations not expressly described above may be added.

[0083] Computer programs incorporating features of the present invention that can be implemented using program code may be encoded and stored on various computer readable storage media; suitable media include magnetic disk or tape, optical storage media such as compact disk (CD) or DVD (digital versatile disk), flash memory, and other non-transitory media. (It is understood that "storage" of data is distinct from propagation of data using transitory media such as carrier waves.) Computer readable media encoded with the program code may include an internal storage medium of a compatible electronic device and/or external storage media readable by the electronic device that can execute the code. In some instances, program code can be supplied to the electronic device via Internet download or other transmission paths.

[0084] Accordingly, although the invention has been described with respect to specific embodiments, it will be

appreciated that the invention is intended to cover all modifications and equivalents within the scope of the following claims.

What is claimed is:

1. A method comprising:

receiving, at a first antenna of a receiver system and at a second antenna of the receiver system, global navigation satellite system (GNSS) signals from a plurality of GNSS satellites wherein the first antenna and the second antenna are mounted to the receiver system in a fixed relative position and define a baseline;

for each received GNSS signal:

extracting, by the receiver system, a first set of observables from the GNSS signal as received by the first antenna, the first set of observables including a first carrier phase;

extracting, by the receiver system, a second set of observables from the GNSS signal as received by the second antenna, the second set of observables including a second carrier phase; and

computing, by the receiver system, a single difference carrier phase (SDCP) between the first carrier phase and the second carrier phase;

assigning, by the receiver system, a weight for each GNSS satellite based at least in part on the SDCP computed for each received GNSS signal; and

determining, by the receiver system, a location of the receiver system using the first and second sets of observables extracted from the received GNSS signals and the weights.

2. The method of claim **1** wherein assigning a weight for each GNSS satellite includes:

determining an orientation of the first antenna and the second antenna;

determining a geometric offset between the first antenna and the second antenna based at least in part on the orientation of the first antenna and the second antenna;

subtracting the geometric offset from the first SDCP to produce a modified SDCP; and

using the modified SDCP to estimate a multipath effect,

wherein the weight is determined using the estimated multipath effect.

3. The method of claim **2** wherein the weight decreases with increasing estimated multipath effect.

4. The method of claim **2** wherein the orientation is determined based on data from an inertial measurement unit mounted to the receiver system in a fixed position relative to the first and second antennas.

5. The method of claim **1** wherein assigning a weight for each GNSS satellite includes:

performing a real-time kinematic (RTK) location determination using the first antenna and the second antenna;

determining a residual for each GNSS satellite based on a result of the RTK location determination; and

assigning a weight for each GNSS satellite based on the residuals.

6. The method of claim **1** wherein assigning a weight for each GNSS satellite includes estimating a multipath contribution to the SDCP and determining the weight based on the multipath contribution.

7. The method of claim **6** wherein assigning a weight for each GNSS satellite includes applying a sigmoid function to the multipath contribution.

8. A method comprising:

receiving global navigation satellite system (GNSS) signals from a plurality of GNSS satellites at a first antenna of a receiver system and at a second antenna of the receiver system, wherein the first antenna and the second antenna are mounted to the receiver system in a fixed relative position and define a baseline, and wherein the GNSS signals include a plurality of GNSS signals having different frequencies;

extracting, by the receiver system, a first set of observables from each GNSS signal received at the first antenna, the first set of observables including a first carrier phase of each received GNSS signal at each of the different frequencies;

extracting, by the receiver system, a second set of observables from each GNSS signal received at the second antenna, the second set of observables including a second carrier phase of each received GNSS signal at of the different frequencies;

computing, by the receiver system, for each GNSS satellite and each frequency, a frequency-specific single difference carrier phase (SDCP) between the first carrier phase and the second carrier phase;

computing, by the receiver system, for each GNSS satellite, a geometry-free SDCP based on the frequency-specific SDCPs at two different frequencies.

assigning, by the receiver system, respective weights to the observations from each GNSS satellite based at least in part on the geometry-free SDCP; and

determining a location of the receiver system using the first and second sets of observables of the received GNSS signals and the weights.

9. The method of claim **8** wherein assigning the weight includes estimating a multipath contribution to the geometry-free SDCP and determining the weight based on the multipath contribution, wherein the weight decreases as the multipath contribution increases.

10. The method of claim **9** wherein assigning the weight includes applying a sigmoid function to the multipath contribution.

11. The method of claim **9** wherein assigning the weight includes assigning zero weight if the multipath contribution exceeds a threshold.

12. The method of claim **8** wherein determining the location of the receiver system includes performing a real-time kinematic (RTK) analysis using information extracted from the GNSS signals received at the first antenna and additional information received from a base unit.

13. A system comprising:

a movable structure;

a first antenna and a second antenna mounted to the movable structure at a fixed baseline distance apart and configured to receive global navigation satellite system (GNSS) signals from each of a plurality of GNSS satellites;

receiver circuitry coupled to the first antenna and the second antenna and configured to extract a first set of observables from a first GNSS signal from a first one of the GNSS satellites as received by the first antenna and a second set of observables from the first GNSS signal as received by the second antenna, wherein the first set of observables includes a first carrier phase and the second set of observables includes a second carrier phase; and

a signal processing engine coupled to the receiver circuitry and configured to:

compute a first single difference carrier phase (SDCP) between the second carrier phase and the first carrier phase;

assign a weight to the first and second sets of observables based at least in part on the first SDCP; and

determine a location of the movable structure using the weight and the first and second sets of observables.

14. The system of claim **13** wherein the fixed baseline distance is less than a meter.

15. The system of claim **13** wherein the signal processing engine is further configured such that assigning the weight to the first and second sets of observables includes:

estimating a multipath contribution to the first SDCP; and

determining the weight based on the multipath contribution, wherein the weight decreases as the multipath contribution increases.

16. The system of claim **15** wherein the signal processing engine is further configured such that assigning the weight to the first and second sets of observables includes:

assigning zero weight if the multipath contribution exceeds a threshold.

17. The system of claim **13** further comprising:

an inertial measurement unit (IMU) coupled to the signal processing engine and configured to determine an orientation of the first antenna and the second antenna,

wherein the signal processing engine is further configured such that assigning the weight includes:

determining a geometric offset between the first antenna and the second antenna based at least in part on the orientation of the first antenna and the second antenna;

subtracting the geometric offset from the first SDCP to produce a modified SDCP; and

using the modified SDCP to estimate a multipath effect, wherein the weight is determined using the estimated multipath effect.

18. The system of claim **13** wherein:

the receiver circuitry is further configured to extract a third set of observables from a second GNSS signal from the first one of the GNSS satellites as received by the first antenna and a fourth set of observables from the second GNSS signal as received by the second antenna, wherein the second GNSS signal has a frequency different from a frequency of the first GNSS signal, wherein the third set of observables includes a third carrier phase and the fourth set of observables includes a fourth carrier phase; and

the signal processing engine is further configured to:

compute a second single difference carrier phase (SDCP) between the third carrier phase and the fourth carrier phase;

compute a geometry-free SDCP from the first SDCP and the second SDCP;

assign a weight to the first, second, third, and fourth sets of observables based at least in part on the geometry-free SDCP; and

determine the location of the movable structure using the weight and the first, second, third, and fourth sets of observables.

19. The system of claim **18** wherein the signal processing engine is further configured such that assigning the weight to the first, second, third, and fourth sets of observables includes:

estimating a multipath contribution to the geometry-free SDCP; and

determining the weight based on the multipath contribution, wherein the weight decreases as the multipath contribution increases.

20. The system of claim **18** wherein the signal processing engine is further configured to:

determine a threshold using respective geometry-free SDCPs computed for a plurality of GNSS satellites; and

assign a respective weight to observables from each of the GNSS satellites based on the threshold,

wherein the receiver circuitry is further configured such that determining the location of the movable structure is based in part on the respective weights.

* * * * *