

MPSTME-NMIMS (Mumbai)

MBA TECH [Data Science]

SUPERCONDUCTING MATERIALS AS THE PHYSICAL SUBSTRATE OF QUANTUM COMPUTATION

13th January, 2026

Aditya Mishra[◇], S046 C2

Meet Jain[†], S024 C1

Laith Shaikh[‡], S068 C3

Soham Sahay[◦], S063 C3

ABSTRACT

Superconducting quantum circuits currently constitute the most technologically mature platform for quantum computation. Despite substantial progress in “qbit” design, control electronics, and error-correcting codes, coherence times and gate fidelities remain constrained by materials-dependent loss mechanisms. This work argues that the dominant bottleneck in superconducting quantum computing is not architectural or algorithmic, but fundamentally materials-based. We analyse the physical origins of energy relaxation and de-phasing in superconducting qbits, emphasizing dielectric loss, two-level systems (TLS), surface oxides, and interface disorder. A comparative assessment of niobium-based and aluminium-based superconductors is presented, highlighting fabrication-dependent trade-offs. We critically examine why high- T_c superconductors fail to support coherent qbits, despite their favourable thermodynamic properties. Josephson junctions are treated as complex material systems whose atomic-scale disorder directly limits reproducibility, noise, and fault-tolerance thresholds. Finally, we discuss scalability and integration challenges,

◇ aditya.mishra10@nmims.in

† meet.jain30@nmims.in

‡ Laith.shaikh10@nmims.in

◦ soham.sahay64@nmims.in

demonstrating that fault-tolerant quantum computation is constrained by irreducible material noise floors. Open problems and future research directions are identified, with an emphasis on interface engineering and materials discovery grounded in physical constraints rather than speculative optimism.

1. INTRODUCTION

The trajectory of superconducting quantum computing has been shaped by a sustained effort to reduce the influence of environmental degrees of freedom on fragile quantum states. From the earliest implementations of the Cooper pair box to the modern transmon and fluxonium architectures, progress has largely been driven by circuit level optimization. In particular, the deliberate engineering of electromagnetic parameters, most notably the ratio of the Josephson energy E_J to the charging energy E_C , has proven to be an effective strategy for suppressing sensitivity to charge noise and stabilizing qbit frequencies¹. By operating in regimes where charge dispersion is exponentially reduced, these designs transformed superconducting qbits from laboratory curiosities into platforms capable of high fidelity control.

As gate fidelities and coherence times have steadily improved, however, the returns from further architectural refinements have begun to diminish. Contemporary devices already operate deep in the transmon or fluxonium regimes, where additional increases in E_J/E_C yield only marginal reductions in de-phasing while introducing new trade-offs, such as reduced anharmonicity or increased sensitivity to other noise channels. At this stage, the dominant error mechanisms are no longer set by the choice of circuit topology alone. Instead, they are increasingly governed by intrinsic properties of

1 J. Koch et al., "Charge-insensitive qbit design derived from the Cooper pair box," *Phys. Rev. A*, vol. 76, p. 042319, 2007.

the materials that constitute the device. The superconductor, the dielectric substrate, and especially the interfaces between them have emerged as the primary sources of de-coherence. This shift marks a qualitative change in the field, from one where clever circuit design could compensate for material imperfections to one where material quality itself sets the ultimate performance ceiling.

Superconductivity, at the most basic level, is described by the condensation of electrons into Cooper pairs that occupy a single macroscopic quantum state. This state can be represented by a complex order parameter $\Psi = \sqrt{n_s} e^{i\phi}$, whose phase ϕ underlies the Josephson effect and enables the construction of non linear superconducting oscillators. In an idealized picture, this condensate supports dissipation free current flow and perfectly coherent dynamics. In practical quantum processors, however, the superconductor is not an ideal continuum. It is a real condensed matter system containing crystal defects, grain boundaries, surface oxides, and residual normal state excitations. When a qubit is formed from such a system, the macroscopic quantum variable that encodes information is inevitably coupled to a dense spectrum of microscopic degrees of freedom.

These couplings manifest as energy relaxation and de-phasing processes, commonly quantified by the coherence times T_1 and T_2 . Atomic scale defects in amorphous dielectrics and native oxides act as two level systems that absorb energy from the qubit and introduce low frequency noise². Non equilibrium quasi-particles, generated by stray radiation or imperfect thermalization, tunnel across Josephson junctions and contribute to both dissipation and phase noise. Even nominally

benign interfaces between a superconductor and its substrate can host fluctuating charges, spins, or strain fields that couple directly to the qubit mode. Collectively, these effects limit coherence in a manner that cannot be eliminated by circuit design alone³.

In this paper, we argue that the transition from Noisy Intermediate Scale Quantum devices to truly scalable, fault tolerant quantum computers is fundamentally a materials science problem. While error correction protocols can in principle tolerate finite error rates, the overhead required grows rapidly as physical qubit performance deviates from ideal thresholds. If de-coherence remains dominated by uncontrolled material defects, the number of physical qubits needed to encode a single logical qubit becomes prohibitively large. Our analysis therefore focuses on identifying and understanding the microscopic origins of loss in superconducting qubits.

We systematically examine the dominant decoherence mechanisms in widely used aluminium based systems, which benefit from well controlled native oxides and relatively low quasi-particle densities. We then contrast these with niobium based alternatives, which offer advantages in terms of critical temperature and fabrication compatibility but introduce additional loss channels associated with more complex oxide chemistry. Finally, we critically assess proposals based on high T_c superconductors, highlighting the severe challenges posed by d wave pairing, intrinsic inhomogeneity, and strong electronic correlations.

The central conclusion of this work is that continued progress toward fault tolerant quantum computation will require a decisive shift in emphasis from circuit architecture to

2 H. Paik and K. D. Osborn, "Reducing quantum-regime dielectric loss of silicon nitride for superconducting quantum circuits," *Applied Physics Letters*, vol. 96, p. 072505, 2010.

3 M. H. Devoret and R. J. Schoelkopf, "Superconducting Circuits for Quantum Information: An Outlook," *Science*, vol. 339, pp. 1169-1174, 2013.

materials engineering. Without substantial improvements in the quality of Josephson junction barriers, dielectric substrates, and interfacial layers, further gains in coherence will be incremental at best. In such a scenario, algorithmic error correction will remain extremely resource intensive, limiting the practical scalability of superconducting quantum processors. By contrast, advances in materials growth, surface treatment, and interface control have the potential to unlock a new regime of performance, enabling us to approach the intrinsic limits of superconducting qubits and move decisively beyond the NISQ era.

2. QUANTUM COHERENCE AND MATERIAL CONSTRAINTS


The coherence of a superconducting qubit is conventionally quantified by two time-scales: the longitudinal energy relaxation time T_1 and the transverse dephasing time T_2 . These quantities provide a direct measure of how strongly the qubit couples to its environment and therefore how long quantum information can be faithfully stored and manipulated. In most contemporary superconducting qubits, particularly transmons, energy relaxation sets the dominant limit, making an understanding of T_1 central to any materials focused analysis of performance.

The relaxation rate $\Gamma_1 = T_1^{-1}$ is governed by the coupling of the qubit's electric field to dissipative environmental degrees of freedom. At a microscopic level, this process can be described using Fermi's Golden Rule, which relates the transition rate between qubit states to the spectral density of environmental noise evaluated at the qubit transition frequency ω_{01} . Explicitly, one may write

$$\frac{1}{T_1} = \frac{1}{\hbar^2} \left| \langle 0 | \hat{A} | 1 \rangle \right|^2 S_\lambda(\omega_{01}),$$

where $\hat{A}$ is the operator through which the qubit couples to a specific noise source λ , and $S_\lambda(\omega)$ is the corresponding noise spectral density. This expression makes clear that improving coherence requires either reducing the matrix element of the coupling operator or suppressing the available environmental modes at the relevant frequency. Circuit design has largely exhausted the former strategy. As a result, attention has increasingly shifted to identifying and mitigating the microscopic sources that dominate $S_\lambda(\omega_{01})$.

2.1 Dielectric Loss and Two Level Systems



In modern transmon devices, the dominant contribution to energy relaxation is widely attributed to dielectric loss arising from Two Level Systems (TLS) hosted in amorphous

materials^{4,5}. These TLS are generally understood as atoms, or small clusters of atoms, that can tunnel between two nearly degenerate configurational minima within a disordered potential landscape. Such configurations naturally arise in amorphous surface oxides, such as AlO_x and NbO_x , as well as at the interfaces between the superconducting film and the underlying substrate.

Each TLS carries an effective electric dipole moment $\mathbf{d}$ that couples directly to the local electric field $\mathbf{E}$ of the qbit mode. The interaction between a single TLS and the qbit field can be modeled by the Hamiltonian

$$H_{\text{int}} = -\mathbf{d} \cdot \mathbf{E} \hat{\sigma}_z^{\text{TLS}},$$

where $\hat{\sigma}_z^{\text{TLS}}$ acts on the two level subspace of the defect. At the millikelvin temperatures relevant for superconducting quantum processors, where $kBT \ll \hbar\omega_{01}$, TLS that are near resonance with the qbit can efficiently absorb energy. This resonant absorption leads directly to photon loss from the qbit mode and thus to a finite T_1 . The collective, macroscopic consequence of a large ensemble of such microscopic defects is conveniently captured by the dielectric loss tangent $\tan\delta$. For a qbit characterized by a capacitance C , the relaxation time limited by dielectric loss can be estimated as

$$T_1 \approx \frac{1}{\omega_{01} \tan \delta_{\text{eff}}},$$

where $\tan\delta_{\text{eff}}$ is an effective loss tangent obtained by summing the loss contributions of

all dielectric regions weighted by their electric field participation ratios⁵. This framework highlights a crucial materials insight. While high purity bulk substrates such as crystalline silicon or sapphire typically exhibit very low loss tangents on the order of 10^{-7} , amorphous surface oxides can have loss tangents as large as 10^{-3} . Because the electric field is strongly concentrated near metal edges and interfaces, even nanometer thick interfacial layers can dominate the total decoherence budget. From this perspective, coherence is not limited by the bulk material quality but by the uncontrolled chemistry and structure of surfaces and interfaces.

2.2 Non-equilibrium Quasi-particles

A second major source of de-coherence arises from non-equilibrium quasi-particles in the superconducting electrodes. In an ideal BCS superconductor at temperatures well below the critical temperature T_c , the density of quasi-particles generated by broken Cooper pairs should be exponentially suppressed. However, experiments consistently report quasi-particle densities far in excess of this equilibrium expectation. The normalized quasi-particle density is often expressed as $x_{qp} = n_{qp}/n_{cp}$, with measured values in the range 10^{-6} to 10^{-8} , several orders of magnitude larger than predicted by simple thermal models⁶.

These excess quasiparticles can tunnel across Josephson junctions, leading to stochastic parity switching events and direct energy relaxation of the qbit. From the qbit's perspective, quasiparticles represent a dissipative bath that couples strongly to the Josephson element itself, making them particularly detrimental to coherence. Despite extensive experimental and theoretical work, the origin of this persistent non-equilibrium population remains incompletely understood. Proposed mechanisms

4 C. Müller, J. H. Cole, and J. Lisenfeld, "Towards understanding two-level-systems in amorphous solids: insights from quantum circuits," *Rep. Prog. Phys.*, vol. 82, p. 124501, 2019.

5 J. M. Martinis et al., "Decoherence in Josephson qubits from Dielectric Loss," *Phys. Rev. Lett.*, vol. 95, p. 210503, 2005.

6 P. J. de Visser et al., "Number fluctuations of quasiparticles in a superconductor," *Phys. Rev. Lett.*, vol. 106, p. 167004, 2011.

include the absorption of high energy photons from cosmic rays or radioactive decay, phonon trapping and bottlenecks in the substrate, and imperfect filtering or shielding of the electromagnetic environment.^{7 8}

What is clear is that quasi-particle poisoning is not a minor technical detail but a fundamental materials and device physics problem. Its persistence underscores the broader theme of this paper: even when operating deep in regimes where circuit design suppresses sensitivity to classical noise, superconducting qubits remain vulnerable to microscopic, materials driven processes. Understanding and ultimately controlling these processes is essential if we are to extend coherence times further and reduce the overhead required for fault tolerant quantum computation.

3. Nb BASED SUPERCONDUCTING MATERIALS

Niobium (Nb) has long occupied a central role in superconducting electronics and microwave engineering. Its relatively high critical temperature, $T_c \approx 9.2$ K, combined with mechanical robustness and compatibility with large scale thin film fabrication, has made it the material of choice for industrial superconducting technologies such as rapid single flux quantum (RSFQ) logic and superconducting microwave resonators. From the perspective of classical superconducting circuits, these properties are highly advantageous, enabling reliable operation, relaxed cryogenic requirements, and reproducible device performance.

When the focus shifts from classical signal processing to quantum coherent circuits, however, the criteria for material suitability

change in a fundamental way. Superconducting qubits are not merely current carrying elements but macroscopic quantum systems whose coherence is exquisitely sensitive to microscopic disorder, inter-facial chemistry, and low energy excitations. In this regime, niobium presents a distinct set of materials science challenges that sharply differentiate it from aluminium based platforms.

One of the primary advantages of aluminium in quantum circuits is the simplicity and self limiting nature of its native oxide, AlO_x . This oxide forms a relatively uniform, stable tunnel barrier that can be grown with good reproducibility and comparatively low defect density. In contrast, niobium readily forms a complex and chemically heterogeneous oxide stack, typically consisting of NbO , NbO_2 , and Nb_2O_5 , depending on processing conditions and ambient exposure. These oxides are often amorphous or poorly crystalline and host a high density of structural defects. From the standpoint of qubit coherence, this complexity is highly problematic, as it provides a fertile environment for Two Level Systems that couple strongly to the qubit's electric field.

The consequences of this oxide chemistry are most severe at the Josephson junction, which is the central non linear element of the qubit. In Nb based junctions, controlling the stoichiometry, thickness, and uniformity of the tunnel barrier is significantly more challenging than in Al AlO_x Al junctions. Even small variations in the local oxide composition can lead to spatial inhomogeneity in the junction transparency, increasing the density of sub-gap states and enhancing dissipation. Experimentally, this manifests as increased dielectric loss, reduced T_1 , and greater device to device variability compared to aluminium based qubits fabricated with otherwise similar geometries.

7 A. P. Vepsäläinen et al., "Impact of ionizing radiation on superconducting qubit coherence," *Nature*, vol. 584, pp. 551–556, 2020.

8 J. M. Martinis, "Saving superconducting quantum processors from decay and correlated errors," *npj Quantum Information*, vol. 7, p. 90, 2021.

Beyond the junction itself, niobium surfaces and interfaces introduce additional sources of loss. Nb films are typically deposited by sputtering, a process that can introduce residual stress, grain boundaries, and impurity incorporation. These micro-structural features can host fluctuating magnetic moments or charge traps that contribute to both energy relaxation and dephasing. Furthermore, the higher critical temperature of Nb implies a larger superconducting gap, which, while beneficial for suppressing thermally generated quasi-particles, also modifies the interaction between non-equilibrium quasi-particles and phonons in ways that are not yet fully understood. In practice, Nb based qubits often exhibit elevated quasi-particle densities, suggesting that higher T_c alone does not guarantee improved quasi particle suppression.

There is also an important systems level consideration. Many fabrication flows developed for Nb in classical superconducting electronics prioritize yield, uniformity, and robustness rather than ultra low loss. Processes such as aggressive plasma etching, multilayer wiring, and dielectric encapsulation, while acceptable for RSFQ circuits, can be detrimental for quantum coherence. Adapting Nb to the stringent requirements of quantum processors therefore demands a substantial rethinking of surface preparation, oxide control, and interface engineering.

Taken together, these considerations explain why, despite its success in classical superconducting technologies, niobium has not displaced aluminium as the dominant material for state of the art superconducting qubits. This does not imply that Nb is fundamentally unsuitable for quantum computation. Rather, it highlights that achieving coherence comparable to or exceeding that of aluminium based systems would require significant advances in oxide chemistry control, junction fabrication,

and surface passivation. Without such advances, the intrinsic materials complexity of niobium remains a limiting factor for its deployment in scalable, high fidelity quantum coherent circuits.

3.1 Surface Chemistry and Oxides

A central distinction between niobium and aluminium in the context of quantum coherent circuits lies in their surface chemistry and, in particular, the nature of their native oxides. Aluminium forms a self limiting, chemically stable, and strongly insulating oxide, Al_2O_3 , with a thickness of only a few nano-meters. This oxide plays a dual role in aluminium based qubits. It serves as a reproducible tunnel barrier in Josephson junctions and, when properly controlled, introduces a relatively low density of electrically active defects compared to other amorphous oxides. As a result, the aluminium aluminium oxide system has become the de facto standard for superconducting qubits.

Niobium, by contrast, forms a complex and stratified oxide structure upon exposure to oxygen. Rather than a single well defined insulating layer, the Nb surface typically consists of a hierarchy of oxides, including NbO, NbO₂, and Nb₂O₅, whose relative thicknesses and compositions depend sensitively on processing history, ambient conditions, and thermal treatments. This chemical complexity has profound implications for quantum coherence.

The lower oxides, NbO and NbO₂, are metallic or semiconducting in nature. When present at the surface of a superconducting film, they can act as parasitic dissipative channels that couple directly to the qubit's electromagnetic fields. Moreover, these conductive or semi conductive layers can participate in proximity effect physics, where superconducting correlations leak into the oxide, creating sub gap states that enhance microwave loss. From the perspective

of a qbit or resonator mode, such layers represent an intrinsic source of dissipation that is difficult to eliminate through circuit design alone⁹.

Above these conductive oxides lies Nb₂O₅, a wide band gap dielectric that is structurally amorphous and known to host a high density of Two Level Systems. These TLS defects couple strongly to electric fields and give rise to significant dielectric loss at microwave frequencies. The combined effect of the conductive lower oxides and the lossy dielectric outer layer results in what is often described as a “lossy crust”¹⁰ at the niobium surface. This crust can dominate the loss budget of Nb based devices, particularly in planar geometries where electric fields are concentrated near metal edges.

Experimentally, this manifests as a substantial reduction in the internal quality factor Q of niobium based resonators compared to their aluminium counterparts, unless special mitigation strategies are employed. Techniques such as aggressive subtractive processing to remove surface oxides, *in situ* surface cleaning prior to film deposition, or the use of capping layers like NbTiN have been shown to partially suppress these loss channels. However, these approaches add complexity to fabrication and introduce their own integration challenges.

The sensitivity of niobium’s oxide structure to processing underscores a broader theme in superconducting quantum hardware. Coherence is not determined solely by the choice of superconducting element but by the detailed chemical and structural properties of the first few nanometers at surfaces and interfaces. In the case of niobium, controlling this surface chemistry to the degree required for fault

tolerant quantum computation remains an open and demanding materials science problem.

3.2 Micro-structure and Grain Boundaries

Beyond surface chemistry, the micro-structural properties of niobium films play a significant role in determining their suitability for quantum coherent circuits. Niobium films used in superconducting devices are most commonly deposited by sputtering, a technique that offers good thickness control and scalability but typically results in polycrystalline micro-structures. These films consist of grains with varying crystallographic orientations separated by grain boundaries, which introduce additional complexity from the standpoint of quantum coherence.

Grain boundaries act as scattering centers for Cooper pairs and can locally suppress the superconducting order parameter. While such effects may be negligible for classical superconducting electronics, they become increasingly relevant in the high frequency, low loss regime required for qbits and resonators. In particular, grain boundaries can act as preferential pinning sites for magnetic flux vortices. Even in nominally zero field environments, residual magnetic fields during cool-down can lead to vortex trapping within the superconducting film. At microwave frequencies, the motion of these vortices under the Lorentz force generated by the oscillating current gives rise to resistive loss, directly reducing the internal quality factor and contributing to qbit energy relaxation.

The impact of vortex related loss is especially pronounced in niobium due to its relatively high lower critical field and strong flux pinning at micro-structural defects. While careful magnetic shielding and controlled cool-down protocols can mitigate vortex trapping, they do not eliminate the underlying susceptibility

9 M. V. Gurevich, "Theory of superconductivity in composite systems," *Phys. Rev. B*, vol. 67, p. 184515, 2003.

10 W. A. Phillips, "Tunneling states in amorphous solids," *Journal of Low Temperature Physics*, vol. 7, pp. 351–360, 1972.

introduced by the polycrystalline nature of the film. As a result, post-structural disorder remains an intrinsic source of loss in sputtered Nb devices.

In principle, epitaxial growth of niobium films offers a route to reducing grain boundary density and improving coherence. However, achieving high quality epitaxial Nb on commonly used substrates such as silicon or sapphire is challenging due to significant lattice mismatch. This mismatch introduces strain into the film, which can relax through the formation of dislocations or other defects. Even when atomically smooth epitaxial layers are achieved, the residual strain alters the phononic spectrum of the film and the substrate near the interface. Such modifications can, in turn, influence the dynamics of Two Level Systems through deformation potential coupling, indirectly affecting both energy relaxation and de-phasing.

These considerations highlight an important trade-off. Eliminating grain boundaries through epitaxy may reduce one class of loss mechanisms while simultaneously enhancing others through strain induced effects. This complexity underscores the difficulty of optimizing niobium films for quantum coherence using micro-structural control alone.

Recent experimental progress with tantalum¹¹ based superconducting circuits has provided valuable insight into these issues. Devices employing tantalum capacitors have demonstrated coherence times that surpass those of comparable niobium based designs, despite tantalum having a similar critical temperature and bulk superconducting properties. The primary advantage of tantalum appears to be its simpler and more stable native oxide, which supports a significantly lower density of TLS

defects¹². These results strongly support the hypothesis that, in planar qbit geometries, surface chemistry and the associated dielectric environment are the dominant determinants of T_1 , outweighing the influence of bulk superconducting properties or micro-structural perfection.¹³

Taken together, the evidence suggests that while micro-structure and grain boundaries contribute to loss in niobium based devices, they are secondary to surface and interface effects. This reinforces the broader conclusion that achieving further gains in coherence will require prioritizing chemical control of surfaces and interfaces over incremental improvements in film crystallinity alone.

4. HIGH TEMPERATURE SUPERCONDUCTORS: *PROMISE AND LIMITATIONS*

High temperature superconductors, most prominently the cuprate family exemplified by $\text{YBa}_2\text{Cu}_3\text{O}_{7-\delta}$ (YBCO), exhibit superconductivity at temperatures accessible with liquid nitrogen cooling. From a technological standpoint, this property has motivated extensive research into their use for power transmission, magnets, and classical superconducting electronics. At first glance, the existence of macroscopic quantum coherence at elevated temperatures appears highly attractive for quantum information processing, where cryogenic complexity represents a major engineering burden. Nevertheless, when evaluated through the lens of qbit coherence,

11 C. D. Wilen et al., "Correlated charge noise and relaxation errors in superconducting qubits," *Nature*, vol. 594, pp. 369–373, 2021.

12 A. P. M. Place et al., "New material platform for superconducting transmon qubits with coherence times exceeding 0.3 milliseconds," *Nat. Commun.*, vol. 12, p. 1779, 2021.

13 J. Gao et al., "Experimental evidence for a surface distribution of two-level systems in superconducting lithographed resonators," *Applied Physics Letters*, vol. 92, p. 152505, 2008.

high T_c superconductors face severe and, in many cases, fundamental limitations.

A central challenge arises from the unconventional pairing symmetry of cuprate superconductors. Unlike conventional low T_c superconductors, which exhibit isotropic s wave pairing, cuprates are characterized by d wave order parameters with nodes in the superconducting gap. These nodes support a finite density of low energy quasi-particle excitations even at temperatures well below T_c . As a result, intrinsic dissipation mechanisms persist in the superconducting state, providing a natural channel for energy relaxation and dephasing in any qbit constructed from these materials. From the perspective of quantum coherence, this gapless or near gapless excitation spectrum is fundamentally incompatible with the long T_1 and T_2 times required for fault tolerant operation.

The materials complexity of cuprates further exacerbates these intrinsic limitations. High T_c superconductors are strongly correlated electron systems whose superconducting properties depend sensitively on oxygen stoichiometry, local strain, and chemical disorder. In YBCO, for example, small variations in the oxygen content δ can lead to substantial changes in the local superconducting gap and carrier density. This intrinsic inhomogeneity produces spatial fluctuations in superconducting properties on nanometer length scales, which translate directly into noise and dissipation for a macroscopic quantum circuit.

Interfaces and surfaces present an even more severe problem. Cuprates are chemically reactive and readily form complex, poorly controlled surface layers when exposed to ambient conditions. These layers are often non superconducting and magnetically active, hosting a high density of localized spins and charge traps. For planar qbit geometries, where electric fields are concentrated at surfaces and


interfaces, such defects would dominate the decoherence budget. Unlike aluminium or even niobium, there is no simple, self limiting oxide that can be reliably exploited as a low loss tunnel barrier for Josephson junctions. Instead, junction fabrication in cuprates typically relies on grain boundary junctions or ramp edge geometries, both of which introduce additional disorder and uncontrolled loss channels.

Josephson junction physics itself is fundamentally altered in high T_c materials. The combination of d wave pairing and strong electronic correlations leads to unconventional current phase relationships, mid-gap Andreev bound states, and enhanced sensitivity to magnetic flux and interface roughness. These effects complicate the realization of well defined, reproducible non linear circuit elements, which are essential for qbit operation. Moreover, the presence of low energy bound states at junction interfaces introduces additional dissipation channels that directly limit coherence times.

Taken together, these factors explain why, despite decades of research and impressive demonstrations of macroscopic quantum phenomena, high temperature superconductors have not emerged as viable platforms for coherent qbits. Their elevated critical temperatures do not compensate for the intrinsic dissipation associated with nodal quasiparticles, strong disorder, and chemically complex interfaces. From the standpoint of quantum information processing, coherence, not T_c , is the decisive metric. In this sense, high T_c superconductors serve as a cautionary example, illustrating that superconductivity alone is insufficient. The detailed symmetry of the order parameter, the nature of low energy excitations, and the chemical stability of surfaces and interfaces are all critical determinants of whether a material can support long lived

quantum coherent states suitable for scalable quantum computation.

4.1 d wave Symmetry and Nodes¹⁴



A defining feature of the cuprate high temperature superconductors is their unconventional pairing symmetry. Extensive experimental and theoretical work has established that materials such as $\text{YBa}_2\text{Cu}_3\text{O}_{7-\delta}$ exhibit $d_{x^2-y^2}$ pairing symmetry, in stark contrast to the isotropic s wave pairing found in conventional superconductors like aluminium and niobium. This distinction has profound consequences for quantum coherence at low energies.

In an s wave superconductor, the superconducting energy gap Δ is finite and approximately uniform over the entire Fermi surface. As a result, quasiparticle excitations are exponentially suppressed at temperatures much lower than the critical temperature, providing a clean spectral window in which coherent quantum dynamics can occur. This fully gapped excitation spectrum is one of the key reasons conventional superconductors are well suited for qbit applications.

By contrast, the d wave gap in cuprates has a strong momentum dependence. The gap function $\Delta(k)$ changes sign under a ninety degree rotation in momentum space and vanishes along nodal directions on the Fermi

surface. At these nodes, the superconducting gap goes to zero, allowing quasiparticle excitations with arbitrarily low energy. Consequently, even in the limit $T \rightarrow 0$, cuprate superconductors host a finite density of low energy quasiparticles.

From the perspective of a superconducting qbit, these nodal quasiparticles represent an intrinsic and unavoidable dissipative bath. The qbit transition couples to electronic excitations in the superconductor through both charge and phase fluctuations. In the presence of nodes, there is no true energy gap protecting the qbit from decay. Instead, the qbit can relax by emitting energy into the continuum of low energy quasiparticle states, leading to enhanced energy relaxation rates and a fundamentally limited T_1 .

Importantly, this limitation is not a consequence of imperfect fabrication or extrinsic disorder but follows directly from the symmetry of the superconducting order parameter itself. Even in a hypothetical, perfectly clean cuprate crystal with ideal interfaces, the nodal structure of the d wave gap would persist. As a result, the availability of low energy quasi particle states is a fundamental property of the material, not a technological artefact.

This intrinsic dissipation channel sharply distinguishes high temperature superconductors from conventional s wave systems in the context of quantum information processing. While cuprates can support macroscopic superconducting currents and flux quantization, the presence of gap nodes makes them ill suited as hosts for long lived quantum two level systems. In this sense, d wave symmetry represents a fundamental obstacle to the use of cuprate superconductors in coherent qbit architectures, independent of the many additional materials challenges associated with these compounds.

¹⁴ C. C. Tsuei and J. R. Kirtley, "Pairing symmetry in cuprate superconductors," *Reviews of Modern Physics*, vol. 72, p. 969, 2000.

4.2 Material Disorder¹⁵

High temperature superconductors are structurally and chemically complex ceramic materials, and this complexity introduces severe constraints on their use in quantum coherent devices. Unlike elemental superconductors such as aluminium or niobium, cuprates are multi component oxides whose superconducting properties emerge from a delicate balance of crystal structure, carrier concentration, and strong electronic correlations. This intrinsic complexity makes disorder not an incidental fabrication issue but a central feature of the material system.

A key parameter in this context is the superconducting coherence length ξ , which in cuprate superconductors is exceptionally short, typically on the order of 1 to 2 nm. Physically, ξ sets the length scale over which the superconducting order parameter can vary without significant energy cost. In materials with such a small coherence length, even atomic scale imperfections can strongly perturb the local superconducting state. Variations in oxygen stoichiometry, point defects, lattice distortions, or cation substitution can all produce substantial spatial fluctuations in the superconducting gap and phase stiffness.

This hypersensitivity to disorder has direct and severe implications for device fabrication. The Josephson junction, which provides the essential non linear inductive element for superconducting qubits, relies on precise control of the superconducting order parameter across a weak link. In conventional s wave superconductors with coherence lengths of tens of nanometres, modest interface roughness or barrier inhomogeneity can be tolerated without catastrophic consequences. In cuprates, by contrast, the relevant length scales are

comparable to the size of a few unit cells. Constructing a reproducible junction therefore requires atomic level control of the barrier interface on the scale of ξ , a requirement that is extremely difficult to meet in practice.¹⁶

As a result, Josephson junctions in high temperature superconductors are most commonly realized using grain boundary junctions, where superconducting regions with different crystallographic orientations are brought into contact. While such junctions have enabled important demonstrations of Josephson physics, they are intrinsically disordered systems. The misorientation angle between grains, local strain, and chemical inhomogeneity at the boundary all vary on nanometer scales, leading to strong spatial fluctuations in the junction transparency and critical current.

For quantum coherent circuits, this translates into several fatal shortcomings. Grain boundary junctions exhibit large parameter spread from device to device, pronounced low frequency noise, and excess dissipation. Their current phase relationships can deviate significantly from the simple sinusoidal form assumed in circuit models, and their critical currents are highly sensitive to temperature and magnetic field. These characteristics make precise frequency targeting and reproducible coupling strengths exceedingly difficult to achieve.

In multi qubit architectures, where frequency crowding and crosstalk already impose stringent design constraints, such variability is unacceptable. qubits must be fabricated with narrowly distributed parameters to allow scalable control, calibration, and error correction. The intrinsic disorder of high temperature superconductors, amplified by their

15 T. Tafuri and J. R. Kirtley, "Weak links in high critical temperature superconductors," *Reports on Progress in Physics*, vol. 68, p. 2573, 2005.

16 G. Catelani et al., "Quasiparticle relaxation of superconducting qubits in the presence of flux," *Physical Review B*, vol. 84, p. 064517, 2011.

short coherence lengths, prevents the level of precision required for such architectures¹⁷.

Taken together, these considerations underscore that the limitations of high temperature superconductors for quantum computation are not merely technological but fundamentally materials driven. The combination of extreme sensitivity to disorder, short coherence lengths, and noisy junction realizations renders HTS materials incompatible with the stringent coherence and reproducibility demands of scalable superconducting qbit platforms.

5. JOSEPHSON JUNCTIONS AS MATERIAL SYSTEMS

The Josephson junction is the defining element of superconducting qbit architectures. It is this component that introduces the necessary non linearity into an otherwise harmonic superconducting circuit, allowing us to spectrally isolate the $|0\rangle \rightarrow |1\rangle$ and $|1\rangle \rightarrow |2\rangle$ transitions and thereby define an effective two level system. From a circuit perspective, the junction is often idealized as a lossless non linear inductance characterized by a Josephson energy E_J . In practice, however, the junction is a complex nanoscale material system whose microscopic properties exert a dominant influence on qbit coherence.

In state of the art superconducting qbits, Josephson junctions are most commonly fabricated using aluminum based trilayer structures of the form Al/AlO_x/Al. Techniques such as Dolan bridge shadow evaporation or Manhattan style shadow evaporation are employed to define junctions with lateral dimensions on the order of tens to hundreds of nanometers. These methods allow for in situ oxidation of the aluminum layer to form the

tunnel barrier, followed by deposition of the counter electrode without breaking vacuum. The resulting oxide barrier is typically only one to two nanometers thick, placing the junction squarely in a regime where atomic scale disorder and interfacial chemistry are unavoidable.

From a materials perspective, the tunnel barrier is not a uniform, crystalline insulator but an amorphous aluminum oxide containing a high density of structural defects. These defects include oxygen vacancies, dangling bonds, and under coordinated aluminium atoms, many of which can act as Two Level Systems. Because the electric field across the junction is extremely strong, even a small number of such defects can couple efficiently to the qbit mode, contributing to both energy relaxation and dephasing. As a result, the Josephson junction itself often represents one of the most significant sources of loss in a superconducting qbit.

The fabrication process further influences junction quality in subtle ways. Parameters such as oxidation pressure, oxidation time, and base electrode roughness all affect the stoichiometry and defect density of the AlO_x barrier. Small variations in these parameters can lead to substantial changes in critical current density and junction transparency, introducing device to device variability. While considerable progress has been made in controlling these factors, the reproducibility required for large scale, multi qbit systems places increasingly stringent demands on junction fabrication.

It is therefore useful to view the Josephson junction not merely as a circuit element but as a nanoscale material system whose properties must be engineered with atomic precision. The non linearity that enables qbit operation arises from coherent tunneling of Cooper pairs across the barrier. At the same time, incoherent tunneling of quasiparticles and coupling to localized defect states within the barrier

¹⁷ D. J. Van Harlingen, "Phase-sensitive tests of the symmetry of the pairing state in the high-temperature superconductors," *Rev. Mod. Phys.*, vol. 67, p. 515, 1995.

introduce dissipation and noise. Balancing these competing processes is one of the central challenges in superconducting quantum hardware.

As qbit coherence times continue to improve, the relative contribution of junction related loss becomes increasingly apparent. In many modern designs, bulk dielectric and substrate losses have been sufficiently suppressed that the Josephson junction barrier itself sets the ultimate limit on T_1 . This realization reinforces the central argument of this paper. Further progress toward fault tolerant superconducting quantum computation will depend critically on our ability to engineer Josephson junctions as low loss, well controlled material systems, rather than treating them as idealized, black box circuit components.

5.1 The Amorphous Barrier Problem

At the heart of essentially all state of the art superconducting qbits lies an ultrathin amorphous tunnel barrier, typically aluminum oxide, AlO_x . While AlO_x is favored for its large bandgap and its ability to form reproducibly under controlled oxidation, its amorphous nature introduces fundamental limitations that are increasingly relevant as coherence times improve. From a quantum materials perspective, the tunnel barrier is not a passive separator but an active source of disorder and noise.

Because the AlO_x barrier lacks long range crystalline order, its thickness is not perfectly uniform across the junction area. Instead, the barrier thickness d fluctuates on atomic length scales due to local variations in oxidation, surface roughness of the aluminum electrodes, and intrinsic structural disorder in the oxide. These fluctuations have an outsized impact on junction properties because the Josephson critical current depends exponentially on the barrier thickness, $I_c \propto e^{-d/\lambda}$, where λ is an

effective decay length determined by the barrier height and electronic structure.

As a consequence, even sub nanometer variations in d lead to strong spatial inhomogeneity in the supercurrent density. Rather than flowing uniformly across the junction, the current becomes concentrated in localized regions where the barrier is thinnest. This current crowding not only enhances sensitivity to local defects but also amplifies the influence of microscopic fluctuations on macroscopic device parameters. In effect, the junction behaves as a parallel network of microchannels, each with slightly different transparency and noise characteristics.

In addition to thickness variations, the amorphous barrier hosts a spectrum of localized defect states, including pinholes, oxygen vacancies, and resonant traps. These defects can intermittently trap and release charge or quasiparticles, leading to temporal fluctuations in the effective junction transparency. Such processes give rise to low frequency, or $1/f$, noise in the critical current. In a superconducting qbit, fluctuations in I_c translate directly into fluctuations of the Josephson energy E_J , which in turn manifest as phase noise and dephasing of the qbit¹⁸.

Crucially, this noise mechanism is intrinsic to the amorphous nature of the barrier. While careful optimization of oxidation conditions can reduce defect densities, it cannot eliminate the fundamental structural disorder that gives rise to barrier inhomogeneity. As qbits are operated in regimes where sensitivity to other noise sources has been strongly suppressed, $1/f$ critical current noise originating in the junction barrier becomes an increasingly dominant contributor to decoherence.

¹⁸ S. Sendelbach et al., "Magnetism in SQUIDs at Millikelvin Temperatures," *Phys. Rev. Lett.*, vol. 100, p. 227006, 2008.

The amorphous barrier problem thus represents a fundamental materials bottleneck for superconducting qubits. It highlights the tension between the practical advantages of AlO_x junctions and their intrinsic limitations as hosts for coherent quantum dynamics. Addressing this challenge will likely require a departure from conventional amorphous tunnel barriers toward more ordered or epitaxial alternatives, or entirely new approaches to realizing low loss non linear elements. Without such innovations, the Josephson junction barrier itself will continue to set a hard limit on achievable qubit coherence.

5.2 Junction Aging and Reproducibility

Beyond its role as an immediate source of loss and noise, the amorphous tunnel barrier in conventional Josephson junctions presents a more subtle but equally serious challenge for scalable quantum processors: long term stability and reproducibility. The aluminum oxide barrier formed by in situ oxidation is not a thermodynamic ground state but a metastable amorphous phase. As a result, its microscopic structure can evolve slowly over time through diffusion and local rearrangement of oxygen and aluminum atoms, a process commonly referred to as junction aging.

This structural evolution leads to gradual changes in the effective barrier height and thickness, which in turn modify the junction's critical current I_c . Because the qubit transition frequency ω_{01} depends sensitively on the Josephson energy $E_J \propto I_c$, even small drifts in the barrier properties can produce measurable shifts in qubit frequency. In isolated devices, such frequency drift may be tolerable or correctable through recalibration. In large scale, fixed frequency transmon architectures, however, it becomes a serious systems level problem.

Fixed frequency designs rely on careful frequency allocation to avoid unwanted

resonances between neighboring qubits and between qubits and parasitic modes. Frequency collisions lead to enhanced crosstalk, leakage during gate operations, and correlated errors that are difficult to mitigate using standard control techniques. When qubit frequencies drift unpredictably over time due to junction aging, these carefully engineered frequency spacings can be compromised. The resulting errors are particularly problematic because they are not static and therefore cannot be fully compensated by calibration or software level corrections.

This issue directly impacts scalability. As the number of qubits increases, the available frequency bandwidth becomes increasingly crowded, leaving less margin for drift. In this regime, even slow, percent level changes in I_c over months or years can render a processor unusable for high fidelity operation. From this perspective, junction aging is not merely a materials curiosity but a fundamental obstacle to building stable, long lived quantum processors.

One proposed solution to this problem is the use of epitaxial tunnel barriers, such as crystalline Al_2O_3 , grown with well defined stoichiometry and long range order. In principle, a crystalline barrier represents a true thermodynamic phase with greatly reduced structural diffusion, offering improved long term stability and reproducibility. Such barriers could suppress both aging related drift and defect induced noise by eliminating much of the atomic scale disorder inherent to amorphous oxides.

In practice, however, epitaxial barriers introduce their own set of challenges. Achieving high quality epitaxial Al_2O_3 on aluminum or other superconducting electrodes requires precise control of lattice matching and interface chemistry. Lattice mismatch can introduce strain, dislocations, and interfacial defects that degrade junction performance. Moreover, early demonstrations of epitaxial barriers have often suffered from high leakage currents, indicating

the presence of pinholes or extended defects that compromise the tunnel barrier's integrity.

These tradeoffs underscore the central dilemma facing Josephson junction engineering. Amorphous barriers are relatively easy to fabricate and integrate but suffer from intrinsic disorder and long term instability. Crystalline barriers promise superior stability and potentially lower noise but are far more demanding in terms of materials growth and interface control. Resolving this tension is one of the key open challenges in superconducting quantum hardware and will likely require new materials systems, growth techniques, or entirely new approaches to implementing non linear circuit elements suitable for fault tolerant quantum computation.

6. SCALABILITY AND INTEGRATION CHALLENGES

Scaling superconducting quantum processors beyond the regime of a few dozen qubits and into architectures with $N > 1000$ qubits introduces a new class of materials challenges that are qualitatively distinct from those encountered in single qbit or small scale devices. At this level of integration, coherence is no longer determined solely by the performance of an isolated qbit, but by the uniformity, stability, and compatibility of materials across an entire chip and fabrication stack. Effects that are negligible at small scales become system limiting when replicated thousands of times.¹⁹

One of the most immediate challenges is device to device variability. Even when individual qbits exhibit excellent coherence, small statistical variations in Josephson junction properties, film thickness, or interface quality lead to a spread in qbit frequencies, anharmonicities, and coupling strengths. In a dense multi qbit architecture, this variability complicates frequency allocation and

control, increasing the likelihood of spectral crowding and unintended interactions. As the number of qbits grows, the acceptable tolerance on such variations shrinks, placing increasingly stringent demands on materials uniformity and process control at the wafer scale.

Integration also requires the introduction of additional materials that are not present in single qbit test structures. Multi layer wiring, interlayer dielectrics, crossovers, and through substrate vias are often necessary to route control and readout signals without excessive crowding. Each additional layer and interface introduces new dielectric volumes and surfaces that can host Two Level Systems and other loss mechanisms. Even if the qbit itself is well optimized, these ancillary materials can couple parasitically to the qbit mode through stray electric and magnetic fields, degrading coherence in ways that are difficult to predict or model.

Thermal and quasiparticle management present further challenges at scale. In large processors, control lines, readout resonators, and packaging elements provide multiple pathways for high energy radiation and phonons to enter the chip. A single cosmic ray event or substrate phonon burst can generate quasiparticles that spread across many qbits, producing correlated errors. Mitigating such events requires not only improved shielding and filtering but also careful materials choices that promote quasiparticle trapping and rapid recombination. These considerations become increasingly important as system size grows and error correlations become more damaging to fault tolerant protocols.

Mechanical and chemical compatibility across the full materials stack is another critical factor. Differences in thermal expansion coefficients between superconducting films, dielectrics, and substrates can introduce strain during cooldown from room temperature to millikelvin operation.

¹⁹ D. Rosenberg et al., "3D integrated superconducting qbits," *npj Quantum Information*, vol. 3, p. 42, 2017.

This strain can modify interface properties, activate defect states, or even lead to micro cracking in thin films. Over thousands of qbits, such effects can accumulate, reducing yield and long term reliability.²⁰

Finally, scalability imposes constraints on reproducibility over time. Large scale quantum processors are expected to operate reliably over months or years, not just immediately after fabrication. As discussed earlier, metastable materials such as amorphous tunnel barriers and surface oxides can evolve, leading to drift in qbit parameters. In a processor with thousands of qbits, even rare aging related failures become statistically inevitable. Ensuring long term stability therefore requires materials and interfaces that are not only low loss but also thermodynamically stable under operating conditions.

In this regime, scalability is not merely an engineering problem of connecting more qbits. It is a materials systems problem in which surfaces, interfaces, and bulk properties must be controlled with unprecedented precision and uniformity. Without advances in materials integration that address variability, loss, and long term stability simultaneously, scaling superconducting quantum processors to the sizes required for fault tolerant quantum computation will remain an elusive goal.

6.1 Three Dimensional Integration and Crosstalk

As superconducting quantum processors scale in size and complexity, purely planar integration strategies encounter fundamental limitations. In a two dimensional layout, the number of control and readout lines that can be routed to the edge of a chip is constrained by the available perimeter. For processors with hundreds or

thousands of qbits, this constraint becomes prohibitive, necessitating the adoption of three dimensional integration techniques such as through silicon vias and flip chip bonding to separate qbit planes from control and readout circuitry.

While three dimensional integration offers a path to increased wiring density and improved scalability, it introduces a new set of materials and coherence challenges. Through silicon vias must be fabricated with superconducting liners or fills that remain lossless at millikelvin temperatures and microwave frequencies. In practice, this requirement is difficult to satisfy. Imperfections at the via sidewalls, residual normal metal regions, or poor interfaces between the superconducting fill and the silicon substrate can introduce dissipation and act as sources of quasiparticle generation.

Flip chip bonding further complicates the materials landscape. Superconducting bump bonds, most commonly made from indium, are used to establish electrical and mechanical connections between stacked chips. These bonds must remain superconducting, mechanically stable, and low loss under repeated thermal cycling. Indium is soft and chemically reactive, and its surfaces readily oxidize, potentially forming lossy interfacial layers. Any resistive or dielectric loss introduced at the bump bonds can couple directly into control lines and resonators, degrading qbit performance in ways that are difficult to isolate experimentally.

The use of interposer substrates, which often sit between the qbit chip and the control chip, adds yet another source of loss. Interposers introduce additional dielectric volume in close proximity to the qbits, increasing the participation ratio of surfaces and interfaces that may host Two Level Systems. Even if the bulk interposer material has a low intrinsic loss tangent, the large surface area associated with vias, metallization, and

²⁰ D. R. W. Yost et al., "Solid-state qbits with through-silicon vias," *npj Quantum Information*, vol. 6, p. 59, 2020.

bonding interfaces can dominate the overall dielectric loss budget.

Electromagnetic crosstalk presents a parallel challenge that becomes increasingly severe in dense three dimensional wiring environments. Control and readout lines routed in close proximity can couple capacitively and inductively, leading to unintended drive of neighboring qubits or leakage into sensitive resonators. For high fidelity gate operations, the required isolation between channels can exceed 100 dB across relevant frequency bands. Achieving such isolation demands meticulous impedance matching, shielding, and ground plane engineering at the chip and package level.

These requirements are further complicated by the kinetic inductance of the thin superconducting films typically used for wiring. In narrow or thin conductors, kinetic inductance can become comparable to or even dominate the geometric inductance, altering signal propagation, impedance, and crosstalk in ways that are difficult to predict using classical microwave design alone. Variations in film thickness or microstructure across a wafer can therefore translate into non uniform wiring properties, undermining efforts to achieve consistent isolation across a large processor²¹.

Together, these factors illustrate that three dimensional integration is not a simple extension of planar design but a fundamentally new materials and electromagnetic problem. Successfully scaling superconducting quantum processors will require integrated solutions that simultaneously address superconductivity, dielectric loss, mechanical stability, and microwave isolation. Without such solutions, the benefits of three dimensional integration risk being offset by increased decoherence and

crosstalk, limiting the practical scalability of superconducting quantum computing platforms.

6.2 Thermal Load and Cryogenic Compatibility

Signal delivery infrastructure constitutes a critical bottleneck in the cryogenic operation of superconducting quantum processors, as it forms the dominant thermal link between the ambient environment and the millikelvin stage. Microwave control and readout signals are typically routed from room temperature to the qubit plane through a hierarchy of coaxial cables, attenuators, filters, and coaxial-to-planar transitions. Each of these elements contributes both conductive and radiative thermal loads, which must be carefully managed to remain within the limited cooling power of dilution refrigerators at temperatures below 20 mK.

The thermal conductivity of interconnect materials plays a central role in determining the achievable qubit density and wiring complexity. Metallic coaxial cables fabricated from high-conductivity materials such as copper or silver provide excellent microwave performance but impose an excessive conductive heat load when directly connected to the coldest stages. As a result, practical architectures rely on stainless steel, cupronickel, or superconducting coaxial lines that suppress electronic thermal transport at low temperatures. Even with these mitigations, the cumulative thermal load from tens to hundreds of signal lines becomes a limiting factor for large-scale integration, necessitating aggressive thermal anchoring at intermediate temperature stages and careful optimization of cable geometry and material composition.

At the chip level, coaxial-to-planar transitions introduce additional constraints. These transitions must provide broadband impedance matching while minimizing parasitic loss and stray coupling, all under severe thermal and

21 F. Arute et al., "Quantum supremacy using a programmable superconducting processor," *Nature*, vol. 574, pp. 505-510, 2019.

mechanical constraints. Planar transmission lines such as coplanar waveguides or microstrip resonators are typically patterned from superconducting thin films to eliminate ohmic dissipation at millikelvin temperatures. However, the choice of superconducting material directly affects both the electromagnetic properties and the thermal budget of the system. Materials with high kinetic inductance, including NbTiN and granular aluminum, enable compact resonator designs and enhanced impedance engineering, which are advantageous for dense frequency multiplexing and strong qubit–resonator coupling.

The integration of high kinetic inductance superconductors with low-loss qubit materials presents substantial fabrication challenges. qubit coherence requirements impose stringent limits on dielectric loss, interface roughness, and chemical contamination. Multi-layer fabrication stacks that combine different superconductors, dielectrics, and normal-metal components often require multiple deposition, lithography, and etching steps. Each additional processing step increases the probability of introducing interface defects, trapped charges, or residual contamination, all of which can act as sources of two-level system noise and contribute to excess dissipation. In particular, the interfaces between high kinetic inductance films and conventional low-loss superconductors such as aluminum or niobium are susceptible to interdiffusion and the formation of disordered interfacial layers, which degrade both superconducting and dielectric properties.

From a cryogenic compatibility perspective, mechanical stress and differential thermal contraction across heterogeneous material stacks further complicate device reliability. Cooling from room temperature to the millikelvin regime induces significant strain due to mismatched thermal expansion coefficients

among substrates, superconducting films, and dielectric layers. These stresses can lead to microcracks, delamination, or changes in film morphology, thereby reducing fabrication yield and long-term device stability. Such effects become increasingly pronounced as device complexity and wafer-scale integration are pursued.

Overall, thermal load management and cryogenic compatibility impose tightly coupled constraints on materials selection, interconnect design, and fabrication strategy. While high kinetic inductance superconductors offer compelling electromagnetic advantages, their incorporation into scalable quantum processor architectures requires careful balancing of thermal conductivity, microwave performance, and materials purity. Continued progress in this area will depend on advances in low-thermal-conductivity interconnects, improved interface engineering, and fabrication techniques that minimize contamination while maintaining compatibility with complex multi-layer superconducting device stacks.

7. IMPLICATIONS FOR FAULT-TOLERANT QUANTUM COMPUTING

The implementation of fault-tolerant quantum computing relies fundamentally on the principles formalized by the threshold theorem. According to this theorem, provided that the physical error rates of qubits, denoted as p , remain below a critical threshold p_{th} , logical qubits encoded via surface codes or other topological error-correcting schemes can achieve arbitrarily low error probabilities. In practical terms, this threshold is often on the order of 10^{-2} , meaning that qubits must maintain exceptionally high fidelity in the presence of environmental decoherence, control imperfections, and residual noise. However, the theorem implicitly assumes that noise is local and uncorrelated across qubits, an assumption

that is increasingly challenged by real materials and device environments.²²

Material defects and extrinsic perturbations introduce error mechanisms that are neither local nor statistically independent. For instance, high-energy radiation events, including cosmic rays and natural radioactivity within the substrate, can deposit substantial energy into the silicon lattice, generating coherent phonon bursts that propagate across the chip. These phonons can simultaneously excite multiple qubits, inducing correlated relaxation and dephasing events that violate the independence assumption central to conventional topological codes. Experimental observations have demonstrated that such "fatal" events can cause the near-simultaneous decoherence of large qubit subsets, thereby producing logical errors that cannot be corrected by surface codes regardless of code distance or concatenation level. The spatial and temporal correlation of these events imposes a fundamental limit on achievable logical error suppression and, by extension, on the scalability of fault-tolerant architectures.

In addition to correlated error sources, intrinsic material limitations constrain qubit coherence times, particularly the energy relaxation time T_1 . If the baseline material-induced noise floor restricts T_1 such that the idle qubit error rate approaches the surface code threshold, the required code distance d to maintain logical qubit lifetimes sufficient for computational tasks becomes impractically large. Scaling to code distances in excess of tens or hundreds of physical qubits per logical qubit imposes severe overheads in fabrication, wiring, and cryogenic cooling, effectively rendering the quantum processor nonviable for near-term applications. Consequently, improvements in material quality, interface engineering, and substrate purification

are not merely incremental optimizations; they constitute an essential prerequisite for the realization of practically fault-tolerant quantum computing.

Therefore, the pursuit of scalable, high-fidelity quantum processors must treat materials science as a core component of architecture design rather than a secondary consideration. Advanced materials that mitigate correlated decoherence, suppress two-level system defects, and extend T_1 and T_2 coherence times directly expand the feasible operating window for surface codes and related error-correcting protocols. Only through such integrated efforts can fault-tolerant quantum computing move from theoretical plausibility toward practical, large-scale implementation.

8. OPEN PROBLEMS & FUTURE DIRECTIONS

Advancing the coherence and scalability of superconducting qubits requires a fundamental rethinking of materials paradigms that have dominated the field to date. Standard amorphous oxides, widely used in Josephson junctions and dielectric layers, introduce two-level system defects that remain a primary source of decoherence. Overcoming these limitations necessitates the development of novel materials strategies that target both intrinsic and extrinsic sources of loss.

Crystalline Interfaces: One promising direction is the fabrication of epitaxially grown superconductor-dielectric heterostructures²³. By achieving lattice-matched, atomically ordered interfaces, it is possible to substantially suppress the density of two-level system defects that originate at disordered amorphous boundaries. Candidate material systems include Re/Al₂O₃

22 C. D. Wilen et al., "Correlated charge noise and relaxation errors in superconducting qubits," *Nature*, vol. 594, pp. 369–373, 2021.

23 A. Megrant et al., "Planar superconducting resonators with internal quality factors above one million," *Applied Physics Letters*, vol. 100, p. 113510, 2012.

heterostructures as well as entirely nitride-based junctions such as NbN/AlN/NbN. These materials offer the potential for high kinetic inductance, robust superconducting gaps, and low microwave loss. However, minimizing dielectric loss while maintaining reliable junction formation presents substantial technical challenges, particularly when integrating these layers with low-loss qbit electrodes. Controlled growth, interface passivation, and post-deposition annealing are all areas requiring systematic investigation to realize the theoretical advantages of these structures.

Substrate Engineering: Another strategy to mitigate dielectric-induced decoherence is to minimize or eliminate substrate participation altogether. Membrane-based qbit architectures²⁴, in which the qbit is suspended above the substrate in vacuum, represent a radical departure from conventional planar fabrication. This approach removes the dominant lossy dielectric contributions of the bulk substrate and allows the qbit to interact predominantly with free space and carefully engineered electromagnetic environments. Nevertheless, this architecture introduces new challenges, including mechanical resonances of the membrane that couple to qbit dynamics and the risk of structural instability. Precise phonon engineering and stabilization mechanisms are therefore essential to ensure that the benefits of substrate removal outweigh the new sources of decoherence introduced.

Alternative Superconductors: Materials selection remains a critical lever for improving qbit lifetimes. Recent studies have shown that tantalum²⁵ films can achieve significantly higher

coherence times compared to aluminum or niobium in certain device geometries. This observation suggests that refractory metals with naturally low-loss surface oxides may provide a pathway toward intrinsically more coherent qbits. Systematic exploration of these materials, including the identification of suitable deposition conditions, native oxide control, and interface quality, is a pressing research objective. Extending this exploration to other refractory metals and alloys may reveal additional candidates for next-generation superconducting qbits.

AI-Driven Discovery: Computational approaches, particularly machine learning and artificial intelligence, offer emerging opportunities to accelerate materials discovery. While parameter optimization using machine learning is becoming increasingly common, the application of these tools to the ab initio identification of low-loss dielectrics remains at an early stage. A major challenge lies in the complex relationship between atomic structure and two-level system density at millikelvin temperatures. Accurately modeling the many-body quantum dynamics that govern TLS formation and interaction with superconducting circuits is computationally demanding and currently intractable for large systems. Nevertheless, AI-driven frameworks capable of predicting structure-property relationships, screening candidate materials, and guiding experimental synthesis represent a promising frontier in the quest to overcome fundamental decoherence limits.

In summary, the convergence of advanced materials synthesis, substrate engineering, novel superconductors, and AI-driven discovery defines the next horizon in superconducting quantum computing. Each approach addresses a complementary facet of the decoherence problem, and only through an integrated strategy that combines materials innovation with

24 K. Cicak et al., "Low-loss vacuum-gap capacitance for superconducting circuits," *Applied Physics Letters*, vol. 96, p. 092502, 2010.

25 A. P. M. Place et al., "New material platform for superconducting transmon qbits with coherence times exceeding 0.3 milliseconds," *Nature Communications*, vol. 12, p. 1779, 2021.

precise fabrication and characterization can scalable, high-fidelity quantum processors be realized.

9. CONCLUSION

The pursuit of superconducting quantum computation is inseparable from the materials science that underpins it. While the transmon architecture has successfully addressed charge noise, the field has now reached a stage where further performance gains are dictated not by circuit design alone but by the microscopic properties of the materials themselves. Surface oxides, the pervasive presence of two-level systems, and the subtle dynamics of non-equilibrium quasiparticles collectively define the coherence limits of today's devices. Even high-T_c superconductors, despite their intrinsically large energy gaps, remain largely unsuitable due to d-wave pairing symmetry and structural disorder inherent in ceramic films. The Josephson junction, often treated as a simple, idealized element in circuit models, is in reality a complex and disordered material system. Fluctuations at the atomic scale within these junctions pose genuine challenges to achieving reliable error correction and sustaining fault-tolerant operation.

Looking forward, progress will be determined less by the cleverness of new Hamiltonian designs and more by the careful, patient elimination of microscopic disorder. Success in this domain will require a combination of precise interface engineering, meticulous materials purification, and rigorous control over fabrication processes. Achieving fault-tolerant quantum computing will therefore represent not only a triumph of quantum circuit design but also a profound victory for the discipline of materials science, demonstrating the power of harmonizing solid-state physics with the delicate demands of quantum information. It is through this union of physical insight,

experimental craftsmanship, and materials mastery that the promise of scalable, high-fidelity quantum computation can ultimately be realized.

10. REFERENCES

- [1] J. Koch et al., "Charge-insensitive qubit design derived from the Cooper pair box," *Phys. Rev. A*, vol. 76, p. 042319, 2007.
- [2] H. Paik and K. D. Osborn, "Reducing quantum-regime dielectric loss of silicon nitride for superconducting quantum circuits," *Appl. Phys. Lett.*, vol. 96, p. 072505, 2010.
- [3] M. H. Devoret and R. J. Schoelkopf, "Superconducting Circuits for Quantum Information: An Outlook," *Science*, vol. 339, pp. 1169–1174, 2013.
- [4] C. Müller, J. H. Cole, and J. Lisenfeld, "Towards understanding two-level-systems in amorphous solids: insights from quantum circuits," *Rep. Prog. Phys.*, vol. 82, p. 124501, 2019.
- [5] J. M. Martinis et al., "Decoherence in Josephson qubits from Dielectric Loss," *Phys. Rev. Lett.*, vol. 95, p. 210503, 2005.
- [6] P. J. de Visser et al., "Number fluctuations of quasiparticles in a superconductor," *Phys. Rev. Lett.*, vol. 106, p. 167004, 2011.
- [7] A. P. Vepsäläinen et al., "Impact of ionizing radiation on superconducting qubit coherence," *Nature*, vol. 584, pp. 551–556, 2020.
- [8] J. M. Martinis, "Saving superconducting quantum processors from decay and correlated errors," *npj Quantum Inf.*, vol. 7, p. 90, 2021.
- [9] M. V. Gurevich, "Theory of superconductivity in composite systems," *Phys. Rev. B*, vol. 67, p. 184515, 2003.
- [10] W. A. Phillips, "Tunneling states in amorphous solids," *J. Low Temp. Phys.*, vol. 7, pp. 351–360, 1972.
- [11] C. D. Wilen et al., "Correlated charge noise and relaxation errors in superconducting qubits," *Nature*, vol. 594, pp. 369–373, 2021.
- [12] A. P. M. Place et al., "New material

- platform for superconducting transmon qubits with coherence times exceeding 0.3 milliseconds," *Nat. Commun.*, vol. 12, p. 1779, 2021.
- [13] J. Gao et al., "Experimental evidence for a surface distribution of two-level systems in superconducting lithographed resonators," *Appl. Phys. Lett.*, vol. 92, p. 152505, 2008.
- [14] C. C. Tsuei and J. R. Kirtley, "Pairing symmetry in cuprate superconductors," *Rev. Mod. Phys.*, vol. 72, p. 969, 2000.
- [15] T. Tafuri and J. R. Kirtley, "Weak links in high critical temperature superconductors," *Rep. Prog. Phys.*, vol. 68, p. 2573, 2005.
- [16] G. Catelani et al., "Quasiparticle relaxation of superconducting qubits in the presence of flux," *Phys. Rev. B*, vol. 84, p. 064517, 2011.
- [17] D. J. Van Harlingen, "Phase-sensitive tests of the symmetry of the pairing state in the high-temperature superconductors," *Rev. Mod. Phys.*, vol. 67, p. 515, 1995.
- [18] S. Sendelbach et al., "Magnetism in SQUIDs at Millikelvin Temperatures," *Phys. Rev. Lett.*, vol. 100, p. 227006, 2008.
- [19] D. Rosenberg et al., "3D integrated superconducting qubits," *npj Quantum Inf.*, vol. 3, p. 42, 2017.
- [20] D. R. W. Yost et al., "Solid-state qubits with through-silicon vias," *npj Quantum Inf.*, vol. 6, p. 59, 2020.
- [21] F. Arute et al., "Quantum supremacy using a programmable superconducting processor," *Nature*, vol. 574, pp. 505–510, 2019.
- [22] A. Megrant et al., "Planar superconducting resonators with internal quality factors above one million," *Appl. Phys. Lett.*, vol. 100, p. 113510, 2012.
- [23] K. Cicak et al., "Low-loss vacuum-gap capacitance for superconducting circuits," *Appl. Phys. Lett.*, vol. 96, p. 092502, 2010.
- [24] C. D. Wilen et al., "Correlated charge noise and relaxation errors in superconducting qubits," *Nature*, vol. 594, pp. 369–373, 2021.
- [25] A. P. M. Place et al., "New material platform for superconducting transmon qubits with coherence times exceeding 0.3 milliseconds," *Nat. Commun.*, vol. 12, p. 1779, 2021. (duplicate cited separately for Tantalum qubits)