

Assignment - 7

Transform Analysis of LTI Systems

March 31, 2018

Task 1

Consider the following LTI system:

$$H(z) = \frac{(z^{-1} - 0.9e^{-j0.2\pi})(z^{-1} - 0.9e^{j0.2\pi})}{(1 - 0.9e^{j0.2\pi}z^{-1})(1 - 0.9e^{-j0.2\pi}z^{-1})}.$$

Also, consider the following input $x[n]$:

$$x[n] = \text{sinc}\left(\frac{\pi(n-30)}{16}\right) \cos(\omega_0 n), 0 \leq n \leq 60.$$

Questions

1. Plot the magnitude response, phase response (unwrapped), phase response (principal value) and group delay of the system. For group delay, it is already known that a close approximation to the derivative of a signal is using the following scaled difference equation on its sampled version:

$$(y[nT] - y[(n-1)T])/T,$$

where T is the sampling interval of the signal. How much group delay is present for signals around frequencies $0.2\pi, 0.4\pi, 0.9\pi$, all in radians per sample?

2. Draw the spectrum of $x[n]$ for $\omega_0 = 0.2\pi, 0.4\pi, 0.9\pi$. What is the effect of changing ω_0 on the spectrum of $x[n]$.
3. Pass $x[n]$ through the system for the three values of ω_0 ? Did you see any change in the signal in the corresponding output? Do you see any change in the signal envelope at the output? Give reason for any change in the output corresponding to the three inputs.

The lab manual is exclusively for the students of the University of Engineering and Technology, Lahore. © 2018 UET Lahore.