Multimedia
Fall 2019
Lecture 3
JPEG

Dr. Mona Soliman

IT Dept.

JPEG


JPEG Compression
Color Transform
Down-sampling
Forward DCT
Quantization
Encoding
JPEG-Compressed Image Data
Raw Image Data
Color Transform
Up-sampling
Inverse DCT
De-quantization
Decoding
JPEG Decompression

4-JPEG: ENCODING

1. DC encoding
2. ZigZag order
3. AC encoding

DC TERM OF DCT COEFFICIENTS

- The first element in each transformed block is the DC coefficient Term
- DC term is a measure of the average of spatial block values (e.g luminance)
- The changes in DC coefficients values of consecutive blocks is small
- The DC coefficients are coded separately from the AC ones.
- ***Differential encoding*** (DPCM) is applied on all DC coefficients

DIFFERENTIAL ENCODING OF DC TERMS



Image in Spatial Domain
(Divided into Blocks each of 8x8 pixels)



Image in Frequency Domain
(Divided into DCT Blocks each of 8x8 pixels)

DC Terms of the Whole Image
(To be Compressed as Differential Coding)

ZIGZAG SCAN OF DCT COEFFICIENTS AFTER QUANTIZATION

0	1	5	6	14	15	27	28
2	4	7	13	16	26	29	42
3	8	12	17	25	30	41	43
9	11	18	24	31	40	44	53
10	19	23	32	39	45	52	54
20	22	33	38	46	51	55	60
21	34	37	47	50	56	59	61
35	36	48	49	57	58	62	63

- Transform Coefficients
  - DC coefficient
  - AC coefficients



The DC coefficient and lower-frequency AC coefficients, both horizontal and vertical, are scanned first

HOW TO READ ZIGZAG ORDER?? EXAMPLE

ENCODING OF AC COEFFICIENTS

- The remaining 63 values in the vector are the AC coefficients

- Run Lenght Coding (RLE) followed by Entrpy Coding “Huffman” is applied on the AC coefficients.

- In RLE, AC coefficients are divided into pairs; each pair is made up of (*skip, value*) where skip is the number of zeros in the run and value is the next Non-Zero Value.

  {#-zeros-to-skip , next non-zero value}.

Encoding of AC Coefficients "Steps"

1. Read AC coefficients in Zigzag order
2. Apply Run Length Code (*Use category number from category table not number it self*)
3. Apply Huffman coding on output of Run Length Code
4. Coding using Huffman code and additional bits

RLE, CATEGORIES TABLE



Note: ***MSB of -ive "Additional Bits" is "0"***
MSB of +ive "additional Bits" is "1"



Category	AC coefficient values	Additional Bits
1	-1,1	0,1
2	-3,-2,2,3	00,01,10,11
3	-7...-4,4...7	000,001,010,011,100,101,110,111
4	15...-8,8...15	0000,0001,0010, 0011,.....
5	-31...-16,16...31	
6	-63...-32,32...63	
7	-127...-33,33...127	
8	-255...-128,128...255	
9	-511...-256,256...511	
10	-1023...-512,512...1023	

RLE- HUFFMAN ENCODING FOR JPEG

Example:

-2,0,0,2,0,0,3,2,0,1,0,0,-2,0,-1,0,0,1,0,0,-1,000000000.....0000

RLE- HUFFMAN ENCODING FOR JPEG

Encoding

Huffman Table

0/2	10
1/1	010
2/1	11
2/2	00
EOB	011



Compressed Size =37 Bits

RLE- HUFFMAN ENCODING FOR JPEG

Decoding



0/2	10
1/1	010
2/1	11
2/2	00
EOB	011

COMPRESSED/DECOMPRESSED IMAGE

Figure 2 – Peppers



Figure 3 – DCT of Peppers



Figure 4 – Quantized DCT of Peppers

Figure 6 – Quality 50 – 84% Zeros

Figure 7 – Quality 20 – 91% Zeros

Figure 8 – Quality 10 – 94% Zeros

JPEG ENCODING



The Encoder model of JPEG compression standard

JPEG DECODING