SAO SKETCH – OLED VERSION



SAO PORT (6-pin, 2x3, 0.1 inch spacing, male pins)
    https://hackaday.io/project/175182-simple-add-ons-sao
    Adam Tech BHR-06-VUA male, polarized header
    https://www.digikey.com/en/products/detail/adam-tech/BHR-06-VUA/10414837

OLED DISPLAY (Address 0x3C, 128 x 128 pixel, 1.5 inch, 16 shade grayscale, SSD1327 controller)
    https://learn.adafruit.com/adafruit-grayscale-1-5-128x128-oled-display
    Optional address 0x3D selectable by moving resistor in upper left on the back of the blue OLED board.

ACCELEROMETER (Address 0x19, STM LIS3DHTR, 3-axis)
    https://learn.sparkfun.com/tutorials/lis3dh-hookup-guide/all
    CS is high for I2C mode.
    ADC theoretical input range is 0.8 to 1.6 V (aka 1.2 +/- .4)
    ADC 1 and 2 used for potentiometers. ADC3 for internal temperature.
    Optional address 0x18 if R3 (SA0 high) is moved to R4 position (SA0 low).

OPTIONAL JP3 & JP4 CONFIG
    Solder pads 1-2 to connect accelerometer inerrupt output pins to SAO GPIO 1&2.
    Solder pads 2-3 to connect analog potentiometer outputs to SAO GPIO 1&2

POTENTIOMETERS/ANALOG KNOBS (Accessed through accelerometer)
    Left pot connected to accelerometer input ADC1.
    Right pot connected to accelerometer input ADC2.

All non-polarized capacitors are X7R or X5R ceramic unless otherwise noted.

https://hackaday.io/project/197581-etch-sao-sketch

Concept and design by Andy Geppert @ www.MachineIdeas.com

Sheet: /
File: SAO_Sketch.kicad_sch

Title: SAO Sketch – OLED Version

Size: A	Date: 2024-12-10	**Rev: 1.2**
KiCad E.D.A. 8.0.4		Id: 1/1