


Cisco Power Calculator -Power Results



Disclaimer: The Cisco Power Calculator is intended to be an educational resource and a starting point in planning your power requirement; it is not a final recommendation from Cisco. This tool does not check for software compatibility. To determine the power requirements and software most appropriate for your company we suggest you work with a Cisco representative, Cisco channel partner or a solutions provider.

Product Family:Catalyst 6800

Power Consumption/Heat Dissipation Summary			
Slot	Line Card	Optional DFC	Power Over Ethernet Capabilities
1	C6880-X-LE-16P10G	--	--
2	C6880-X-LE-16P10G	--	--
3	C6880-X-LE-16P10G	--	--
4	C6880-X-LE-16P10G	--	--
5	WS-C6880-X-LE	--	--
Minimum Power Supply		Percentage Of Power Used	
Two C6880-X-3KW-DC in Combined Mode		80.15 % 	
Total Output Current(@50V)	Total Output Power	Total Typical Output Power	Total Heat Dissipation
37.40 Amps	1870.00 Watts	1496.00 Watts	8629.79 BTU/Hr


Quick Facts



Selected Chassis	WS-C6880-X-LE
Selected Supervisor Engine	WS-C6880-X-LE
Selected Voltage	-60 Volts DC
Selected FanTray	WS-C6880-X-FAN
Chassis Slots	5
Power Supply Options	Two C6880-X-3KW-DC in Combined Mode
Line Card Slots	4
Rack Units	5

WARNING :

Combined mode does not provide power supply redundancy. In combined mode, if one of the power supplies fails, the system will power down modules until the system power allocation is under the power budget of the remaining power supply

Power Supply Details				
Minimum Power Supply	Percentage of Power used	Total Output Current(@50V) for This PSU(A)	Total Output Current(@50V) Used (A)	Total Output Current(@50V) Remaining (A)
Two C6880-X-3KW-DC in Combined Mode	80.15 % 	46.66	37.40	9.26

Configuration Details					
Slot	Line Card	Output Current(@42V) (A)	Output Power (W)	Typical Power Used (W)	Heat Dissipation (BTU/Hr)
FAN1	WS-C6880-X-FAN	4.00	200.00	160.00	922.97
1	C6880-X-LE-16P10G	6.20	310.00	248.00	1430.61
2	C6880-X-LE-16P10G	6.20	310.00	248.00	1430.61
3	C6880-X-LE-16P10G	6.20	310.00	248.00	1430.61
4	C6880-X-LE-16P10G	6.20	310.00	248.00	1430.61
5	WS-C6880-X-LE	8.60	430.00	344.00	1984.39
		Output Current(@42V) (A)	Output Power (W)	Typical Power Used (W)	Heat Dissipation (BTU/Hr)
	Total	37.40	1870.00	1496.00	8629.79

PLEASE REFER TO THE NOTES PAGE FOR IMPORTANT INFORMATION :

NOTE :

- The Catalyst 6880 backplane power connectors for the linecards, fan trays and Supervisors operate at 50V. The power supplies take the power from the source and convert it into a 50V feed for these power connectors.
- Output Power is the amount of power delivered from the Power Supply to the Catalyst 6880. To figure Input Power, divide output power by .85 (typical efficiency of the power supplies).
- Output Power and Heat Dissipation numbers computed by the Cisco Power Calculator are maximum values and can be used for facility power and cooling capacity planning. These figures are not indicative of the actual power draw or heat dissipation. Typical power draw is about 20% lower than the maximum value shown. Also note that most of power allocated for PoE devices is dissipated at the end points.
- Output from the Cisco Power Calculator may not match the output from "show power" or certain "show energywise" commands due to the way the system dynamically allocates power for PoE device bootup. This dynamically allocated power will not affect the overall selection of the proper power supply by the Cisco Power Calculator.
- The Power Calculator attempts to provide the power budget rules employed in the latest software releases. It does not account for changes in the power management software made in previous versions. Please consult the power management section of the Release Notes for a history of changes to the software power management operation.