TABLE 4.2 BASIC FOURIER TRANSFORM PAIRS

Signal	Fourier transform	Fourier series coefficients (if periodic)
$\sum_{k=-\infty}^{+\infty} a_k e^{jk\omega_0 t}$	$2\pi \sum_{k=-\infty}^{+\infty} a_k \delta(\omega - k\omega_0)$	a_k
$e^{j\omega_0 t}$	$2\pi\delta(\omega-\omega_0)$	$a_1 = 1$ $a_k = 0$, otherwise
$\cos\omega_0 t$	$\pi[\delta(\omega-\omega_0)+\delta(\omega+\omega_0)]$	$a_1 = a_{-1} = \frac{1}{2}$ $a_k = 0$, otherwise
$\sin\omega_0 t$	$\frac{\pi}{j}[\delta(\omega-\omega_0)-\delta(\omega+\omega_0)]$	$a_1 = -a_{-1} = \frac{1}{2j}$ $a_k = 0$, otherwise
$x(t) = 1$	$2\pi\delta(\omega)$	$a_0 = 1,\ a_k = 0,\ k \neq 0$ (this is the Fourier series representation for any choice of $T > 0$)
Periodic square wave $x(t) = \begin{cases} 1, & \lvert t\rvert < T_1 \\ 0, & T_1 < \lvert t\rvert \le \frac{T}{2} \end{cases}$ and $x(t+T) = x(t)$	$\sum_{k=-\infty}^{+\infty} \frac{2\sin k\omega_0 T_1}{k}\delta(\omega - k\omega_0)$	$\frac{\omega_0 T_1}{\pi}\,\mathrm{sinc}\left(\frac{k\omega_0 T_1}{\pi}\right) = \frac{\sin k\omega_0 T_1}{k\pi}$
$\sum_{n=-\infty}^{+\infty}\delta(t-nT)$	$\frac{2\pi}{T}\sum_{k=-\infty}^{+\infty}\delta\left(\omega - \frac{2\pi k}{T}\right)$	$a_k = \frac{1}{T}$ for all k
$x(t)\begin{cases} 1, & \lvert t\rvert < T_1 \\ 0, & \lvert t\rvert > T_1 \end{cases}$	$\frac{2\sin\omega T_1}{\omega}$	—
$\frac{\sin Wt}{\pi t}$	$X(j\omega) = \begin{cases} 1, & \lvert\omega\rvert < W \\ 0, & \lvert\omega\rvert > W \end{cases}$	—
$\delta(t)$	1	—
$u(t)$	$\frac{1}{j\omega} + \pi\delta(\omega)$	—
$\delta(t-t_0)$	$e^{-j\omega t_0}$	—
$e^{-at}u(t),\ \mathcal{R}e\{a\} > 0$	$\frac{1}{a+j\omega}$	—
$te^{-at}u(t),\ \mathcal{R}e\{a\} > 0$	$\frac{1}{(a+j\omega)^2}$	—
$\frac{t^{n-1}}{(n-1)!}e^{-at}u(t)$, $\mathcal{R}e\{a\} > 0$	$\frac{1}{(a+j\omega)^n}$	—

TABLE 4.1 PROPERTIES OF THE FOURIER TRANSFORM

Section	Property	Aperiodic signal	Fourier transform
		$x(t)$ $y(t)$	$X(j\omega)$ $Y(j\omega)$
4.3.1	Linearity	$ax(t) + by(t)$	$aX(j\omega) + bY(j\omega)$
4.3.2	Time Shifting	$x(t-t_0)$	$e^{-j\omega t_0}X(j\omega)$
4.3.6	Frequency Shifting	$e^{j\omega_0 t}x(t)$	$X(j(\omega-\omega_0))$
4.3.3	Conjugation	$x^*(t)$	$X^*(-j\omega)$
4.3.5	Time Reversal	$x(-t)$	$X(-j\omega)$
4.3.5	Time and Frequency Scaling	$x(at)$	$\frac{1}{\lvert a\rvert}X\left(\frac{j\omega}{a}\right)$
4.4	Convolution	$x(t) * y(t)$	$X(j\omega)Y(j\omega)$
4.5	Multiplication	$x(t)y(t)$	$\frac{1}{2\pi}\int_{-\infty}^{+\infty}X(j\theta)Y(j(\omega-\theta))d\theta$
4.3.4	Differentiation in Time	$\frac{d}{dt}x(t)$	$j\omega X(j\omega)$
4.3.4	Integration	$\int_{-\infty}^{t}x(t)dt$	$\frac{1}{j\omega}X(j\omega) + \pi X(0)\delta(\omega)$
4.3.6	Differentiation in Frequency	$tx(t)$	$j\frac{d}{d\omega}X(j\omega)$
4.3.3	Conjugate Symmetry for Real Signals	$x(t)$ real	$\begin{cases} X(j\omega) = X^*(-j\omega) \\ \mathcal{R}e\{X(j\omega)\} = \mathcal{R}e\{X(-j\omega)\} \\ \mathcal{I}m\{X(j\omega)\} = -\mathcal{I}m\{X(-j\omega)\} \\ \lvert X(j\omega)\rvert = \lvert X(-j\omega)\rvert \\ \sphericalangle X(j\omega) = -\sphericalangle X(-j\omega) \end{cases}$
4.3.3	Symmetry for Real and Even Signals	$x(t)$ real and even	$X(j\omega)$ real and even
4.3.3	Symmetry for Real and Odd Signals	$x(t)$ real and odd	$X(j\omega)$ purely imaginary and odd
4.3.3	Even-Odd Decomposition for Real Signals	$x_e(t) = \mathcal{E}v\{x(t)\}\quad [x(t)\text{ real}]$ $x_o(t) = \mathcal{O}d\{x(t)\}\quad [x(t)\text{ real}]$	$\mathcal{R}e\{X(j\omega)\}$ $j\mathcal{I}m\{X(j\omega)\}$

4.3.7 Parseval's Relation for Aperiodic Signals

$$\int_{-\infty}^{+\infty}\lvert x(t)\rvert^2 dt = \frac{1}{2\pi}\int_{-\infty}^{+\infty}\lvert X(j\omega)\rvert^2 d\omega$$

Discrete Fourier Transform Pairs and Properties (info)

Definition Discrete Fourier Transform and its Inverse

Let x[n] be a periodic DT signal, with period N.

N-point Discrete Fourier Transform $X[k] = \sum_{n=0}^{N-1} x[n]e^{-j2\pi\frac{kn}{N}}$

Inverse Discrete Fourier Transform $x[n] = (1/N)\sum_{k=0}^{N-1} X[k]e^{j2\pi\frac{kn}{N}}$

$e^{j2\pi k_0 n}$	$N\delta[((k-k_0))_N]$
$\cos(\frac{2\pi}{N}k_0 n)$	$\frac{N}{2}(\delta[((k-k_0))_N] + \delta[((k+k_0))_N])$

IVT: $x(0) = \lim_{z\to\infty} X(z)$

FVT: $x(\infty) = \lim_{z\to 1} X(z)(1-z^{-1})$

IVT: $x(0) = \lim_{s\to\infty} sX(s)$

FVT: $x(\infty) = \lim_{s\to 0} sX(s)$

TABLE 5.2 BASIC DISCRETE-TIME FOURIER TRANSFORM PAIRS

Signal	Fourier Transform	Fourier Series Coefficients (if periodic)
$\sum_{k=\langle N\rangle} a_k e^{jk(2\pi/N)n}$	$2\pi\sum_{k=-\infty}^{+\infty} a_k\delta\left(\omega - \frac{2\pi k}{N}\right)$	a_k
$e^{j\omega_0 n}$	$2\pi\sum_{l=-\infty}^{+\infty}\delta(\omega-\omega_0-2\pi l)$	(a) $\omega_0 = \frac{2\pi m}{N}$ $a_k = \begin{cases} 1, & k = m, m\pm N, m\pm 2N,\ldots \\ 0, & \text{otherwise} \end{cases}$ (b) $\frac{\omega_0}{2\pi}$ irrational $\Rightarrow$ The signal is aperiodic
$\cos\omega_0 n$	$\pi\sum_{l=-\infty}^{+\infty}\{\delta(\omega-\omega_0-2\pi l)+\delta(\omega+\omega_0-2\pi l)\}$	(a) $\omega_0 = \frac{2\pi m}{N}$ $a_k = \begin{cases} \frac{1}{2}, & k = \pm m, \pm m\pm N, \pm m\pm 2N,\ldots \\ 0, & \text{otherwise} \end{cases}$ (b) $\frac{\omega_0}{2\pi}$ irrational $\Rightarrow$ The signal is aperiodic
$\sin\omega_0 n$	$\frac{\pi}{j}\sum_{l=-\infty}^{+\infty}\{\delta(\omega-\omega_0-2\pi l)-\delta(\omega+\omega_0-2\pi l)\}$	(a) $\omega_0 = \frac{2\pi r}{N}$ $a_k = \begin{cases} \frac{1}{2j}, & k = r, r\pm N, r\pm 2N,\ldots \\ -\frac{1}{2j}, & k = -r, -r\pm N, -r\pm 2N,\ldots \\ 0, & \text{otherwise} \end{cases}$ (b) $\frac{\omega_0}{2\pi}$ irrational $\Rightarrow$ The signal is aperiodic
$x[n] = 1$	$2\pi\sum_{l=-\infty}^{+\infty}\delta(\omega-2\pi l)$	$a_k = \begin{cases} 1, & k = 0, \pm N, \pm 2N,\ldots \\ 0, & \text{otherwise} \end{cases}$
Periodic square wave $x[n] = \begin{cases} 1, & \lvert n\rvert \le N_1 \\ 0, & N_1 < \lvert n\rvert \le N/2 \end{cases}$ and $x[n+N] = x[n]$	$2\pi\sum_{k=-\infty}^{+\infty} a_k\delta\left(\omega - \frac{2\pi k}{N}\right)$	$a_k = \frac{\sin[(2\pi k/N)(N_1+\frac{1}{2})]}{N\sin[2\pi k/2N]},\ k \neq 0, \pm N, \pm 2N,\ldots$ $a_k = \frac{2N_1+1}{N},\ k = 0, \pm N, \pm 2N,\ldots$
$\sum_{k=-\infty}^{+\infty}\delta[n-kN]$	$\frac{2\pi}{N}\sum_{k=-\infty}^{+\infty}\delta\left(\omega - \frac{2\pi k}{N}\right)$	$a_k = \frac{1}{N}$ for all k
$a^n u[n],\ \lvert a\rvert < 1$	$\frac{1}{1-ae^{-j\omega}}$	—
$x[n] = \begin{cases} 1, & \lvert n\rvert \le N_1 \\ 0, & \lvert n\rvert > N_1 \end{cases}$	$\frac{\sin[\omega(N_1+\frac{1}{2})]}{\sin(\omega/2)}$	—
$\frac{\sin Wn}{\pi n} = \frac{W}{\pi}\,\mathrm{sinc}\left(\frac{Wn}{\pi}\right)$ $0 < W < \pi$	$X(\omega) = \begin{cases} 1, & 0 \le \lvert\omega\rvert \le W \\ 0, & W < \lvert\omega\rvert \le \pi \end{cases}$ $X(\omega)$ periodic with period 2π	—
$\delta[n]$	1	—
$u[n]$	$\frac{1}{1-e^{-j\omega}} + \sum_{k=-\infty}^{+\infty}\pi\delta(\omega-2\pi k)$	—
$\delta[n-n_0]$	$e^{-j\omega n_0}$	—
$(n+1)a^n u[n],\ \lvert a\rvert < 1$	$\frac{1}{(1-ae^{-j\omega})^2}$	—
$\frac{(n+r-1)!}{n!(r-1)!}a^n u[n],\ \lvert a\rvert < 1$	$\frac{1}{(1-ae^{-j\omega})^r}$	—

TABLE 10.2 SOME COMMON z-TRANSFORM PAIRS

Signal	Transform	ROC
1. $\delta[n]$	1	All z
2. $u[n]$	$\frac{1}{1-z^{-1}}$	$\lvert z\rvert > 1$
3. $-u[-n-1]$	$\frac{1}{1-z^{-1}}$	$\lvert z\rvert < 1$
4. $\delta[n-m]$	z^{-m}	All z, except 0 (if $m > 0$) or ∞ (if $m < 0$)
5. $\alpha^n u[n]$	$\frac{1}{1-\alpha z^{-1}}$	$\lvert z\rvert > \lvert\alpha\rvert$
6. $-\alpha^n u[-n-1]$	$\frac{1}{1-\alpha z^{-1}}$	$\lvert z\rvert < \lvert\alpha\rvert$
7. $n\alpha^n u[n]$	$\frac{\alpha z^{-1}}{(1-\alpha z^{-1})^2}$	$\lvert z\rvert > \lvert\alpha\rvert$
8. $-n\alpha^n u[-n-1]$	$\frac{\alpha z^{-1}}{(1-\alpha z^{-1})^2}$	$\lvert z\rvert < \lvert\alpha\rvert$
9. $[\cos\omega_0 n]u[n]$	$\frac{1-[\cos\omega_0]z^{-1}}{1-[2\cos\omega_0]z^{-1}+z^{-2}}$	$\lvert z\rvert > 1$
10. $[\sin\omega_0 n]u[n]$	$\frac{[\sin\omega_0]z^{-1}}{1-[2\cos\omega_0]z^{-1}+z^{-2}}$	$\lvert z\rvert > 1$
11. $[r^n\cos\omega_0 n]u[n]$	$\frac{1-[r\cos\omega_0]z^{-1}}{1-[2r\cos\omega_0]z^{-1}+r^2z^{-2}}$	$\lvert z\rvert > r$
12. $[r^n\sin\omega_0 n]u[n]$	$\frac{[r\sin\omega_0]z^{-1}}{1-[2r\cos\omega_0]z^{-1}+r^2z^{-2}}$	$\lvert z\rvert > r$

TABLE 9.1 PROPERTIES OF THE LAPLACE TRANSFORM

Section	Property	Signal	Laplace Transform	ROC
		$x(t)$ $x_1(t)$ $x_2(t)$	$X(s)$ $X_1(s)$ $X_2(s)$	R R_1 R_2
9.5.1	Linearity	$ax_1(t)+bx_2(t)$	$aX_1(s)+bX_2(s)$	At least $R_1 \cap R_2$
9.5.2	Time shifting	$x(t-t_0)$	$e^{-st_0}X(s)$	R
9.5.3	Shifting in the s-Domain	$e^{s_0t}x(t)$	$X(s-s_0)$	Shifted version of R (i.e., s is in the ROC if $s-s_0$ is in R)
9.5.4	Time scaling	$x(at)$	$\frac{1}{\lvert a\rvert}X\left(\frac{s}{a}\right)$	Scaled ROC (i.e., s is in the ROC if s/a is in R)
9.5.5	Conjugation	$x^*(t)$	$X^*(s^*)$	R
9.5.6	Convolution	$x_1(t) * x_2(t)$	$X_1(s)X_2(s)$	At least $R_1 \cap R_2$
9.5.7	Differentiation in the Time Domain	$\frac{d}{dt}x(t)$	$sX(s)$	At least R
9.5.8	Differentiation in the s-Domain	$-tx(t)$	$\frac{d}{ds}X(s)$	R
9.5.9	Integration in the Time Domain	$\int_{-\infty}^{t} x(\tau)d(\tau)$	$\frac{1}{s}X(s)$	At least $R \cap \{\mathcal{R}e\{s\} > 0\}$

9.5.10 Initial- and Final-Value Theorems

If $x(t) = 0$ for $t < 0$ and $x(t)$ contains no impulses or higher-order singularities at $t = 0$, then

$$x(0^+) = \lim_{s\to\infty} sX(s)$$

If $x(t) = 0$ for $t < 0$ and $x(t)$ has a finite limit as $t \longrightarrow \infty$, then

$$\lim_{t\to\infty} x(t) = \lim_{s\to 0} sX(s)$$

TABLE 10.1 PROPERTIES OF THE z-TRANSFORM

Section	Property	Signal	z-Transform	ROC
		$x[n]$ $x_1[n]$ $x_2[n]$	$X(z)$ $X_1(z)$ $X_2(z)$	R R_1 R_2
10.5.1	Linearity	$ax_1[n]+bx_2[n]$	$aX_1(z)+bX_2(z)$	At least the intersection of R_1 and R_2
10.5.2	Time shifting	$x[n-n_0]$	$z^{-n_0}X(z)$	R, except for the possible addition or deletion of the origin
10.5.3	Scaling in the z-domain	$e^{j\omega_0 n}x[n]$ $z_0^n x[n]$ $a^n x[n]$	$X(e^{-j\omega_0}z)$ $X\left(\frac{z}{z_0}\right)$ $X(a^{-1}z)$	R z_0R Scaled version of R (i.e., $\lvert a\rvert R$ = the set of points $\{\lvert a\rvert z\}$ for z in R)
10.5.4	Time reversal	$x[-n]$	$X(z^{-1})$	Inverted R (i.e., R^{-1} = the set of points z^{-1}, where z is in R)
10.5.5	Time expansion	$x_{(k)}[n] = \begin{cases} x[r], & n = rk \\ 0, & n \neq rk \end{cases}$ for some integer r	$X(z^k)$	$R^{1/k}$ (i.e., the set of points $z^{1/k}$, where z is in R)
10.5.6	Conjugation	$x^*[n]$	$X^*(z^*)$	R
10.5.7	Convolution	$x_1[n] * x_2[n]$	$X_1(z)X_2(z)$	At least the intersection of R_1 and R_2
10.5.7	First difference	$x[n]-x[n-1]$	$(1-z^{-1})X(z)$	At least the intersection of R and $\lvert z\rvert > 0$
10.5.7	Accumulation	$\sum_{k=-\infty}^{n} x[k]$	$\frac{1}{1-z^{-1}}X(z)$	At least the intersection of R and $\lvert z\rvert > 1$
10.5.8	Differentiation in the z-domain	$nx[n]$	$-z\frac{dX(z)}{dz}$	R

10.5.9 Initial Value Theorem

If $x[n] = 0$ for $n < 0$, then

$$x[0] = \lim_{z\to\infty} X(z)$$

TABLE 9.2 LAPLACE TRANSFORMS OF ELEMENTARY FUNCTIONS

Transform pair	Signal	Transform	ROC
1	$\delta(t)$	1	All s
2	$u(t)$	$\frac{1}{s}$	$\mathcal{R}e\{s\} > 0$
3	$-u(-t)$	$\frac{1}{s}$	$\mathcal{R}e\{s\} < 0$
4	$\frac{t^{n-1}}{(n-1)!}u(t)$	$\frac{1}{s^n}$	$\mathcal{R}e\{s\} > 0$
5	$-\frac{t^{n-1}}{(n-1)!}u(-t)$	$\frac{1}{s^n}$	$\mathcal{R}e\{s\} < 0$
6	$e^{-\alpha t}u(t)$	$\frac{1}{s+\alpha}$	$\mathcal{R}e\{s\} > -\alpha$
7	$-e^{-\alpha t}u(-t)$	$\frac{1}{s+\alpha}$	$\mathcal{R}e\{s\} < -\alpha$
8	$\frac{t^{n-1}}{(n-1)!}e^{-\alpha t}u(t)$	$\frac{1}{(s+\alpha)^n}$	$\mathcal{R}e\{s\} > -\alpha$
9	$-\frac{t^{n-1}}{(n-1)!}e^{-\alpha t}u(-t)$	$\frac{1}{(s+\alpha)^n}$	$\mathcal{R}e\{s\} < -\alpha$
10	$\delta(t-T)$	e^{-sT}	All s
11	$[\cos\omega_0 t]u(t)$	$\frac{s}{s^2+\omega_0^2}$	$\mathcal{R}e\{s\} > 0$
12	$[\sin\omega_0 t]u(t)$	$\frac{\omega_0}{s^2+\omega_0^2}$	$\mathcal{R}e\{s\} > 0$
13	$[e^{-\alpha t}\cos\omega_0 t]u(t)$	$\frac{s+\alpha}{(s+\alpha)^2+\omega_0^2}$	$\mathcal{R}e\{s\} > -\alpha$
14	$[e^{-\alpha t}\sin\omega_0 t]u(t)$	$\frac{\omega_0}{(s+\alpha)^2+\omega_0^2}$	$\mathcal{R}e\{s\} > -\alpha$
15	$u_n(t) = \frac{d^n\delta(t)}{dt^n}$	s^n	All s
16	$u_{-n}(t) = \underbrace{u(t) * \cdots * u(t)}_{n \text{ times}}$	$\frac{1}{s^n}$	$\mathcal{R}e\{s\} > 0$