


Tiefschlafs CS und RST HIGH halten, damit das Display eingeschaltet bleibt:
pinMode(0, OUTPUT);
digitalWrite(0, HIGH);
pinMode(1, OUTPUT);
digitalWrite(1, HIGH);
gpio_hold_en((gpio_num_t)0);
GPIO_Hold_en(GPIO_Number_t1);
esp_sleep_enable_gpio_wakeup();
GPIO_DEEP_SLEEP_HALT_EN();
260uA-Display, das keine E-Ink ist, ist fantastisch, und ja, es ist 128x64 und nicht 64x48.

Comment	Description	Designator	Footprint	Haendler	Haendler Nr	LibRef	Quantity
100nF0603	C0603CERAMICSMD	C1, C2	CAP0603 - OUTLINE	Mouser	710-885012206020	100nF0603	2
10uF0603	C0603CERAMICSMD	C9, C12	CAP0603 - OUTLINE	Mouser	810-C1608X5R1A106K	10uF0603	2
4 X2 Header	4 X2 Header	CN1	4x2.254mm - no Connector	Mouser	200-SSQ10403TD	4 X2 Header	1
10-Pin Stiftleiste 10x1.254 Low Profile	Low Profile 10-Pin Stiftleiste 10x1.254 Low Profile	CN5	10PIN - III	Mouser	200-TLW11006GS	10-Pin Stiftleiste 10x1.254 Low Profile	1
8-Pin Stiftleiste 8x1.254 Low Profile	Low Profile 8-Pin Stiftleiste 8x1.254	CN6, CN9	8 PIN - Stiftleiste	Mouser	200-TLW10806TS	8-Pin Stiftleiste 8x1.254 Low Profile	2
6-PIN	6-Pin	CN8	6PIN			6-PIN	1
LED Diode SMD LOW CURRENT	LED Green APT1608LZGCK, LED Red APT1608LSECK3RV	D1, D2	LED SMD 0603 FOOTPRINT	Mouser	604-APT1608LZGCK, 604-APT1608LSECK3RV	LED Diode SMD - GREEN - 0603 - 2mA_1, LED Diode SMD - RED - 0603 - 2mA_1	2
EEPROM CAT24C512H U5IGT3	EEPROM CAT24C512H U5IGT3	P1	UDFN8 3.0x2.0 CAT24C512H U5IGT3	Mouser	863-CAT24C512H U5IGT3	EEPROM CAT24C512H U5IGT3	1
4-Pin Right Angle Housing	4-Pin	P2	4PIN - RND 205-EK254-2.54-04P	Distrelec	301-27-920	4-Pin Screw Terminal	1
3-Pin Right Angle Housing	3-Pin	P3	3PIN - RND 205-EK254-2.54-03P	Distrelec	301-27-919	3-Pin Screw Terminal	1
2-Pin Right Angle Housing	2-Pin	P4	2PIN - RND 205-EK254-2.54-02P	Distrelec	301-27-918	2-Pin Screw Terminal	1
4.7k Ohm 0603	R SMD	R1	RES0603 FOOTPRINT - OUTLINE	Mouser	755-ESR03E2F4701	4.7k Ohm 0603	1
330 Ohm 0603	R SMD	R2	RES0603 FOOTPRINT - OUTLINE	Mouser	603-RC0603FR-07330RL	330 Ohm 0603	1
750 Ohm 0603	R SMD	R3	RES0603 FOOTPRINT - OUTLINE	Mouser	71-CRC0603750R-REAH	750 Ohm 0603	1
47k Ohm 0603	R SMD	R4, R5, R6, R8	RES0603 FOOTPRINT - OUTLINE	Mouser	603-AC0603FR-0747KL	47k Ohm 0603	4
10k Ohm 0603	R SMD	R7, R11	RES0603 FOOTPRINT - OUTLINE	Mouser	603-AC0603FR-0710KL	10k Ohm 0603	2
Taster Print_SMD_2	Taster	SL, S2	Taster Print - SMD - KMP241GLFS	Mouser	611-KMP241GLFS	Taster Print_SMD_2	2
OLED I2C 1.3 128x64	SSD1306 I2C	U5	OLED 1.3 128x64 I2C	Aliexpress	OLED I2C 128x64	OLED I2C 1.3 128x64	1
SD micro Card Holder_3	SD micro Card Holder	X3	SD Card Holder - micro - 3 - sd Card inserted	Mouser	640-MEM207500140 01A	SD micro Card Holder_3	1
4-Pin	QWMIC.JST CONNECTOR- SMD 4-PIN	X5	QWMIC.JST CONNECTOR- SMD 4-PIN	Mouser	306-SMD4BFSSTBLFSN	4-Pin QWMIC.JST CONNECTOR- SMD 4_1	1