Technische Universität Hamburg

Data Science Foundations

Low-dimensional Control under Embodiment Constraints: From LQR to Reinforcement Learning

Bachelor's Thesis
am Institut Data Science Foundations
Technische Universität Hamburg

vorgelegt von
Alexander Michael Kranz
am
31.10.2026

Erstprüfer:	Prof. Dr. N. Ay
Zweitprüfer	Dr. Manfred Eppe
Betreuung:	Dr. Adwait Datar

Alexander Michael Kranz
geboren am: 09.02.2004
Matrikelnummer: 590156
Studiengang: Data Science

Abstract

Your English abstract here (mandatory if written in English and recommended otherwise).

Zusammenfassung

Hier die deutsche Zusammenfassung einfügen (notwendig).

Contents

1 Introduction **1**

2 Background **3**
2.1 Preliminaries . . . 3
2.1.1 Linear State-Space Models . . . 3
2.1.2 The Double Integrator . . . 5
2.1.3 The Linear Quadratic Regulator . . . 6
2.2 Motivation . . . 8
2.3 Experimental Setup . . . 10
2.3.1 The Modified Loop . . . 10
2.3.2 Metrics and Robustness . . . 13
2.3.3 Test Protocol . . . 16
2.4 Approach . . . 18

3 Robustness of LQR Solvers in Different Dimensions **21**
3.1 A Known Model . . . 21
3.1.1 Setting . . . 21
3.1.2 Results . . . 24
3.1.3 Noise Experiments . . . 25
3.1.4 Discussion . . . 26
3.2 Unknown Model across Dimensions . . . 27
3.2.1 Setting . . . 27
3.2.2 Results . . . 30
3.2.3 Noise Experiments on Large Inflation . . . 30
3.2.4 Discussion . . . 33
3.3 Discussion . . . 34

4 Robustness of Reinforcement Learning Approaches **35**
4.1 PPO and Its Variants . . . 35
4.1.1 Proximal Policy Optimization . . . 35
4.1.2 Training Setup . . . 36
4.1.3 Policy Architectures . . . 36
4.2 Comparison across Dimensions . . . 39
4.3 Noise on Large Inflation . . . 41

4.4 Discussion 44

5 Perception-Based Experiments **45**
5.1 Artificial Inflation to Pixel Size 45
5.1.1 Setting 45
5.1.2 Results 46
5.2 The New Environment and the Position-Velocity Encoder 46
5.2.1 Pixelated Environment 46
5.2.2 Position-Velocity Encoder 47
5.3 Effect of Visual Inputs on the Solvers 48
5.3.1 Setting 48
5.3.2 Results 49
5.4 Noisy Perception 49
5.4.1 Setting 49
5.4.2 Results 50
5.5 Discussion 50

6 Conclusion **51**

A Nomenclature **53**
A.1 Notation 53
A.2 Noise Intensities 57
A.3 Noise Intensities of the Perception Environment 57
A.4 Policy Architectures 58

B Complete Simulation Results **61**
B.1 Learning Rate of Model-based PG 61
B.2 Nuclear-Norm Weight of S-PI 62
B.3 N4SID Identification Length 63
B.4 Sample Size 65
B.5 Learning Rate of Model-free NPG 66
B.6 Step Size and Nuclear-Norm Weight of S-PI (Model-Free) 66
B.7 Noise on the Identified Model 67
B.8 Parameters for the RL Solvers 68
B.8.1 Deviations from SB3 Standard Parameters 68
B.8.2 Learning Rates for the RL Solvers 69
B.8.3 Stopping Rule of the RL Solvers 69

Bibliography **73**

List of Figures

3.1 Suboptimality S of the solvers on the true model for each inflation size. . . . 24
3.2 Suboptimality S of the solvers on the true model under *large* inflation and external disturbance at different intensities. . . . 25
3.3 Suboptimality S of the solvers on the true model under measurement noise at intensity *divergent*. . . . 26
3.4 Policy size $|K|$ (Definition 2.1) learned without the model, for each inflation size. . . . 31
3.5 Suboptimality S of the solvers without the model for each inflation size. . . . 31
3.6 Suboptimality S of the solvers without the model under *large* inflation. 32
3.7 Suboptimality S of the solvers without the model under *large* inflation and measurement noise. . . . 33

4.1 Training suboptimality $(J - J^*)/J^*$ of the PPO variants under *large* inflation. . . . 40
4.2 Policy size (Definition 2.1) of the PPO variants for each inflation size. 40
4.3 Suboptimality S of the PPO variants for each inflation size. . . . 41
4.4 Suboptimality S of the PPO variants under *large* inflation and different noise types. . . . 42
4.5 Suboptimality S of the PPO variants under *large* inflation and measurement noise. . . . 43

5.1 Observation and actuation in the camera environment. . . . 47
5.2 An observation without measurement noise, and with measurement noise of intensity *standard* and *divergent*. . . . 50

A.1 Actor architectures of our PPO variants. For each layer, the number below indicates its neurons. The critic receives the same encoder structure and uses its own 64-64 tanh perceptron with a scalar output. Visualization created with Claude Code. . . . 59

B.1 Training suboptimality of Model-based PG over the solver iterations for each learning rate under *large* inflation. Median and range over ten seeds. . . . 62

B.2 Training suboptimality of S-PI over the solver iterations for each nuclear-norm weight λ under *large* inflation. Median and range over ten seeds. 63
B.3 Median training suboptimality of N4SID + Model-based PG per trajectory length T and Hankel horizon under *large* inflation. 64
B.4 Median training suboptimality of N4SID + Model-based PG per trajectory length T and Hankel horizon under *medium* inflation. . . 64
B.5 Training suboptimality of Model-free NPG over the environment steps for each rollout length l and number of trajectories N_{traj} under *large* inflation. Median and range over ten seeds. 65
B.6 Final training suboptimality of Model-free NPG for each rollout length l and number of trajectories N_{traj} under *large* inflation. . . . 65
B.7 Training suboptimality of Model-free NPG over the environment steps for each learning rate under *large* inflation. Median and range over ten seeds. 66
B.8 TODO: Suboptimality S of the model-free solvers under *large* inflation and parametric uncertainty at intensity *strong*. 68
B.9 Training suboptimality for different learning rates for Linear PPO under *large* inflation. 69
B.10 Training suboptimality of the RL solvers over the environment steps under *large* inflation. 71

List of Tables

2.1 Preset inflation sizes. 12
2.2 Parameters of the convergence rule (Definition 2.2) for the LQR solvers. 17
2.3 Environment step budget of the RL solvers per inflation size. 17

3.1 Size of the policy architectures on the true model, across every inflation size. 24
3.2 Relative degradation κ and Absolute degradation $\Delta\hat{J}/\hat{J}^*$ under *large* inflation and each noise channel at intensity *strong*. 26
3.3 Identification settings per inflation size. 28

4.1 Median and worst seed of the relative degradation κ under *large* inflation and parametric uncertainty of increasing intensity. 41

5.1 Initial learning rate η_0 at the *pixel* size, extrapolated from *large* with (5.1). 46

A.2 Standard deviation per noise channel and intensity, calibrated to the cost ratio ρ_ℓ of (2.36). Every value reaches its ratio within 0.9 %. 57
A.3 Standard deviation per noise channel and intensity, calibrated to the cost ratio ρ_ℓ of (2.36). Every value reaches its ratio within 9.4 %. Measurement noise is set by hand and not calibrated. 58

B.1 Model-based PG under *large* inflation, over the seeds. 61
B.2 S-PI under *large* inflation, over the seeds. 62
B.3 N4SID + Model-based PG on a system with *medium* inflation with a Hankel horizon of 5. 63
B.4 N4SID + Model-based PG on a system with *large* inflation with a Hankel horizon of 5. Identified counts the seeds a model was obtained from and stable those whose controller left the plant stable. 63
B.5 Model-free NPG: training suboptimality $(J - J^*)/J^*$ per inflation size (rows) and sample-size combination (columns). 66
B.6 Model-free NPG under *large* inflation, over the seeds. 66
B.7 S-PI (model-free) with $\lambda = 4000$ under *large* inflation, over the seeds. 67
B.8 S-PI (model-free) with $\lambda = 40000$ under *large* inflation, over the seeds. 67

B.9 S-PI (model-free) with $\lambda = 400000$ under *large* inflation, over the seeds. Stable counts the seeds whose controller left the plant stable. 67
B.10 Relative degradation κ and Absolute degradation $\Delta\hat{J}/\hat{J}^*$ under *large* inflation and each noise channel at intensity *strong*. 68
B.11 Parameters of the PPO solvers that differ from the SB3 defaults. . . 68
B.12 Initial learning rate η_0 of the PPO solvers per inflation size. 69
B.13 Stopping-rule settings with the lowest median regret. 70
B.14 RL runs best policy, as a share of the step budget, and the regret of the policy after 75 % of the budget, of the final policy, and of the policy with the best $\bar{g}_j$. 70

Chapter 1

Introduction

For a robot, our world is a messy place, consisting of a multitude of variables, all influencing what a correct behavior would be at any given moment. Rightfully, newer, larger controller models have equated to better (at least theoretical) performance [35, 25, 9]. However, when transferring them over from training in a digital environment to an actual embodiment, not only do limitations in memory space and energy usage arise [43, p. 7], but the real world also behaves slightly differently, which the controller needs to be robust against [57, 38]. So ideally, we should remove unnecessary parameters, while still maintaining those helping us adapt to variable environments. This leaves us with the question: *Is it possible to train a low-dimensional controller for an embodied agent, that is performant yet robust?*

Inspired by nature, it has been shown that more complex behavior can be expressed by simple control architectures if combined with the right embodiment [31, 34]. However, finding this simple architecture remains difficult as an embodiment might offer a large number of sensors and actuators, which outnumber the dimension governing the underlying dynamics [59, 26]. Synergizing these, like in nature [6], is thus the goal here. And while low-dimensional controllers for embodiment have been studied before [33, 5], bringing robustness into the equations remains, to our knowledge, still an unsolved question we aim to contribute to.

To be able to quantify performance and what optimal means, we rely on a very well-researched example [21, 16]: the linear quadratic regulator, which, together with some related work, we will introduce in Chapter 2. We use the also well-known double integrator as our environment, and artificially produce higher input and output dimensions via projection for our controllers to train on, to simulate overparameterization like mentioned above in Chapter 3. Then, we will introduce noise to the environment during testing and compare the robustness between them. The next step consists of moving from these simpler, gain-matrix-based controllers to reinforcement learning (RL) approaches based on proximal policy optimization [47] (Chapter 4), while still maintaining our optimal controller from

before as the comparison. Robustness evaluations are a part of this again. Finally, we move to an example closer to reality in Chapter 5, by introducing a real simulated environment, still based on the double integrator, which however will be observed by a camera, and influenced by multiple thrusters, which differ from each other. Again introducing noise in a second step here, this allows us to understand the behavior of low-dimensional controllers better, as we slowly increase the complexity of the setup throughout. We end this thesis in Chapter 6 by discussing our findings, pointing out limitations of our work, before outlining possible future directions.

Chapter 2

Background

Before turning to the experiments, we need to lay the groundwork and reasoning for them. We start by defining some important concepts from control theory, as well as introducing the system that serves as our core example throughout (Section 2.1). Then, we discuss the current state of research around embodiment, low-dimensional control, and in that context robustness as well (Section 2.2). We further reason about the relevance of this thesis, as well as comparable papers. After that, we move on to introducing our specifically chosen setup for our experiments, define constants used and explain our test protocol (Section 2.3). Finally, we walk the reader through our upcoming chapters, building on the previously introduced information, and giving reason for certain design choices (Section 2.4).

2.1 Preliminaries

Here, we revisit the concepts that are necessary for understanding the following chapters. This section introduces basics of control theory, such as linear state-space models (Section 2.1.1), the double integrator as our example (Section 2.1.2), and the linear quadratic regulator (Section 2.1.3).

2.1.1 Linear State-Space Models

In control theory, the evolution of an agent together with its environment is described by a *state-space model*: a rule that assigns to every point of a state space the instantaneous rate at which the system moves through it. Throughout this thesis we restrict attention to the class of *linear* systems, for which this rule is linear in both the state and the input [62, pp. 3–4].

Such a continuous-time system is given by

$$\dot{x}(t) = A_c\, x(t) + B_c\, u(t), \qquad x(0) = x_0, \tag{2.1a}$$

$$y(t) = C\, x(t) + D\, u(t), \tag{2.1b}$$

where $x(t) \in \mathbb{R}^n$ is the *state vector*, $u(t) \in \mathbb{R}^m$ the *input vector* chosen by the agent, and $y(t) \in \mathbb{R}^q$ the *output vector*, i.e. the output observed and thus available to the feedback controller. Accordingly, $A_c \in \mathbb{R}^{n\times n}$ is called the *system matrix*, $B_c \in \mathbb{R}^{n\times m}$ the *input matrix*, $C \in \mathbb{R}^{q\times n}$ the *output matrix*, and $D \in \mathbb{R}^{q\times m}$ the *feedthrough matrix*.

The two equations in (2.1) play fundamentally different roles, and it is helpful to explain their distinction. Equation (2.1a) is a differential equation: it does not compute the state, which is assumed to be known at every instant, but prescribes its *rate of change*. The pair (A_c, B_c) therefore governs how the system *behaves*, with A_c describing its autonomous dynamics and B_c describing how the input of the agent influences them. Equation (2.1b), in contrast, contains no derivative at all. It is an instantaneous readout, and the pair (C, D) therefore describes how the system is *observed* rather than how it evolves. We set $D = 0$ throughout, which is the standard assumption for systems in which the actuator has no direct instantaneous influence on the sensor [62, p. 4].

Given an input signal $u(\cdot)$, the trajectory of (2.1a) is obtained by integration and is given in closed form by the variation-of-constants formula [62, p. 13, Eq. (2.20)]

$$x(t) = e^{A_c t}x_0 + \int_0^t e^{A_c(t-s)}B_c\,u(s)\,\mathrm{d}s, \tag{2.2}$$

where $e^{A_c t}$ denotes the matrix exponential.

Full-state measurement. Generally, we assume that the state is fully measurable and therefore set $C = I_n$, which reduces (2.1b) to $y(t) = x(t)$. However, when we introduce disturbances through noise, this is no longer the case. More details on this are given in Section 2.3.1.2.

2.1.1.1 Discretization

Digital controllers, as in our case, do not act continuously: they sample the output at a fixed rate and hold the computed control input constant until the next sampling point. The learning algorithms studied in this thesis operate on such sampled trajectories as well, so our model has to reflect this. The standard approach is the *zero-order hold* (ZOH) [62, p. 118]. Fixing a sampling period $h > 0$ and writing $x_k \coloneqq x(kh)$, the input is assumed to be piecewise constant [62, Eq. (7.1)],

$$u(t) = u_k \qquad \text{for } t \in [kh,\,(k+1)h), \quad k \in \mathbb{N}_0. \tag{2.3}$$

Substituting (2.3) into (2.2) over a single sampling interval and applying the change of variables $\tau = (k+1)h - s$ yields the discrete-time model

$$x_{k+1} = A_d\,x_k + B_d\,u_k, \tag{2.4}$$

with [62, p. 136, Eqs. (7.26)–(7.28)]

$$A_d = e^{A_c h}, \qquad B_d = \left(\int_0^h e^{A_c\tau}\,\mathrm{d}\tau\right) B_c. \tag{2.5}$$

We use the implementation from SciPy [48] to carry out this transformation in the code. Unless stated otherwise, all experiments in this thesis are carried out in discrete time with sampling period $h = 0.01\,\mathrm{s}$, and we drop the subscript d in the following, writing simply A and B.

2.1.2 The Double Integrator

To make the comparisons across all chapters meaningful, all experiments are built on a single system: the *double integrator*, a frictionless point mass of unit mass moving along a line under an applied force u [40, pp. 87–88]. Its dynamics are Newton's second law,

$$\ddot{p}(t) = u(t), \tag{2.6}$$

where $p(t)$ denotes the position of the mass. We simplify by using a mass of one, so that force and acceleration coincide numerically. Choosing position and velocity as the state, $x = [\,p,\ v\,]^\top \in \mathbb{R}^2$, the second-order equation (2.6) decomposes into the first-order system

$$\dot{p}(t) = v(t), \qquad \dot{v}(t) = u(t), \tag{2.7}$$

in which the first equation is the definition of velocity and the second is (2.6) itself. In the notation of (2.1) this gives

$$A_c = \begin{bmatrix} 0 & 1 \\ 0 & 0 \end{bmatrix}, \qquad B_c = \begin{bmatrix} 0 \\ 1 \end{bmatrix}, \qquad C = I_2, \qquad D = 0. \tag{2.8}$$

The entry $(A_c)_{12} = 1$ should be read as stated in Section 2.1.1: the rate of change of position is given by the current velocity.

Because $A_c^2 = 0$, the matrix exponential in (2.5) truncates after two terms, $e^{A_c h} = I + A_c h$, and the discretization is available in closed form:

$$A_d = \begin{bmatrix} 1 & h \\ 0 & 1 \end{bmatrix}, \qquad B_d = \begin{bmatrix} h^2/2 \\ h \end{bmatrix}. \tag{2.9}$$

This system is the minimal nontrivial choice for our purposes. It is second-order, so the state is not directly actuated and the controller must account for momentum. It is *controllable* for every $h > 0$, i.e. an input sequence can navigate it from any initial state to any final state [62, p. 127, Def. 7.2].[1] Additionally, it is not open-loop stable: an unforced discrete-time system $x_{k+1} = Ax_k$ is *stable* if and only if all eigenvalues of A lie strictly inside the unit disk [62, p. 127, Thm. 7.1], i.e. if its *spectral radius* $\rho(A) \coloneqq \max_i |\lambda_i(A)|$ satisfies $\rho(A) < 1$. Here, A_c has a double eigenvalue at the origin and A_d correspondingly a double eigenvalue at 1, so $\rho(A_d) = 1$. The last property matters for the learning experiments: an uncontrolled or badly initialized policy diverges, so the assumption of a known stabilizing initial gain (Section 2.3.3) is a restriction.

[1] Controllability, with its weaker form stabilizability, and the dual notions observability and detectability are standard structural properties of linear systems. If the reader wishes to read up on their formal definitions, we kindly refer them to [62, Chs. 3–4 and pp. 127–129].

2.1.3 The Linear Quadratic Regulator

Now that we have defined our state-space model and the system we study, it is time to introduce our controller, which is based on the *linear quadratic regulator* (LQR) problem.

Here, the setting is that our system starts at an arbitrary initial state in its state space, and the goal of our controller is to return to the zero state as fast as possible. At the same time, the control input should be limited to a realistic quantity, such that it could actually be produced by an actuator. Both requirements can be combined into a single cost function, where Q describes the former, while R associates costs to control input. Over a finite horizon T, this gives the cost [63, pp. 5–6, Eqs. (1.3) and (1.5)]

$$V_T(x_0, u) = \int_0^T \left(x(t)^\top Q\, x(t) + u(t)^\top R\, u(t)\right) \mathrm{d}t, \qquad Q = Q^\top \succeq 0, \quad R = R^\top \succ 0. \tag{2.10}$$

We notice two further restrictions here: Q is required to be positive semi-definite, meaning that deviating from the origin never reduces the cost, and R must be positive definite, such that every control input results in a cost.

As the original formula relates to a continuous problem with a fixed end time T, it does not fit our goal well of evaluating over an infinite discrete horizon. The following formula offers exactly that [62, p. 137, Eq. (7.30)]:

$$J(x_0, u) = \sum_{k=0}^{\infty} \left(x_k^\top Q\, x_k + u_k^\top R\, u_k\right). \tag{2.11}$$

This sum does not necessarily converge. If the closed loop does not decay, the costs do not vanish and J tends to $+\infty$. Using this as our definition, J becomes well defined for every gain.

2.1.3.1 The Optimal Gain

What makes the LQR problem special is that its solution is a static linear feedback law: the optimal input at time k depends only on the current state of the model. Introducing a gain matrix $K \in \mathbb{R}^{m\times n}$, we write it as[2]

$$u_k = -K x_k. \tag{2.12}$$

Our controller is thus reduced to choosing a matrix, and the optimal controller is given by the optimal gain matrix K^*.

As we are dealing with a discrete-time system, that gain is obtained from the *discrete algebraic Riccati equation* (DARE)

$$P = A^\top P A - A^\top P B \left(R + B^\top P B\right)^{-1} B^\top P A + Q, \tag{2.13}$$

[2]Note that the minus in front of K has been chosen as the convention for this thesis. This turns our closed loop into the format $A - BK$, while some referenced literature uses $A + BK$. Formulas cited have been adapted to our convention by replacing K with $-K$.

whose stabilizing solution $P = P^\top \succeq 0$ yields

$$K^* = \left(R + B^\top P B\right)^{-1} B^\top P A, \qquad u_k^* = -K^* x_k. \tag{2.14}$$

The matrix P is additionally our *cost-to-go* matrix, meaning that we can use it to calculate the optimal cost incurred from any state x onwards with

$$J^*(x) = x^\top P x. \tag{2.15}$$

Whether (2.13) has such a solution at all depends on two structural properties of the system, stabilizability and detectability [CITE: discrete-time source]:

Theorem 2.1 (Existence and uniqueness)**.** *Let (A, B) be stabilizable and let $(A, Q^{1/2})$ be detectable. Then the DARE (2.13) has a unique symmetric positive semi-definite solution P, which is the only stabilizing one, and the resulting closed loop satisfies $\rho(A - BK^*) < 1$. If $(A, Q^{1/2})$ is observable, P is positive definite.*

For the double integrator, both conditions hold: (A, B) is controllable and thus stabilizable, and with $Q = I_n$ (Section 2.3.3) the pair $(A, Q^{1/2}) = (A, I_n)$ is also observable. Thus $P \succ 0$, and K^* is well defined in all our experiments.

2.1.3.2 The Cost as a Function of the Gain

Equation (2.14) solves the problem, but it solves it directly and tells us nothing about the quality of non-optimal gains. As the learning algorithms of the following chapters will produce such K directly, we need to be able to calculate the cost as a function of K.

Fix a gain K and write the resulting closed loop as $x_{k+1} = A_K x_k$ with $A_K \coloneqq A - BK$. Substituting (2.12) into (2.11) shows that the cost is again a quadratic form, $J(x_0, K) = x_0^\top P_K x_0$, where P_K now solves the far simpler discrete *Lyapunov equation*

$$P_K = A_K^\top P_K A_K + Q + K^\top R K, \tag{2.16}$$

which is linear in the unknown P_K and has a unique solution whenever $\rho(A_K) < 1$. This restricts us to the set of stabilizing gains

$$\mathcal{K} \coloneqq \left\{K \in \mathbb{R}^{m \times n} : \rho(A - BK) < 1\right\}, \tag{2.17}$$

outside of which we set the cost to $+\infty$, consistent with the remark after (2.11).

One dependency remains, namely on the initial state. Evaluating the gain based on a single x_0 would reward gains that happen to fit that one point, so we instead draw the initial state from a distribution, $x_0 \sim \mathcal{D}$, and average. Writing $\Sigma_0 \coloneqq \mathbb{E}_{x_0 \sim \mathcal{D}}[x_0 x_0^\top]$ for its second moment, the objective becomes

$$f(K) \coloneqq \mathbb{E}_{x_0 \sim \mathcal{D}}\left[x_0^\top P_K x_0\right] = \operatorname{tr}\left(P_K \Sigma_0\right), \tag{2.18}$$

using the cyclic property of the trace. Equation (2.18) is the object that every remaining chapter of this thesis minimizes, and the algorithms differ only in how much of the model is known to them.

2.2 Motivation

An agent acting in its environment receives observational input and responds to it with a commanded control input. In other words, the agent is a function in relation to its environment, and to find an optimal behavior, we need to approximate this optimal function as closely as possible. While neural networks are known to be universal approximators [4, 14], and hence able to approximate any function, in the case of an embodied agent, different constraints need to be taken into account. Ay [2] names additionally to external embodiment constraints possible intrinsic constraints, and argues that such can even be "beneficial" for the control structure. Additionally, fewer parameters for deployment are helpful due to energy usage and storage capacity, the core of the notion of cheap design [CITE: TODO]. So, for such embodied agents, the goal is to find an "embodied universal approximator" [33, p. 3], which restricts the neural network architecture to an intrinsic, unknown dimension, encoding physical properties belonging to the agent and the environment, while disallowing impossible movements [33, Sec. 3].

Biology motivates this approach even further: here it is clear to see that by commanding a body, some features of the control architecture can be simplified and delegated to the embodiment [34]. For example, McGeer's passive walker [31] clearly shows that some movements can be produced by the body without any control input, just by choosing the right embodiment. While obviously here being simplified to not include any control at all, it can quite simply be extended with such [30]. Müller and Hoffmann [34, p. 4] mention such a combination, a robot climbing up walls, whose design was inspired by geckos, indeed using energy for control, however very little compared to an approach not exploiting this specific embodiment design. Further, it can be seen that the complex behaviors are not only less energy-intensive to produce, but also utilize muscle synergies [6] and thus fewer control parameters. And while it is difficult to clearly attribute the effect of the embodiment [65], for us, this gives reason to believe that the simplicity, and thus efficiency, comes from a low-dimensionality of the controller [33].

That this is indeed true for certain examples has been shown both in theory and practice before [5, 32, 28]. Li et al. [28] call this lower dimension "intrinsic dimension", which is the dimensionality required for the model to be able to find policies. They show, for example, that for achieving 90 % of the performance of a fully connected network on MNIST, the dimensionality can be reduced by 99.6 %. For a convolutional neural network, it is still a 99.3 % reduction. Others show that the "least complex model which is able to learn an optimal policy does learn faster" [32]. For a neural network, being more parameter-efficient can be done in different ways, some of which we look at in Chapter 4. In comparison, for LQR, where the controller is a gain matrix, the corresponding approach is reducing its rank [42]. However, while these approaches are more parameter-efficient while achieving similar or slightly worse performance, it was also observed that they tend to perform even worse when encountering noise [5].

Robustness to noise, however, is one of the important characteristics of controllers acting under real-world conditions [40, 43]. One approach to achieving this in nature is the principle of "redundancy and diversity" [23], which stands in direct contrast to our goal of reducing redundant parameterizations. Another reason for producing robust controllers is the difficult transfer from a digital training environment to real-world embodiments, commonly referred to as the "reality gap" [57, 38]. Approaches to training robust controllers typically introduce noise already during training, be it by using a linear quadratic Gaussian (LQG) controller or by including variations to the dynamics [40, 38]. These approaches, however, do not look at low-dimensionality, which makes sense as Kitano [23, p. 833] poses that robustness cannot be increased without sacrificing performance or accepting "increased resource demands".

Before taking a look at the more complex case of RL, we start simpler by using the simpler and better-understood LQR. This approach has been taken before [41] and does make sense given the guarantees regarding convergence and effectiveness of policy optimization for it [13, 55], as well as the understanding of its geometry [56]. It also offers methods which produce certain structures in its controller, like sparsity or our desired low-dimensionality, as given by structured policy iteration (S-PI) [37]. Approaches can generally be categorized into two groups if the underlying dynamics are unknown and only data is available: estimating the model and then applying a model-based solver (indirect), or using the data to estimate the gain matrix (direct) [67]. Both the indirect, as in system identification with uncertainty bounds [7], and the direct setting, with an $\mathcal{H}_\infty$ constraint that bounds the closed-loop gain from disturbance to output [66], have been studied with regard to robustness, but, to our knowledge, not in combination with low-rank policies.

Research evaluating RL on control tasks has also shown that there is room for simplification, for example using linear policies instead of complex, fully connected neural networks [29, 39]. This, together with the fact that parameters in neural networks are highly dependent, and thus redundant [10], allows us to assume that low-dimensionality can improve efficiency here. Examples of this exist, for example by factorizing a discretized low-rank policy into a thin and wide matrix [44] or by introducing an orthogonal projection inside the layer structure [58]. While they produce lower dimensionality, a different approach uses "information bottlenecks", which exhibit better generalization behavior in unseen environments [18, Sec. 4.2], which again could help us with robustness.

A clear case where low-dimensional dynamics underlie a high-dimensional observational space is in perception-based tasks. Agents observing only images instead of the states of simple control tasks are faced with the challenge of extracting these states from a high-dimensional, often nonlinear encoding [61, Sec. 1]. Many approaches, based on state representation learning (SRL), exist, which use different variants to create a latent embedding of the image, used as a state [26]. The most interesting approach, especially for us looking at embodied agents, is the usage of so-called "priors", which restrict the latent space by using knowledge about the

environment [26]. This brings us back to Ay's argument that the embodiment actively defines the action space [2]. Robotic priors were introduced by Jonschkowski and Brock [19] in 2015, and then further refined by Botteghi et al. [3] for continuous action spaces. A more specific version restricted to position and velocity also exists here, training a model to encode an image into a low-dimensional position state, from which the velocity is calculated by finite differences [20]. While all that sounds promising, in contrast stand findings hinting that the problems of robust control also apply to perception-based control, as noise induced through perception directly affects the performance [64] and thus needs approaches for improving it [8].

Our goal for this thesis is therefore to look a bit deeper at the combination of low-dimensionality and robustness in an empirical way, motivated by the findings of Datar and Ay [5]. LQR serves as the perfect, well-investigated basis [41], offering low-rank approaches that have been proposed and analyzed theoretically, but have not yet been applied in practice and under noise [37]. Previously investigated policies for LQR under noise in comparison did not look at low-dimensionality specifically [66]. For RL, low-dimensionality has been explored previously [1, 54], and also in comparison with robustness [27], but does not take into account the embodiment we are interested in. Closing this gap, our main interest is to compare robustness properties for low-dimensional policies for embodied agents under increasingly more complex and noisier environments.

2.3 Experimental Setup

2.3.1 The Modified Loop

2.3.1.1 An Inflated Model

To allow us to investigate a controller that has many redundant inputs and outputs, acting on a system with low-dimensional dynamics, we first need to create such a setup for our previously introduced double integrator. We do this by keeping the dynamics, so the state progression, like the loop above, but projecting the observation into a higher dimension, as well as projecting actuation down from such a higher dimension.

More specifically, we show the modification to our loop with two random orthonormal matrices U_1 and U_2. For an inflated input dimension d_{in} and output dimension d_{out}, the two lifts are constructed the following way:

$$U_1 \in \mathbb{R}^{d_{\text{in}} \times n}, \quad U_1^\top U_1 = I_n, \qquad U_2 \in \mathbb{R}^{m \times d_{\text{out}}}, \quad U_2 U_2^\top = I_m, \tag{2.19}$$

where U_1 is the orthonormal factor of the QR decomposition of a random matrix, whose entries are sampled from the standard normal distribution. U_2 is the transpose of such a factor sampled from a separately drawn matrix. A single step of

the loop then becomes

$$y_k = U_1 x_k, \tag{2.20a}$$
$$v_k = -K y_k, \qquad K \in \mathbb{R}^{d_{\text{out}} \times d_{\text{in}}}, \tag{2.20b}$$
$$u_k = U_2 v_k, \tag{2.20c}$$
$$x_{k+1} = A x_k + B u_k = A x_k + B U_2 \, v_k. \tag{2.20d}$$

Compared with (2.1), the output matrix thus becomes $C = U_1$, so that $q = d_{\text{in}}$, and the controller acts through the input matrix $BU_2 \in \mathbb{R}^{n \times d_{\text{out}}}$.

This way, the controller only sees the inflated observation and acts in a higher dimension. As any actuation effort is penalized, its weight $\tilde{R}$ acts on the inflated actuation and therefore has the dimension $d_{\text{out}} \times d_{\text{out}}$. To simplify things, we also have the state weight $\tilde{Q}$ in this lifted dimension, acting on the observation. Here and in the following, a tilde marks the inflated counterpart of a quantity of the uninflated problem. As U_1 has orthonormal columns, and we use $\tilde{Q} = I_{d_{\text{in}}}$ throughout, this simplifies to

$$\begin{aligned} (U_1 x_k)^\top \tilde{Q} \, (U_1 x_k) &= x_k^\top U_1^\top U_1 \, x_k \\ &= x_k^\top I_n \, x_k \\ &= x_k^\top Q \, x_k, \qquad Q = I_n, \end{aligned} \tag{2.21}$$

with the uninflated Q of Section 2.1.3, so it indeed still penalizes how far our mass is from zero. The cost in the modified loop then becomes

$$\begin{aligned} J(x_0, K) &= \sum_{k=0}^{\infty} \left(y_k^\top \tilde{Q} \, y_k + v_k^\top \tilde{R} \, v_k \right) \\ &= \sum_{k=0}^{\infty} \left(x_k^\top U_1^\top \tilde{Q} \, U_1 x_k + x_k^\top U_1^\top K^\top \tilde{R} K U_1 x_k \right), \end{aligned} \tag{2.22}$$

with the closed loop $x_{k+1} = (A - BU_2 K U_1) \, x_k$.

Throughout the thesis, we use the following synonyms for different d_{in} and d_{out} dimensionalities, applied to the loop, which can be found in Table 2.1.

2.3.1.2 Noise Injection

Now, the second thing we want to take a look at is robustness to small changes or variations in the environment. We thus introduce four different types of disturbances to be included in our model, commonly known as noise. They are distinguished by the point at which they affect the loop: what the controller *observes* (measurement noise), what its output actually *does* (control noise), what the plant *is* (parametric uncertainty), and what else *acts* on it (external disturbance). Each of them can be activated separately, so that we can clearly isolate the cause of an effect. Throughout this section k indexes the sampling instants, and σ denotes the standard deviation of the respective noise.

Table 2.1: Preset inflation sizes.

Name	d_{in}	d_{out}
base	2	1
small	10	5
medium	50	25
large	200	100
pixel	18 432	256

2.3.1.3 Measurement Noise

Here we influence the sensors used to measure the model state, such that capturing the same state twice does not lead to the same observation y_k.

Let n_k^{m} denote the measurement noise at step k. Then

$$n_k^{\text{m}} \sim \mathcal{N}\big(0, \sigma_{\text{m}}^2 I_{d_{\text{in}}}\big)\,, \qquad y_k = U_1 x_k + n_k^{\text{m}}, \qquad \sigma_{\text{m}} \in \mathbb{R}_+, \tag{2.23}$$

drawn independently at every step.

2.3.1.4 Control Noise

Control noise, as the name says, acts on the applied control input. With it, we try to model the difference between the intended movement of an actuator and its actual action due to different factors. Here we deal with *multiplicative* noise, which scales with the input. In detail this means that the applied controller output $\tilde{v}_k$ is obtained as

$$n_k^{\text{c}} \sim \mathcal{N}\big(0, \sigma_{\text{c}}^2 I_{d_{\text{out}}}\big)\,, \qquad \tilde{v}_k = (\mathbf{1}_{d_{\text{out}}} + n_k^{\text{c}}) \odot v_k, \tag{2.24}$$

where $\odot$ denotes the elementwise product, so that σ_{c} is the *relative* error. Applying this to the input, the next step becomes

$$x_{k+1} = A\, x_k + BU_2\, \tilde{v}_k. \tag{2.25}$$

2.3.1.5 Parametric Uncertainty

This noise acts directly on the matrices of the model. Here, we either decide to keep it time invariant, meaning $\Delta_k^A = \Delta_0^A$ and $\Delta_k^B = \Delta_0^B$ for all k, or to resample it at every step. The former models a wrongly identified system, while the latter simulates one that continuously changes. As with measurement noise, it is additive. Applied, it acts on the system the following way:

$$\big(\Delta_k^A\big)_{ij}\,,\ \big(\Delta_k^B\big)_{ij} \overset{\text{i.i.d.}}{\sim} \mathcal{N}\big(0, \sigma_{\text{p}}^2\big)\,, \qquad x_{k+1} = \big(A + \Delta_k^A\big)\, x_k + \big(B + \Delta_k^B\big)\, U_2\, \tilde{v}_k. \tag{2.26}$$

Worth noting is that resampling every step leaves the model correct *on average*, since $\mathbb{E}[\Delta_k^A] = \mathbb{E}[\Delta_k^B] = 0$, and mainly adds variance to the trajectory. This stands in contrast to the time-invariant version, where we have a discrepancy between what we compute actions on and what actually happens.

2.3.1.6 External Disturbance

This noise models external influences, like a wind pushing on our agent, or rain hitting it with some frequency. It only affects the position, so with the first unit vector $e_1 \in \mathbb{R}^n$ and σ_d as the noise amplitude, we get

$$n_k^\mathrm{d} = \sigma_\mathrm{d} \sin(0.01\, k)\, e_1. \tag{2.27}$$

As the disturbance acts on the true state x_k, it is applied before any lifting of the observation (2.20a). The loop can thus be described as

$$x_{k+1} = A\, x_k + B U_2\, \tilde{v}_k + n_k^\mathrm{d}. \tag{2.28}$$

2.3.1.7 The Full Loop

While we, until now, have only regarded each noise type on its own, there is also the possibility to include them all at once. Combining all the channels with the inflated loop, a single step becomes

$$y_k = U_1 x_k + n_k^\mathrm{m}, \tag{2.29a}$$
$$v_k = -K y_k, \tag{2.29b}$$
$$\tilde{v}_k = (\mathbf{1}_{d_\mathrm{out}} + n_k^\mathrm{c}) \odot v_k, \tag{2.29c}$$
$$x_{k+1} = \left(A + \Delta_k^A\right) x_k + \left(B + \Delta_k^B\right) U_2\, \tilde{v}_k + n_k^\mathrm{d}. \tag{2.29d}$$

2.3.2 Metrics and Robustness

In this thesis we try to answer two main questions. First, how well a trained low-dimensional controller performs generally, as well as under influences unknown to it during training. Thus we aim to define here the metrics to quantify our results.

2.3.2.1 Cost and Suboptimality

By Section 2.1.3.1 no gain achieves a lower cost (2.18) than K^*, and every controller we train is therefore in the best case only as good as it. This serves as our baseline, and we evaluate the cost produced by our controllers in relation to it.

While we can easily calculate the infinite-horizon cost of a gain via the Lyapunov equation (2.16), we cannot effectively use it. The reason for that is that (2.16) can only be applied to the closed loop; however, when adding noise to our evaluation, this is not the case anymore. Additionally, the neural networks we train in later chapters do not admit a gain-matrix-based policy K, which would need a different approach anyway.

So, we instead evaluate them over a fixed horizon via rollout. Hence for a given controller, a noise condition c, which is a subset of channels and an intensity

(Section 2.3.2.4), and a horizon T, we simulate starting from a randomly drawn $x_0 \sim \mathcal{D}$. The resulting loop (2.29) under c thus accumulates

$$J_T^{(i,s)}(K;c) = \sum_{k=0}^{T-1} \Big((U_1 x_k)^\top \tilde{Q}\, (U_1 x_k) + \tilde{v}_k^\top \tilde{R}\, \tilde{v}_k \Big), \tag{2.30}$$

where s indexes the seed the run was trained under and i the episode within it.

It is important to note where $\tilde{Q}$ and $\tilde{R}$ act. As $\tilde{Q}$ penalizes the difference from the origin, we apply it on the inflated state *before* any noise is applied. This way we can evaluate the actual position of the mass, as shown in (2.21). For $\tilde{R}$, we handle it differently. Here, every actuation energy adds to the cost, irrespective of its origin (so whether the controller commanded it or it is noise).

Writing $\mathcal{F}$ for the pairs (s,i) whose episode stayed finite, the cost estimate becomes

$$\hat{J}_T(K;c) = \frac{1}{|\mathcal{F}|} \sum_{(s,i)\in\mathcal{F}} J_T^{(i,s)}(K;c), \qquad \mathcal{F} = \Big\{ (s,i) \;:\; J_T^{(i,s)}(K;c) < \infty \Big\}. \tag{2.31}$$

Given this information, we can state our main metric, which is the relative excess of the cost produced by a trained controller over the cost of the optimal controller K^* under the same condition. It is taken *per episode*, meaning an episode (s,i) of a trained controller and episode (s,i) of the baseline are compared here. Both start from the same x_0 and are affected by the same noise. Overall this yields

$$S^{(i,s)}(K;c) = \frac{J_T^{(i,s)}(K;c) - J_T^{(i,s)}(K^*;c)}{J_T^{(i,s)}(K^*;c)}, \qquad \hat{S}(K;c) = \frac{1}{|\mathcal{F}|} \sum_{(s,i)\in\mathcal{F}} S^{(i,s)}(K;c), \tag{2.32}$$

where $S = 0$ means that the trained controller performed as well as our baseline and $S = 0.1$ that it did 10 % worse.

2.3.2.2 Robustness to Noise

Our second metric relates to robustness, and helps us evaluate how much a controller is influenced by a noise condition c. It is the ratio of the test cost under noise c to the test cost under the clean loop. Formalized, this gives

$$\kappa^{(s)}(K;c) \coloneqq \frac{\hat{J}_T^{(s)}(K;c)}{\hat{J}_T^{(s)}(K;\varnothing)}, \tag{2.33}$$

where $\hat{J}_T^{(s)}$ is (2.31) containing only the episodes of seed s. Thus, the closer $\kappa^{(s)}(K;c)$ is to 1, the more robust a controller is. We can also compare this to the performance of the optimal gain, which we calibrated in (2.36) to specific ratios, by taking the ratio of the costs averaged over all seeds,

$$\kappa(K;c) \coloneqq \frac{\hat{J}_T(K;c)}{\hat{J}_T(K;\varnothing)}, \tag{2.34}$$

for which $\kappa_\ell = \kappa(K^*; c_\ell)$ holds by (2.36). As a result, this gives us the possibility to compare whether a specific trained controller is more or less robust than the baseline, or any other controller.

2.3.2.3 The Size of a Policy

We have often mentioned "low-dimensional" controllers until now; however, we want to make the number of parameters comparable, not only between different LQR controllers, but also across LQR and RL. So it is indeed a question of size. For a neural network we can simply count the number of weights and biases of the actor. For a gain matrix, however, we need to find a definition that is comparable to it.

The simplest approach for a $K \in \mathbb{R}^{m\times n}$ is the number of its entries, mn. In Chapter 3, however, we reduce the rank of K. Optimizing the storage size for K of rank r, the singular value decomposition [63, p. 85, Thm. 13.1] separates it into

$$K = U\Sigma V^\top, \qquad U \in \mathbb{R}^{m\times r}, \quad \Sigma = \operatorname{diag}(\sigma_1, \ldots, \sigma_r), \quad V \in \mathbb{R}^{n\times r}, \tag{2.35}$$

with U and V having orthonormal columns and $\sigma_1 \geq \cdots \geq \sigma_r > 0$ being the non-zero singular values. Hence, we only need to store mr entries for U, r for the diagonal of Σ and rn for V, which in total yields $r(m+n+1)$. For a small enough r this is less, so we take the minimum of both:

Definition 2.1 (Policy size)**.** The size of a linear policy $K \in \mathbb{R}^{m\times n}$ of rank $r = \operatorname{rank}(K)$ is

$$|K| \coloneqq \min\left\{mn,\ r\,(m+n+1)\right\},$$

the number of real numbers required to store it. The size of a neural policy is its total number of trainable parameters in the actor.

2.3.2.4 Noise Intensity

Section 2.3.1.2 introduced four channels which change the system compared to the base model. Each noise channel is separated further into five intensities,

$$\textit{none} \prec \textit{weak} \prec \textit{standard} \prec \textit{strong} \prec \textit{divergent},$$

where *none* leaves the system as it is and thus serves as our control condition. All the other intensities are calibrated by how much they increase the cost of the optimal gain K^* on the uninflated system. For each channel c and intensity ℓ, we choose the standard deviation in a way such that with the test protocol of Section 2.3.3

$$\hat{J}_T(K^*; c_\ell) = \kappa_\ell\, \hat{J}_T(K^*; \varnothing), \qquad \kappa_\ell \in \{1.2,\ 1.5,\ 3,\ 10\} \tag{2.36}$$

applies for *weak*, *standard*, *strong* and *divergent* respectively. For K^*, the increase stays the same under inflation for all channels except control noise. As it acts elementwise on the inflated output, it is averaged out over the number of actuators:

strong control noise raises the cost of K^* by a factor of 3.0 without inflation, but only by 1.22 and 1.05 at the sizes $d_{\text{in}} \times d_{\text{out}} = 50 \times 25$ and 200×100. For simplicity, however, we do not vary the levels by size, but instead accept this as a side effect. The concrete standard deviations per channel are listed in Table A.2.

2.3.3 Test Protocol

Having introduced our metrics, we now define a protocol for how we train and compare the different solver approaches with these metrics.

First, we note that we always use $\tilde{Q} = I_{d_{\text{in}}}$ and $\tilde{R} = I_{d_{\text{out}}}$ (so $Q = I_n$ and $R = I_m$ on the uninflated system), which weighs position, velocity and control effort equally. Initial states are drawn uniformly from the box $[-10, 10] \times [-1, 1]$. Some solvers require an initial stabilizing gain, which for the uninflated system is $K_0 = [\,0.1,\ 0.5\,]$, whose closed loop has $\rho(A - BK_0) \approx 0.9975$. On an inflated system, we use

$$\tilde{K}_0 = U_2^\top K_0 U_1^\top + N, \qquad U_2 N U_1 = 0, \qquad \|N\|_F = 0.5. \tag{2.37}$$

We create the random matrix N such that $U_2 N U_1 = 0$, and thus adding it does not change the stability property of the matrix. This way, the effective gain remains $U_2 \tilde{K}_0 U_1 = K_0$, while $\tilde{K}_0$ is full rank, which offers the possibility of rank reduction.

We train for each algorithm ten different solvers, starting from ten different fixed seeds, until convergence. We define convergence for LQR solvers as follows:

Definition 2.2 (Convergence)**.** Let g_j be the signal that a solver observes at iteration j, and let $\bar{g}_j$ be its mean over the last N_{w} iterations. The solver has *converged* at the first iteration j for which

$$\bar{g}_j \geq (1 - \varepsilon_{\text{rel}})\, \bar{g}_{j - N_{\text{p}}},$$

i.e. once the average has not decreased by the relative tolerance ε_{rel} within the last N_{p} iterations. After an iteration with an infinite signal, the comparison restarts, such that we never compare with a window across an infinite iteration.

The signal is something the solver itself observes and optimizes for. For Model-based PG and N4SID + Model-based PG it is the cost (2.18) on the true or identified model, for S-PI and N4SID + S-PI the regularized objective of S-PI (Section 3.1), and for Model-free NPG and S-PI (model-free) the rollout estimate of the cost. All variants of S-PI additionally stop once $\|K_{j+1} - K_j\|_F < 10^{-8}$. For all of them, we use the best iterate by $\bar{g}_j$ to identify the policy we want to use.

The parameters of Definition 2.2 for the model-based and the model-free solvers are listed in Table 2.2.

The number of steps the plant progressed and solver iterations until convergence are also counted and reported. An upper cap of 20 000 iterations is set to prevent looping.

Table 2.2: Parameters of the convergence rule (Definition 2.2) for the LQR solvers.

Parameter	Model-based solvers	Model-free solvers
Window N_{w}	1	50
Patience N_{p}	50	100
Relative tolerance $\varepsilon_{\mathrm{rel}}$	10^{-4}	10^{-3}

For RL-based algorithms we do not use such early-stopping logic. Following our experiments in Section B.8.3, we observed that implementing such a rule would lead to worse policies in the end. Instead, the best policy is achieved close to the end, which leads us to running each algorithm for as many steps as noted in Table 2.3, and then taking the final policy. Every 25 000 environment steps throughout, we evaluate the current policy's performance, to track its training process.

Table 2.3: Environment step budget of the RL solvers per inflation size.

	small	*medium*	*large*
Budget (environment steps)	10^7	$1.5 \cdot 10^7$	$3 \cdot 10^7$

After our controllers have been trained, we evaluate them per seed for *100 episodes* each, running for *2000 steps* per episode with a sampling period of $h = 0.01\,\mathrm{s}$. Each episode calculates its empirical cost (2.30), and thus its suboptimality (2.32) in comparison to the optimal gain on the same exact trajectory, with the same sampled $x_0 \sim \mathcal{D}$. In the end, for each solver architecture, we get a distribution of suboptimalities over a total of 1000 trajectories.

The inflated size is always the same between training and evaluation. For noise experiments, however, the controller is trained on a clean system, and then exposed to one with noise activated during testing.

Under the stronger conditions, individual rollouts might diverge. To keep our mean finite, we remove them from the mean calculation, and report them separately as the divergence rate

$$D(K;c) \coloneqq \frac{1}{MN} \left| \left\{ (s,i) \;:\; J_T^{(i,s)}(K;c) = \infty \right\} \right|, \tag{2.38}$$

where $M = 10$ is the number of seeds and $N = 100$ the number of episodes per seed. An individual episode can be missing from the result for another reason. Where the *baseline* evaluation of episode (s,i) diverged, $S^{(i,s)}$ has no value at all, since (2.32) would divide by an infinity. Those episodes are excluded from $\hat{S}$ and noted separately.

2.4 Approach

As mentioned before, the LQR serves as the perfect starting example, which is exactly why we start our investigation here. For our investigations, we will use the double integrator, as mentioned in Section 2.1.2.

First, as a basis, we will start by comparing the standard policy gradient (PG) approach [13] with S-PI [37] on the true model. Their relative performance to the baseline will be evaluated under the different inflation sizes introduced in Table 2.1. Then, the same controllers will be exposed to the different noise channels and intensities we introduced.

Afterwards, we will take a look at the cases where we do not have access to the real model. We compare the relative performance of both direct and indirect approaches to our baseline, which is the optimal controller calculated via the DARE (2.13) on the true model. For the indirect approaches, we will use numerical algorithms for subspace state-space system identification (N4SID) [60] to estimate the underlying model from one trajectory. A more detailed description, as well as the exact parameters selected, will be provided in the sections discussing the results. With this estimated model as the basis, we employ three different approaches on how to learn our policy, called N4SID + DARE, N4SID + Model-based PG and N4SID + S-PI. All these will also be discussed in Chapter 3.

Our first approach for Chapter 3 is to compare our selected methods across the inflation sizes, and see how increasing the dimension affects the performance of each. As the next step, we will apply the different noise channels named in Section 2.3.1.2 first to the base double integrator, where no overparameterization exists. The results we observe here will then be compared with evaluations of the controllers for a system with *large* inflation under different noise channels and strengths.

In Chapter 4, we will then first introduce RL-based approaches. With proximal policy optimization (PPO) [47] being one of the most used architecture variants in robotics [45, 36, 22], we choose this as our main architecture, and apply different variations of it. First, by using only one layer and dropping the activation function and the biases, we force the trained controller to be linear, which allows us to extract it as a gain matrix that we can closely compare with our LQR approaches (Linear PPO). The fully connected, standard version is named Fully-connected PPO, and will also be evaluated. Additionally, we will introduce structures that force the observations through a low-dimensional latent space. Here, we will reuse the N4SID system identifier from before, by using the transpose of its identified observation matrix $\hat{C}$, we project the high-dimensional observation into a lower dimension, and then train PPO with this as the input. Therefore, the name for it is State encoder + PPO. A similar approach is used for Scalable encoder + PPO, which is based on Jonschkowski and Brock [19] and Botteghi et al. [3], and uses robotic priors to derive a low-dimensional latent state via a trainable encoder. Again, the construction following this encoder is PPO. Lastly, we implement the orthonormal bottlenecks introduced by Todorov and Sabatelli [58] (Bottleneck PPO).

It consists of sampling a fixed matrix U_{b} with d_{b} orthonormal columns, which is added at the end of a trainable feature extractor, and used to project the output into a d_{b}-dimensional space. Like with the other encoders, we follow it with our PPO architecture.

All these low-dimensional approaches, if visualized, exhibit a "bow-tie" shape, which in nature can actually improve robustness [23]. So this is indeed interesting to investigate. However, first, like in Chapter 3, we start by comparing these different approaches across the different inflation sizes, without any noise applied, to see how they generally behave. Then, we introduce noise, and compare our approaches under *large* inflation dimensions.

Taking our results from the experiments on the artificially inflated dimensions, we create a new setup, still using the double integrator as our underlying structure. Here, we will observe the mass via a simulated camera, and place a number of actuators evenly distributed among angles on a half-circle. This will give us an actual high-dimensional input, as well as a high-dimensional output, that is in reality governed by low-dimensional dynamics.

By inputting images into our existing solvers, the dimensionality increases drastically. To be able to cleanly separate effects caused by the nonlinearity of the image construction from architecture-related effects, we will first artificially inflate our inputs and outputs to exactly the sizes that will later be used by the pixelated environment. This evaluation will only be done on Scalable encoder + PPO, Fully-connected PPO and Bottleneck PPO, as the other approaches either do not scale well or are not relevant to the comparison.

Then, using the same architectural constructions for these solvers, but applied to our new environment, we compare them with the additionally introduced position-velocity encoder [20] (Position-Velocity Encoder + PPO), which uses similar robotic priors to Scalable encoder + PPO, but focuses more on position, velocity and acceleration. It learns positional encodings from the observations, and then calculates the velocity state based on finite differences. Here, it is quite clear that we use knowledge of the limitations of the embodiment to construct more optimal controllers, again in a bow-tie shape. Finally, we will introduce this environment to noise as well, and observe the effects of it.

Chapter 3

Robustness of LQR Solvers in Different Dimensions

3.1 A Known Model

We start by comparing two approaches that have knowledge of the underlying model, and thus do not need to estimate gradients but can calculate them exactly. This allows us to clearly separate the benefits of a low-dimensional controller from estimation errors.

3.1.1 Setting

Fazel et al. [13] introduced global convergence guarantees for policy gradient methods based on the true model in 2018. The paper describes a method for calculating the gradient of a policy from the system and cost matrices, and updating the policy accordingly. As the paper uses the same $u_k = -Kx_k$ convention as we do, we can implement the loop directly in the following way.

Starting from an initial, stabilizing gain $K_0 \in \mathcal{K}$ and the second moment Σ_0 of the initial state distribution, every iteration j first solves the discrete Lyapunov equation (2.16) for P_{K_j} using the implementation from SciPy [49]. The state correlation matrix Σ_{K_j} then follows from solving a second Lyapunov equation,

$$\Sigma_{K_j} = (A - BK_j)\Sigma_{K_j}(A - BK_j)^\top + \Sigma_0, \tag{3.1}$$

where, for initial states drawn uniformly from $[-10, 10] \times [-1, 1]$ as described in Section 2.1.3.2, $\Sigma_0 = \mathrm{diag}\,(10^2/3,\, 1^2/3)$. The policy gradient

$$\nabla f(K_j) = 2\left(\left(R + B^\top P_{K_j} B\right) K_j - B^\top P_{K_j} A\right) \Sigma_{K_j} \tag{3.2}$$

is then used for a gradient step on the gain matrix. Algorithm 1 summarizes the loop.

Algorithm 1 Model-based PG

Require: stabilizing gain $K_0 \in \mathcal{K}$, second moment Σ_0, step size η

1: **for** $j = 0, 1, 2, \ldots$ **do**
2: solve (2.16) for P_{K_j}
3: solve (3.1) for Σ_{K_j}
4: compute the policy gradient $\nabla f(K_j)$ by (3.2)
5: update the gain by $K_{j+1} = K_j - \eta \nabla f(K_j)$
6: **end for**

The fixed learning rate η is a hyperparameter, which we set to $\eta = 10^{-5}$ for all inflation sizes, based on experiments whose results can be found in Section B.1. This policy gradient approach serves us as the basic, fully parameterized implementation for this experiment.

It is important to note that the above implementation is described for the uninflated loop. However, this can be easily applied to our inflated version by replacing every quantity with its inflated counterpart: $\tilde{A} = U_1 A U_1^\top$, $\tilde{B} = U_1 B U_2$, the inflated weights $\tilde{Q}$, $\tilde{R}$ in (2.22), $\tilde{\Sigma}_0 = U_1 \Sigma_0 U_1^\top$ and the initial gain $\tilde{K}_0$ from (2.37), such that the resulting gain is $K \in \mathbb{R}^{d_{\text{out}} \times d_{\text{in}}}$.

Now we also want to implement a solver that produces a low-dimensional controller. As in our case the controller is characterized by the gain matrix, and for matrices dimensionality is "often [...] expressed by means of the rank" [42], we aim at learning a low-rank gain matrix. However, to make this comparable later to RL approaches that rely on the number of parameters, we measure the complexity of a gain by its policy size $|K|$ from Definition 2.1, which uses the more efficient version between the full and the factored parameterization.

Recht et al. [42] have already shown that nuclear norm minimization introduces low-rank solutions for convex matrix problems. However, as we are dealing with a non-convex optimization problem [13], we cannot transfer the results over directly. Here, Park et al. [37] offer us an approach to impose different structures on our policy during learning via regularizers based on norms, one of them being the nuclear norm. We implement the model-based approach introduced there with small adaptations in the following way.

We reuse the computation of the gradient $\nabla f(K_j)$ from Algorithm 1. For inducing the structure, we optimize the regularized cost $f(K) + \lambda \|K\|_*$, where the nuclear norm $\|\cdot\|_*$ can be reduced by eliminating singular values of K, and λ is its weight in the whole cost. It further uses an adaptive learning rate, combined with a line search criterion, consisting of a stability and a sufficient decrease condition. Starting from the initial step size $\eta = 1/(2\lambda)$, following the paper's recommendation of $\mathcal{O}(1/\lambda)$, each iteration takes a gradient step and applies the proximal operator of the nuclear norm, which soft-thresholds the singular values,

$$K^+ = U \operatorname{diag}\left(\max\{\sigma_1 - \eta\lambda, 0\}, \ldots, \max\{\sigma_{\bar{r}} - \eta\lambda, 0\}\right) V^\top, \qquad \bar{r} \coloneqq \min\{d_{\text{out}}, d_{\text{in}}\}, \tag{3.3}$$

where $U \operatorname{diag}(\sigma_1, \ldots, \sigma_{\bar{r}}) V^\top$ is the singular value decomposition of the gradient step $K_j - \eta \nabla f(K_j)$. The candidate K^+ is accepted if it is stabilizing, $\rho(A - BK^+) < 1$, and satisfies the sufficient decrease condition

$$f(K^+) \leq f(K_j) - \eta \operatorname{tr}\left(\nabla f(K_j)^\top G\right) + \frac{\eta}{2}\|G\|_F^2, \qquad G \coloneqq \frac{1}{\eta}\left(K_j - K^+\right). \tag{3.4}$$

Otherwise, the step size is reduced to $\beta\eta$ and the proximal step is repeated. The learning loop further can be stopped earlier if the criterion $\|K_{j+1} - K_j\|_F \leq \varepsilon$ is satisfied. Algorithm 2 summarizes the loop.

Algorithm 2 S-PI

Require: stabilizing gain $K_0 \in \mathcal{K}$, second moment Σ_0, weight λ, factor β, tolerance ε

1: **for** $j = 0, 1, 2, \ldots$ **do**
2: compute $\nabla f(K_j)$ as in Algorithm 1
3: set the initial step size $\eta = 1/(2\lambda)$
4: **for** at most 20 line search steps **do**
5: compute the candidate K^+ by (3.3)
6: **if** $\rho(A - BK^+) < 1$ and (3.4) holds **then**
7: **break**
8: **end if**
9: reduce the step size, $\eta \leftarrow \beta\eta$
10: **end for**
11: update the gain, $K_{j+1} = K^+$
12: **if** $\|K_{j+1} - K_j\|_F \leq \varepsilon$ **then**
13: **stop**
14: **end if**
15: **end for**

As one can see, there are a lot of parameters that can be modified here. We set $\varepsilon = 10^{-8}$, and use the same $\beta = 0.5$ as in the experiments section of Park et al. [37]. For λ, as it defines the learning rate as well, we have run an experiment with various values, which can be found in Section B.2. A value of $\lambda = 5$ has shown the most promising results across the sizes.

One thing that we implemented differently than the paper is the cap on the number of line search iterations in line four, which we set to 20. Some of our previous experiments had shown that if we leave it uncapped, for unstable updates which are impossible to stabilize, the loop runs until the update produces no effect at all.

Now that we have defined our controllers and how they learn, we test them in comparison to the DARE-calculated solution (2.13) from Section 2.1.3.1.

3.1.2 Results

We apply our solvers to the *base* and inflated versions of the true model, for now noise-free, as described in Section 2.3.1.1. Specifically, as in Section 2.3.3, we train ten controllers per solver, before evaluating them on the test episodes. The results are then pooled.

The most interesting finding is how much faster S-PI converges compared to Model-based PG. While it achieves its best training suboptimality within around 50 iterations, Model-based PG still falls drastically short of it after 450 iterations. We can also see in Table 3.1 that the reduction in complexity for all inflation sizes has worked well with S-PI. For our test suboptimality, S-PI also outperforms Model-based PG here by at least one order of magnitude. Figure 3.1 visualizes this.

Table 3.1: Size of the policy architectures on the true model, across every inflation size.

	Policy parameters				Gain rank			
Solver	base	small	medium	large	base	small	medium	large
Baseline	2	16	76	301	1.0	1.0	1.0	1.0
Model-based PG	2	50	1250	20000	1.0	5.0	25.0	100.0
S-PI	2	16	76	301	1.0	1.0	1.0	1.0





Figure 3.1: Suboptimality S of the solvers on the true model for each inflation size.

Overall, this looks very promising for S-PI; still, our goal is to find out whether it is also a robust controller.

3.1.3 Noise Experiments

Now, we reuse the controllers we trained in Section 3.1.2 and evaluate them under the test protocol with noise (Section 2.3.1.2) injected.

When looking at the results, one can notice that our baseline controller, which was optimal for the clean loop, mostly performs worse than our trained controllers, except for external disturbance. However, when only comparing Model-based PG with S-PI, we can see differences in their performance, depending on the type of noise that is applied, as well as whether the loop is inflated or not. For parametric uncertainty, no real difference can be seen between the mean performance of all controllers; however, Model-based PG shows a higher variance. When looking at external disturbance under *large* inflation, one can notice that with increasing noise it becomes clearer that S-PI is more robust here compared to Model-based PG. While for *weak* and *standard* their total spread still shows some overlap, for *strong* and *divergent* S-PI shows a cleanly separated suboptimality below Model-based PG (Fig. 3.2).




(a) Intensity *standard*.

(b) Intensity *divergent*.

Figure 3.2: Suboptimality S of the solvers on the true model under *large* inflation and external disturbance at different intensities.

For control noise in comparison, we can see that here Model-based PG is more robust on average across settings. However, its worst-case performance here is worse than that of S-PI, so it has an overall wider spread of suboptimalities. Still, both mostly outperform the baseline controller. Measurement noise becomes an interesting case here. While both controllers outperform the baseline, under no inflation, Model-based PG seems to be much more robust here. However, when looking at the controllers under *large* inflation with the same noise level applied, Model-based PG deteriorates here, with the spread now reaching suboptimality values worse than baseline. Compared to that, S-PI shows more robustness here

with little variation and stays at a similar value, better than baseline. Figure 3.3 visualizes this.



(a) *base* inflation.

(b) *large* inflation.

Figure 3.3: Suboptimality S of the solvers on the true model under measurement noise at intensity *divergent*.

Overall, for the *strong* level and *large* inflation, this is how both controllers compare to the baseline and each other across the noise channels (Table 3.2).

Table 3.2: Relative degradation κ and Absolute degradation $\Delta\hat{J}/\hat{J}^*$ under *large* inflation and each noise channel at intensity *strong*.

	Relative degradation κ						Absolute degradation $\Delta\hat{J}/\hat{J}^*$					
Solver	none	measurement	control	parametric	disturbance	all channels	none	measurement	control	parametric	disturbance	all channels
Baseline	1	3.02 ± 0.198	2.76 ± 0.0212	2.98 ± 1.06	3.03 ± 0.219	106 ± 17.4	0	2 ± 0.00746	1.76 ± 0.18	2.02 ± 1.22	2.01 ± 0.0467	105 ± 22.8
Model-based PG	1	3.02 ± 0.198	2.72 ± 0.0205	2.96 ± 1.06	3.06 ± 0.222	102 ± 16.2	0	2 ± 0.00695	1.72 ± 0.177	2 ± 1.21	2.04 ± 0.0472	101 ± 21.2
S-PI	1	3 ± 0.196	2.75 ± 0.021	2.97 ± 1.06	3.03 ± 0.219	105 ± 17.1	0	1.98 ± 0.00737	1.75 ± 0.18	2.01 ± 1.22	2.01 ± 0.0468	104 ± 22.5

3.1.4 Discussion

Generally, we note that trained controllers are mostly at an advantage compared to statically calculated controllers with regard to robustness. By not achieving full optimality on the nominal problem, they can endure measurement and control noise better; however, they are still more affected by external disturbances. When comparing now trained fully parameterized and structured approaches, differences definitely appear. Changes in the underlying model, as in parametric uncertainty, affect all controllers mostly the same, with on average no real difference to the baseline. Looking at the other cases, we find that low-dimensional controllers actually offer better robustness in strong noise related to the inputs of the controller, especially the larger the input dimension. Measurement noise shows this clearly, as the performance of an overparameterized controller degrades here with increasing

size, while a regularized controller stays robust across sizes. This stems from the construction of our initial policy. As the full-rank component of $\tilde{K}_0$ is not affected by any inflated input on the nominal plant, Model-based PG, contrary to S-PI, does not remove it. These components then become costly under measurement noise, whereas S-PI stays resistant. However, related to the output dimensions, under control noise reduced controllers perform worse on average, but still better in the worst case than the full controller. And under *large* size the reduction in needed parameters is two orders of magnitude, which shows the efficiency of the reduced controller.

3.2 Unknown Model across Dimensions

Now we take a look at the more realistic case, where we do not know the underlying model, and compare different approaches. Before we can get into the results, we first take a deeper look at the solvers that we use and how the experiments are set up.

3.2.1 Setting

First, we introduce our basis for the indirect model-free approach, which is based on system identification. N4SID, introduced by Van Overschee and De Moor [60], uses "the projection of the future outputs [of the system] onto the past and future inputs and the past outputs" [60, Sec. 3]. These projections are then called "a function of the system matrices and the input-output block Hankel matrices" [60, Sec. 3], which allows us to reconstruct exactly that from the results. Important are further the assumptions that the systems are observable and controllable [62, pp. 127–128]. For simplicity, we rely on the implementation of N4SID from SIPPY [50], which we integrate into our own setup. This implementation allows us to recover the system matrices A, B and C, whereas the cost matrices $\tilde{Q}$ and $\tilde{R}$ are choices of the controller design (Section 2.3.3), and thus already known beforehand.

The collection of observation and action data runs the plant for T steps under the initial gain, with a randomly sampled excitation added on top of it,

$$v_k = -\tilde{K}_0 y_k + \sigma_e w_k, \qquad w_k \sim \mathcal{N}(0, I_{d_{\text{out}}}), \qquad k = 0, \dots, T-1. \tag{3.5}$$

The paper mentions that the approximation error becomes smaller as the number of block rows of the Hankel matrices grows [60, Sec. 5.3]. With the number of columns being dependent on our trajectory length T, we aim to find the best combination of both. Denoting the number of block rows as the "Hankel horizon", we evaluated different combinations to find the optimal setting to use in our experiment. The full results of the selection can be found in Section B.3. Specifically, we use the settings in Table 3.3.

The resulting identified system then serves as a surrogate for the true model for the model-based approaches from Section 3.1.1. We use for N4SID + Model-based

Table 3.3: Identification settings per inflation size.

Name	Trajectory length T	Hankel horizon
base	500	5
small	500	5
medium	500	5
large	2000	5

PG an $\eta = 10^{-4}$ and for N4SID + S-PI $\lambda = 1$ across all sizes. This thus produces results without ever having access to the real model.

An attentive reader might now ask why we would even want to use these iterative approaches, if we could just solve the DARE (2.13) directly on this estimation. And indeed we include this N4SID + DARE controller as an indicator for how well N4SID identifies the system in our following comparisons.

Additionally, we also use direct model-free approaches, which are variations of the model-based approaches from Section 3.1. Unlike before, they do not calculate the gradient directly, but estimate it based on the returns of N_{traj} pairs of perturbed versions $K \pm \Xi_i$ of the current policy K, each simulated for l steps. As one might assume, more "data" could conversely lead to better estimation and thus better policy updates, but it requires more computation. So, to settle this, we evaluated different combinations of them in Section B.4. The best trade-off between computational efficiency and quality gave $N_{\text{traj}} = 200$ and $l = 500$.

We use the model-free natural policy gradient (NPG) estimation described by Fazel et al. [13], which at its core consists of the loop in Algorithm 3. Instead of the proposed single-point estimator, we use a two-point estimator inspired by Duchi et al. and Mania et al. [11, 29], as this drastically reduced the variance of the estimates, and thus the instability of the controller.

We further aim to clarify a couple of things about the given loop. Subtracting the mean difference $\bar{\delta}$ does not change the expected value of the estimate, since $\mathbb{E}[\Xi_i] = 0$, but lowers its variance. A rollout whose observation exceeds $\|y_k\| = 10^5$, we count as diverged. It is therefore ended early and charged a penalty cost of 10^{10}. Additionally, for inflated dimensions, $\hat{\Sigma}_K$ is singular, so we precondition with its truncated pseudoinverse $\hat{\Sigma}_K^{\dagger}$ instead, which discards singular values below 10^{-6} times the largest one.

Our full learning algorithm is then given in Algorithm 4.

After some evaluations, we have decided on a smoothing parameter of $r = 0.5$, and a learning rate of $\eta_{\text{base}} = 0.1$, $\eta_{\text{small}} = 0.03$, $\eta_{\text{medium}} = 0.01$ and $\eta_{\text{large}} = 0.01$ based on the results in Section B.5.

Next, we implement a model-free version of S-PI that relies on the same gradient es-

Algorithm 3 Two-point gradient estimation

Require: gain $K \in \mathbb{R}^{d_{\text{out}} \times d_{\text{in}}}$, number of perturbation pairs N_{traj}, rollout length l, smoothing radius r

for $i = 1, \dots, N_{\text{traj}}$ **do**
  sample Ξ_i uniformly from the matrices with $\|\Xi_i\|_F = r$
  sample an initial state $x_0 \sim \mathcal{D}$
  simulate $K + \Xi_i$ and $K - \Xi_i$ for l steps from x_0, with stage costs $c_k^{\pm}$ and observations $y_k^{\pm}$
  $\hat{J}_i^{\pm} = \sum_{k=0}^{l-1} c_k^{\pm}, \quad \hat{\Sigma}_i^{\pm} = \sum_{k=0}^{l-1} y_k^{\pm} \left(y_k^{\pm}\right)^{\top}, \quad \delta_i = \hat{J}_i^{+} - \hat{J}_i^{-}$
end for
$\bar{\delta} = \frac{1}{N_{\text{traj}}} \sum_{i=1}^{N_{\text{traj}}} \delta_i$
$\widehat{\nabla f}(K) = \frac{1}{N_{\text{traj}}} \sum_{i=1}^{N_{\text{traj}}} \frac{d_{\text{out}} d_{\text{in}}}{2r^2} \left(\delta_i - \bar{\delta}\right) \Xi_i$
$\hat{\Sigma}_K = \frac{1}{N_{\text{traj}}} \sum_{i=1}^{N_{\text{traj}}} \left(\hat{\Sigma}_i^{+} + \hat{\Sigma}_i^{-}\right)$
$\hat{f}(K) = \frac{1}{N_{\text{traj}}} \sum_{i=1}^{N_{\text{traj}}} \frac{1}{2} \left(\hat{J}_i^{+} + \hat{J}_i^{-}\right)$
return $\widehat{\nabla f}(K)$, $\hat{\Sigma}_K$, $\hat{f}(K)$

Algorithm 4 Model-free NPG

Require: stabilizing gain $K_0 \in \mathcal{K}$, N_{traj}, l, r, step size η

for $j = 0, 1, 2, \dots$ **do**
  compute $\widehat{\nabla f}(K_j)$ and $\hat{\Sigma}_{K_j}$ by Algorithm 3
  update the gain by $K_{j+1} = K_j - \eta \, \widehat{\nabla f}(K_j) \, \hat{\Sigma}_{K_j}^{\dagger}$
end for

timation (Algorithm 3) as Model-free NPG. Another crucial difference, apart from the estimation of the gradient compared to the calculation, is the "usage of a fixed stepsize η, rather than an adaptive stepsize from a backtracking linesearch" [37, Sec. 3.1], as that would require access to the function value $f(K) = \operatorname{tr}(P_K \Sigma_0)$. Before we look at how we select this step size and λ, we define our learning loop in Algorithm 5.

Algorithm 5 S-PI (model-free)

Require: stabilizing gain $K_0 \in \mathcal{K}$, N_{traj}, l, r, fixed step size η, weight λ, tolerance ε

for $j = 0, 1, 2, \dots$ **do**
  compute $\widehat{\nabla f}(K_j)$ by Algorithm 3
  compute K_{j+1} by (3.3), with $\widehat{\nabla f}(K_j)$ in place of $\nabla f(K_j)$
  if $\|K_{j+1} - K_j\|_F < 10^{-8}$ **then**
    stop
  end if
end for

Now to the selection of the parameters. Park et al. already note the difficulty of finding a fixed step size that does not produce divergence of the method [37]. Also, the example shown only uses the model-based approach and the regularizer to induce sparse structure, not the model-free variant combined with low dimensionality. So during our first tests, we often ran into either unstable controllers, or ones that did not induce any structure at all, hinting at a too low λ. If we remember the proximal step (3.3), we can see that it depends on both the step size and λ, as every singular value is mapped to

$$\sigma_i \mapsto \max\{\sigma_i - \eta\lambda, 0\}. \tag{3.6}$$

Even after some improvement by using the two-point estimator (Algorithm 3), it remained quite a difficult topic. So rather extensive experiments on the variation of λ and the step size can be found in Section B.6. Based on those, we selected $\lambda_{\text{base}} = 4$ and $\eta_{\text{base}} = 3.5 \times 10^{-6}$, $\lambda_{\text{small}} = 400$ and $\eta_{\text{small}} = 3.5 \times 10^{-5}$, $\lambda_{\text{medium}} = 400$ and $\eta_{\text{medium}} = 3.5 \times 10^{-5}$; and $\lambda_{\text{large}} = 40\,000$ and $\eta_{\text{large}} = 3.5 \times 10^{-8}$.

3.2.2 Results

Looking at the time until convergence, as well as the achieved training suboptimality, we notice that S-PI (model-free) produced under *large* inflation a very expensive gain, while still not achieving a strong reduction in rank. As this was the same problem we observed during our parameter search (Section B.6), we accept it as an unsuccessful attempt and difficult to implement. Apart from this, it is noticeable that Model-free NPG takes longer to converge the larger the inflation gets, with it being much slower than N4SID + S-PI and N4SID + Model-based PG, where N4SID + S-PI again is still much faster than N4SID + Model-based PG. The fastest approach here is the DARE solution, as it only requires the identification step, and no iteration.

Looking at the policy sizes, we can see that N4SID + S-PI indeed reduces its size to that of the optimal policy, with the DARE policy also being smaller than the iterative versions, but still slightly larger (Fig. 3.4).

Analyzing the resulting test suboptimality, we see the expected worse performance of S-PI (model-free), but also that the direct approaches underperform the indirect (identification) approaches. Here, we can also notice a difference: with increasing inflation size, the Model-free NPG trains for more iterations, with an increase from 167 at *base* to 610 at *large*, while for the identification-based policies it stays similar. What also jumps out is that N4SID + DARE in some cases even achieves optimal performance (Fig. 3.5).

3.2.3 Noise Experiments on Large Inflation

We first start by analyzing the effects we can observe on the uninflated system under noise. For parametric uncertainty, the spread of suboptimality again ranges




Figure 3.4: Policy size $|K|$ (Definition 2.1) learned without the model, for each inflation size.





Figure 3.5: Suboptimality S of the solvers without the model for each inflation size.

from $+0.1$ to -0.1 for all the iteratively trained approaches, with the DARE solution having a much smaller spread, centered around the baseline. Still, it is observable that the N4SID-based solvers perform on average much better than the direct approaches. For control noise a similar structure can be noticed; here, however, the spreads separate much more clearly into worse for direct approaches and better for indirect approaches. For both external disturbance and measurement noise, the DARE solution remains closely spread around 0. For external disturbance, all the other solvers except for Model-free NPG perform worse than the

baseline, while Model-free NPG sits at a suboptimality of -0.1 for *divergent*. For measurement noise, the image suddenly flips, with Model-free NPG performing worse, while all the other approaches sit at a suboptimality of around -0.01.

Now inflating the system to *large* size and repeating our experiments, we see similar observations for parametric uncertainty, except for S-PI (model-free), which performs worse than the others by multiple orders of magnitude. Looking at control noise, on average Model-free NPG performs best here, even though the spread under *strong* or *divergent* control noise admits episodes worse than the baseline. Iterative N4SID solvers in comparison here do also outperform the baseline, but are slightly worse than Model-free NPG. However, they remain consistently below baseline across all intensities and runs. The most interesting observation here is that, even though S-PI (model-free) performs much worse on the clean plant, its median is on par with Model-free NPG under *divergent* control noise (Fig. 3.6), even though its mean lies above the baseline.




(a) External disturbance at intensity *strong*.

(b) Control noise at intensity *divergent*.

Figure 3.6: Suboptimality S of the solvers without the model under *large* inflation.

For external disturbance, the indirect solvers perform worse here, while Model-free NPG is clearly the robust choice here, under any strength. Again, it is noticeable that the stronger the noise gets, the more runs of S-PI (model-free) achieve a negative suboptimality. While on average still worse, under *divergent* intensity, some do indeed perform the same as Model-free NPG. This phenomenon can also be observed with measurement noise: here, S-PI (model-free) is on average at a suboptimality of 10, 1 and 0.1 for *weak*, *standard* and *strong*, but for *divergent* it then clearly sits at -1. With increasing intensity, the spread can be seen shifting more and more downwards. Between indirect solvers, N4SID + S-PI is the only one that stays below baseline at every intensity, performing better than N4SID + Model-based PG, which differs from it only by its full-rank gain. Overall, it can

be seen that the reduction-based solvers do perform better here than their fully parameterized counterparts under *divergent* intensity (Fig. 3.7).



(a) Intensity *standard*.

(b) Intensity *divergent*.

Figure 3.7: Suboptimality S of the solvers without the model under *large* inflation and measurement noise.

3.2.4 Discussion

Overall, we notice that for a clean plant, identifying the system and solving the DARE based on these observations is the fastest solution, and even under noise it achieves a performance similar to the baseline solution. A good alternative is offered by approaches that use the same identified system and combine it with model-based approaches. They offer, in the case of S-PI, a much shorter training than direct approaches, and, due to their suboptimality on the nominal loop, they are more robust to control noise. Compared to them, direct approaches require much more training, and perform worse on the clean system. The only exception is external disturbance, where Model-free NPG, as a fully parameterized, iteratively trained policy, outperforms all other approaches.

This distinction between fully parameterized and dimensionally reduced must also be made. While the direct S-PI (model-free) approach varies quite a lot in its performance, under measurement noise on inflated systems, it improves in comparison to its counterpart, and even outperforms it under *divergent* noise. N4SID + S-PI compared with N4SID + Model-based PG does so across all measurement noise intensities.

Combining both of these distinctions, in most cases, except for external disturbance, an N4SID + S-PI-based controller is the best choice. It offers the advantages of fast training of N4SID, better performance than baseline under control noise, together with the robustness under measurement noise from the reduced

dimensionality, while also being orders of magnitude smaller. Solving the DARE directly also offers a good solution, being stable across all experiments, but it is often outperformed by the reduced controller.

3.3 Discussion

We take from this chapter that direct approaches are mostly outperformed by indirect approaches, which try to identify the model first. They require around four orders of magnitude of training steps less, and achieve performances close to optimal on the clean plant. By not reaching full optimality, they are less affected by control noise than the DARE solution on the clean plant. Regarding noise, it is also noticeable that the strength of low-dimensional controllers is their resistance to measurement noise, which becomes much clearer under increasingly larger dimensions as full-rank parameterizations do not remove components in the null space. With these learnings in mind, we will now progress to our RL approaches next.

Chapter 4

Robustness of Reinforcement Learning Approaches

Having seen how low dimensionality affects robustness with a simple, LQR-based controller, we now want to take a look at a setting which allows us to judge architectures used in more complex tasks as well. Still, we will stay with our introduced double-integrator system, but change the controllers for now.

4.1 PPO and Its Variants

4.1.1 Proximal Policy Optimization

Before getting into our implementation details, we want to explain the basic construction of PPO. Introduced by Schulman et al. [47] in 2017, it is an actor-critic algorithm, which means it consists of an actor, guided by a policy, that is simulated in an environment, and a critic, which tries to estimate the underlying value function based on the current policy and the actor's returns [24]. In the case of PPO, as we are trying to optimize a policy via policy gradient optimization, we "[construct] an objective function whose gradient is the policy gradient estimator" [47, Sec. 2.1]. What makes PPO special is the construction of this surrogate function, based on ideas from Trust Region Policy Optimization [46]. In the paper, two approaches are proposed: a Clipped Surrogate Objective or an Adaptive Kullback–Leibler (KL) Penalty Coefficient. The former clips the probability ratio past a limit set by a hyperparameter, imposing constraints on the policy update size [47, Sec. 3], while the latter, rather than setting a fixed KL for an update, sets a target KL divergence [47, Sec. 4]. In case further interest arises, we refer to the original paper [47]. With the probability ratio $r_k(\theta)$ between the current policy π_θ

and the policy $\pi_{\theta_{\text{old}}}$ that collected the data, the clipped objective becomes

$$\begin{aligned} r_k(\theta) &= \frac{\pi_\theta(v_k \mid y_k)}{\pi_{\theta_{\text{old}}}(v_k \mid y_k)}, \\ L^{\text{CLIP}}(\theta) &= \hat{\mathbb{E}}_k \left[\min \left\{ r_k(\theta)\hat{A}_k,\ \text{clip}\left(r_k(\theta), 1-\varepsilon_{\text{clip}}, 1+\varepsilon_{\text{clip}}\right)\hat{A}_k \right\} \right]. \end{aligned} \tag{4.1}$$

4.1.2 Training Setup

However, as has been noted before [12, 15], the actual implementation of PPO matters, and can influence the effectiveness of it in practice. For our construction, we use the architecture provided by Stable-Baselines3 (SB3) [52]. As the standard architecture, for our Fully-connected PPO, we use the standard two-layer multilayer perceptron (MLP) with 64 neurons per layer for both the actor and the critic [51]. Table B.11 in Section B.8 lists all deviations from the default parameters. After evaluating different values, we settled on the learning rates in Table B.12, which differ by inflation size.

After initial runs with this basic setup, we could observe some divergence behavior, which led us to consider additional implementation improvements, as suggested by Huang et al. [17]. Specifically, we modified the discount factor to $\gamma = 0.999$ instead of 0.99 and used the reward normalization implementation from SB3 [53], based on a discounted moving average [17, continuous-action Detail 8]. However, the two most effective changes were:

1. Using learning-rate annealing instead of a fixed rate [17, Detail 4]. Now the learning rate is decreased with every update, such that at the end of the step budget (Table 2.3) it is equal to 0. So this is

$$\eta(N_{\text{env}}) = \eta_0 \max\left\{1 - \frac{N_{\text{env}}}{N_{\max}},\ 0\right\}. \tag{4.2}$$

2. Separating the feature extractors for actor and critic [17, Detail 13]. As described in the SB3 documentation [51], to reduce computation, in the standard implementation, the extractor is shared by default. For extractors that are trained together with PPO, we separate actor and critic extractors, such that they are trained separately. Later, when introducing pretrained extractors which are fixed post-training, those will be shared again.

Algorithm 6 summarizes the resulting training loop.

4.1.3 Policy Architectures

Now that we have introduced the base construction, it is easier for us to describe variations of it. We start with Linear PPO, which allows us to compare the performance of PPO to the previous chapter. Here, our actor becomes a single layer, with the bias removed, such that we can rewrite this network as

$$\mu(y_k) = W y_k = -K y_k, \qquad K \coloneqq -W \in \mathbb{R}^{d_{\text{out}} \times d_{\text{in}}}, \tag{4.3}$$

Algorithm 6 PPO implemented here

Require: initial actor π_θ and critic V_ϕ, initial learning rate η_0, step budget $N_{\max}$

$N_{\text{env}} \leftarrow 0$
while $N_{\text{env}} < N_{\max}$ **do**
  run π_θ for 2048 steps, sampling $v_k \sim \pi_\theta(\cdot \mid y_k)$; store y_k, v_k and the rewards
  normalize the rewards by a running estimate of the return's standard deviation
  compute the advantages $\hat{A}_k$ and value targets with V_ϕ
  $\theta_{\text{old}} \leftarrow \theta$, set the learning rate $\eta(N_{\text{env}})$ by (4.2)
  for epoch $= 1, \ldots, 10$ **do**
    for each minibatch of 64 stored steps **do**
      take an Adam step on $-L^{\text{CLIP}}(\theta) + 0.5 \cdot$ (value loss of V_ϕ), with the gradient norm clipped to 0.5
    end for
    if the approximate KL divergence to $\pi_{\theta_{\text{old}}}$ exceeds $1.5 \cdot 0.02$ **then**
      break
    end if
  end for
  $N_{\text{env}} \leftarrow N_{\text{env}} + 2048$
  if 25 000 steps have passed since the last evaluation **then**
    evaluate π_θ for the learning curve
  end if
end while
return the final policy π_θ

which allows us to extract a gain matrix K that is comparable to the previous chapter. A second, already known, component is used for State encoder + PPO. Here, we reuse an identified system from N4SID (Section 3.2) to encode an observation into a latent state:

$$\hat{x}_k = \hat{C}^\top y_k, \qquad \hat{C} \in \mathbb{R}^{d_{\text{in}} \times \hat{n}}, \quad \hat{C}^\top \hat{C} = I_{\hat{n}}. \tag{4.4}$$

The input dimension for both the actor and the critic thus becomes $\hat{n}$, which is the order of the identified model.

However, as we will later scale our inputs to larger dimensions (Chapter 5), N4SID will become infeasible for such dimensions. Still, we want to stay in line with the idea of encoding our observations into a latent state, as this exactly introduces the bow-tie structure we want. So, we introduce another encoder, which offers this scalability, and call the combination Scalable encoder + PPO. This feature extractor is based on the results of Jonschkowski and Brock [19] and Botteghi et al. [3], which use robotic priors. Robotic priors, simply described, are prior knowledge, like physical laws, from which we define loss functions. By adding them to the training process, and optimizing for them, we can ensure that the learned representation is in line with these laws. As mentioned in Section 2.4, this

allows us to make use of the embodiment to improve our controller architecture. Here, we will use the following priors [3]:

- simplicity: the relevant information is lower in dimensionality than the observation,
- temporal coherence: state changes are rather slow,
- proportionality: similar actions should show similar output magnitudes,
- repeatability: similar actions in similar states should show similar state changes,
- causality: prevents the trivial solution of mapping every observation to the same point.

We modify the loss calculations taken from the paper [3] slightly, by dropping the $\mathcal{L}_{\text{reg}}$ term, and thus get the total loss function of

$$\mathcal{L} = \omega_1 \mathcal{L}_{\text{temp}} + \omega_2 \mathcal{L}_{\text{prop}} + \omega_3 \mathcal{L}_{\text{rep}} + \omega_4 \mathcal{L}_{\text{caus}}, \tag{4.5}$$

with $\omega_1 = \omega_2 = \omega_3 = 1$ and $\omega_4 = 2$.

As this encoder must be trained first, we pretrain it for 20 epochs on 20 000 collected environment steps, before freezing its parameters and prepending it to the actor and the critic. The data is collected by running a policy using the initial gain $\tilde{K}_0$ or a randomly drawn action in a 70 %/30 % split on the environment for at most 800 consecutive steps.

An important parameter is also the dimension of the latent state, which we set to the actual "2" here. Although for later application, one might not know the real, underlying dimension of the dynamics, we want to make it comparable across the solvers by using the same low dimension. And as N4SID mostly correctly identifies the true dimension, we use it here as well. Algorithm 7 summarizes the pretraining.

The second trainable extractor we used is based on the paper by Todorov and Sabatelli [58], using orthogonal bottlenecks. It consists of a fully connected MLP, with 512 neurons in the first, and 256 neurons in the second and third layer, using a ReLU activation function. Following it is a matrix with orthonormal columns, which projects the output into a state of bottleneck dimension d_{b}, which we here set to 2. Like U_1 in (2.19), the matrix is the orthonormal factor of the QR decomposition of a random matrix with standard normal entries, so that the feature extractor output $z_k \in \mathbb{R}^{d_z}$ is mapped to

$$U_{\text{b}}^\top z_k \in \mathbb{R}^{d_{\text{b}}}, \qquad U_{\text{b}} \in \mathbb{R}^{d_z \times d_{\text{b}}}, \quad U_{\text{b}}^\top U_{\text{b}} = I_{d_{\text{b}}}. \tag{4.6}$$

Unlike the previous encoder, this one is trained together with PPO, so the actor and critic train them separately, while the projection matrix U_{b} stays the same for both.

Figure A.1 in Section A.4 visualizes the architectures of all our solvers.

Algorithm 7 Pretraining of the scalable encoder

Require: initial gain $\tilde{K}_0$, action bound $a_{\max}$, encoder $f_\psi \colon \mathbb{R}^{d_{\text{in}}} \to \mathbb{R}^2$, weights $\omega_1, \ldots, \omega_4$

for $k = 0, \ldots, 20\,000 - 1$ **do**
  with probability 0.3, draw v_k uniformly from $[-a_{\max}/10, a_{\max}/10]^{d_{\text{out}}}$, otherwise set $v_k = -\tilde{K}_0 y_k$
  apply v_k, store (y_k, v_k, y_{k+1}), and reset the plant after 800 steps
end for
for epoch $= 1, \ldots, 20$ **do**
  for each minibatch of 128 stored transitions **do**
    pair every transition with a randomly drawn second transition
    take an Adam step on $\omega_1\mathcal{L}_{\text{temp}} + \omega_2\mathcal{L}_{\text{prop}} + \omega_3\mathcal{L}_{\text{rep}} + \omega_4\mathcal{L}_{\text{caus}}$ of these pairs
  end for
end for
standardize the latent state with its mean and standard deviation over the stored observations
freeze ψ and place f_ψ in front of the actor and the critic

4.2 Comparison across Dimensions

Looking at achieved suboptimality during training, we overall see a learning process in all of our architectures (Fig. 4.1). Noticeable, however, is the long stagnation in the beginning of the learning, before decreasing towards the end. Significant is also Linear PPO, which does not achieve an improvement under *large*, but this was expected, given its unsuccessful learning-rate search results (Fig. B.9).

Looking at the complexity of our trained policies, we notice that the difference between our "low-dimensional" and fully connected architectures. Especially under *small* and *medium*, Scalable encoder + PPO is even larger than Fully-connected PPO, while the others are on par. However, under *large* a difference does become noticeable, with Fully-connected PPO being around 1.6 times the size of Scalable encoder + PPO, and 2.2 times the size of State encoder + PPO or Bottleneck PPO (Fig. 4.2).

Regarding the performance, we can see that under *small* inflation all controllers achieve a similar median, with Scalable encoder + PPO being the worst of them all. However, when looking at the spreads, State encoder + PPO also has some runs in the 10 to 1000 suboptimality range. The best one here, and also in *medium*, is Linear PPO, which shows little spread.

Looking at *medium*, here Fully-connected PPO becomes worse regarding its median, followed by Scalable encoder + PPO, even though the spread of Scalable encoder + PPO still has worse runs. The other low-dimensional controllers show a good median similar to Linear PPO, however have a wider spread, with some runs worse than 100 suboptimality.




Figure 4.1: Training suboptimality $(J - J^*)/J^*$ of the PPO variants under *large* inflation.




Figure 4.2: Policy size (Definition 2.1) of the PPO variants for each inflation size.

Now under *large* it becomes interesting, as Linear PPO's performance has deteriorated, becoming the worst controller of them all. Scalable encoder + PPO is still second, now again worse than the fully connected version. However, Bottleneck PPO shows a similar performance as under *medium*, while most others (except for Fully-connected PPO) have shifted upwards. The simple State encoder + PPO also remains in a good spot even though it has worsened in comparison to Bottleneck PPO (Fig. 4.3).




Figure 4.3: Suboptimality S of the PPO variants for each inflation size. The boxes indicate the interquartile range, while the central line marks the median, and the whiskers span the 5th to 95th percentile. Points show episodes outside this range.

4.3 Noise on Large Inflation

Similar to what we have seen before in Section 3.2.3, parametric uncertainty seems to affect all controllers similarly and generally increases suboptimality across all architectures. The median is shifted upwards, and especially apparent at *divergent*, the worst-case runs get a couple of orders of magnitude worse (Table 4.1).


Table 4.1: Median and worst seed of the relative degradation κ under *large* inflation and parametric uncertainty of increasing intensity.

	Median				Worst seed			
Solver	*weak*	*standard*	*strong*	*divergent*	*weak*	*standard*	*strong*	*divergent*
Baseline	1.19	1.45	2.42	5.75	1.37	1.83	4.55	25.7
Linear PPO	2.28	8.83	164	1.53×10^3	5.66	27.4	1.07×10^3	1.07×10^4
Bottleneck PPO	1.19	1.58	7.86×10^3	2.39×10^5	1.45	55.6	4.53×10^5	2.28×10^7
State encoder + PPO	1.19	1.6	2.37×10^3	2.82×10^5	1.49	97.3	8.88×10^5	2.91×10^7
Scalable encoder + PPO	1.29	1.89	3.73×10^3	4.78×10^5	26.5	135	3.47×10^5	2.03×10^7
Fully-connected PPO	1.23	17.9	1.95×10^4	8.39×10^5	1.73	2.46×10^3	1.27×10^6	3.23×10^7

However, this does not help us too much to answer the question whether low-dimensional architectures are more robust here.

So let us take a look at external disturbance next. Here we can see that the median suboptimality of all approaches remains mostly stable throughout the increase in the noise, except for Bottleneck PPO, whose median improves into being even better than the baseline. Here, the shift of the interquartile range becomes also

interesting, as with increasing noise intensity its width becomes smaller and sits between -0.01 and -0.1. State encoder + PPO and Fully-connected PPO behave quite similarly, both with a spread across the 0 line (sometimes better, sometimes worse) and a similar median. Fully-connected PPO only differs by maintaining a wider interquartile range even under *divergent* noise. Linear PPO sits above the baseline, similar to its noise-free testing, whereas Scalable encoder + PPO shows an increasing spread under stronger noise, with its interquartile range becoming smaller. Overall, it can be seen that Bottleneck PPO indeed outperforms the other architectures here (Fig. 4.4a).



(a) External disturbance at intensity *strong*.


(b) Control noise at intensity *strong*.

Figure 4.4: Suboptimality S of the PPO variants under *large* inflation and different noise types.

Similarly, the robustness of Bottleneck PPO can be observed under control noise, where its median continuously shifts downwards with growing noise intensity, until falling below the baseline at *strong* (Fig. 4.4b). Otherwise, the order of performance for the other policies stays mostly the same, with just the spread under increasing noise passing the baseline. This however can most likely be attributed to a less robust baseline controller than performance of the others.


Lastly, let us take a look at measurement noise. Under *weak* intensity, Linear PPO shows some wide spread, while generally the low-dimensional architectures show a mean lower than the fully connected ones. With the step to *standard*, not much can be seen apart from an increase in the spread of Scalable encoder + PPO across the baseline. At *strong*, all, except for Fully-connected PPO, shift their interquartile range across the baseline, in a similar spread, even though for Scalable encoder + PPO, the median also shifts towards -0.1, being the only architecture here. Still, some worst-case runs are measured at around 1000 suboptimality. Fully-connected PPO in comparison sits between 0.1 and 10 suboptimality. Under *divergent* mea-

surement noise, we can see that the low-dimensional controllers outperform Linear PPO and Fully-connected PPO here. All their medians lie below the baseline and have a very thin spread of the interquartile range. Scalable encoder + PPO shows some runs being much worse than Fully-connected PPO; however, for Bottleneck PPO and State encoder + PPO, all the runs are below the median of Fully-connected PPO. Linear PPO's median also lies below the baseline and a little short of the other controllers, but has a spread similar to Fully-connected PPO, whose median sits above the baseline between 0.1 and 0.01 (Fig. 4.5).



(a) Intensity *standard*.

(b) Intensity *strong*.



(c) Intensity *divergent*.

Figure 4.5: Suboptimality S of the PPO variants under *large* inflation and measurement noise.

4.4 Discussion

Throughout our experiments we can see that Bottleneck PPO outperforms all the other controllers, be it on the clean plant or under noise. While for some it might only be on par with other constructions, under *divergent* noise it exhibits very promising robustness properties. State encoder + PPO and Fully-connected PPO perform quite similarly, except under measurement noise, where State encoder + PPO is more reliable. Scalable encoder + PPO sadly is not as promising throughout, with worse performances than the rest, and much more variability. However, the effectiveness of its low-dimensional construction against measurement noise can still be seen here. Interesting to see is that Linear PPO, even though its training was ineffective, and it thus performed worse throughout most experiments, outclassed Fully-connected PPO under *divergent* measurement noise.

Again, we have seen that low-dimensional approaches are more robust than fully parameterized ones under increasing measurement noise especially. Still, it depends on how exactly the policy is constructed, as we also have observed differences between the approaches. And while Bottleneck PPO of course already displayed a better suboptimality post-training than Fully-connected PPO, as it has continuously, and even with greater leads outperformed its fully connected counterpart while also containing only half the parameters, we can more and more support our thesis that low-dimensional controllers can perform at least as well as fully connected ones if the design is cleverly chosen.

Chapter 5

Perception-Based Experiments

From the previous artificially inflated inputs, we aim to move to a more realistic example, which shows the robustness of low-dimensional controllers in a scenario involving an image observation as input. We do this by first using our setup from the previous chapter to scale it to a dimension, which resembles image inputs. Afterwards, we actually build a new environment, which combines perception-based observation with multiple actuators acting on our double integrator.

5.1 Artificial Inflation to Pixel Size

5.1.1 Setting

As mentioned, we take our loop from before (Section 2.3.1.1) and scale it up further. The input dimension in this case becomes 18 432, while we set the output dimension to 256. These numbers were specifically selected to match the setup in Section 5.2, such that we can compare both more closely. For the input dimension, this is a 96×96 image stack of two images, while for the output dimension it was chosen due to the specific construction.

We further note that State encoder + PPO cannot be applied at this scale, as the identification for such large matrices is computationally impossible. Additionally, we excluded Linear PPO, as it was only used to compare with LQR approaches before.

Due to computational complexity and time restrictions, we reduced the training steps to 10^7 and did not run experiments to determine the optimal learning rate here. Instead, we used the optimal learning rate for *large*, and scaled it via

$$\eta_0^{\text{pixel}} = \eta_0^{\text{large}} \sqrt{\frac{d_{\text{in}}^{\text{large}}}{d_{\text{in}}^{\text{pixel}}}} = \eta_0^{\text{large}} \sqrt{\frac{200}{18\,432}} \approx 0.104\, \eta_0^{\text{large}}, \tag{5.1}$$

rounded to two digits as in (B.1), which leaves us with the values in Table 5.1.

Table 5.1: Initial learning rate η_0 at the *pixel* size, extrapolated from *large* with (5.1).

Solver	*large*	*pixel*
Bottleneck PPO	$6.7 \cdot 10^{-6}$	$7 \cdot 10^{-7}$
Scalable encoder + PPO	$2.2 \cdot 10^{-6}$	$2.3 \cdot 10^{-7}$
Fully-connected PPO	$6.7 \cdot 10^{-6}$	$7 \cdot 10^{-7}$
FC-Extractor + PPO	—	$7 \cdot 10^{-7}$

5.1.2 Results

5.2 The New Environment and the Position-Velocity Encoder


5.2.1 Pixelated Environment

For our perception setup, we still use the underlying double integrator as a basis, however now simulate its actual movement. This simulation is observed by a monochromatic camera producing 96×96-pixel images of a mass with a radius of two pixels moving horizontally in front of a black background. The visible range is from -12 to 12 meters, so a total of 24 meters, corresponding to 0.25 meters per pixel. To be able to see changes between the pictures, we hold any action commanded by the agent for 30 time steps before capturing another frame. The agent then receives a stack of two images as the input. Figure 5.1a shows an example of such an image.

But not only the input is high-dimensional compared to the actual state. We also modify the way our mass is actuated. We also replace the single actuator with 256 thrusters, distributed equally around a half circle, so thruster $i \in \{0, \dots, 255\}$ sits at an angle $\theta_i = \pi i/256$. Each thruster can actuate in the range $v_i \in [-1, 1]$, however, due to the angle, only $s \cos \theta_i$ effective acceleration is produced on the mass, where s is a scaling factor.[1]

This leads to some thrusters being more effective than others, while all are charged for the commanded output, so some energy might be lost. For example, the only vertically acting thruster $\theta = \pi/2$ cannot affect the mass in any way, and would thus only waste energy if used. Figure 5.1b visualizes the thrust directions for eight thrusters.

[1]The most energy-efficient and thus cheapest way to produce an acceleration a is the least-norm allocation, which uses the thrusters based on their output effectiveness $v_i = a \cos \theta_i / (128 \cdot s)$, where $128 = \sum_i \cos^2 \theta_i$. For the horizontal, and thus most effective thruster this is $a = 128 \cdot s$. We choose s here such that 1.5 times the maximum acceleration demanded by our optimal controller can be reached without clipping, which is $26\,\mathrm{m/s^2}$, so $s = 26/128$.



(a) The two frames of one observation, cropped to rows around the mass.

(b) Schematic of the effect of eight thrusters. Created with Claude Code.

Figure 5.1: Observation and actuation in the camera environment.

With our chosen frame and action repeat, a pixel difference between two frames can only be guaranteed at velocities above 0.83 m/s. Otherwise, motion is only visible if the mass crosses a pixel boundary, making velocity generally hard to identify. For a better approximation the number of frames stacked could be increased, or anti-aliasing could be used to display changes better. But this will further be discussed in Section 5.5.

5.2.2 Position-Velocity Encoder

For this new environment, we introduce another feature extractor, which is based on robotic priors used in Scalable encoder + PPO [19]. Called Position-Velocity Encoders [20], it tries to encode a position and velocity state from an observation, by learning a latent position state, and then reconstructing the velocity state using temporal differences. As we specifically look for position and velocity in our states, we can construct even more specific priors, again in line with our reasoning that knowledge about the embodiment helps in designing the controller architecture (Section 2.4). The priors used in [20, Sec. III-B] are:

1. Variation: "Positions of relevant things vary."
2. Slowness: "Positions change slowly."
3. Inertia: "Velocities change slowly."
4. Conservation: "Velocity magnitudes change slowly."
5. Controllability: "Controllable things are relevant."

For our implementation, we follow the paper's recommended approach. Each frame is input into a convolutional neural network (CNN), which encodes a latent position state $s_k^{(\mathrm{p})}$ from it. Its dimension is a hyperparameter, but recommended to be set to five [20, Sec. III-C], which we follow. The velocity is then calculated as the difference between two frames, or $s_k^{(\mathrm{v})} = \alpha \left(s_k^{(\mathrm{p})} - s_{k-1}^{(\mathrm{p})} \right)$, where α is the inverse of the time between two agent actions. For the weighting of our prior loss terms, we use the combination suggested for similar tasks in [20, Tab. I], and thus exclude the

controllability prior. For the training process we further follow the one proposed in [20, Sec. III-C]. For details on how exactly the total loss function is constructed, we refer the reader to the original paper [20]. We train this extractor with data of 20 000 agent steps, which is split into episodes of 810 environment steps, which at our action repeat corresponds to 27 agent actions. Similar to before, we use K_0 acting on the true state in 70 % with least-norm allocation through the thrusters and random, uniformly distributed actuation in 30 % of the time, before freezing the extractor's weights and using it in front of our PPO construct (Section 4.1).

Scalable encoder + PPO is pretrained with a similar data split for this setting.

5.3 Effect of Visual Inputs on the Solvers

5.3.1 Setting

For the experiments here, we use the optimal gain under our action repeat (Section 5.2.1) as our reference and compare it with different approaches, which here consist of Pixels + PPO (equivalent to FC-Extractor + PPO), Scalable encoder + PPO, Bottleneck PPO as well as our Position-Velocity Encoder + PPO (Section 5.2.2). As they reuse the already introduced architectures, they will not be repeated here. The only difference is that we increase the latent dimension of Scalable encoder + PPO to 5, which is the same as Position-Velocity Encoder + PPO, after initial results showed a weak performance with 2. The optimal controller for this setup actually does not act based on the perception, but instead has access to the real state, while the output remains our thrusters, for which it uses the least-norm allocation. It is therefore optimal for this setup, and serves as our comparison. Given the knowledge it has about the true state, we call it "Oracle (true state)" in our visualizations. For the other approaches, except for Position-Velocity Encoder + PPO, which takes images as an input, we flatten the images, such that they receive an 18 432-dimensional input vector. The learning rates we use here are identical to the ones extrapolated in Table 5.1. As we did not use Position-Velocity Encoder + PPO (Section 5.2.2) before, we copy the learning rate from Scalable encoder + PPO for it, as it is the most similar (both use robotic priors).

However, we also modify some of our PPO parameters for this setting. Not mentioned parameters equate to their Chapter 4 values. Specifically, we

- set $\gamma = 0.97$, which gives us around $1/(1-\gamma) \approx 33$ effective agent steps. Multiplying this with our agent action interval of 0.3 s gives us roughly 10 s of effective horizon, equal to what we used before;
- raise the reward clipping threshold from 10 to ∞, so the reward is never clipped;
- charge the input cost on the command before clipping, though only enact the clipped command;

- end the episode with a penalty if the mass exits the observable area. The penalty is set to twice the cost that a mass sitting at the edge of the screen would incur until the end of the episode.

The last three points relate a bit to each other, and were changes that were implemented after initial test failures. Here, we noticed that by charging the cost only after clipping, the controller never learned to actually control the mass in some cases. For these, it would produce increasingly larger command inputs, but could never return from this instability, as every action above this threshold had the same effect. Also, clipping the reward like in Chapter 4 had the side effect that leaving the screen became an economically reasonable choice, so the model chose this behavior more often. Combined with this, we started charging the penalty, which promotes staying on screen even more.

We also need to slightly adapt our test protocol (Section 2.3.3) to this new environment. To maintain similarity to the previous experiments, we choose 27 agent steps per episode during training, corresponding to 810 environment steps. The overall training step budget is chosen as 10^7 agent steps. For one test episode we use $\lceil 2000/30 \rceil = 67$ agent steps, corresponding to 2010 environment steps.

5.3.2 Results

5.4 Noisy Perception

5.4.1 Setting

As our environment setup changed drastically, the cost increases associated with the noise levels calculated from before no longer apply. Thus, we again ran a calibration with the optimal controller to set them to respective levels (Section A.3). With these new values, we can use them like before to change how the loop behaves. Parametric uncertainty still changes the underlying model, external disturbance still acts on the position of our mass, and control noise changes the commanded actuation outputs. Measurement noise now affects the visual input, as shown in Fig. 5.2, by applying Gaussian noise to all the pixels in the image. Here, we set the levels ourselves, as the optimal controller is not acting from the camera image, but rather from the true state, so this noise does not affect it. Still, the chosen values are found in the appendix (Table A.3).

We now run the trained controllers from Section 5.3 on noise-affected trajectories at different strengths under the test protocol introduced in Section 5.3.1. To make the comparison under each noise channel equal, we exclude our optimal controller baseline, as it does not observe the measurement noise like the other controllers do. So instead we use the cost ratio (2.33) of each controller to its clean run from Section 5.3.




Figure 5.2: An observation without measurement noise, and with measurement noise of intensity *standard* and *divergent*.

5.4.2 Results

5.5 Discussion

Chapter 6

Conclusion

You generally cover three things in the Conclusions section, and each of these usually merits a separate subsection:

1. Conclusions
2. Summary of Contributions
3. Future Research

Conclusions are not a rambling summary of the thesis: they are short, concise statements of the inferences that you have made because of your work. It helps to organize these as short numbered paragraphs, ordered from most to least important. All conclusions should be directly related to the research question stated in the introduction. Examples:

1. The problem stated in the introduction has been solved: as shown in Sections ? to ??, an algorithm capable of handling large-scale Zylon problems in reasonable time has been developed.
2. The principal mechanism needed in the improved Zylon algorithm is the Grooty mechanism.
3. Etc.

The Summary of Contributions will be much sought and carefully read by the examiners. Here you list the contributions of new knowledge that your thesis makes. Of course, the thesis itself must substantiate any claims made here. There is often some overlap with the Conclusions, but that's okay. Concise numbered paragraphs are again best. Organize from most to least important. Examples:

1. Developed a much quicker algorithm for large-scale Zylon problems.
2. Demonstrated the first use of the Grooty mechanism for Zylon calculations.
3. Etc.

The Future Research subsection is included so that researchers picking up this work in future have the benefit of the ideas that you generated while you were working on the project. Again, concise numbered paragraphs are usually best.

Appendix A

Nomenclature

A.1 Notation

The following table contains the conventions regarding symbols used throughout this thesis, together with the place where each is defined:

Symbol	**Meaning**	**Defined in**
Sets and operators		
$\mathbb{R}$, $\mathbb{C}$, $\mathbb{N}_0$	real numbers, complex numbers, natural numbers including zero	
I_n, $\mathbf{1}_n$, e_1	identity matrix and all-ones vector of dimension n, first unit vector	
$M^\top$, $M^\dagger$	transpose and (truncated) pseudoinverse of M	Algorithm 4
tr, rank, diag	trace, rank, diagonal matrix	
$\lambda_i(M)$, $\sigma_i(M)$	i-th eigenvalue and i-th singular value of M	
$U\Sigma V^\top$	singular value decomposition, $\Sigma = \operatorname{diag}(\sigma_1, \ldots, \sigma_r)$	(2.35)
$\rho(M)$	spectral radius, $\max_i \lvert\lambda_i(M)\rvert$	Section 2.1.2
$M \succeq 0$, $M \succ 0$	M symmetric positive semi-definite / positive definite	
$\lVert\cdot\rVert$, $\lVert\cdot\rVert_F$, $\lVert\cdot\rVert_*$	Euclidean (spectral) norm, Frobenius norm, nuclear norm	
$\lvert\cdot\rvert$	absolute value, cardinality of a set, size of a policy	Definition 2.1
$\odot$	elementwise product	(2.24)

Symbol	Meaning	Defined in
$\mathbb{E}$, $\hat{\mathbb{E}}_k$	expectation, empirical average over the collected steps	(4.1)
$\mathcal{N}(\mu, \Sigma)$	Gaussian distribution with mean μ and covariance Σ	
∇f, $\widehat{\nabla f}$	gradient of f and its estimate	(3.2), Algorithm 3
System description		
n, m, q	dimension of the state, input and output	(2.1)
t, k, h	continuous time, discrete step index, sampling period	(2.3)
$x_k \in \mathbb{R}^n$	state	(2.4)
$u_k \in \mathbb{R}^m$	control input of the plant	(2.4)
$y_k \in \mathbb{R}^q$	observed output	(2.1)
p, v	position and velocity of the double integrator, $x = [\, p,\ v\,]^\top$	(2.7)
A_c, B_c	continuous-time system and input matrix	(2.1)
A, B	their zero-order-hold discretizations	(2.5)
C, D	output and feedthrough matrix; $D = 0$ throughout	(2.1)
A_K	closed-loop matrix, $A_K = A - BK$	(2.16)
Optimal control		
Q, R	state and input cost matrices, $Q \succeq 0$, $R \succ 0$	(2.10)
$V_T(x_0, u)$	continuous-time cost over the finite horizon T	(2.10)
$J(x_0, u)$, $J(x_0, K)$	infinite-horizon cost of an input sequence or of a gain	(2.11)
$K \in \mathbb{R}^{m \times n}$	feedback gain, $u_k = -Kx_k$	(2.12)
K^*, u_k^*	optimal gain and optimal input	(2.14)
P, $J^*(x)$	stabilizing solution of the DARE and optimal cost-to-go $x^\top P x$	(2.13), (2.15)
P_K	solution of the Lyapunov equation for a fixed K	(2.16)
$\mathcal{K}$	set of stabilizing gains	(2.17)
K_0	stabilizing initial gain of the uninflated system, $K_0 = [\, 0.1,\ 0.5\,]$	Section 2.3.3

Symbol	**Meaning**	**Defined in**
$\mathcal{D}$, Σ_0	distribution of x_0 and its second moment $\mathbb{E}[x_0 x_0^\top]$	(2.18)
$f(K)$	expected cost of a gain, $\mathrm{tr}(P_K \Sigma_0)$	(2.18)
Inflated system		
d_{in}, d_{out}	inflated dimension of the controller input and output	(2.19)
U_1, U_2	lifts with orthonormal columns and rows	(2.19)
$K \in \mathbb{R}^{d_{\mathrm{out}} \times d_{\mathrm{in}}}$	inflated feedback gain, $v_k = -K y_k$	(2.20)
v_k, $\tilde{v}_k \in \mathbb{R}^{d_{\mathrm{out}}}$	controller output, before and after control noise	(2.20), (2.24)
$\tilde{Q}$, $\tilde{R}$	inflated state and input cost, $\tilde{Q} = I_{d_{\mathrm{in}}}$, $\tilde{R} = I_{d_{\mathrm{out}}}$; $U_1^\top \tilde{Q} U_1 = Q = I_n$	(2.22)
$\tilde{K}_0$, N	inflated initial gain $U_2^\top K_0 U_1^\top + N$ and its full-rank component, $U_2 N U_1 = 0$	(2.37)
$\tilde{A}$, $\tilde{B}$, $\tilde{\Sigma}_0$	model in the inflated coordinates, $U_1 A U_1^\top$, $U_1 B U_2$, $U_1 \Sigma_0 U_1^\top$	Section 3.1
Noise		
n_k^{m}, σ_{m}	measurement noise and its standard deviation	(2.23)
n_k^{c}, σ_{c}	control noise (relative) and its standard deviation	(2.24)
Δ_k^A, Δ_k^B, σ_{p}	parametric perturbations and their standard deviation	(2.26)
n_k^{d}, σ_{d}	external disturbance and its amplitude	(2.27)
c, $\varnothing$	noise condition (channels and intensity), noise-free condition	(2.30)
ℓ, c_ℓ, κ_ℓ	noise intensity, a channel at intensity ℓ, its cost ratio	(2.36)
Evaluation and training protocol		
T	horizon of a rollout	(2.30)
s, i	index of the seed and of the episode	(2.30)
M, N	number of seeds and of episodes per seed	(2.38)
$J_T^{(i,s)}(K; c)$	empirical cost of one episode	(2.30)
$\hat{J}_T(K; c)$, $\mathcal{F}$	mean empirical cost, set of finite episodes	(2.31)
$S^{(i,s)}(K; c)$, $\hat{S}(K; c)$	suboptimality of one episode and its mean	(2.32)

Symbol	Meaning	Defined in
$\hat{J}_T^{(s)}(K;c)$, $\kappa^{(s)}(K;c)$	mean empirical cost of seed s, its ratio to the clean loop	(2.33)
$\kappa(K;c)$	cost ratio to the clean loop over all seeds, $\kappa_\ell = \kappa(K^*;c_\ell)$	(2.34)
$D(K;c)$	divergence rate	(2.38)
$\lvert K\rvert$, r	size and rank of a linear policy	Definition 2.1
j	iteration index of a solver	Definition 2.2
g_j, $\bar{g}_j$	convergence signal and its moving mean	Definition 2.2
N_{w}, N_{p}, $\varepsilon_{\mathrm{rel}}$	window, patience and relative tolerance of the convergence rule	Definition 2.2
LQR solvers		
η	step size (learning rate)	Algorithm 1
Σ_K	state correlation matrix of a gain	(3.1)
λ	weight of the nuclear-norm regularizer	(3.3)
K^+, $\bar{r}$	candidate gain of S-PI, number of its singular values	(3.3)
G	gradient mapping	(3.4)
β, ε	step-size reduction factor and stopping tolerance of S-PI	Algorithm 2
σ_{e}, w_k	excitation amplitude and excitation noise for identification	(3.5)
$\hat{n}$, $\hat{C}$, $\hat{x}_k$	order and output matrix of the identified model, encoded state $\hat{C}^\top y_k$	(4.4)
N_{traj}, l, r	number of perturbation pairs, rollout length, smoothing radius	Algorithm 3
Ξ_i	perturbation of the gain	Algorithm 3
$c_k^{\pm}$, $\hat{J}_i^{\pm}$	stage cost and rollout cost of $K \pm \Xi_i$	Algorithm 3
δ_i, $\bar{\delta}$	cost difference of a pair and its mean	Algorithm 3
$\hat{\Sigma}_K$, $\hat{f}(K)$	estimated state correlation and cost	Algorithm 3
Reinforcement learning		
θ, π_θ, μ	actor parameters, policy, mean of the policy	(4.1), (4.3)
ϕ, V_ϕ	critic parameters and critic	Algorithm 6
$r_k(\theta)$, $\hat{A}_k$	probability ratio and advantage estimate	(4.1)
L^{CLIP}, $\varepsilon_{\mathrm{clip}}$	clipped surrogate objective and clip range	(4.1)
γ	discount factor	Section 4.1.2

Symbol	Meaning	Defined in
η_0, N_{env}, $N_{\max}$	initial learning rate, environment steps so far, step budget	(4.2)
W	weight matrix of Linear PPO, $W = -K$	(4.3)
f_ψ, ψ	scalable encoder and its parameters	Algorithm 7
$a_{\max}$	action bound	Algorithm 7
$\mathcal{L}$, $\omega_1, \ldots, \omega_4$	prior loss and its weights	(4.5)
z_k, d_{z}	output of the bottleneck extractor and its dimension	(4.6)
U_{b}, d_{b}	orthonormal bottleneck projection and bottleneck dimension	(4.6)

A.2 Noise Intensities

The settings used for the different noise intensities, obtained by the calibration (2.36) on the non-inflated system. It is important to note that parametric noise is resampled at every step, and that the disturbance noise uses its sinusoidal variant (2.27).

Table A.2: Standard deviation per noise channel and intensity, calibrated to the cost ratio ρ_ℓ of (2.36). Every value reaches its ratio within 0.9 %.

Channel	*none*	*weak*	*standard*	*strong*	*divergent*
Cost ratio ρ_ℓ	1	1.2	1.5	3	10
Measurement σ_{m}	0	0.389	0.607	1.22	2.58
Control σ_{c}	0	1.07	1.67	3.19	5.68
Parametric σ_{p}	0	0.0211	0.0304	0.0451	0.0582
Disturbance σ_{d}	0	0.00767	0.0122	0.0246	0.0519

A.3 Noise Intensities of the Perception Environment

The settings used for the different noise intensities in the perception-based environment of Section 5.2, obtained by the calibration (2.36) with the optimal controller acting on the true state as reference. Measurement noise is not calibrated but set by hand (Section 5.4.1).

Table A.3: Standard deviation per noise channel and intensity, calibrated to the cost ratio ρ_ℓ of (2.36). Every value reaches its ratio within 9.4 %. Measurement noise is set by hand and not calibrated.

Channel	*none*	*weak*	*standard*	*strong*	*divergent*
Cost ratio ρ_ℓ	1	1.2	1.5	3	10
Control σ_c	0	1.31	2.13	4.24	8.96
Parametric σ_p	0	0.0158	0.0167	0.0232	0.0359
Disturbance σ_d	0	0.00737	0.0115	0.0231	0.0494
Measurement σ_m	0	0.0625	0.125	0.25	0.5

A.4 Policy Architectures

The actor architectures of the PPO variants introduced in Section 4.1.3.




Figure A.1: Actor architectures of our PPO variants. For each layer, the number below indicates its neurons. The critic receives the same encoder structure and uses its own 64-64 tanh perceptron with a scalar output. Visualization created with Claude Code.

Appendix B

Complete Simulation Results

Here the results from some hyperparameter tuning are shown. For simplicity, mostly the ones under *large* inflation are shown, unless named otherwise, as this is the most challenging setting from what we have observed. The remaining plots and tables can be found in the repository[CITE: https://collaborating.tuhh.de/ccf6681/low-dimensional-control-from-lqr-to-rl].

B.1 Learning Rate of Model-based PG

Figure B.1 and Table B.1 show the results for *large* inflation.

Table B.1: Model-based PG under *large* inflation, over the seeds.

Learning rate	1e-06	3e-06	1e-05	3e-05	0.0001	0.0012
True cost J	5858 ± 0.001042	5852 ± 0.0003911	5849 ± 0.0001285	5848 ± 0.001456	$1.243 \times 10^4 \pm 1.059$	$1.243 \times 10^4 \pm 1.059$
Training suboptimality $(J - J^*)/J^*$	$0.00173 \pm 1.78 \times 10^{-7}$	$0.000605 \pm 6.69 \times 10^{-8}$	$0.000163 \pm 2.2 \times 10^{-8}$	$4.04 \times 10^{-5} \pm 2.49 \times 10^{-7}$	1.13 ± 0.000181	1.13 ± 0.000181
Test cost	5978 ± 5281	5972 ± 5276	5969 ± 5273	5968 ± 5273	$1.276 \times 10^4 \pm 1.147 \times 10^4$	$1.276 \times 10^4 \pm 1.147 \times 10^4$
Iterations	2390 ± 0	1123 ± 0	454 ± 0	1306 ± 1	64 ± 0	20000 ± 0
Iterations to 1 %	1039 ± 0	342 ± 0	84 ± 0	1040 ± 1	–	–
Env. steps to 1 %	0 ± 0	0 ± 0	0 ± 0	0 ± 0	–	–
Env. steps to convergence	0 ± 0	0 ± 0	0 ± 0	0 ± 0	0 ± 0	0 ± 0




Figure B.1: Training suboptimality of Model-based PG over the solver iterations for each learning rate under *large* inflation. Median and range over ten seeds.

B.2 Nuclear-Norm Weight of S-PI

Table B.2 and Fig. B.2 show the results for *large* inflation.

Table B.2: S-PI under *large* inflation, over the seeds.

λ	1	5	20	50	200	1000
True cost J	5848 ± 0.0009277	$5848 \pm 4.736 \times 10^{-5}$	$5849 \pm 6.53 \times 10^{-5}$	5851 ± 0.0005886	5878 ± 0.0002686	6146 ± 0.0005713
Training suboptimality $(J - J^*)/J^*$	$2.87 \times 10^{-7} \pm 1.59 \times 10^{-7}$	$4.81 \times 10^{-6} \pm 8.1 \times 10^{-9}$	$7.4 \times 10^{-5} \pm 1.12 \times 10^{-8}$	$0.000429 \pm 1.01 \times 10^{-7}$	$0.00506 \pm 4.59 \times 10^{-8}$	$0.0509 \pm 9.77 \times 10^{-8}$
Gain rank	3.8 ± 0.9	1.0 ± 0.0	1.0 ± 0.0	1.0 ± 0.0	1.0 ± 0.0	1.0 ± 0.0
Test cost	5968 ± 5272	5968 ± 5272	5969 ± 5273	5971 ± 5275	5998 ± 5299	6274 ± 5539
Iterations	155 ± 1	77 ± 1	68 ± 0	72 ± 0	68 ± 0	64 ± 0
Spectral radius	0.9914 ± 0.0000	0.9914 ± 0.0000	0.9916 ± 0.0000	0.9919 ± 0.0000	0.9929 ± 0.0000	0.9952 ± 0.0000




Figure B.2: Training suboptimality of S-PI over the solver iterations for each nuclear-norm weight λ under *large* inflation. Median and range over ten seeds.

B.3 N4SID Identification Length

Figures B.3 and B.4 show the results for *large* and *medium* inflation over all trajectory lengths and Hankel horizons, Tables B.3 and B.4 the detailed results for a Hankel horizon of five.

Table B.3: N4SID + Model-based PG on a system with *medium* inflation with a Hankel horizon of 5.

Trajectory length T	500	1000	2000	4000	8000
Training suboptimality $(J - J^*)/J^*$	$3.15 \times 10^{-5} \pm 2.09 \times 10^{-7}$	$3.17 \times 10^{-5} \pm 2.48 \times 10^{-7}$	$3.16 \times 10^{-5} \pm 2.06 \times 10^{-7}$	$3.15 \times 10^{-5} \pm 3.6 \times 10^{-7}$	$3.16 \times 10^{-5} \pm 1.96 \times 10^{-7}$
Iterations	346 ± 1	346 ± 1	346 ± 1	346 ± 1	346 ± 1
Env. steps to convergence	500 ± 0	$10^3 \pm 0$	$2 \times 10^3 \pm 0$	$4 \times 10^3 \pm 0$	$8 \times 10^3 \pm 0$
Env. steps to best policy	500 ± 0	$10^3 \pm 0$	$2 \times 10^3 \pm 0$	$4 \times 10^3 \pm 0$	$8 \times 10^3 \pm 0$
Wall time (s)	1.1 ± 0.1	1.2 ± 0.0	1.4 ± 0.0	1.9 ± 0.0	2.9 ± 0.1

Table B.4: N4SID + Model-based PG on a system with *large* inflation with a Hankel horizon of 5. Identified counts the seeds a model was obtained from and stable those whose controller left the plant stable.

Trajectory length T	500	1000	2000	4000	8000
Identified	0/10	10/10	10/10	10/10	10/10
Stable	0/10	10/10	10/10	10/10	10/10
Training suboptimality $(J - J^*)/J^*$	–	0.00382 ± 0.00269	$3.21 \times 10^{-5} \pm 4.14 \times 10^{-7}$	$3.18 \times 10^{-5} \pm 1.12 \times 10^{-7}$	$3.18 \times 10^{-5} \pm 8.71 \times 10^{-8}$
Iterations	–	347 ± 9	346 ± 0	346 ± 0	346 ± 0
Env. steps to convergence	–	$10^3 \pm 0$	$2 \times 10^3 \pm 0$	$4 \times 10^3 \pm 0$	$8 \times 10^3 \pm 0$
Env. steps to best policy	–	$10^3 \pm 0$	$2 \times 10^3 \pm 0$	$4 \times 10^3 \pm 0$	$8 \times 10^3 \pm 0$
Wall time (s)	–	23.0 ± 1.0	26.4 ± 0.6	29.7 ± 0.9	36.4 ± 2.0




Figure B.3: Median training suboptimality of N4SID + Model-based PG per trajectory length T and Hankel horizon under *large* inflation.




Figure B.4: Median training suboptimality of N4SID + Model-based PG per trajectory length T and Hankel horizon under *medium* inflation.

B.4 Sample Size

Figures B.5 and B.6 show the results of Model-free NPG for *large* inflation, Table B.5 the training suboptimality for all inflation sizes.




Figure B.5: Training suboptimality of Model-free NPG over the environment steps for each rollout length l and number of trajectories N_{traj} under *large* inflation. Median and range over ten seeds.




Figure B.6: Final training suboptimality of Model-free NPG for each rollout length l and number of trajectories N_{traj} under *large* inflation.

Table B.5: Model-free NPG: training suboptimality $(J - J^*)/J^*$ per inflation size (rows) and sample-size combination (columns).

(l, m)	200, 100	200, 200	500, 100	500, 200	800, 100	800, 200
base	0.1868 ± 0.329	0.078 ± 0.003253	0.00253 ± 0.001248	0.003342 ± 0.0009051	0.002967 ± 0.001213	0.003835 ± 0.00146
small	0.3514 ± 0.2896	0.2185 ± 0.06357	0.003464 ± 0.002515	0.002264 ± 0.002548	0.00296 ± 0.002492	0.00183 ± 0.001281
medium	0.4981 ± 0.2409	0.2816 ± 0.0991	0.007411 ± 0.007269	0.002158 ± 0.001353	0.1171 ± 0.3566	0.2279 ± 0.4766
large	0.9981 ± 0.1889	0.631 ± 0.2237	0.3369 ± 0.4452	0.006577 ± 0.004818	0.2726 ± 0.4367	0.005664 ± 0.004618

B.5 Learning Rate of Model-free NPG

Figure B.7 and Table B.6 show the results for *large* inflation.




Figure B.7: Training suboptimality of Model-free NPG over the environment steps for each learning rate under *large* inflation. Median and range over ten seeds.

Table B.6: Model-free NPG under *large* inflation, over the seeds.

Learning rate	0.001	0.003	0.01	0.03	0.1
True cost J	6423 ± 150.4	6074 ± 100.1	5887 ± 28.18	9906 ± 3502	$1.243 \times 10^4 \pm 1.059$
Training suboptimality $(J - J^*)/J^*$	0.0982 ± 0.0257	0.0386 ± 0.0171	0.00658 ± 0.00482	0.694 ± 0.599	1.13 ± 0.000181
Test cost	6555 ± 5793	6198 ± 5476	6007 ± 5306	$1.032 \times 10^4 \pm 1.04 \times 10^4$	$1.276 \times 10^4 \pm 1.147 \times 10^4$
Iterations	617 ± 112	617 ± 82	610 ± 104	390 ± 373	101 ± 0
Iterations to 1 %	–	–	509 ± 110	700 ± 36	–
Env. steps to 1 %	–	–	$1.02 \times 10^8 \pm 2.2 \times 10^7$	$1.4 \times 10^8 \pm 7.29 \times 10^6$	–
Env. steps to convergence	$1.23 \times 10^8 \pm 2.23 \times 10^7$	$1.23 \times 10^8 \pm 1.64 \times 10^7$	$1.22 \times 10^8 \pm 2.08 \times 10^7$	$7.41 \times 10^7 \pm 7.83 \times 10^7$	$6.87 \times 10^5 \pm 7.44 \times 10^4$

B.6 Step Size and Nuclear-Norm Weight of S-PI (Model-Free)

Here, we show different combinations of values for the stepsize and λ under *large* inflation. Excluded are the tables for $\lambda = 400$, as no rank reduction could be

observed (λ too low), as well as $\lambda = 4 \times 10^6$, as here all produced controllers were unstable (λ too high).

From the remainders, we picked a value that exhibits rank reduction, while at the same time having a low suboptimality. Tables B.7 to B.9 show the results for the remaining values of λ.

Table B.7: S-PI (model-free) with $\lambda = 4000$ under *large* inflation, over the seeds.

Step size	3.5e-10	3.5e-09	3.5e-08	3.5e-07	3.5e-06
True cost J	$1.241 \times 10^4 \pm 18.05$	$1.213 \times 10^4 \pm 245.3$	9581 ± 30.62	8030 ± 19.81	8956 ± 103.1
Training suboptimality $(J - J^*)/J^*$	1.12 ± 0.00309	1.07 ± 0.042	0.638 ± 0.00524	0.373 ± 0.00339	0.531 ± 0.0176
Gain rank	100.0 ± 0.0	100.0 ± 0.0	100.0 ± 0.0	96.7 ± 2.1	81.7 ± 5.0
Spectral radius	0.9975 ± 0.0000	0.9975 ± 0.0000	0.9976 ± 0.0000	0.9979 ± 0.0000	0.9983 ± 0.0000
Iterations	50 ± 0	50 ± 0	50 ± 0	50 ± 0	50 ± 0
Env. steps to convergence	$10^7 \pm 0$	$10^7 \pm 0$	$10^7 \pm 0$	$10^7 \pm 0$	$10^7 \pm 0$
Env. steps to best policy	$2.8 \times 10^6 \pm 3.11 \times 10^6$	$5.7 \times 10^6 \pm 4.6 \times 10^6$	$10^7 \pm 0$	$10^7 \pm 0$	$10^7 \pm 0$

Table B.8: S-PI (model-free) with $\lambda = 40000$ under *large* inflation, over the seeds.

Step size	3.5e-10	3.5e-09	3.5e-08	3.5e-07	3.5e-06
True cost J	$1.238 \times 10^4 \pm 16.65$	$1.195 \times 10^4 \pm 11.76$	9927 ± 33	$7.525 \times 10^4 \pm 1.206 \times 10^4$	$4.124 \times 10^4 \pm 1.244 \times 10^4$
Training suboptimality $(J - J^*)/J^*$	1.12 ± 0.00285	1.04 ± 0.00201	0.698 ± 0.00564	11.9 ± 2.06	6.05 ± 2.13
Gain rank	100.0 ± 0.0	100.0 ± 0.0	53.3 ± 4.5	58.8 ± 4.9	28.1 ± 10.7
Spectral radius	0.9975 ± 0.0000	0.9975 ± 0.0000	0.9979 ± 0.0000	0.9999 ± 0.0000	0.9997 ± 0.0001
Iterations	50 ± 0	50 ± 0	50 ± 0	50 ± 0	50 ± 0
Env. steps to convergence	$10^7 \pm 0$	$10^7 \pm 0$	$10^7 \pm 0$	$10^7 \pm 0$	$10^7 \pm 0$
Env. steps to best policy	$9.02 \times 10^6 \pm 3.1 \times 10^6$	$10^7 \pm 0$	$10^7 \pm 0$	$9.64 \times 10^6 \pm 3.1 \times 10^5$	$1.22 \times 10^6 \pm 1.14 \times 10^5$

Table B.9: S-PI (model-free) with $\lambda = 400000$ under *large* inflation, over the seeds. Stable counts the seeds whose controller left the plant stable.

Step size	3.5e-10	3.5e-09	3.5e-08	3.5e-07	3.5e-06
Stable	10/10	10/10	0/10	0/10	0/10
True cost J	$1.242 \times 10^4 \pm 4.022$	$1.245 \times 10^4 \pm 28.56$	–	–	–
Training suboptimality $(J - J^*)/J^*$	1.12 ± 0.000688	1.13 ± 0.00488	–	–	–
Gain rank	100.0 ± 0.0	15.6 ± 0.5	–	–	–
Spectral radius	0.9975 ± 0.0000	0.9978 ± 0.0000	–	–	–
Iterations	50 ± 0	50 ± 0	–	–	–
Env. steps to convergence	$10^7 \pm 0$	$10^7 \pm 0$	–	–	–
Env. steps to best policy	$10^7 \pm 0$	$10^7 \pm 0$	–	–	–

B.7 Noise on the Identified Model

Table B.10 and Fig. B.8 show the results of model-free approaches under *large* inflation and *strong* noise.

Table B.10: Relative degradation κ and Absolute degradation $\Delta\hat{J}/\hat{J}^*$ under *large* inflation and each noise channel at intensity *strong*.

	Relative degradation κ						Absolute degradation $\Delta\hat{J}/\hat{J}^*$					
Channel	Baseline	N4SID + DARE	N4SID + Model-based PG	N4SID + S-PI	Model-free NPG	S-PI (model-free)	Baseline	N4SID + DARE	N4SID + Model-based PG	N4SID + S-PI	Model-free NPG	S-PI (model-free)
none	1	1	1	1	1	1	0	0	0	0	0	0
measurement	3.02 ± 0.198	3.02 ± 0.198	3.09 ± 0.205	3 ± 0.196	3.59 ± 0.339	1 ± 0.00198	2 ± 0.00746	2 ± 0.00748	2.07 ± 0.0072	1.98 ± 0.00733	2.58 ± 0.215	0.00524 ± 0.00901
control	2.76 ± 0.0212	2.76 ± 0.0213	2.74 ± 0.0209	2.75 ± 0.0212	2.66 ± 0.0413	1.11 ± 0.0078	1.76 ± 0.18	1.76 ± 0.18	1.74 ± 0.179	1.75 ± 0.179	1.67 ± 0.178	0.484 ± 0.0449
parametric	2.98 ± 1.06	2.98 ± 1.06	2.97 ± 1.06	2.97 ± 1.06	3.21 ± 1.44	$1.48 \times 10^4 \pm 1.88 \times 10^4$	2.02 ± 1.22	2.02 ± 1.22	2.01 ± 1.21	2.01 ± 1.22	2.25 ± 1.52	$6.71 \times 10^4 \pm 8.54 \times 10^4$
disturbance	3.03 ± 0.219	3.03 ± 0.219	3.04 ± 0.22	3.03 ± 0.219	2.87 ± 0.201	1.5 ± 0.101	2.01 ± 0.0467	2.01 ± 0.0468	2.02 ± 0.047	2.01 ± 0.0469	1.86 ± 0.0543	2.18 ± 0.293
all channels	106 ± 17.4	106 ± 17.4	105 ± 16.6	104 ± 17.1	124 ± 21.2	$2.06 \times 10^4 \pm 3.52 \times 10^4$	105 ± 22.8	105 ± 22.8	104 ± 21.6	104 ± 22.4	124 ± 22.9	$9 \times 10^4 \pm 1.49 \times 10^5$




Figure B.8: TODO: Suboptimality S of the model-free solvers under *large* inflation and parametric uncertainty at intensity *strong*.

B.8 Parameters for the RL Solvers

B.8.1 Deviations from SB3 Standard Parameters

Table B.11 lists the parameters of the PPO solvers in Chapter 4 that differ from the defaults of SB3 (version 2.9.0) [52, 51, 53]. All other parameters keep their default values.

Table B.11: Parameters of the PPO solvers that differ from the SB3 defaults.

Parameter	SB3 default	Used here
Discount factor γ	0.99	0.999
Learning rate	$3 \cdot 10^{-4}$, constant	Table B.12, annealed by (4.2)
Target KL divergence	none	0.02
Initial log standard deviation	0	-2
Orthogonal initialization	yes	no

B.8.2 Learning Rates for the RL Solvers

For each solver and inflation size, we train three seeds with each initial learning rate

$$\eta_0 \in 3 \cdot 10^{-4} \sqrt{\frac{10}{d_{\text{in}}}} \cdot \left\{0.01,\ \tfrac{1}{30},\ 0.1,\ \tfrac{1}{3},\ 1\right\}, \tag{B.1}$$

rounded to two digits. The final rates were then chosen based on inspection of the training curves (Table B.12). For Linear PPO under *large* every gain becomes unstable during training (Fig. B.9).

Table B.12: Initial learning rate η_0 of the PPO solvers per inflation size.

Solver	*small*	*medium*	*large*
Linear PPO	$1 \cdot 10^{-4}$	$4.5 \cdot 10^{-6}$	$2.2 \cdot 10^{-6}$
Bottleneck PPO	$3 \cdot 10^{-5}$	$4.5 \cdot 10^{-5}$	$6.7 \cdot 10^{-6}$
State encoder + PPO	$1 \cdot 10^{-4}$	$4.5 \cdot 10^{-5}$	$6.7 \cdot 10^{-6}$
Scalable encoder + PPO	$1 \cdot 10^{-4}$	$1.3 \cdot 10^{-5}$	$2.2 \cdot 10^{-6}$
Fully-connected PPO	$3 \cdot 10^{-5}$	$1.3 \cdot 10^{-5}$	$6.7 \cdot 10^{-6}$




Figure B.9: Training suboptimality for different learning rates for Linear PPO under *large* inflation.

B.8.3 Stopping Rule of the RL Solvers

Table B.13: Stopping-rule settings with the lowest median regret.

ε_{rel}	N_{p}	N_{w}	budget used	median regret	max regret
0.001	40	10	20 %	19 %	279 %
0.003	40	10	20 %	20 %	279 %
0.01	40	10	20 %	20 %	279 %
0.03	40	10	19 %	23 %	279 %
0.001	40	5	16 %	26 %	279 %
0.003	40	5	16 %	26 %	279 %
0.01	40	5	16 %	26 %	279 %
0.03	40	5	16 %	27 %	279 %
0.001	40	3	15 %	29 %	288 %
0.003	40	3	15 %	29 %	288 %

Table B.14: RL runs best policy, as a share of the step budget, and the regret of the policy after 75 % of the budget, of the final policy, and of the policy with the best $\bar{g}_j$.

Solver	Size	best policy at	regret at 75 %	regret final	regret by $\bar{g}_j$
Linear PPO	*small*	98 %	0.79 %	0.018 %	0.11 %
Bottleneck PPO	*small*	99 %	1.2 %	0.034 %	1.9 %
State encoder + PPO	*small*	87 %	1.6 %	0.22 %	0.2 %
Scalable encoder + PPO	*small*	80 %	2.1 %	0.94 %	1.4 %
Fully-connected PPO	*small*	87 %	1.9 %	0.43 %	0.64 %
FC-Extractor + PPO	*small*	99 %	1.4 %	0.019 %	0.97 %
Linear PPO	*medium*	98 %	1.4 %	0.14 %	0.077 %
Bottleneck PPO	*medium*	94 %	2.2 %	0.046 %	0.13 %
State encoder + PPO	*medium*	98 %	2.7 %	0.066 %	1.8 %
Scalable encoder + PPO	*medium*	98 %	2.1 %	0.17 %	8.1 %
Fully-connected PPO	*medium*	57 %	3.7 %	1.9 %	3.7 %
FC-Extractor + PPO	*medium*	98 %	0.98 %	0.047 %	0.72 %
Linear PPO	*large*	3.7 %	1664 %	391 %	391 %
Bottleneck PPO	*large*	97 %	0.94 %	0.084 %	0.084 %
State encoder + PPO	*large*	98 %	1 %	0.03 %	0.044 %
Scalable encoder + PPO	*large*	99 %	6.5 %	0.002 %	1.2 %
Fully-connected PPO	*large*	94 %	3.2 %	0.55 %	1.2 %
FC-Extractor + PPO	*large*	99 %	1 %	0.022 %	1.3 %




Figure B.10: Training suboptimality of the RL solvers over the environment steps under *large* inflation.

Bibliography

[1] Alekh Agarwal, Sham Kakade, Akshay Krishnamurthy, and Wen Sun. FLAMBE: Structural complexity and representation learning of low rank MDPs. In *Advances in Neural Information Processing Systems (NeurIPS)*, volume 33, pages 20095–20107, 2020.

[2] Nihat Ay. Geometric design principles for brains of embodied agents. *KI – Künstliche Intelligenz*, 29(4):389–399, 2015.

[3] Nicolò Botteghi, Khaled Alaa, Mannes Poel, Beril Sirmacek, Christoph Brune, Abeje Mersha, and Stefano Stramigioli. Low dimensional state representation learning with robotics priors in continuous action spaces. In *2021 IEEE/RSJ International Conference on Intelligent Robots and Systems (IROS)*, 2021.

[4] G. Cybenko. Approximation by superpositions of a sigmoidal function. *Mathematics of Control, Signals, and Systems*, 2(4):303–314, 1989.

[5] Adwait Datar and Nihat Ay. Universal and cheap control architectures for embodied agents. Poster, Institute for Data Science Foundations, Hamburg University of Technology, 2025.

[6] Andrea d'Avella, Philippe Saltiel, and Emilio Bizzi. Combinations of muscle synergies in the construction of a natural motor behavior. *Nature Neuroscience*, 6(3):300–308, 2003.

[7] Sarah Dean, Horia Mania, Nikolai Matni, Benjamin Recht, and Stephen Tu. On the sample complexity of the linear quadratic regulator. *Foundations of Computational Mathematics*, 20(4):633–679, 2020.

[8] Sarah Dean, Nikolai Matni, Benjamin Recht, and Vickie Ye. Robust guarantees for perception-based control. In *Proceedings of the 2nd Conference on Learning for Dynamics and Control (L4DC)*, volume 120 of *PMLR*, 2020. arXiv:1907.03680.

[9] Mostafa Dehghani et al. Scaling vision transformers to 22 billion parameters. In *Proceedings of the 40th International Conference on Machine Learning (ICML)*, volume 202 of *PMLR*, pages 7480–7512, 2023. arXiv:2302.05442.

[10] Misha Denil, Babak Shakibi, Laurent Dinh, Marc'Aurelio Ranzato, and Nando de Freitas. Predicting parameters in deep learning. In *Advances in Neural Information Processing Systems (NeurIPS)*, volume 26, 2013. arXiv:1306.0543.

[11] John C. Duchi, Michael I. Jordan, Martin J. Wainwright, and Andre Wibisono. Optimal rates for zero-order convex optimization: The power of two function evaluations. *IEEE Transactions on Information Theory*, 61(5):2788–2806, 2015.

[12] Logan Engstrom, Andrew Ilyas, Shibani Santurkar, Dimitris Tsipras, Firdaus Janoos, Larry Rudolph, and Aleksander Madry. Implementation matters in deep policy gradients: A case study on PPO and TRPO. In *International Conference on Learning Representations (ICLR)*, 2020. arXiv:2005.12729.

[13] Maryam Fazel, Rong Ge, Sham M. Kakade, and Mehran Mesbahi. Global convergence of policy gradient methods for the linear quadratic regulator. In *Proceedings of the 35th International Conference on Machine Learning (ICML)*, volume 80 of *PMLR*, pages 1467–1476, 2018.

[14] Kurt Hornik, Maxwell Stinchcombe, and Halbert White. Multilayer feedforward networks are universal approximators. *Neural Networks*, 2(5):359–366, 1989.

[15] Chloe Ching-Yun Hsu, Celestine Mendler-Dünner, and Moritz Hardt. Revisiting design choices in proximal policy optimization. arXiv:2009.10897 [cs.LG], 2020.

[16] Bin Hu, Kaiqing Zhang, Na Li, Mehran Mesbahi, Maryam Fazel, and Tamer Başar. Toward a theoretical foundation of policy optimization for learning control policies. *Annual Review of Control, Robotics, and Autonomous Systems*, 6, 2023.

[17] Shengyi Huang, Rousslan Fernand Julien Dossa, Antonin Raffin, Anssi Kanervisto, and Weixun Wang. The 37 implementation details of proximal policy optimization. In *ICLR Blog Track*, 2022. `https://iclr-blog-track.github.io/2022/03/25/ppo-implementation-details/`, accessed 2026-10-07.

[18] Maximilian Igl, Kamil Ciosek, Yingzhen Li, Sebastian Tschiatschek, Cheng Zhang, Sam Devlin, and Katja Hofmann. Generalization in reinforcement learning with selective noise injection and information bottleneck. In *Advances in Neural Information Processing Systems (NeurIPS)*, volume 32, 2019. arXiv:1910.12911.

[19] Rico Jonschkowski and Oliver Brock. Learning state representations with robotic priors. *Autonomous Robots*, 39(3):407–428, 2015.

[20] Rico Jonschkowski, Roland Hafner, Jonathan Scholz, and Martin Riedmiller. PVEs: Position-velocity encoders for unsupervised learning of structured state representations. arXiv:1705.09805 [cs.RO], 2017.

[21] Rudolf E. Kalman. Contributions to the theory of optimal control. *Boletín de la Sociedad Matemática Mexicana*, 5:102–119, 1960.

[22] Elia Kaufmann, Leonard Bauersfeld, Antonio Loquercio, Matthias Müller, Vladlen Koltun, and Davide Scaramuzza. Champion-level drone racing using deep reinforcement learning. *Nature*, 620:982–987, 2023.

[23] Hiroaki Kitano. Biological robustness. *Nature Reviews Genetics*, 5(11):826–837, 2004.

[24] Vijay R. Konda and John N. Tsitsiklis. Actor-critic algorithms. In *Advances in Neural Information Processing Systems 12 (NIPS 1999)*, pages 1008–1014. MIT Press, 2000.

[25] Hojoon Lee, Dongyoon Hwang, Donghu Kim, Hyunseung Kim, Jun Jet Tai, Kaushik Subramanian, Peter R. Wurman, Jaegul Choo, Peter Stone, and Takuma Seno. SimBa: Simplicity bias for scaling up parameters in deep reinforcement learning. In *13th International Conference on Learning Representations (ICLR)*, 2025. arXiv:2410.09754.

[26] Timothée Lesort, Natalia Díaz-Rodríguez, Jean-François Goudou, and David Filliat. State representation learning for control: An overview. *Neural Networks*, 108:379–392, 2018.

[27] Chenliang Li, Junyu Leng, Jiaxiang Li, Youbang Sun, Shixiang Chen, Shahin Shahrampour, and Alfredo Garcia. AdaRL: Adaptive low-rank structures for robust policy learning under uncertainty. arXiv:2510.11899 [cs.LG], 2025.

[28] Chunyuan Li, Heerad Farkhoor, Rosanne Liu, and Jason Yosinski. Measuring the intrinsic dimension of objective landscapes. In *6th International Conference on Learning Representations (ICLR)*, 2018.

[29] Horia Mania, Aurelia Guy, and Benjamin Recht. Simple random search provides a competitive approach to reinforcement learning. In *Advances in Neural Information Processing Systems (NeurIPS)*, volume 31, 2018. arXiv:1803.07055.

[30] Tad McGeer. Stability and control of two-dimensional biped walking. Technical Report CSS-IS TR 88-01, Simon Fraser University, Burnaby, BC, Canada, 1988.

[31] Tad McGeer. Passive dynamic walking. *The International Journal of Robotics Research*, 9(2):62–82, 1990.

[32] Guido Montúfar, Keyan Ghazi-Zahedi, and Nihat Ay. Geometry and determinism of optimal stationary control in partially observable markov decision processes. *arXiv:1503.07206 [math.OC]*, 2015.

[33] Guido Montúfar, Keyan Ghazi-Zahedi, and Nihat Ay. A theory of cheap control in embodied systems. *PLOS Computational Biology*, 11(5):e1004427, 2015.

[34] Vincent C. Müller and Matej Hoffmann. What is morphological computation? on how the body contributes to cognition and control. *Artificial Life*, 23(1):1–24, 2017.

[35] Michal Nauman, Mateusz Ostaszewski, Krzysztof Jankowski, Piotr Miłoś, and Marek Cygan. Bigger, regularized, optimistic: Scaling for compute and sample-efficient continuous control. In *Advances in Neural Information Processing Systems 37 (NeurIPS 2024)*, 2024. arXiv:2405.16158.

[36] OpenAI, Marcin Andrychowicz, Bowen Baker, Maciek Chociej, Rafal Józefowicz, Bob McGrew, Jakub Pachocki, Arthur Petron, Matthias Plappert, Glenn Powell, Alex Ray, Jonas Schneider, Szymon Sidor, Josh Tobin, Peter Welinder, Lilian Weng, and Wojciech Zaremba. Learning dexterous in-hand manipulation. *The International Journal of Robotics Research*, 39(1):3–20, 2020.

[37] Youngsuk Park, Ryan A. Rossi, Zheng Wen, Gang Wu, and Handong Zhao. Structured policy iteration for linear quadratic regulator. In *Proceedings of the 37th International Conference on Machine Learning (ICML)*, volume 119 of *PMLR*, 2020. arXiv:2007.06202.

[38] Xue Bin Peng, Marcin Andrychowicz, Wojciech Zaremba, and Pieter Abbeel. Sim-to-real transfer of robotic control with dynamics randomization. In *2018 IEEE International Conference on Robotics and Automation (ICRA)*, pages 3803–3810, 2018.

[39] Aravind Rajeswaran, Kendall Lowrey, Emanuel Todorov, and Sham Kakade. Towards generalization and simplicity in continuous control. In *Advances in Neural Information Processing Systems (NeurIPS)*, volume 30, pages 6550–6561, 2017.

[40] Venkatesh G. Rao and Dennis S. Bernstein. Naive control of the double integrator. *IEEE Control Systems Magazine*, 21(5):86–97, 2001.

[41] Benjamin Recht. A tour of reinforcement learning: The view from continuous control. *Annual Review of Control, Robotics, and Autonomous Systems*, 2:253–279, 2019.

[42] Benjamin Recht, Maryam Fazel, and Pablo A. Parrilo. Guaranteed minimum-rank solutions of linear matrix equations via nuclear norm minimization. *SIAM Review*, 52(3):471–501, 2010.

[43] Nicholas Roy, Ingmar Posner, Tim Barfoot, Philippe Beaudoin, Yoshua Bengio, Jeannette Bohg, Oliver Brock, Isabelle Depatie, Dieter Fox, Dan Koditschek, Tomas Lozano-Perez, Vikash Mansinghka, Christopher Pal, Blake Richards, Dorsa Sadigh, Stefan Schaal, Gaurav Sukhatme, Denis Thérien, Marc Toussaint, and Michiel Van de Panne. From machine learning to robotics: Challenges and opportunities for embodied intelligence. arXiv:2110.15245 [cs.RO], 2021.

[44] Sergio Rozada and Antonio G. Marques. Matrix low-rank trust region policy optimization. arXiv:2405.17625 [cs.LG], 2024.

[45] Nikita Rudin, David Hoeller, Philipp Reist, and Marco Hutter. Learning to walk in minutes using massively parallel deep reinforcement learning. In *Proceedings of the 5th Conference on Robot Learning (CoRL)*, volume 164 of *Proceedings of Machine Learning Research*, pages 91–100, 2022. arXiv:2109.11978.

[46] John Schulman, Sergey Levine, Philipp Moritz, Michael Jordan, and Pieter Abbeel. Trust region policy optimization. In *Proceedings of the 32nd International Conference on Machine Learning (ICML)*, volume 37 of *PMLR*, pages 1889–1897, 2015. arXiv:1502.05477.

[47] John Schulman, Filip Wolski, Prafulla Dhariwal, Alec Radford, and Oleg Klimov. Proximal policy optimization algorithms. arXiv:1707.06347 [cs.LG], 2017.

[48] SciPy documentation: Continuous-to-discrete conversion, `cont2discrete`. `https://docs.scipy.org/doc/scipy/reference/generated/scipy.signal.cont2discrete.html`, 2026. Accessed 2026-10-17.

[49] SciPy documentation: Discrete Lyapunov solver, `solve_discrete_lyapunov`. `https://docs.scipy.org/doc/scipy/reference/generated/scipy.linalg.solve_discrete_lyapunov.html`, 2026. Accessed 2026-10-15.

[50] SIPPY Python library: Subspace identification for linear systems, N4SID. `https://github.com/CPCLAB-UNIPI/SIPPY`, 2026. Accessed 2026-10-15.

[51] Stable-Baselines3 documentation: Policy networks. `https://stable-baselines3.readthedocs.io/en/master/guide/custom_policy.html`, 2026. Accessed 2026-10-07.

[52] Stable-Baselines3 documentation: PPO. `https://stable-baselines3.readthedocs.io/en/master/modules/ppo.html`, 2026. Accessed 2026-10-07.

[53] Stable-Baselines3 documentation: Vectorized environments, VecNormalize. `https://stable-baselines3.readthedocs.io/en/master/guide/vec_envs.html`, 2026. Accessed 2026-10-14.

[54] Stefan Stojanovic, Yassir Jedra, and Alexandre Proutiere. Model-free low-rank reinforcement learning via leveraged entry-wise matrix estimation. In *Advances in Neural Information Processing Systems (NeurIPS)*, volume 37, 2024.

[55] Shokichi Takakura and Kazuhiro Sato. Structured output feedback control for linear quadratic regulator using policy gradient method. arXiv:2203.00289 [math.OC], 2023.

[56] Shahriar Talebi, Yang Zheng, Spencer Kraisler, Na Li, and Mehran Mesbahi. Policy optimization in control: Geometry and algorithmic implications. arXiv:2406.04243 [math.OC], 2024.

[57] Josh Tobin, Rachel Fong, Alex Ray, Jonas Schneider, Wojciech Zaremba, and Pieter Abbeel. Domain randomization for transferring deep neural networks from simulation to the real world. In *2017 IEEE/RSJ International Conference on Intelligent Robots and Systems (IROS)*, pages 23–30, 2017.

[58] Aleksandar Todorov and Matthia Sabatelli. Learning in low-dimensional subspaces: Orthogonal bottlenecks for reinforcement learning. *Reinforcement Learning Journal*, 2026. arXiv:2605.26012.

[59] Emanuel Todorov and Michael I. Jordan. Optimal feedback control as a theory of motor coordination. *Nature Neuroscience*, 5(11):1226–1235, 2002.

[60] Peter Van Overschee and Bart De Moor. N4SID: Subspace algorithms for the identification of combined deterministic-stochastic systems. *Automatica*, 30(1):75–93, 1994.

[61] Manuel Watter, Jost Tobias Springenberg, Joschka Boedecker, and Martin Riedmiller. Embed to control: A locally linear latent dynamics model for control from raw images. In *Advances in Neural Information Processing Systems (NeurIPS)*, volume 28, 2015. arXiv:1506.07365.

[62] Herbert Werner. Control systems theory and design. Lecture notes, Institute of Control Systems, Hamburg University of Technology, 2021.

[63] Herbert Werner. Optimal and robust control. Lecture notes, Institute of Control Systems, Hamburg University of Technology, 2021.

[64] Jingxi Xu, Bruce Lee, Nikolai Matni, and Dinesh Jayaraman. How are learned perception-based controllers impacted by the limits of robust control? In *Proceedings of the 3rd Conference on Learning for Dynamics and Control (L4DC)*, volume 144 of *PMLR*, 2021. arXiv:2104.00827.

[65] Keyan Zahedi and Nihat Ay. Quantifying morphological computation. *Entropy*, 15(5):1887–1915, 2013.

[66] Kaiqing Zhang, Bin Hu, and Tamer Başar. Policy optimization for $\mathcal{H}_2$ linear control with $\mathcal{H}_\infty$ robustness guarantee: Implicit regularization and global convergence. *SIAM Journal on Control and Optimization*, 59(6):4081–4109, 2021.

[67] Feiran Zhao, Florian Dörfler, Alessandro Chiuso, and Keyou You. Data-enabled policy optimization for direct adaptive learning of the LQR. arXiv:2401.14871 [math.OC], 2024.

Erklärung der Urheberschaft

Ich versichere an Eides statt, dass ich die Bachelor's Thesis im Studiengang Data Science selbstständig verfasst und keine anderen als die angegebenen Hilfsmittel – insbesondere keine im Quellenverzeichnis nicht benannten Internet-Quellen – benutzt habe. Es wurden keine Quellen genutzt, die nicht genannt wurden. Alle Stellen, die wörtlich oder sinngemäß aus Veröffentlichungen entnommen wurden, sind als solche kenntlich gemacht. Ich versichere weiterhin, dass ich die Arbeit vorher nicht in einem anderen Prüfungsverfahren eingereicht habe und die eingereichte schriftliche Fassung der auf dem elektronischen Speichermedium entspricht.

Ort, Datum Unterschrift

Erklärung zur Veröffentlichung

Ich erkläre mein Einverständnis mit der Einstellung dieser Bachelor's Thesis in den Bestand der Bibliothek.

Ort, Datum Unterschrift