Harmony NG Integration Architecture

Design document for the Harmony NG custom integration. Last updated 2026-11-09.

Written 2026-11-06. The section "As built" records where the implementation differs from the design.

The Hub's native API, REST plus one WebSocket, is the primary layer. MQTT through Home Assistant's MQTT integration is the second full layer. The Logitech protocol on port 8088 is a firmware-only option for the core Harmony integration. One event bus in hub_daemon feeds all three, so the two full layers carry identical information. Measured Hub resources leave an order of magnitude of headroom.


Requirements and constraints

The integration replaces Home Assistant's core Harmony integration for Hubs running harmony-ng, where the Logitech protocol no longer exists. We maintain both the firmware and the integration, so the Hub side is part of the design space.

Requirement	Meaning for the design
Push model, no polling	Every state change reaches Home Assistant as an event. REST is used only at startup and for commands
Very efficient	One socket per Hub, small JSON frames, nothing persisted to flash at runtime
User chooses the layer	The config flow offers API or MQTT. Both expose the same entities and services
Entities independent of the layer	Unique ids, entity ids and names derive from the Hub id and the entity key only. The user can switch API to MQTT or back and keep every entity, its history and its automations
Legacy protocol in firmware only	A Hub setting enables the Logitech WebSocket protocol so the core integration works, with its limits
Full functionality on each full layer	One firmware event model fans out to every transport, so no layer lags another
Platinum quality	All 54 quality scale rules addressed; typed PyPI client with injected session for the API layer
Hub resources	29 MB RAM, idle CPU, 1.7 MB free flash. Flash is the scarce resource
Discovery at network level	mDNS announces the Hub. Discovery never depends on a broker

Decisions already taken: API is primary and default; MQTT is a first-class alternative consumed through Home Assistant's MQTT integration; the Hub's own MQTT discovery entities are removed in the MQTT rewrite (as built they are kept, see As built); the legacy shim is in the first firmware milestone; the firmware's three transports are independent toggles while the integration uses one transport per config entry; entity identity never encodes the transport, so the transport can be changed in place without losing entities.

Architecture at a glance



Every state change is emitted once into hub_events and delivered by whichever sinks are enabled. The integration binds one transport per config entry and the same coordinator and entities sit behind both. The legacy port serves the core integration and other Harmony clients with the stock protocol's narrower data.

Transport comparison

For a single Home Assistant instance the Hub cannot tell the two full layers apart. The API wins on responsiveness, acks and having no third system in the path. MQTT wins when several consumers share the events. The legacy protocol is thin by design.

Criterion	API: REST + WebSocket	MQTT via HA MQTT integration	Legacy 8088, core integration
Push today	Activity progress only. State needs get_state. PR #74 adds BT, RF, config	Progress and buttons. Retained state republished every 30 s, not on change	Nothing exists yet
Push after firmware work	Complete, immediate, one socket	Complete, one broker hop	Activity state and start progress only
Data	Everything the Hub knows	Same, once published. Inventory needs chunked retained topics	Activities, devices, commands, current activity. No battery, BT, RF, buttons

Criterion	API: REST + WebSocket	MQTT via HA MQTT integration	Legacy 8088, core integration
Control	Request and reply with acks, 409 on busy, press, hold, release	Fire and forget today. Response topic with correlation id in the rewrite	Full remote semantics with request-id-bound progress
Button events	Firmware change, about 10 lines	Exist, but lost without broker and releases dropped	Not in the protocol
Latency	Direct LAN socket, keepalive every 30 s	One broker hop, single-digit ms on a LAN	Same socket model as API
Hub memory per consumer	About 12 KB per client	About 12 KB total, independent of consumers	About 12 KB per client
Infrastructure	None	Broker, HA MQTT integration, credentials on the Hub	None
Offline detection	Socket drop, HA reconnects with backoff	LWT retained status	Socket drop
Consumers	16 socket clients	Unlimited through the broker	Several clients
Auth	REST auth exists. WebSocket upgrade unauthenticated today	Broker auth and ACLs	None in the protocol
Discovery	mDNS, to be added	mDNS, same record	SSDP, to be added
Integration code	Typed PyPI client, session injected	HA MQTT helpers, no library	None, core integration unchanged
Compatibility value	Our integration only	Node-RED, openHAB, any MQTT consumer	Core integration, Homey, openHAB binding, pyharmony scripts
Main risk	WebSocket upgrade unauthenticated until firmware milestone 1 lands	Two-place configuration; duplicate entities if Hub discovery stays on	Stock quirks must match aioharmony exactly

A fourth variant, Hub-generated MQTT discovery entities with no custom integration, is rejected. MQTT discovery has no remote platform, every entity is C code with fixed buffers, and it cannot be scored against the quality scale.

Firmware today

Verified on 2026-11-05 against upstream main plus the #74 and #81 branches; #74 merged upstream that day. hub_daemon is a single select() loop with a hand-rolled HTTP and WebSocket server on port 8089, an orchestrator ticked every 40 ms, a hand-rolled MQTT 3.1.1 client and cJSON. Paths are relative to payload/source.

Surface	What exists	What is missing or wrong
HTTP server	Backlog 32, one detached thread per connection with a 512 KB stack, hard cap of 8 threads (hub_daemon.c:45). Digest, Bearer and PAT auth on /api/* (http_server.c:429-452). CORS * everywhere	A ninth concurrent request is refused. Static files and the WebSocket upgrade are not authenticated
WebSocket	RFC 6455 upgrade on any path, 16 clients (ws_server.h:7), 4 KB inbound frame buffer (hub_ws.c:51). Actions: ping, get_state, send_command with press, hold, release, start_activity, stop_activity, cancel_activity, bt_key, bt_text, bt_mouse (hub_ws.c:76-328)	Upgrade runs before the auth check (http_server.c:514-518); the token form in API.md 11.4 does not exist. No activity_state push, only activity_progress (hub_ws.c:16-48). No server keepalive. Main has no locking on the client list and no loop on partial sends

Surface	What exists	What is missing or wrong
PR #74	state_watch.c, 236 lines: a 1 s thread active while a client is connected, pushes bt_status, rf_status and config_changed with key files, plus mutexes, send_all and 503 at capacity	Merged upstream on 2026-11-05. Baselines reset on reconnect, so nothing is sent until the next change
PR #81	POST /api/rf/wake?slot=N, 70 lines with tests	Open on the fork; folded into firmware milestone 1
Orchestrator	States IDLE, STARTING, RUNNING, STOPPING; busy during STARTING and STOPPING; returns -2 when busy, mapped to HTTP 409. Progress callback at start, per step, on completion and on cancel (orchestrator.c:138-441)	The callback's only consumer is the progress broadcast. State transitions themselves are not published
MQTT	Reconnect backoff 5 to 60 s, LWT on status, retained state JSON, progress, button pulses on remotes/slotN/Cmd (hub_mqtt.c). Subscribes to activity/set, command/#, send_command, sync, remote sleep, pronto	Retained state only republished every 30 s or on connect (hub_mqtt.c:1070-1080). Button releases dropped (:859-861). Events lost with return -1 when the broker is down (:855). HA discovery hardcoded with fixed buffers (hub_mqtt_ha.c:196-431)
Button events	hub_rf posts /api/button-press (rf_keymap.c:175), dispatched to MQTT only (http_api_remotes.c:383)	No WebSocket path at all
Discovery	None. harmony.local appears only as a label in openapi.yaml:21-23	No mDNS, no SSDP
Legacy protocol	No trace of XMPP, 8088, hbus, stateDigest or SSDP in any daemon. Only host tools probe stock port 8088	Everything must be written
OpenAPI	88 paths documented	docs/openapi.yaml fails to parse at line 1206, column 78

Live payloads from the Hub: inventory 28 KB for 4 devices and 202 commands, activities 1 KB, rf/status 1.1 KB, bt-status 0.5 KB. The status endpoint's total_kb and free_kb report the /data flash partition, not RAM (http_api_system.c:30-38).

Firmware plan

One module, hub_events, owns a small set of events: activity state, activity progress, config changed, BT status, RF status, remote button. The orchestrator, the state watcher and the button handler emit into it. Three sinks subscribe: the WebSocket broadcaster, the MQTT publisher and the legacy shim. Full functionality on every layer then holds by construction. Line counts are estimates excluding tests, which add about a third. Reference points from the tree: state_watch.c is 236 lines for three pushed types, the #74 WebSocket hardening is 97, the #81 wake endpoint is 70 with tests, the MQTT discovery code is 440. Every item is specified in HA_INTEGRATION_FIRMWARE_SPEC.md in the firmware repository's docs folder, one pull request per milestone on the fork.

Feature	Layer	Where	New lines	Notes
Event bus: event struct, subscribe, emit	Shared	new hub_events.c and .h, hooks in hub_daemon.c, orchestrator.c, http_api_remotes.c	150 to 200	Foundation for every row below
Activity state event on every transition	Shared	orchestrator.c	20 to 30	Emit where progress already fires

Feature	Layer	Where	New lines	Notes
Port the #74 watcher to the bus	Shared	existing branch	20 to 40	423 lines already written
Remote button event with release, never dropped	Shared	http_api_remotes.c	20 to 30	Replaces the MQTT-only dispatch
hub_rf pushes RF status instead of being polled	Shared	rf_api.c, hub_daemon.c	40 to 60	Removes the 1 s poll in the watcher
Remote unit id over RF	Shared	elite_ui, rf_main.c	60 to 100	The remote reads its manufacturing partition and reports it; rf_status gains remote_id per slot
Infrared capture mode and ir_received event	API	http_api_commands.c, ir_i2s.c, ir_encoder.c	80 to 120	Serves the infrared receiver entity; capture pauses for sends and shares the timing representation with the encoder
WebSocket sink for every bus event	API	hub_ws.c	80 to 120	Reuses existing JSON builders
WebSocket auth on upgrade with PAT or Bearer	API	http_server.c, http_auth.c, ws_server.c	40 to 60	Closes the documented but missing token check
Server keepalive ping and dead-client reaping	API	ws_server.c	30 to 50	Clients today only drop on send failure
Full state snapshot on connect	API	hub_ws.c	40 to 60	Activity, BT, RF, config version in one frame
Raw IR endpoint: carrier, signed timings, port mask, repeats	API	http_api_commands.c, calls hw_ir_send_raw	50 to 80	Serves the infrared emitter entities. The raw path exists in hw_action.c and ir_encoder.c, only the endpoint is missing
mDNS responder, _harmony-ng._tcp with TXT record	Discovery	new hub_mdns.c	200 to 300	TXT: id, version, auth, mqtt base topic. Kernel 2.6.31 has no SO_REUSEPORT, one responder owns 5353
MQTT rewrite on the bus: publish on change, retained state, BT, RF, inventory, config version	MQTT	replaces hub_mqtt.c and hub_mqtt_ha.c	600 to 900	Today 1542 lines. Discovery entities deleted in this change
MQTT command channel with correlation id and response topic	MQTT	inside the rewrite	100 to 150	Acks and busy errors equal to the API layer
MQTT button events with release, QoS 1	MQTT	inside the rewrite	20 to 40	Replaces the pulse-then-zero scheme
MQTT inventory chunked per device	MQTT	inside the rewrite	30 to 50	28 KB exceeds the 4 KB packet buffer
MQTT raw IR command topic	MQTT	inside the rewrite	20 to 40	Same payload as the API endpoint, so the emitter entities work on both transports
Legacy provisioning POST on 8088	Legacy	new hbus_server.c	40 to 60	activeRemoteId, hubSwVersion, discoveryServer
Legacy WebSocket listener on the select loop	Legacy	hub_daemon.c, reuse ws_server.c	60 to 100	Second listener via http_server_init(port)

Feature	Layer	Where	New lines	Notes
Legacy command handlers: state digest, config, current activity, holdAction, runactivity, changeChannel, sync, discovery info	Legacy	hbus_server.c	300 to 400	Maps onto orchestrator getters and the press, hold, release path
Legacy activity start sequencing: code 100 progress bound to the request id, final 200, state digest 1 then 2, startActivityFinished	Legacy	hbus_server.c as a bus sink	100 to 150	Without the bound 200 the core integration times out after 60 s
Stock config schema: activity and device lists, control groups, JSON-in-string actions, timeStampHash	Legacy	new hbus_config.c	250 to 350	Numeric string ids, PowerOff activity with id -1
SSDP responder with device description XML	Legacy	new hub_ssdp.c	150 to 250	Shares UDP plumbing with mDNS
Settings and web UI toggle, off by default	Legacy	config_store.c, http_api_system.c, frontend	40 to 80	Plus the OpenAPI entry
OpenAPI file fix	Docs	docs/openapi.yaml	1	Line 1206

Milestone	New lines
Shared event model and API layer	680 to 1010
mDNS	200 to 300
MQTT rewrite	770 to 1180
Legacy shim with SSDP and toggle	940 to 1390
Everything	2610 to 3840

The event bus lands first, since every other row emits into it or consumes it. The shim should be verified against a recorded aioharmony session, not only against the core integration, because the core integration tolerates silence on most commands and would hide framing mistakes that other Harmony clients will not.

Hub resource budget

The whole programme adds under 300 KB of steady-state RAM, under 1 MB at peak and 50 to 90 KB of flash on a Hub with 21 MB of RAM available and an idle CPU. Flash is the only tight resource, which sets the rule that all new code lives inside hub_daemon.

Baseline measured on 2026-11-05 on a Hub with one activity running and no WebSocket client connected. The stock Logitech runtime used 12 to 16 MB and 15 to 30 percent CPU on the same hardware.

Resource	Measured	Source
SoC	Atheros AR9344, MIPS 24Kc, kernel 2.6.31	/api/system-info
RAM total / available	29 MB / 21 MB	/proc/meminfo
Load average	0.00, 41 processes	/api/system-info
hub_daemon resident	908 KB, 2 threads, 468 KB text	/proc/pid/status

Resource	Measured	Source
hub_rf resident	324 KB, 6 threads	/proc/pid/status
hub_btstack resident	560 KB, 1 thread	/proc/pid/status
hub_daemon binary	516 KB, static, built with -Os -s	release bundle
/data flash	1712 KB free of 5120	df
/cache flash	1756 KB free of 5120	df
Inventory payload	28 KB, 4 devices, 202 commands	/api/inventory

Feature	RAM	Flash	CPU	Fit
Event bus	Under 2 KB static	3 to 6 KB	Nil, calls on the existing 40 ms loop	Fits
State push, button events, snapshot on connect	A few KB transient per event via cJSON	2 to 4 KB	Nil	Fits
WebSocket sink, auth, keepalive	About 12 KB per client; 16 clients about 200 KB worst case	3 to 6 KB	One ping per client every 30 s	Fits. Runs on the select loop, not the 8 HTTP threads
State watcher as in #74	One thread, 1 s file poll plus an HTTP call to hub_rf while a client is connected	0	Small, constant	Fits. Pushing from hub_rf removes the poll
mDNS responder	One UDP socket, 1500 byte buffer	8 to 15 KB	Answers on queries only	Fits
MQTT rewrite	4 KB packet buffer, 32 subscriptions, as today	Net zero or negative	Lower than today: publish on change, not on a timer	Fits. Inventory chunked per device
Legacy listener and handlers	Same per-client cost as WebSocket	15 to 25 KB	Nil	Fits
Legacy config generation	40 to 60 KB of JSON for 202 commands; cJSON tree peaks at 150 to 300 KB, freed after send	Included	A few ms per config request, once per client connect	Fits. Build on demand, never cache
SSDP responder	Shares UDP plumbing; 1 KB description XML	6 to 10 KB	Nil	Fits

Three rules follow from the measurements. All new code goes inside hub_daemon, because a separate static MIPS binary costs about 100 KB of flash for its libc copy alone, as the 104 KB DHCP daemon shows, while code added to hub_daemon costs 1 to 2 KB per 100 lines. Nothing in the bus, the shim or the MQTT layer writes flash at runtime; only user settings persist. Push and the shim stay on the select loop, since the 8-thread HTTP cap refuses a ninth request; the 512 KB stacks are virtual, not resident, so they are not a memory problem.

The peak case to test on hardware before merging is 16 socket clients plus a legacy config request during an activity switch, which exercises every transient allocation at once.

Integration design

One entity model, two interchangeable backends. Entities, services and devices never know which transport is active.

Transport abstraction. A HarmonyNgTransport protocol class with async connect, disconnect, fetch_snapshot, start_activity, power_off, cancel, send_command with press, hold and release, bt_key, ir_raw, rf_wake, sync, and an event callback. Two implementations: ApiTransport wraps the PyPI client (REST plus WebSocket); MqttTransport subscribes and publishes through homeassistant.components.mqtt and correlates command responses by id. Both transports serve the full entity set. A transport still reports capabilities so that an older firmware missing a feature degrades by leaving the affected entity registered and unavailable, never by deleting it.

Coordinator. A DataUpdateCoordinator with no update_interval. Every transport event calls async_set_updated_data from a callback. The coordinator holds one HubState dataclass: activity id and state, busy and sending, inventory with config version, BT hosts, RF slots with battery and sync, firmware and version. REST or a retained-topic read happens once at setup and again on a config_changed event. A missed-heartbeat watchdog marks the entry unavailable and reconnects with backoff.

Config flow. Steps: discovered Hub or manual host and port; optional Personal Access Token, validated by one status call; transport choice with API as default and MQTT as the alternative, shown with conditional fields for the MQTT base topic prefilled from the Hub's TXT record or status call. Reauth flow for an invalidated token. Reconfigure flow for host and transport. Options flow with reload for default activity and inter-command delay, the two options core users already have. Unique id is the Hub's stable id from the TXT record or status call, never the host.

Changing transport. The transport is a setting of the config entry, never part of any identity. The reconfigure flow lets the user switch between API and MQTT: it validates the new transport against the same Hub id, refuses a Hub whose id differs, writes the new transport into entry data and reloads the entry. The config entry id, the device identifiers, every unique id and therefore every entity id, friendly name, history, area, label and automation stay untouched, because none of them ever contained the transport, host, port or base topic. No migration step exists by design: a transport change behaves exactly like a host change. The one real migration is for users of the Hub's old MQTT discovery entities, which live under the mqtt domain: the MQTT rewrite stops publishing them, and the integration offers a repair that removes the orphaned mqtt entities and lists their replacements so automations can be repointed.

Discovery. mDNS only, service _harmony-ng._tcp, TXT keys id, ver, api, auth, mqtt, topic, legacy, name. The flow updates the stored host when a known id appears on a new address. No MQTT-triggered discovery.

Library split. A typed package pyharmonyng on PyPI holds the API client: aiohttp session injected, REST models, WebSocket listener with reconnect, exceptions, py.typed. It has no Home Assistant imports and its own tests. The MQTT backend lives inside the integration because it is Home Assistant specific. This satisfies the three Platinum rules for the API layer and keeps the MQTT layer exempt from inject-websession with a documented reason.

Repo layout. custom_components/harmony_ng with **init**.py, config_flow.py, const.py, coordinator.py, entity.py, transport/ (base.py, api.py, mqtt.py), remote.py, select.py, sensor.py, binary_sensor.py, button.py, event.py, infrared.py, diagnostics.py, repairs.py, services.py, icons.json, translations/en.json, quality_scale.yaml, brand/. tests/ mirror the modules with snapshot tests per platform.

Services. Entity services on the remote entity: send_command with device, delay_secs, hold_secs and num_repeats as in core, plus sync. Integration services registered in async_setup: ir_send for a device command by name with port and repeats; raw codes go through the infrared emitter entities instead, bt_key with key and action, activity_help and activity_cancel. All raise translated HomeAssistantError on failure and return response data where useful.

Error handling. The library raises typed exceptions: HarmonyNgConnectionError, HarmonyNgAuthError, HarmonyNgBusyError for 409, HarmonyNgApiError. The coordinator maps them to ConfigEntryAuthFailed, ConfigEntryNotReady or UpdateFailed and never logs what Home Assistant logs itself.

Compatibility with core automations. The remote entity keeps the same attribute names, activity_list semantics and PowerOff handling as core, so turn_on with activity, turn_off and send_command port unchanged. Entity ids differ by domain, which a rename at migration time covers.

Entity and device model

One Hub device, one child device per RF remote slot, and the same entity set on either transport. Every entity sets has_entity_name and takes its name from a translation key, never from the device name. Unique ids are the Hub id plus the entity key, with the remote id for per-remote entities and the host address for per-Bluetooth-host entities; device identifiers are the Hub id alone. Neither carries the transport, host, port or MQTT base topic, so API and MQTT produce identical registry entries and switching between them changes nothing in the entity registry.

Device	Identifier	Relationship	Fields
Hub	(harmony_ng, hub id)	Root device of the config entry	manufacturer Logitech, model Harmony Hub, model_id from skin, sw_version harmony-ng version, hw_version Logitech base firmware, configuration_url `http://host:8089`, serial_number hub id
RF remote, one per paired remote	(harmony_ng, remote id), the remote's own unit id read from its manufacturing partition and reported over RF; the slot number is an attribute	via_device_id to the Hub, since it is a separate product with its own firmware and battery	model from the slot (Elite, Ultimate), sw_version remote firmware
Configured IR or BT device	(harmony_ng, hub id:device:id), a child device of the Hub	One remote entity per device for send_command without naming the device; added and retired as the inventory changes	name, manufacturer, model from the inventory

Platform	Entity	Source	Device	Category	Notes
remote	Hub remote	activity state, inventory	Hub	main entity, name None	turn_on with activity, turn_off, send_command with device, delay_secs, hold_secs, num_repeats; attributes current_activity, activity_list, last_activity, activity_starting, devices_list as in core

Platform	Entity	Source	Device	Category	Notes
select	Activity	activity state, inventory	Hub	none	options PowerOff plus activity names, same as core
sensor	Activity state	orchestrator state	Hub	diagnostic	enum: idle, starting, running, stopping
sensor	Firmware	status	Hub	diagnostic	harmony-ng version string
sensor	Uptime, named Last boot	status	Hub	diagnostic, disabled by default	timestamp device class; the Hub's boot_time as built
sensor	Battery	rf_status	Remote slot	diagnostic	device class battery, percent
sensor	Battery voltage	rf_status	Remote slot	diagnostic, disabled by default	voltage device class, millivolts, shown in volts as built
binary_sensor	Charging	rf_status	Remote slot	diagnostic	device class battery_charging
binary_sensor	Config in sync	rf_status	Remote slot	diagnostic	problem device class, inverted
binary_sensor	Hub busy	activity state	Hub	diagnostic	running device class
binary_sensor	Bluetooth host connected, one per paired host	bt_status	Hub	diagnostic	connectivity device class, dynamic add and remove
button	Power off	command	Hub	none	same as the Hub's MQTT button today
button	Sync remotes	command	Hub	config	push-config
button	Wake remote	command, PR #81	Remote slot	config	per slot
button	Sleep remote	command	Remote slot	config	per slot
button	Cancel activity	command	Hub	config	resets a stuck interlock
event	Remote button	button events	Remote slot	none	event types press and release with the button name as attribute; uses the standard button event types
update	Hub firmware	update-status endpoints	Hub	config	first release; installed version from the status, latest from the Hub's release check polled daily; install calls update-apply and the Hub restarts
infrared	IR emitter, one per output: front blaster, jack 1, jack 2	raw IR endpoint	Hub	none	first release; subclasses InfraredEmitterEntity; Home Assistant supplies raw timings and a carrier, the Hub never sees Pronto; lets core IR integrations such as lg_infrared or samsung_infrared use the Hub as their blaster

Services beyond the remote entity's own: harmony_ng.ir_send (device and command by name, with port and repeats), harmony_ng.bt_key (key, action press, hold, release, target), harmony_ng.activity_help and harmony_ng.activity_cancel. All target the Hub device and raise translated errors.

Diagnostics redact the host, token and Bluetooth addresses and include the last snapshot, the transport in use, the Hub version and the configured mDNS record. Repair issues cover:

firmware too old for the event bus, legacy mode enabled on the Hub while our integration is configured, and the Hub's MQTT discovery entities still present.

Quality scale plan

All 54 current rules are addressed. For custom integrations the tier is self-declared: hassfest skips quality_scale.yaml for non-core code and the Marketplace states there are no tiers for custom integrations, so the file is our own tracking and the manifest key documents the claim. Only four rules are exempt, each with a justification the rule page accepts.

Tier	Rules	Plan
Bronze, 20	action-setup, appropriate-polling, brands, common-modules, config-flow, config-flow-test-coverage, dependency-transparency, docs-actions, docs-conditions, docs-high-level-description, docs-installation-instructions, docs-removal-instructions, docs-triggers, entity-event-setup, entity-unique-id, has-entity-name, runtime-data, test-before-configure, test-before-setup, unique-config-entry	All done. appropriate-polling is satisfied by having no polling. brands via the custom brand folder. docs rules written against the README and docs folder
Silver, 10	action-exceptions, config-entry-unloading, docs-configuration-parameters, docs-installation-parameters, entity-unavailable, integration-owner, log-when-unavailable, parallel-updates, reauthentication-flow, test-coverage	All done. reauthentication-flow is required because auth is optional, not absent: an invalidated PAT triggers reauth. parallel-updates 0 on read-only platforms, 1 on remote, select, button
Gold, 21	devices, diagnostics, discovery, discovery-update-info, docs-data-update, docs-examples, docs-known-limitations, docs-supported-devices, docs-supported-functions, docs-troubleshooting, docs-use-cases, dynamic-devices, entity-category, entity-device-class, entity-disabled-by-default, entity-translations, exception-translations, icon-translations, reconfiguration-flow, repair-issues, stale-devices	All done; mDNS shipped with firmware milestone 2. dynamic-devices and stale-devices are required, not exempt, because remote slots and Bluetooth hosts come and go: listener-based adds and async_remove_config_entry_device
Platinum, 3	async-dependency, inject-websession, strict-typing	async-dependency and strict-typing done via the typed asyncio library with py.typed. inject-websession done for the API transport. For an entry on the MQTT transport the rule is exempt: no HTTP session exists, which is the exception the rule page names

Rule	Status	Justification
discovery, discovery-update-info	todo until mDNS lands, then done	The Hub does not announce itself today; firmware milestone 1 adds the record
inject-websession	done for API, exempt for MQTT	The MQTT transport makes no HTTP requests
infrared platform entity	first release	Not a scale rule, listed for completeness. The platform hands the emitter raw timings and a carrier, so no Pronto mapping is involved; the firmware raw send path exists and only needs an endpoint
update entity	deferred	update-apply needs validation on hardware before Home Assistant can trigger it

Test coverage target is 97 percent per the repository rule, above the 95 percent the scale asks for. Snapshot tests per platform, a config flow test per step and error, a diagnostics snapshot, and transport tests that replay recorded Hub frames for both backends.

Home Assistant platform changes to apply first

Home Assistant 2026.11.0 shipped on 2026-11-04. The integration targets a minimum of 2026.8.0, which stays valid, but the shared scaffolding that integration repositories are generated from must be updated before this integration is built on it. Entity naming rules in code did not change; the frontend now composes device and entity names, so entity names must never carry the hub or device name.

Change	Since	Deadline	Action in the scaffolding
HACS replaced by the built-in Marketplace, same catalog and hacs.json	2026.11	now	README and install docs say Marketplace; add the categories manifest key; keep version in the manifest
pytest-homeassistant-custom-component declared broken; official pytest-homeassistant from core	2026.11	now	Switch the dev dependency and imports; match the package version to the HA version
Developer docs moved to contributors.home-assistant.io	2026-10-16	redirects for now	Update links in CLAUDE.md and docs
Config entry functions return None; failure by raising	2026.11	bool still accepted	Return None, use async_unload_platforms_or_raise; tests patch setup with return_value None
DeviceInfo is a dataclass, keyword-only, via_device_id, no default_ fields	2026.11	via_device removed 2027.8	Construct with keywords; resolve the parent registry id for via_device_id
async_get_device deprecated	2026.8	2027.8	Use async_get_device_by_identifier with the entry id
step_id required on every form, menu and progress result	2026.10	2027.5	Pass step_id everywhere
In-place entity id changes	2026.11	compat removed 2027.11	Base entity implements async_entity_id_changed
Repair issues bound to a config entry	2026.11	none	Pass config_entry_id; use async_refresh_issues
Update listener combined with reload-on-update flows	2026.6	error from 2026.12	Keep OptionsFlowWithReload, drop add_update_listener
Central abort reasons translated by core	2026.10	none	Remove already_in_progress, reauth_successful, reconfigure_successful, single_instance_allowed from abort translations

Change	Since	Deadline	Action in the scaffolding
Conditional form fields with visible	2026.11	none	Use for the transport step
Child devices	2026.9	none	Optional for configured IR and BT devices; remotes stay via_device_id
Undefined sentinel replaces UNDEFINED	2026.12	none	Migrate when the floor reaches 2026.12
Custom brand images	2026.3	none	Keep the brand folder
Probatio replaces voluptuous	2026.9	none	No code change; error text in tests may differ
Entity service registration helper	2025.10	hass arg removed 2026.10	Use async_register_platform_entity_service
infrared and radio_frequency entity platforms	2026.4, 2026.5	Platform split into InfraredEmitterEntity and InfraredReceiverEntity; the old InfraredEntity name is a deprecated alias removed in 2027.6. Subclass InfraredEmitterEntity directly	infrared emitter in the first release, one entity per output. Receiver later at most: ir_i2s.c can capture, but nothing exposes it and capture has to release the transmit handle. radio_frequency not applicable: the platform models sub-GHz OOK transmitters, the CC2544 is a 2.4 GHz packet radio speaking eQuad to the remotes
Quality scale not validated for custom integrations	current	none	Keep quality_scale.yaml for tracking; declare the tier in the manifest

The changes above belong to the shared scaffolding rather than to this integration, so they are a separate piece of work and should land first.

Milestones and sequencing

Firmware leads by one milestone, because the integration's API transport needs the event bus and the state push before it can be tested end to end. The scaffolding update is independent and lands first.

1. Scaffolding: apply the Home Assistant platform changes to the shared integration scaffolding so every repository generated from it receives them.
2. Firmware milestone 1: event bus, activity state push, the #74 watcher ported, button events, WebSocket auth, keepalive, snapshot on connect, raw IR endpoint, mDNS, legacy shim with SSDP and toggle, OpenAPI fix. Verified on the Hub with a recorded aioharmony session and the core integration.
3. Library: pyharmonyng on PyPI with REST models, WebSocket listener, typed exceptions and its own tests against recorded frames.
4. Integration milestone 1: API transport, config flow with mDNS, remote, select, sensors, binary sensors, buttons, event, infrared emitters, diagnostics, repairs, services. Platinum rules done except MQTT-specific ones.
5. Firmware milestone 2: MQTT rewrite on the bus, command response topics, raw IR command topic, chunked inventory, discovery entities removed, release note naming the integration as the replacement.
6. Integration milestone 2: MQTT transport, transport step in the config flow, parity tests that run the same entity snapshots on both backends.

7. Integration milestone 3: update entity, infrared receiver (needs the firmware's capture item), child devices with a remote per configured device. Written ahead of the firmware; the receiver stays unavailable until the Hub lists ir_capture.

Decision	Taken
Primary layer	API, default in the config flow
Second full layer	MQTT through Home Assistant's MQTT integration: the Hub publishes to the broker, the integration subscribes
Legacy protocol	Firmware-only setting, off by default, in milestone 1; the core integration is the client
Hub MQTT discovery entities	Removed in the MQTT rewrite, with a release note. As built: kept at the upstream maintainer's request
Discovery	mDNS only; the transport is chosen in the flow, never implied by how the Hub was found
Firmware transports	Independent toggles; WebSocket always on for the web UI
Integration transports	One per config entry

Open questions: whether configured IR and BT devices become child devices in the first release or later. The PyPI name pyharmonyng was free on 2026-11-06.

As built

Status on 2026-11-09, with integration release 0.1.7 and firmware specification 1.1. The firmware specification's status table says which firmware parts are merged upstream, open or not posted yet.

Infrared capture. The capture state is part of the Hub's status fields, so it is in the snapshot's hub object and in MQTT `<base>/hub`: `ir_capture`, plus `ir_capture_error` only while the receiver has a problem. Every change is pushed as a WebSocket event `{"type":"ir_capture","ir_capture":true}` and republishes `<base>/hub`. The mode is off after every Hub start, so the receiver entity turns it on again after each reconnect and retries a failed start every 30 s while the Hub does not report it on.

MQTT commands. Request ids are strings; the Hub executes a request with a numeric id and does not answer it. The Hub subscribes to `<base>/cmd` at QoS 1 before it publishes `online` (firmware PR #99), so a command sent the moment `online` arrives is answered. The capture retry exists for firmware before that fix, where `online` went out first and such a command could be lost.

Remote model. Each RF slot carries `model`, `model_name` (null while unknown), `skin` and `equad_id`; the product comes from the remote's skin id. Firmware with the A4 fix keeps the skin when a config push rewrites the Hub's version file, so the model survives a `hub_rf` restart. On firmware without it the model is unknown after such a restart until the remote reboots, and the integration keeps the last known model per remote id.

Boot time. The status fields carry `boot_time` (Unix time, null until the Hub's clock is set). The Last boot sensor uses it; only firmware without it falls back to the snapshot time minus `uptime_sec`.

Battery. Each slot's battery object carries `reported_at` (Unix time or null) and `restored` (true for a report `hub_rf` restored after a restart). The integration shows the time of the last report as a sensor.

Hub MQTT discovery. The firmware keeps Home Assistant MQTT discovery, rebuilt on the v2 topics with the same object ids, instead of removing it. Both sets of entities can exist when a user enables discovery on the Hub and also sets up this integration. The repair for orphaned discovery entities still assumes removal and needs revising.

Activities. The Hub lists PowerOff (id -1) with the activities; the integration leaves it out of the activity list, as the core integration does. The select still offers PowerOff and the remote reports it as the current activity while off.

Bluetooth. After a `hub_btstack` restart every host that was connected comes back, the activity's host first (firmware PR #101). Since upstream 506794a power-off no longer disconnects the hosts and nothing reconnects while the activity is off, so the connectivity sensors can show hosts connected for a while after power-off.

Sources

- harmony-ng firmware repository, main at f44074d (includes #74) plus branch feat/rf-wake (#81): payload/source, docs/API.md, docs/openapi.yaml, README.md.
- Readings taken on 2026-11-05 from a Hub running harmony-ng main: GET /api/status, /api/system-info, /api/inventory, /api/activities, /api/rf/status, /api/bt-status, plus /proc/meminfo, /proc/pid/status and df from a shell on the Hub. Read-only.
- aioharmony tag v1.0.8, ehendrix23/aioharmony: harmonyclient.py, hubconnector_websocket.py, hubconnector_xmpp.py, const.py, responsehandler.py. GitHub
- Home Assistant core 2026.9.3 source: homeassistant/components/harmony, mqtt, infrared, radio_frequency, remote.
- Home Assistant 2026.11 release notes, 2026.10, 2026.9.
- Developer blog index, posts from 2025-11-01 to 2026-11-05.
- Integration quality scale and rules.
- Entity naming and Naming things in Home Assistant.
- Marketplace integration guide and hacs.json reference.
- pytest-homeassistant on PyPI and the pytest-homeassistant-custom-component notice.
- hassfest quality_scale.py in core 2026.11.0.