

Quick Set up and Installation Process

This first section is a quick step-by-step guide. The details and context are found in the remainder of this document. You must read the entire document before you start your deployment to ensure success.

Note: The Cisco IP DECT 6800 Phone products support single cell, dual cell, and multicell deployments. All call control systems may not support multicell deployment. Currently, Cisco Webex Calling and Webex Calling Carrier support single cell and multicell deployment. Before you begin, check with your call control provider to ensure that they support the deployment models described in this guide.

Note: There are many ways to install the base stations. This guide provides the best practices and the recommended deployment models supported by Cisco TAC.

Plan for the Device Installation

These instructions are for the planner:

1. Review the site to install the DECT system.
 - Plan the location of the base stations.
 - Each base station covers 50m (164 feet) indoors. The base stations should be installed within 50 meters for good coverage. The location of the base station may be impacted by objects or barriers that create radio obstruction and interference. The handsets provide a free site survey tool to identify the impact of these potential barriers.
 - Each base station requires an Ethernet cable.
 - A power outlet is required for each base station if the Ethernet switch does not provide Power over Ethernet.
2. Determine the DECT equipment required:
 - Available base stations and repeater:
 - Cisco IP DECT DBS-110 Single-Cell Base Station
 - Cisco IP DECT DBS-210 Multi-Cell Base Station
 - Cisco IP DECT RPT-110 Repeater

Note: Repeaters do not have Ethernet port. Deployment of repeaters can be done using power adapters.

- The base stations vary in their support for SIP registrations and concurrent calls. For more information, see *Matching the Base Stations to the Density Requirements*.
- Each handset supports up to 2 SIP registrations.
- Available handsets:
 - Cisco IP DECT Phone 6823 Handset

- Cisco IP DECT Phone 6825 Handset
 - Cisco IP DECT Phone 6825 Ruggedized Handset
 - A foot stand is provided to place the base station on a table or shelf.
 - An optional kit is also available, but sold separately, to mount the base stations on the wall or ceiling.
 - The part numbers of the products are listed in the section *Product IDs*
3. Order and receive the equipment.
 4. Ship the equipment to the installation site.

The equipment may be upgraded either at a staging site before reshipping or at the installation site after reshipping. For information about firmware upgrade, see *Upgrade the Devices*.

Upgrade the Devices

These instructions may be completed at a staging site or at the installation site.

1. Unpack and register the base stations to the call system.
2. Upgrade the base stations to the desired firmware version, if necessary.
 - The base stations and handsets are shipped with a firmware version that may be used in production or upgraded to the latest firmware upgrade supported by the call control system.
 - Cisco's best practice recommendation is to use the most recent firmware load available on Cisco.com.
 - Each base station may take up to one hour to upgrade.
3. Select and set the desired configuration parameters. Follow the instructions in the *Cisco IP DECT 6800 Series Administration Guide* to configure the base stations.
4. Unpack the handsets and remove the battery which is inside the rear battery door of each handset. Remove the plastic shield from the battery and reinstall the battery.
 - There is only one way that the battery fits inside the handset: if it isn't sliding into its slot easily, turn the battery over and try again.
 - The battery comes partially charged and the handset should be left on its cradle to charge fully before using the handset.
 - You can register each handset with the base station before charging and then upgrade the firmware while they charge on the cradle.
5. Register the handsets to the base stations.
6. If the base station sends a more recent firmware load to the handset, the handset may require one hour to complete the upgrade.