

Bit index	Name	Instruction Dependency	Description
19	Press Setup Button N times	M	The Device will enter the target state when setup button is pressed N times with maximum 1 second between each press. The exact value of N SHALL be made available via PI key.
20	Power Cycle N times	M	The Device will automatically enter the target state after exactly N power OFF/ON sequences (unplug/re-plug, remove/re-insert batteries) starting from the powered ON state. A non-zero X value provides the minimum number of seconds to keep the device in the ON state before the next iteration. A non-zero Y value specifies the total elapsed time during which exactly N power cycles must be detected in order to enter the desired state. A non-zero Z value means that the device will blink Z times to indicate that the sequence was detected, before entering the desired state. If a variable (X, Y, or Z) is set to 0, then the corresponding aspect of the instruction is not specified. The format of the PI key's value SHALL be N,X,Y,Z where N,X,Y and Z are variable length decimal values (no leading zeros) and there are no spaces or other characters present in the value. For example, 5,1,10,3 indicates that within 10 seconds the device must be powered OFF then ON 5 times, remaining in the ON state each time for at least 1 second, and the device will blink 3 times to indicate success before entering the target state. Alternatively, 8,0,20,0 indicates that within 20 seconds the device must be powered OFF then ON 8 times in order to enter the target state.
21	Press Button for N seconds with indication	M	The Device will enter the target state when the button is pressed for N seconds. A non-zero Z value means that the device will blink Z times to indicate that the action was detected, before entering the desired state. The format of the PI key's value SHALL be N,Z where N and Z are variable length decimal values (no leading zeros) and there are no spaces or other characters present in the value. For example, 10,3 indicates that the button must be held for 10 seconds, and the device will blink 3 times before entering the target state.

Note 1: When the PH key indicates a light to blink (one or more of bits 9, 11, 16 or 18 is set), information on color of light MAY be made available via PI key. When using such color indication in PI key, only basic primary and secondary colors that could unambiguously be decoded by a commissioner and understood by an end-user, but without worry of localization, SHOULD be used, e.g. white, red, green, blue, orange, yellow, purple.