

This key/value pair SHALL only be returned in the DNS-SD TXT record if the PH bitmap value has a bit set which has PI Dependency = M or has a bit set which has PI Dependency = 0 and the Commissionee wants to indicate related information as mentioned in Note 1 above. See Table 5, “Pairing and Reset Hint Values” for more information. The PH key SHALL NOT have more than one bit set which has a mandatory dependency on the PI key (PI Dependency = M) to avoid ambiguity in PI key usage.

4.3.1.13. TXT key for Joint Fabric

The optional key JF indicates the capabilities of an Ecosystem Administrator that can or is participating in the Joint Fabric.

The JF key SHALL be present in the DNS-SD TXT record if and only if the Node is capable of being a Joint Fabric Administrator.

The JF key SHALL be encoded as a variable-length decimal number in ASCII text, omitting any leading zeroes.

The JF key represents a base-10 numeric value for a bitmap of capabilities for a Joint Fabric Administrator device.

The bitmap of the Joint Fabric key values is defined in Table 6, “Joint Fabric Key Values”.

Table 6. Joint Fabric Key Values

Bit index	Capability	Description
0	Available	This device is capable of acting as a Joint Fabric Administrator. (See Note 1)
1	Administrator	This device is acting as a Joint Fabric Administrator. (See Note 2)
2	Anchor	This device is acting as a Joint Fabric Anchor Administrator. (See Note 2)
3	Datastore	This device is acting as a Joint Fabric Datastore. (See Note 3)

Note 1: bit 0 (Available) SHALL be unset for any of bits 1, 2 or 3 to be set. bit 0 (Available) SHALL be set, bits 1, 2 and 3 SHALL be unset as the default value prior to the Administrator Node being commissioned onto the Joint Fabric. Once an Administrator device is commissioned on the Joint Fabric, bit 0 (Available) SHALL be unset.

Note 2: bit 1 (Administrator) SHALL be set for bit 2 (Anchor) to be set. A device SHALL be a Joint Fabric Administrator to be a Joint Fabric Anchor Administrator. A single device for the Ecosystem (Vendor) which is the Joint Fabric Anchor SHALL have bit 3 (Datastore) set. This means one or more devices MAY have bit 1 (Administrator) and bit 2 (Anchor) set and bit 3 (Datastore) cleared, but at most one device SHALL have bit 3 (Datastore) set.