

Element	Size (bits)	Required	Notes
VENDOR_ID	16	No	Needed only to support devices that need a user-intent or vendor specific flow before commissioning (i.e. a non-zero Custom Flow value). If an accompanying QR code is present on the device with the Custom Flow field set to a non-zero value, or if the device requires Custom commissioning flow , this element SHALL be included.
PRODUCT_ID	16	No*	* This element SHALL be included <i>if and only if</i> the VENDOR_ID element is present.

The Vendor ID and Product ID elements are optional. Including these may provide additional information for the setup flow at the expense of a substantially longer Manual Pairing Code.

Custom Flow for Manual Pairing Code

The encoding for Manual Pairing Code does not have a dedicated field for Custom Flow, as exists in the [Packed Binary Data Structure](#). Instead, this information is encoded in the following way:

- For [Standard commissioning flow](#), the variant of Manual Pairing Code *without* Vendor ID and Product ID SHALL be used. A commissioner encountering such Manual Pairing Code SHALL assume it is a "standard flow" device.
- For [User-intent commissioning flow](#) and [Custom Commissioning flow](#), the variant of Manual Pairing Code *with* Vendor ID and Product ID SHALL be used. For this case, a commissioner SHOULD use Vendor ID and Product ID to lookup the [CommissioningCustomFlow](#) field in the [Distributed Compliance Ledger](#) to determine which of these values applies for this Vendor ID and Product ID combination.

Encoding

The required and optional elements, along with a check digit, are encoded into either an 11-digit or 21-digit decimal numeric string, depending on whether the optional Vendor and Product ID information is included.

Method

Each group of digits in the Pairing Code SHALL be encoded as described in the table below. The left-most digit of the entire string SHALL be represented by *DIGIT[1]*. Groups of multiple digits SHALL be encoded such that the most-significant digit appears first (left-most).

Table 61. Encoding Method without Vendor and Product ID's (*VID_PID_Present == 0*)