

ArmFailSafe command (see [Section 11.10.7.2, “ArmFailSafe”](#)). A Commissioner MAY obtain device information including guidance on the fail-safe value from the Commissionee by reading BasicCommissioningInfo attribute (see [Section 11.10.6.2, “BasicCommissioningInfo”](#)) prior to invoking the [Section 11.10.7.2, “ArmFailSafe”](#) command.

8. The commissioner configures the regulatory information and time cluster as described below. The order of the operations in this commissioning step is not critical.
 - If the Commissionee has at least one instance of the [Network Commissioning cluster](#) on any endpoint with either the **WI** (i.e. Wi-Fi) or **TH** (i.e. Thread) [feature flags set](#) in its FeatureMap, Commissioner SHALL configure regulatory information in the Commissionee using the [Section 11.10.7.4, “SetRegulatoryConfig”](#) command.
 - If the Commissionee supports the [Time Synchronization Cluster](#) server:
 - The Commissioner SHOULD configure UTC time using the [Section 11.17.9.1, “SetUTC-Time”](#) command.
 - The Commissioner SHOULD set the time zone using the [Section 11.17.9.3, “SetTimeZone”](#) command, if the [Section 11.17.5.1, “TimeZone”](#) feature is supported.
 - The Commissioner SHOULD set the DST offsets using the [Section 11.17.9.5, “SetDSTOffset”](#) command if the [Section 11.17.5.1, “TimeZone”](#) feature is supported, and the [Section 11.17.9.4, “SetTimeZoneResponse”](#) from the Commissionee had the DSTOffsetRequired field set to True.
 - The Commissioner SHOULD set a Default NTP server using the [Section 11.17.9.6, “SetDefaultNTP”](#) command if the [Section 11.17.5.2, “NTPClient”](#) feature is supported and the [Section 11.17.8.5, “DefaultNTP”](#) attribute is null. If the current value is non-null, Commissioners MAY opt to overwrite the current value.
9. If the [Terms & Conditions Enhanced Setup Flow](#) feature is supported by both the device and by the commissioner, and [Section 11.10.6.9, “TCAcknowledgementsRequired”](#) is True, the Commissioner SHALL present them as documented in [Terms and Conditions Acknowledgement](#). The user’s responses SHALL be propagated back to the node with [Section 11.10.7.8, “SetTCAcknowledgements”](#).
10. Commissioner SHALL establish the authenticity of the Commissionee as a certified Matter device (see [Section 6.2.3, “Device Attestation Procedure”](#)).
 - If the Commissionee fails the Device Attestation Procedure, for any reason, the Commissioner MAY choose to either continue to the Commissioning, or terminate it, depending on implementation-dependent policies.
 - Upon failure of the procedure, the Commissioner SHOULD warn the user that the Commissionee is not a fully trusted device, and MAY give the user the choice to authorize or deny the commissioning. Such a warning enables user choice in Commissionee trust on their Fabric, for development workflows, as well as homebrew device development. Such a warning SHOULD contain as much information as the commissioner can provide about the Commissionee, and SHOULD be adapted to the reason of the failure, for example by being different between the case of an expired certificate versus a revoked PAI certificate.
 - Reasons for failing the Device Attestation procedure MAY include, but are not limited to, the following:
 - The Commissionee being of a device type currently in development or not yet certified