

(see [certification_type](#) in the [Certification Declaration](#)).

- The Commissionee's PAA not being in the Commissioner's trusted set.
 - The Commissioner having obtained knowledge that a [PAA or PAI certificate](#) presented has been revoked, or that the particular [Device Attestation Certificate](#) has been revoked (see [Section 6.2.4, "Device attestation revocation"](#)).
 - The Commissioner cannot obtain a revocation set or cannot obtain updated revocation information from the CA (see [Section 6.2.4.2, "Determining Revocation Status of an Entity"](#)).
 - The Commissionee failing to prove possession of the Device Attestation private key, either by programming error, malicious intent or other reasons.
 - One of the elements of the Commissionee's Device Attestation Certificate chain not meeting the policy validation steps of the Device Attestation Procedure, including errors on validity period.
- If a Commissioner denies commissioning for any reason, it SHOULD notify the user of the reason with sufficient details for the user to understand the reason, so that they could determine if it would be possible to commission the device using a different Commissioner.
11. Following the Device Attestation Procedure yielding a decision to proceed with commissioning, the Commissioner SHALL request operational CSR from Commissionee using the CSRRequest command (see [Section 11.18.6.5, "CSRRequest Command"](#)). The CSRRequest command will cause the generation of a new operational key pair at the Commissionee.
 12. Commissioner SHALL generate or otherwise obtain an Operational Certificate containing Operational ID after receiving the CSRResponse command from the Commissionee (see [Section 11.18.6.5, "CSRRequest Command"](#)), using implementation-specific means.
 13. Commissioner SHALL install operational credentials (see [Figure 56, "Node Operational Credentials flow"](#)) on the Commissionee using the [Section 11.18.6.13, "AddTrustedRootCertificate"](#) and [AddNOC](#) commands, and SHALL use the [Section 11.18.6.11, "UpdateFabricLabel"](#) command to set a string that the user can recognize and relate to this Commissioner/Administrator. The AdminVendorId field of the AddNOC command SHALL be set to a value for which the [Vendor Schema in DCL](#) contains the name and other information of the Commissioner's manufacturer.
 14. If the Commissionee supports the [Time Synchronization Cluster](#) server, the Commissioner SHOULD set a trusted time source using the [Section 11.17.9.2, "SetTrustedTimeSource"](#) command if the [Section 11.17.5.4, "TimeSyncClient"](#) feature is supported, the [Section 11.17.8.4, "TrustedTimeSource"](#) attribute is null and there is an available trusted time source on the fabric. The Commissioner SHOULD ensure the ACL on the TrustedTimeSource is set to grant the Commissionee View privilege to the Time Synchronization cluster. If the TrustedTimeSource is non-null, the Commissioner MAY opt to overwrite the current value with a node from its own fabric by sending the [Section 11.17.9.2, "SetTrustedTimeSource"](#) command. This step MAY be performed at any point after installing operational credentials, including after sending the CommissioningComplete command.
 15. Commissioner MAY configure the Access Control List (see [Section 9.10, "Access Control Cluster"](#)) on the Commissionee in any way it sees fit, if the singular entry added by the [AddNOC](#) command in the previous step granting Administer privilege over [CASE](#) authentication type for the Node