

of [Fail-Safe timer](#)". Termination of the session prior to the expiration of that timer for any reason (including a successful end of commissioning or an expiry of a fail-safe timer) SHALL also delete the CFSC timer.

Behavior on expiry of Fail-Safe timer

If the fail-safe timer expires before the [Section 11.10.7.6, "CommissioningComplete"](#) command is successfully invoked, the following sequence of clean-up steps SHALL be executed, in order, by the receiver:

1. Terminate any open [PASE](#) secure session by clearing any associated [Section 4.13.3.1, "Secure Session Context"](#) at the Server.
2. Revoke the temporary administrative privileges granted to any open [PASE](#) session (see [Section 6.6.2.9, "Bootstrapping of the Access Control Cluster"](#)) at the Server.
3. If an AddNOC or UpdateNOC command has been successfully invoked, terminate all [CASE](#) sessions associated with the Fabric whose Fabric Index is recorded in the Fail-Safe context (see [Section 11.10.7.2, "ArmFailSafe"](#)) by clearing any associated [Section 4.13.3.1, "Secure Session Context"](#) at the Server.
4. Reset the configuration of all Network Commissioning [Section 11.9.6.2, "Networks"](#) attribute to their state prior to the Fail-Safe being armed.
5. If an UpdateNOC command had been successfully invoked, revert the state of operational key pair, NOC and ICAC for that Fabric to the state prior to the Fail-Safe timer being armed, for the Fabric Index that was the subject of the UpdateNOC command.
6. If an AddNOC command had been successfully invoked, achieve the equivalent effect of invoking the [RemoveFabric command](#) against the [fabric-index](#) stored in the Fail-Safe Context for the Fabric Index that was the subject of the AddNOC command. This SHALL remove all associations to that Fabric including all fabric-scoped data, and MAY possibly factory-reset the device depending on current device state. This SHALL only apply to Fabrics added during the fail-safe period as the result of the [AddNOC command](#).
7. If the [CSRRequest](#) command had been successfully invoked, but no AddNOC or UpdateNOC command had been successfully invoked, then the new operational key pair temporarily generated for the purposes of NOC addition or update (see [Section 6.4.6.1, "Node Operational Certificate Signing Request \(NOCSR\) Procedure"](#)) SHALL be removed as it is no longer needed.
8. Remove any RCACs added by the [AddTrustedRootCertificate command](#) that are not currently referenced by any entry in the [Fabrics attribute](#).
9. Reset the [Section 11.10.6.1, "Breadcrumb"](#) attribute to zero.
10. Optionally: if no factory-reset resulted from the previous steps, it is RECOMMENDED that the Node rollback the state of all non fabric-scoped data present in the Fail-Safe context.

11.10.7.3. ArmFailSafeResponse Command

This command is used to report the result of the ArmFailSafe command.