

ID	Name	Type	Constraint	Quality	Fallback	Access	Conformance
0x000B	Current-MaxRate	uint64	all	C X	0	R V	O
0x000C	Overrun-Count	uint64	all	C X	0	R V	ERRCNT

For all attributes listed above, a null value SHALL be returned if the interface is not currently configured or operational.

11.15.6.1. BSSID Attribute

This attribute SHALL indicate the BSSID for which the Wi-Fi network the Node is currently connected.

11.15.6.2. SecurityType Attribute

This attribute SHALL indicate the current type of Wi-Fi security used.

11.15.6.3. WiFiVersion Attribute

This attribute SHALL indicate the current [IEEE 802.11](#) standard version in use by the Node, per the table below.

11.15.6.4. ChannelNumber Attribute

This attribute SHALL indicate the channel that Wi-Fi communication is currently operating on.

11.15.6.5. RSSI Attribute

This attribute SHALL indicate the current RSSI of the Node's Wi-Fi radio in dBm.

11.15.6.6. BeaconLostCount Attribute

This attribute SHALL indicate the count of the number of missed beacons the Node has detected. If the Node does not have an ability to count beacons expected and not received, this value MAY remain set to zero.

11.15.6.7. BeaconRxCount Attribute

This attribute SHALL indicate the count of the number of received beacons. The total number of expected beacons that could have been received during the interval since association SHOULD match the sum of BeaconRxCount and BeaconLostCount. If the Node does not have an ability to report count of beacons received, this value MAY remain set to zero.

11.15.6.8. PacketMulticastRxCount Attribute

This attribute SHALL indicate the number of multicast packets received by the Node.