

ID	Name	Direction	Response	Access	Conformance
0x00	Identify	client ⇒ server	Y	M	M
0x40	TriggerEffect	client ⇒ server	Y	M	O

1.2.6.1. Identify Command

This command starts or stops the receiving device identifying itself.

This command SHALL have the following data fields:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Identify-Time	uint16	all			M

1.2.6.1.1. Effect on Receipt

On receipt of this command, the device SHALL set the IdentifyTime attribute to the value of the IdentifyTime field. This then starts, continues, or stops the device's identification state as detailed in [IdentifyTime](#).

1.2.6.2. TriggerEffect Command

This command allows the support of feedback to the user, such as a certain light effect. It is used to allow an implementation to provide visual feedback to the user under certain circumstances such as a color light turning green when it has successfully connected to a network. The use of this command and the effects themselves are entirely up to the implementer to use whenever a visual feedback is useful but it is not the same as and does not replace the identify mechanism used during commissioning.

This command SHALL have the following data fields:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	EffectIdentifier	EffectIdentifierEnum	desc			M
1	EffectVariant	EffectVariantEnum	desc			M

1.2.6.2.1. EffectIdentifier Field

This field SHALL indicate the identify effect to use and SHALL contain one of the non-reserved values in [EffectIdentifierEnum](#).

All values of the [EffectIdentifierEnum](#) SHALL be supported. Implementors MAY deviate from the example light effects in [EffectIdentifierEnum](#), but they SHOULD indicate during testing how they handle each effect.