

1.6.8. State Change Table for Lighting

Below is a table of examples of state changes when Level Control and On/Off clusters are on the same endpoint and the Lighting feature is set.

EiO - ExecuteIfOff field in the Options attribute

OnOff – Attribute value of On/Off cluster: FALSE='Off', TRUE='On'

MIN - MinLevel

MAX - MaxLevel

MID – Midpoint between MinLevel and MaxLevel

1.6.8.1. Lighting Device State Change examples

Cur-rentLevel	EiO	OnOff	Physical Device	Com-mand Before After	Cur-rentLevel	OnOff	Physical Device	Device Output Result
<i>any</i>	0	FALSE	Off	Move-ToLevel(l= <i>MID</i> , t=2 sec)	<i>same</i>	FALSE	Off	Stays off
<i>any</i>	0	FALSE	Off	Move-ToLevel-With-OnOff(l= <i>MID</i> , t=2 sec)	<i>MID</i>	TRUE	On (mid-point brightness)	Turns on and output level adjusts or stays at half
<i>any</i>	1	FALSE	Off	Move-ToLevel(l= <i>MID</i> , t=2 sec)	<i>MID</i>	FALSE	Off	Stays off
<i>any</i>	1	FALSE	Off	Move-ToLevel-With-OnOff(l= <i>MID</i> , t=2 sec)	<i>MID</i>	TRUE	On	Turns on and output level adjusts to or stays at half
<i>any</i>	1	FALSE	Off	Move(up, rate=64/s)	<i>MAX</i>	FALSE	Off	Stays off