

cated by the CurrentArea attribute, in seconds.

A value of 0 means that the operation has completed.

When this attribute is null, that represents that there is no time currently defined until operation completion. This MAY happen, for example, because no operation is in progress or because the completion time is unknown.

This attribute SHALL be null if the CurrentArea attribute is null.

If the Progress attribute is available, and it contains an entry matching CurrentArea, the server MAY use the time estimate provided in the EstimatedTime field of that entry to compute the EstimatedEndTime attribute.

The value of this attribute SHALL only be reported in the following cases:

- when it changes to or from 0
- when it decreases
- when it changes to or from null

NOTE

If the device is capable of pausing its operation, this attribute MAY be set to null, to indicate that completion time is unknown, or increment the value while being in the paused state.

1.17.6.6. Progress Attribute

This attribute SHALL indicate the operating status at one or more areas.

Each entry in this list SHALL have a unique value for the AreaID field.

For each entry in this list, the AreaID field SHALL match an entry on the SupportedAreas attribute's list.

When this attribute is empty, that represents that no progress information is currently available.

If the SelectedAreas attribute is empty, indicating the device is not constrained to operate in any specific areas, the Progress attribute list MAY change while the device operates, due to the device adding new entries dynamically, when it determines which ones it can attempt to operate at.

If the SelectedAreas attribute is not empty, and the device starts operating:

- the Progress attribute list SHALL be updated so each entry of SelectedAreas has a matching Progress list entry, based on the AreaID field
- the length of the Progress and SelectedAreas list SHALL be the same
- the entries in the Progress list SHALL be initialized by the server, by having their status set to Pending or Operating, and the TotalOperationalTime field set to null

When the device ends operation unexpectedly, such as due to an error, the server SHALL update all Progress list entries with the Status field set to Operating or Pending to Skipped.