

Also see [Backward Compatibility section](#).

Some, but not all, of the implications of the conformance rules for these attributes are:

- if attribute HoldTime is not supported, these 9 legacy attributes SHALL NOT be supported
- if modality PIR is supported, while both PHY and US modalities are not supported,
 - the 3 legacy attributes related to PIR MAY be supported (if allowed by the other rules)
 - the 6 legacy attributes related to Ultrasonic and PhysicalContact SHALL NOT be supported
- if modality US is supported while both PIR and PHY modalities are not supported:
 - the 3 legacy attributes related to UltraSonic MAY be supported (if allowed by the other rules)
 - the 6 legacy attributes related to PIR and PhysicalContact SHALL NOT be supported
- if modality PHY is supported while both PIR and US modalities are not supported:
 - the 3 legacy attributes related to PhysicalContact MAY be supported (if allowed by the other rules)
 - the 6 legacy attributes related to PIR and Ultrasonic SHALL NOT be supported
- the legacy attributes related to UnoccupiedToOccupiedDelay and UnoccupiedToOccupiedThreshold for a certain modality SHALL be both supported or both not supported
- if none of the modalities PIR, US, and PHY is supported (this case is presented as a PIR sensor for compatibility):
 - the 3 legacy attributes related to PIR MAY be supported (if allowed by the other rules)
 - the 6 legacy attributes related to Ultrasonic and PhysicalContact SHALL NOT be supported

For cases where more than one of the PIR, PHY and US modalities is supported *and* the timing parameters are provided for more than one modality, it is manufacturer specific how to combine those timing parameters.

2.7.6.6. PIROccupiedToUnoccupiedDelay Attribute

This attribute SHALL specify the time delay, in seconds, before the PIR sensor changes to its unoccupied state after the last detection of occupancy in the sensed area.

2.7.6.7. PIRUnoccupiedToOccupiedDelay Attribute

This attribute SHALL specify the time delay, in seconds, before the PIR sensor changes to its occupied state after the first detection of occupancy in the sensed area.

2.7.6.8. PIRUnoccupiedToOccupiedThreshold Attribute

This attribute SHALL specify the number of occupancy detection events that must occur in the period PIRUnoccupiedToOccupiedDelay, before the PIR sensor changes to its occupied state.

2.7.6.9. UltrasonicOccupiedToUnoccupiedDelay Attribute

This attribute SHALL specify the time delay, in seconds, before the Ultrasonic sensor changes to its unoccupied state after the last detection of occupancy in the sensed area.