

3.2.8.7.2. Effect on Receipt

On receipt of this command, a device SHALL set the ColorMode attribute to the value 0 (CurrentHueAndCurrentSaturation) and SHALL then move from its current saturation to the value given in the Saturation field.

The movement SHALL be continuous, i.e., not a step function, and the time taken to move to the new saturation SHALL be equal to the TransitionTime field, in 1/10ths of a second.

3.2.8.8. MoveSaturation Command

This command will move the device to the requested saturation value using a rate.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	MoveMode	MoveModeEnum	all			M
1	Rate	uint8	all			M
2	OptionsMask	OptionsBitmap	desc			M
3	OptionsOverride	OptionsBitmap	desc			M

3.2.8.8.1. MoveMode Field

This field SHALL indicate the mode of movement, as described in the [MoveHue](#) command.

3.2.8.8.2. Rate Field

This field SHALL indicate the rate of movement in steps per second. A step is a change in the device's saturation of one unit.

3.2.8.8.3. OptionsMask and OptionsOverride Fields

These fields SHALL be processed according to section [Use of the OptionsMask and OptionsOverride Fields](#).

3.2.8.8.4. Effect on Receipt

On receipt of this command,

- If the MoveMode field is set to 1 (Up) or 3 (Down)
 - If the Rate field has a value of zero, the command has no effect and a response SHALL be returned with the status code set to INVALID_COMMAND.
 - Otherwise, a device SHALL set the ColorMode attribute to the value 0 (CurrentHueAndCurrentSaturation) and SHALL then move from its current saturation in an up or down direction in a continuous fashion, as detailed in the table.
- If the MoveMode field is set to 0 (Stop), the Rate field SHALL be completely ignored.