

3.2.8.9.4. OptionsMask and OptionsOverride Fields

These fields SHALL be processed according to section [Use of the OptionsMask and OptionsOverride Fields](#).

3.2.8.9.5. Effect on Receipt

On receipt of this command, if the StepSize field has a value of zero, the command has no effect and a response SHALL be returned with the status code set to INVALID_COMMAND.

Otherwise, a device SHALL set the ColorMode attribute to the value 0 (CurrentHueAndCurrentSaturation) and SHALL then move from its current saturation in an up or down direction by one step.

StepMode	Action on Receipt
Up	Increase the device's saturation by one step, in a continuous fashion. However, if the saturation value is already the maximum value then do nothing.
Down	Decrease the device's saturation by one step, in a continuous fashion. However, if the saturation value is already the minimum value then do nothing.

3.2.8.10. MoveToHueAndSaturation Command

This command will move the device to the requested hue and saturation value using a transition.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	Hue	uint8	max 254			M
1	Saturation	uint8	max 254			M
2	Transition-Time	uint16	max 65534			M
3	Options-Mask	Options-Bitmap	desc			M
4	OptionsOverride	Options-Bitmap	desc			M

3.2.8.10.1. OptionsMask and OptionsOverride Fields

These fields SHALL be processed according to section [Use of the OptionsMask and OptionsOverride Fields](#).

3.2.8.10.2. Effect on Receipt

On receipt of this command, a device SHALL set the ColorMode attribute to the value 0 (CurrentHueAndCurrentSaturation) and SHALL then move from its current hue and saturation to the val-