

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	UserIndex	uint16	1 to NumberOfTotalUsersSupported, 0xFFFE			M

For each user to clear, all associated credentials (e.g. PIN, RFID, fingerprint, etc.) SHALL be cleared and the user entry values SHALL be reset to their default values (e.g. UserStatus SHALL be Available, UserType SHALL be UnrestrictedUser) and all associated schedules SHALL be cleared.

A LockUserChange event with the provided UserIndex SHALL be generated after successfully clearing users.

5.2.10.35.1. UserIndex Field

This field SHALL specify a valid User index or 0xFFFE to indicate all user slots SHALL be cleared.

5.2.10.36. SetCredential Command

Set a credential (e.g. PIN, RFID, Fingerprint, etc.) into the lock for a new user, existing user, or ProgrammingUser.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	OperationType	DataOperationTypeEnum	Add, Modify			M
1	Credential	CredentialStruct				M
2	Credential-Data	octstr	desc			M
3	UserIndex	uint16	1 to NumberOfTotalUsersSupported	X		M
4	UserStatus	UserStatusEnum	OccupiedEnabled, OccupiedDisabled	X		M