

| ID     | Name                     | Type                                    | Constraint | Quality | Fallback | Access | Conformance |
|--------|--------------------------|-----------------------------------------|------------|---------|----------|--------|-------------|
| 0x000A | <b>ModulationType</b>    | <a href="#">ModulationTypeEnum</a>      | all        | F       |          | R V    | MD          |
| 0x000B | <b>LatchControlModes</b> | <a href="#">LatchControlModesBitmap</a> | all        | F       |          | R V    | LT          |

#### 5.5.7.1. CurrentState Attribute

This attribute SHALL indicate the current Position, Latching and/or Speed, based on the feature flags set.

A value of null SHALL indicate that:

- The position and latching state are both not known yet because the closure is not calibrated, or
- The product has lost its position and latching state after manual motion during a shutdown.

Changes to this attribute SHALL only be marked as reportable in the following cases:

- When the attribute changes from null to any other value and vice versa, or
- When the Position changes from null to any other value and vice versa, or
- At most once every 5 seconds when the Position changes from one non-null value to another non-null value, or
- When **TargetState.Position** is reached, or
- When **CurrentState.Speed** changes, or
- When **CurrentState.Latch** changes.

The value of the different fields within the structure of this attribute depends on:

- The last SetTarget or Step commands.
- The impact of a MoveTo command received on the [Closure Control Cluster](#) instance associated with this cluster, if such a Closure Control instance exists, as described in [Section 5.5.4, “Association Between Closure Control and Closure Dimension Clusters”](#).

#### 5.5.7.2. TargetState Attribute

This attribute SHALL indicate the target Position, Latching and/or Speed, based on the feature flags set.

A value of null SHALL indicate that the TargetState fields are unknown (typically after a reboot, no target has been yet requested).

Each field SHALL be present only when its corresponding feature is supported. If the feature is not supported the field SHALL NOT be present.