

If this command is executed successfully, a ResetPINResponse command with a new PIN SHALL be returned.

6.13.8.3. ResetPINResponse Command

This command SHALL be generated in response to a ResetPIN command. The data for this command SHALL be as follows:

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	PINCode	string	max 6			M

6.13.8.3.1. PINCode Field

This field SHALL indicate a new PIN of the Content Control feature.

6.13.8.4. Enable Command

The purpose of this command is to turn on the Content Control feature on a media device.

Upon receipt of the Enable command, the media device SHALL set the Enabled attribute to TRUE.

6.13.8.5. Disable Command

The purpose of this command is to turn off the Content Control feature on a media device.

On receipt of the Disable command, the media device SHALL set the Enabled attribute to FALSE.

6.13.8.6. AddBonusTime Command

The purpose of this command is to add the extra screen time for the user.

If a client with Operate privilege invokes this command, the media device SHALL check whether the PINCode passed in the command matches the current PINCode value. If these match, then the RemainingScreenTime attribute SHALL be increased by the specified BonusTime value.

If the PINs do not match, then a response with InvalidPINCode error status SHALL be returned, and no changes SHALL be made to RemainingScreenTime.

If a client with Manage privilege or greater invokes this command, the media device SHALL ignore the PINCode field and directly increase the RemainingScreenTime attribute by the specified BonusTime value.

A server that does not support the PM feature SHALL respond with InvalidPINCode to clients that only have Operate privilege unless:

- It has been provided with the PIN value to expect via an out of band mechanism, and
- The client has provided a PINCode that matches the expected PIN value.