

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	ForecastID	uint32	all			M
1	SlotAdjustments	list[SlotAdjustmentStruct]	max 10			M
2	Cause	AdjustmentCauseEnum	all			M

9.2.9.6.1. ForecastID Field

This field SHALL indicate the ForecastID that is to be modified.

9.2.9.6.2. SlotAdjustments Field

This field SHALL contain a list of SlotAdjustment parameters that should be modified in the corresponding Forecast with matching ForecastID.

9.2.9.6.3. Cause Field

This field SHALL indicate the cause of the request from the EMS.

9.2.9.6.4. Effect on receipt

On receipt of this command, if the ESA supports **FA**, and the **OptOutState** permits the specified **AdjustmentCauseEnum** (see **OptOutState** for details), it SHALL attempt to adjust its forecast.

The client may be an energy management system which has retrieved the forecasts from multiple ESA and then performed some optimization (for example, taking advantage of local solar PV generation).

The ESA SHALL inspect the requested forecast and ensure that it does not exceed the limits set in each of its slots. The ESA manufacturer may also reject the request if it could cause the user's preferences to be breached (for example, if it may cause the home to be too hot or too cold, or a battery to be insufficiently charged).

Note that the client may make an adjustment when the ESA's program has already been started. In this case the ActiveSlotNumber may have moved through the Forecast sequence. Any attempts to modify slots which have already been run SHALL result in the entire command being rejected.

The command allows a single modification to a particular slot, or to multiple slots in a single command by sending a list of modifications.

If the ESA accepts the requested Forecast then it SHALL update its **Forecast** attribute (incrementing its **ForecastID**, and updating its **ForecastUpdateReason** from the Cause value) and run the revised Forecast as its new intended operation.

Note that an ESA may adapt its Forecast based on a slot modification. For example, if an ESA was switched on earlier in the day to take account of available solar PV, then it may not need to use