

ID	Name	Type	Constraint	Quality	Fallback	Conformance
1	State	StateEnum	all			M
2	Fault-StatePreviousState	FaultStateEnum	all			M
4	FaultStateCurrentState	FaultStateEnum	all			M

9.3.10.5.1. SessionID Field

This field SHALL indicate the value of the [SessionID](#) attribute prior to the Fault State being changed. A value of null indicates no sessions have occurred before the fault occurred.

9.3.10.5.2. State Field

This field SHALL indicate the value of the [State](#) attribute prior to the Fault State being changed.

9.3.10.5.3. FaultStatePreviousState Field

This field SHALL indicate the value of the [FaultState](#) attribute prior to the Fault State being changed.

9.3.10.5.4. FaultStateCurrentState Field

This field SHALL indicate the current value of the [FaultState](#) attribute.

9.3.10.6. RFID Event

This event SHALL be generated when a RFID card has been read. This allows a controller to register the card ID and use this to authenticate and start the charging session.

ID	Name	Type	Constraint	Quality	Fallback	Conformance
0	UID	octstr	max 10			M

9.3.10.6.1. UID Field

The UID field (ISO 14443A UID) is either 4, 7 or 10 bytes.

9.4. Energy EVSE Mode Cluster

This cluster is derived from the Mode Base cluster and defines additional mode tags and name-spaced enumerated values for EVSE devices.