

Bit index	Name	Instruction Dependency	Description
0	Power Cycle	no	The Device will automatically enter the target state upon power cycle (unplug/re-plug, remove/re-insert batteries). When used with the target state of Commissioning Mode for a device that is in a factory reset state, this bit SHALL be set to 1 for devices using Standard Commissioning Flow , and set to 0 otherwise.
1	Device Manufacturer URL/App	no	To put the device into the desired state, the user can be sent to the URL specified in the CommissioningCustomFlowUrl of the DeviceModel schema entry indexed by the Vendor ID and Product ID (e.g., as found in the announcement) in the Distributed Compliance Ledger . This URL could lead to a page with instructions, or to an app with instructions. When used with the target state of Commissioning Mode for a device that is in a factory reset state, this bit SHALL be set to 1 for devices requiring Custom Commissioning Flow before they can be available for Commissioning by any Commissioner.
2	Administrator	no	The Device has been commissioned. Any Administrator that commissioned the device provides a user interface that may be used to put the device into Commissioning Mode.
3	Settings menu on the Node	no	The settings menu on the Device provides instructions to put it into the desired state.
4	Custom Instruction	M	The PI key/value pair SHALL describe a custom way to put the Device into the target state. This Custom Instruction option is NOT recommended for use by a Device that does not have knowledge of the user's language preference.
5	Device Manual	no	The Device Manual provides special instructions to put the Device into the target state (see Section 11.23.6.15 , " UserManualUrl "). This is a catch-all option to capture user interactions that are not codified by other options in this table.
6	Press Reset Button	no	The Device will enter the target state when reset button is pressed.
7	Press Reset Button with application of power	no	The Device will enter the target state when reset button is pressed when applying power to it.
8	Press Reset Button for N seconds	M	The Device will enter the target state when reset button is pressed for N seconds. The exact value of N SHALL be made available via PI key.