

5.4.2.1. Announcement and Discovery Using Multiple Technologies

A device SHALL announce on all of the networking technologies it supports as indicated in the Discovery Capability Bitmask (see [Table 58, “Discovery Capabilities Bitmask”](#)), except for NFC (as there is no announcement over NFC interface).

5.4.2.2. Announcement Commencement

A device which is not yet commissioned into a Matter fabric SHALL commence announcing its ability to be commissioned depending on its primary device function and manufacturer-chosen [Device Commissioning Flow](#), per the table below. Nodes that implement [Network Recovery](#) support SHALL announce their need for network recovery on supported commissioning channels, such as Bluetooth LE or Wi-Fi Public Action Frame. Otherwise, Nodes already commissioned into one or more Matter fabrics or already connected to an IP-bearing network that wish to announce their commissioning requests SHALL ONLY do so using DNS-SD over their operational network (see [Section 5.4.2.7, “Using Existing IP-bearing Network”](#) and [Section 4.3, “Discovery”](#)). In the interest of privacy, an already-commissioned Node SHALL NOT commence commissioning announcement using Bluetooth LE or Wi-Fi Public Action Frame.

Primary Device Function	Announcement
Most control originates from a Fabric (excluding Locks and Barrier Access Devices)	SHALL start announcing automatically upon application of power when using Standard commissioning flow . When using User-intent commissioning flow or Custom Commissioning flow , it SHALL NOT start announcing automatically upon application of power.
Most control does not originate from a Fabric (e.g., dishwasher, coffee maker, refrigerator)	SHALL NOT start announcing automatically upon application of power. User-intent commissioning flow or Custom Commissioning flow is required.
Locks and Barrier Access Devices	SHOULD NOT start announcing automatically upon application of power. If Standard commissioning flow is used, additional security considerations are required as listed in Security Best Practices . User-intent commissioning flow or Custom Commissioning flow SHOULD be used. Due to the complexity of installing these device types, if Custom Commissioning flow is used the device is allowed to start announcing automatically upon application of power. If the device starts announcing automatically upon application of power then all counter measures for Standard commissioning flow SHALL apply.

Note that the above guidelines are in place to avoid unnecessary pollution of the 2.4 GHz spectrum and as a mitigation of the privacy threat created due to unnecessary transmissions by a commissionable device.

If announcement has ceased (see [Section 5.4.2.3, “Announcement Duration”](#)), it may be re-initiated via a device-specific user interaction such as a button press or other action defined by the manufacturer and indicated by the methods specified in [Section 5.7, “Device Commissioning Flows”](#).