

A cluster instance with a non-empty list SHALL include the endpoint, upon which the cluster instance resides.

The above rules allow that some endpoints can have an unknown power source, and therefore would not be indicated by any instance of this cluster.

Legacy Implementations

Legacy implementations of this cluster before revision 2, before this attribute was defined, would have implemented this cluster on an application endpoint without indicating it in EndpointList (since that attribute did not exist in revision 1), because it represented a power source for the endpoint, not the entire node.

For example: Bridge implementations support endpoints for bridged devices that have different power sources.

Such implementations followed device type requirements and semantics outside of this cluster, because this attribute did not exist.

Future updates of such a cluster instance on the same endpoint, would allow that same endpoint to be an entry in the EndpointList attribute. Therefore it is valid to list the endpoint upon which the cluster instance exists.

Empty list examples

Typically, there is one power source for the node. Also common is mains power for the node with battery backup power for the node. In both these common cases, for each cluster instance described, the list is empty.

Populated list example

A node has a mains power source with Order as 0 (zero), but some application endpoints (not all) have a battery back up source with Order as 1, which means this list is empty for the Power Source cluster associated with the mains power, because it indicates the entire node, but the Power Source cluster instance associated with the battery backup would list the endpoints that have a battery backup.

11.7.8. Events

ID	Name	Priority	Quality	Access	Conformance
0x00	WiredFault-Change	INFO		V	[WIRED]
0x01	BatFault-Change	INFO		V	[BAT]
0x02	BatCharge-FaultChange	INFO		V	[RECHG]