

already uses the exact same root of trust certificate.

If the NOC provided in the NOCValue encodes an [Operational Identifier](#) for a <Root Public Key, FabricID> pair already present on the device, then the device SHALL process the error by responding with a StatusCode of [FabricConflict](#) as described in [Section 11.18.6.7.2, “Handling Errors”](#).

If the device already has the CommissionedFabrics attribute equal to the SupportedFabrics attribute, then the device’s operational credentials table is considered full and the device SHALL process the error by responding with a StatusCode of [TableFull](#) as described in [Section 11.18.6.7.2, “Handling Errors”](#).

If the [CaseAdminSubject](#) field is not a valid [ACL subject](#) in the context of [AuthMode](#) set to CASE, such as not being in either the [Operational](#) or [CASE Authenticated Tag](#) range, then the device SHALL process the error by responding with a StatusCode of [InvalidAdminSubject](#) as described in [Section 11.18.6.7.2, “Handling Errors”](#).

Otherwise, the command is considered an addition of credentials, also known as "joining a fabric", and the following SHALL apply:

1. A new FabricIndex SHALL be allocated, taking the next valid [fabric-index](#) value in monotonically incrementing order, wrapping around from 254 (0xFE) to 1, since value 0 is reserved and using 255 (0xFF) would prevent cluster specifications from using nullable fabric-idx fields.
2. An entry within the [Fabrics attribute](#) table SHALL be added, reflecting the matter-fabric-id RDN within the NOC’s subject, along with the public key of the [trusted root](#) of the chain and the [AdminVendorID](#) field.
3. The operational key pair associated with the incoming NOC from the NOCValue, and generated by the prior CSRRequest command, SHALL be recorded for subsequent use during [CASE](#) within the fail-safe timer period (see [Section 5.5, “Commissioning Flows”](#)).
4. The incoming NOCValue and ICACValue (if present) SHALL be stored under the FabricIndex associated with the new [Fabric Scope](#), along with the RootCACertificate provided with the prior successful AddTrustedRootCertificate command invoked in the same fail-safe period.
 - a. Implementation of certificate chain storage MAY separate or otherwise encode the components of the array in implementation-specific ways, as long as they follow the correct format when being read from the [NOCs](#) list or used within other protocols such as [CASE](#).
5. The [NOCs](#) list SHALL reflect the incoming NOC from the NOCValue field and ICAC from the ICACValue field (if present).
6. The [operational discovery](#) service record SHALL immediately reflect the new Operational Identifier, such that the Node immediately begins to exist within the Fabric and becomes reachable over [CASE](#) under the new operational identity.
7. The receiver SHALL create and add a new Access Control Entry using the [CaseAdminSubject](#) field to grant subsequent Administer access to an Administrator member of the new Fabric. It is RECOMMENDED that the Administrator presented in CaseAdminSubject exist within the same entity that is currently invoking the AddNOC command, within another of the Fabrics of which it is a member.
 - a. If the Managed Device Feature is implemented by the ACL cluster, then one or more ARL entries with the new FabricIndex MAY be added to the [ARL attribute](#).