

Bit	Name	Summary	Conformance
2	UpdateTime	Device updates the associated time attribute.	M
3	UpdateStartHue	Device updates the associated start hue attribute.	M

3.2.6.3.1. UpdateAction Bit

This bit SHALL indicate whether the server adheres to the Action field in order to process the command.

- 0 = Device SHALL ignore the Action field.
- 1 = Device SHALL adhere to the Action field.

3.2.6.3.2. UpdateDirection Bit

This bit SHALL indicate whether the device updates the ColorLoopDirection attribute with the Direction field.

- 0 = Device SHALL ignore the Direction field.
- 1 = Device SHALL update the ColorLoopDirection attribute with the value of the Direction field.

3.2.6.3.3. UpdateTime Bit

This bit SHALL indicate whether the device updates the ColorLoopTime attribute with the Time field.

- 0 = Device SHALL ignore the Time field.
- 1 = Device SHALL update the value of the ColorLoopTime attribute with the value of the Time field.

3.2.6.3.4. UpdateStartHue Bit

This bit SHALL indicate whether the device updates the ColorLoopStartEnhancedHue attribute with the value of the StartHue field.

- 0 = Device SHALL ignore the StartHue field.
- 1 = Device SHALL update the value of the ColorLoopStartEnhancedHue attribute with the value of the StartHue field.

3.2.6.4. DriftCompensationEnum Type

This data type is derived from enum8.